Quik VOICE

VP-1410A
Digital Voice Processor

FEATURES

- High quality voice & sound generation
- 10 messages with direct trigger pins
- Playback-only with external EPROM or ROM
- Stand-alone operation
- 128K x 8 direct memory addressing, expandable
- Single 5V DC supply voltage
- Low power consumption
- Internal RC oscillator or external clock
- Continuous Variable Slope Delta (CVSD) modulation
- Sampling rate from 24Kbps to 128 Kbps
- Message digitization with the VP-880 system
- 48-pin DIP (VP-1410A) or 48-pin QFP (VP-1410AF)

GENERAL DESCRIPTIONS


The VP-1410A Digital Voice Processor is an advanced CMOS LSI chip designed for multiple-message playback applications. It can access up to 10 different messages of variable length stored in external EPROM or ROM chips. Message activation is simplified since each message has its own trigger pin . If memory bank switching technique is used, the number of messages supported can be easily expanded to 20, 40 or more.

The VP-1410A is totally self-contained. It can access the external memory all by itself without the help from any microprocessor. Although the chip provides only 16 address lines, an external counter can be easily added to extend the memory addressing to virtuely no limitation. Therefore very long message length can be achieved easily. Overall, the VP-1410A offers high voice quality and flexible memory addressing that no other chips can.


APPLICATIONS

- Multiple message playback
- Sound effects generator
- Digital message repeaters for consumer, industrial, security and telecommunication products

VP-1410A (DIP48) Pin Assignment



VP-1410AF (QFP48) Pin Assignment



Eletech Enterprise Co., Ltd.
531-3F Chung-Cheng Road
Hsin Tien, Taipei Hsien, Taiwan
Tel:+886 2-2218-0068 Fax:+886 2-2218-0254

http://www.eletech.com

Eletech Electronics, Inc.
16019 Kaplan Avenue
Industry, CA 91744, U.S.A.
Tel: (626) 333-6394 Fax: (626) 333-6494

ABSOLUTE MAXIMUM RATINGS*

Supply Voltage, V_{DD} - V_{SS} ..... 0 to 5.5V
Input Volotage, V_{IN} ..... V_{SS} to V_{DD}
Operating Temperature, T_{OP} ..... -10°C to 60°C
Storage Temperature, T_{ST} ..... -20°C to 80°C


* Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied.

ELECTRICAL CHARACTERISTICS

(V_{DD} = 5V, F_{OSC} = 2048KHz, F_{CLOCK} = 32 KHz unless otherwise specified)

Symbol	Parameter		Min.	Typ.	Max.	Units
V_{DD}	Supply Voltage		4.5	5	5.5	V
I_{DD}	Standby Current			1.4		mA
I_{DRIVE}	Clock Drive Current		12			mA
I_{SINK}	Clock Sink Current		12			mA
V_{IH}	Input	High	3.5		5	V
V_{IL}	Voltage	Low	0		1.5	V
I_{DRIVE}	Output	Drive	3	4		mA
I_{SINK}	Current	Sink	3	4		mA
T_{RESET}	Reset Pulse Width		500			ns
T_{tr}	I/O Input Pulse Width			35		us
F_C	Internal Memory Search Clock			12		MHz

TIMING DIAGRAM



PIN DESCRIPTIONS

A0 - A16
Output, address bus, expandable by adding a counter. Note that VP-1410AF does not have A16.

ANG & $\overline{\text{ANG}}$
Output, differential analog audio signal.

ANGD
Input, analog signal to be connected to the external comparator output.

C1
Input, internal RC oscillator. If external clock is to be used, it must be connected to this pin and its frequency 64x the sampling rate.

CLK DRV
Output, buffered clock signal, a square wave of the same frequency as the sampling rate.

D0 - D7
Input, data bus.

ENV
Input, to be connected to an external integrator output.

INT
Output, connected to an external integrator to produce envelope waveform.

GND
Ground.

I/O1 ~ I/O10
Input/output, trigger pin, active low. I/O1 is for message #1, I/O2 is for message #2 and etc. When the chip is idle but not under reset, this pin is the trigger input and pulsing it will put the chip in the "Play" mode and start the message. Once in the "Play" mode, the pin becomes a "low" output until the message is over.

R1
Output, internal oscillator pin. Leave un-connected when using external clock.


$\overline{\text{READ}}$
Output, active low. It indicates the chip is in the "Play" mode. This signal is usually used to enable memory output.

RESET
Input, active high. Reset the chip back to the "Idle" mode. This pin is level sensitive.

TEST
For factory use only, keep it un-connected.

VCC
Input, supply voltage.

Block Diagram



APPLICATION NOTES

1. VP-1410AF Missing A16

Due to packaging constraint, the VP-1410AF does not provide address line A16. Therefore, A16 must be generated externally by adding a binary counter, as explained below.

2. Memory Address Expansion

The VP-1410A's internal 17-bit address counter covers memory space up to 128K x 8, or 1M bits. It can be easily expanded by just adding an external binary counter, clocked by the falling edge of address line A16. The first counter output becomes A17, the second output becomes A18 and etc. This is possible since once started, the VP-1410A will continue to play until it reaches the EOM (End Of Message) flag. When the internal address counter reaches the maximum count before the chip sees the EOM flag, the counter simply overflows and restarts from zero again. Therefore the VP-1410A can access an unlimited amount of memory by adding an external address counter.

3. EOM (End Of Message) Flag

The EOM flag consists of six consecutive bytes of "AA", or "10101010" in binary format. After a trigger signal is received, the VP-1410A uses the internal 12MHz system clock to scan through memory space and finds the correct message by counting the number of EOM flags. For example, to find the 5th message, it must scan through each and every memory location until it finds 4 EOM flags. The first byte following the 4th EOM flag is the first byte of the 5th message.


4. Creating Master EPROM File on the VP-880 System

Follow these steps to create the master EPROM file:

1. Digitize, edit and save each message in a separate file.
2. Use VP-880's function "H" to combine all the messages together. The VP-880 program will automatically search and eliminate any EOM flag within each messge, which is naturally formed during digitization. It will then put a EOM flag at the end of each message and combine them into one or several master files.


CIRCUIT DESIGN EXAMPLES

1. 10-Message Playback, 8M EPROM



PACKAGING INFORMATION

48L 10*10*2.0mm PQFP (Footprint : 5.0mm)



DIMENSIONS	MILLIMETERS			INCHES		
SYMBOLS	MIN	NOM	MAX	MIN	NOM	MAX
A	2.10	2.20	2.30	0.083	0.087	0.091
A1	0.15	0.20	0.25	0.006	0.008	0.010
A2	—	2.00	—	—	0.079	—
D	14.80	15.00	15.20	0.583	0.591	0.598
D1	9.95	10.00	10.05	0.392	0.394	0.396
E	14.80	15.00	15.20	0.583	0.591	0.598
E1	9.95	10.00	10.05	0.392	0.394	0.396
e		0.75 BSC			0.030 BSC	
b		0.33 TYP			00.013 TYP	
c		0.15 TYP			0.006 TYP	
L	1.60	1.70	1.80	0.063	0.067	0.071
L1	2.40	2.50	2.60	0.094	0.098	0.102
θ	0°	—	10°	0°	—	10°


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.