16-Channel High Performance Differential Output, 192 kHz, 24-Bit DAC

Data Sheet

ADAU1966

FEATURES

118 dB DAC dynamic range and SNR
−98 dB THD + N
Differential voltage DAC output
2.5 V digital and 3.3 V or 5 V analog and IO supplies
299 mW total (19 mW/channel) quiescent power at AVDD = 3.3 V
PLL generated or direct MCLK master clock
Low EMI design
Linear regulator driver to generate digital supply
Supports 24-bit and 32 kHz to 192 kHz sample rates
Low propagation 192 kHz sample rate mode
Log volume control with autoramp function
Temperature sensor with digital readout ±3°C accuracy
SPI and I²C controllable for flexibility
Software-controllable clickless mute
Software power-down
Right-justified, left-justified, I²S, and TDM modes
Master and slave modes with up to 16-channel input/output
80-lead LQFP package
Qualified for automotive applications

APPLICATIONS

Automotive audio systems
Home theater systems
Digital audio effects processors

GENERAL DESCRIPTION

The ADAU1966 is a high performance, single-chip DAC that provides 16 digital-to-analog converters (DACs) with differential output using the Analog Devices, Inc., patented multibit sigma-delta (Σ-Δ) architecture. An SPI/I²C port is included, allowing a microcontroller to adjust volume and many other parameters. The ADAU1966 operates from 2.5 V digital and 3.3 V or 5 V analog supplies. A linear regulator is included to generate the digital supply voltage from the analog supply voltage. The ADAU1966 is available in an 80-lead LQFP package.

The ADAU1966 is designed for low EMI. This consideration is apparent in both the system and circuit design architectures. By using the on-board PLL to derive the internal master clock from an external LRCLK, the ADAU1966 can eliminate the need for a separate high frequency master clock and can be used with or without a bit clock. The DACs are designed using the latest Analog Devices continuous time architectures to further minimize EMI. By using 2.5 V digital supplies, power consumption is minimized, and the digital waveforms are a smaller amplitude, further reducing emissions.

FUNCTIONAL BLOCK DIAGRAM




Figure 1.

Rev. C
Document Feedback

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781.329.4700 ©2011–2013 Analog Devices, Inc. All rights reserved.
Technical Support www.analog.com

TABLE OF CONTENTS

Features ... 1
Applications ... 1
General Description ... 1
Functional Block Diagram ... 1
Revision History ... 3
Specifications ... 4
Analog Performance Specifications ... 4
Crystal Oscillator Specifications ... 6
Digital Input/Output Specifications ... 7
Power Supply Specifications ... 7
Digital Filters ... 8
Timing Specifications ... 8
Absolute Maximum Ratings ... 10
Thermal Resistance ... 10
ESD Caution ... 10
Pin Configuration and Function Descriptions ... 11
Typical Performance Characteristics ... 14
Application Circuits ... 15
Theory of Operation ... 16
Digital-to-Analog Converters (DACs) ... 16
Clock Signals ... 16
Power-Up and $\overline{\text{RST}}$ ... 17
Standalone Mode ... 18
I²C Control Port ... 18
Serial Control Port: SPI Control Mode ... 20
Power Supply and Voltage Reference ... 20
Serial Data Ports—Data Format ... 20
Time-Division Multiplexed (TDM) Modes ... 20
Temperature Sensor ... 21
Additional Modes ... 23
Register Summary ... 24
Register Details ... 25
PLL and Clock Control 0 Register ... 25
PLL and Clock Control 1 Register ... 26
Block Power-Down and Thermal Sensor Control 1 Register ... 27
Power-Down Control 2 Register ... 28
Power-Down Control 3 Register ... 29
Thermal Sensor Temperature Readout Register ... 30
DAC Control 0 Register ... 31
DAC Control 1 Register ... 32
DAC Control 2 Register ... 33
DAC Individual Channel Mutes 1 Register ... 34
DAC Individual Channel Mutes 2 Register ... 35
Master Volume Control Register ... 36
DAC 1 Volume Control Register ... 36
DAC 2 Volume Control Register ... 37
DAC 3 Volume Control Register ... 37
DAC 4 Volume Control Register ... 38
DAC 5 Volume Control Register ... 38
DAC 6 Volume Control Register ... 39
DAC 7 Volume Control Register ... 39
DAC 8 Volume Control Register ... 40
DAC 9 Volume Control Register ... 40
DAC 10 Volume Control Register ... 41
DAC 11 Volume Control Register ... 41
DAC 12 Volume Control Register ... 42
DAC 13 Volume Control Register ... 42
DAC 14 Volume Control Register ... 43
DAC 15 Volume Control Register ... 43
DAC 16 Volume Control Register ... 44
Common-Mode and Pad Strength Register ... 44
DAC Power Adjust 1 Register ... 45
DAC Power Adjust 2 Register ... 46
DAC Power Adjust 3 Register ... 47
DAC Power Adjust 4 Register ... 48
Outline Dimensions ... 52
Ordering Guide ... 52
Automotive Products ... 52

REVISION HISTORY

3/13—Rev. B to Rev. C

Changes to Table 2 and Table 3 5
Changes to Table 4 6
Changes to I²C Control Port Section 18
Changes to Figure 13, Table 19, Table 20, Table 21, and Table 22 19
Changes to Serial Control Port: SPI Control Mode Section 20

8/12—Rev. A to Rev. B

Change to Table 10 10

7/12—Rev. 0 to Rev. A

Changed Output Resistance at Each Pin Parameter from 100 Ω to 33 Ω 4
Changes to Figure 13 19
Added Figure 14 20
Updated Outline Dimensions 52

9/11—Revision 0: Initial Version

SPECIFICATIONS

Performance of all channels is identical, exclusive of the interchannel gain mismatch and interchannel phase deviation specifications. Master clock = 12.288 MHz (48 kHz f_S, 256 × f_S mode), input sample rate = 48 kHz, measurement bandwidth = 20 Hz to 20 kHz, word width = 24 bits, load capacitance (digital output) = 20 pF, load current (digital output) = ±1 mA or 1.5 kΩ to ½ DVDD supply, input voltage high = 2.0 V, input voltage low = 0.8 V, unless otherwise noted.

ANALOG PERFORMANCE SPECIFICATIONS

Specifications guaranteed at AVDDx = 5 V and an ambient temperature of 25°C. Supply voltages = AVDDx = 5 V, DVDD = 2.5 V, ambient temperature[1] (T_A) = 25°C, unless otherwise noted.

Table 1.

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
DIGITAL-TO-ANALOG CONVERTERS					
Dynamic Range	20 Hz to 20 kHz, −60 dB input				
No Filter (RMS)		105	115.5		dB
With A-Weighted Filter (RMS)		108	118		dB
Total Harmonic Distortion + Noise	0 dBFS		−90		dB
	Two channels running, −1 dBFS		−98		dB
	16 channels running, −1 dBFS		−98	−85	dB
Full-Scale Differential Output Voltage	AVDDx = 5.0 V		3.00 (±8.49)		V rms (V p-p)
Gain Error		−10		+10	%
Offset Error		−25	−6	+25	mV
Gain Drift		−30		+30	ppm/°C
Interchannel Isolation			100		dB
Interchannel Phase Deviation			0		Degrees
Volume Control Step			0.375		dB
Volume Control Range			95.25		dB
De-emphasis Gain Error				±0.6	dB
Output Resistance at Each Pin			33		Ω
REFERENCE VOLTAGES					
Temperature Sensor Reference Voltage	TS_REF pin, AVDDx = 5.0 V		1.50		V
Common-Mode Reference Output	CM pin, AVDDx = 5.0 V	2.14	2.25	2.29	V
External Reference Voltage Source	CM pin, AVDDx = 5.0 V		2.25		V
TEMPERATURE SENSOR					
Temperature Accuracy		−3		+3	°C
Temperature Readout Range		−60		+140	°C
Temperature Readout Step Size			1		°C
Temperature Sample Rate		0.25		6	Hz
REGULATOR					
Input Supply Voltage	VSUPPLY pin	3.0	5	5.5	V
Regulated Output Voltage	VSENSE pin	2.26	2.50	2.59	V

[1] Functionally guaranteed at −40°C to +125°C case temperature.

Specifications guaranteed at AVDDx = 5 V and an ambient temperature of 105°C. Supply voltages = AVDDx = 5 V, DVDD = 2.5 V, ambient temperature[1] (T_A) = 105°C, unless otherwise noted.

Table 2.

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
DIGITAL-TO-ANALOG CONVERTERS					
Dynamic Range	20 Hz to 20 kHz, −60 dB input				
No Filter (RMS)		109	113.5		dB
With A-Weighted Filter (RMS)		110.5	116		dB
Total Harmonic Distortion + Noise	0 dBFS		−85		dB
	Two channels running −1 dBFS		−92.5		dB
	Eight channels running −1 dBFS		−92.5	−85	dB
Full-Scale Differential Output Voltage	AVDDx = 5.0 V		3.00 (±8.49)		V rms (V p-p)
Gain Error		−10		+10	%
Offset Error		−25	−6	+25	mV
Gain Drift		−30		+30	ppm/°C
Interchannel Isolation			100		dB
Interchannel Phase Deviation			0		Degrees
Volume Control Step			0.375		dB
Volume Control Range			95.25		dB
De-emphasis Gain Error				±0.6	dB
Output Resistance at Each Pin			33		Ω
REFERENCE					
Temperature Sensor Reference Voltage	TS_REF pin, AVDDx = 5.0 V		1.50		V
Common-Mode Reference Output	CM pin, AVDDx = 5.0 V	2.14	2.25	2.29	V
External Reference Voltage Source	CM pin, AVDDx = 5.0 V		2.25		V
REGULATOR					
Input Supply Voltage	VSUPPLY pin	3.0	5	5.5	V
Regulated Output Voltage	VSENSE pin	2.25	2.50	2.55	V

[1] Functionally guaranteed at −40°C to +125°C case temperature.

Specifications guaranteed at AVDDx = 3.3 V and an ambient temperature of 25°C. Supply voltages = AVDDx = 3.3 V, DVDD = 2.5 V, ambient temperature[1] (T_A) = 25°C, unless otherwise noted.

Table 3.

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
DIGITAL-TO-ANALOG CONVERTERS					
Dynamic Range	20 Hz to 20 kHz, −60 dB input				
No Filter (RMS)		109	111		dB
With A-Weighted Filter (RMS)		111.5	113.5		dB
Total Harmonic Distortion + Noise	0 dBFS		−90		dB
	Two channels running −1 dBFS		−97		dB
	Eight channels running −1 dBFS		−97	−85	dB
Full-Scale Differential Output Voltage	AVDDx = 3.3 V		2.00 (±5.66)		V rms (V p-p)
Gain Error		−10		+10	%
Offset Error		−25	−6	+25	mV
Gain Drift		−30		+30	ppm/°C
Interchannel Isolation			100		dB
Interchannel Phase Deviation			0		Degrees
Volume Control Step			0.375		dB
Volume Control Range			95.25		dB
De-Emphasis Gain Error				±0.6	dB
Output Resistance at Each Pin			33		Ω

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
REFERENCE					
Temperature Sensor Reference Voltage	TS_REF pin, AVDDx = 3.3 V		1.50		V
Common-Mode Reference Output	CM pin, AVDDx = 3.3 V	1.43	1.50	1.56	V
External Reference Voltage Source	CM pin, AVDDx = 3.3 V		1.50		V
REGULATOR					
Input Supply Voltage	VSUPPLY pin	3.0	5	5.5	V
Regulated Output Voltage	VSENSE pin	2.26	2.50	2.59	V

[1] Functionally guaranteed at −40°C to +125°C case temperature.

Specifications guaranteed at AVDDx = 3.3 V and an ambient temperature of 105°C. Supply voltages = AVDDx = 3.3 V, DVDD = 2.5 V, ambient temperature[1] (T_A) = 105°C, unless otherwise noted.

Table 4.

Parameter	Conditions/Comments	Min	Typ	Max	Unit
DIGITAL-TO-ANALOG CONVERTERS					
Dynamic Range	20 Hz to 20 kHz, −60 dB input				
No Filter (RMS)		108	109		dB
With A-Weighted Filter (RMS)		110	112		dB
Total Harmonic Distortion + Noise	0 dBFS		−85		dB
	Two channels running −1 dBFS		−92		dB
	Eight channels running −1 dBFS		−92	−83	dB
Full-Scale Differential Output Voltage	AVDDx = 3.3 V		2.00 (5.66)		V rms (V p-p)
Gain Error		−10		+10	%
Offset Error		−25	−6	+25	mV
Gain Drift		−30		+30	ppm/°C
Interchannel Isolation			100		dB
Interchannel Phase Deviation			0		Degrees
Volume Control Step			0.375		dB
Volume Control Range			95.25		dB
De-emphasis Gain Error				±0.6	dB
Output Resistance at Each Pin			33		Ω
REFERENCE					
Temperature Sensor Reference Voltage	TS_REF pin, AVDDx = 3.3 V		1.50		V
Common-Mode Reference Output	CM pin, AVDDx = 3.3 V	1.43	1.50	1.56	V
External Reference Voltage Source	CM pin, AVDDx = 3.3 V		1.50		V
REGULATOR					
Input Supply Voltage	VSUPPLY pin	3.0	5	5.5	V
Regulated Output Voltage	VSENSE pin	2.25	2.50	2.55	V

[1] Functionally guaranteed at −40°C to +125°C case temperature.

CRYSTAL OSCILLATOR SPECIFICATIONS

Table 5.

Parameter	Min	Typ	Max	Unit
Transconductance, T_A = 25°C	6.4	7 to 10	14	mmhos
Transconductance, T_A = 105°C	5.2	7.5 to 8.5	12	mmhos

DIGITAL INPUT/OUTPUT SPECIFICATIONS

−40°C < T_A < +105°C, IOVDD = 5.0 V and 3.3 V ± 10%.

Table 6.

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
High Level Input Voltage (VIH)	IOVDD = 5.0 V	3.7			V
	IOVDD = 3.3 V	2.5			V
Low Level Input Voltage (VIL)	IOVDD = 5.0 V			1.3	V
	IOVDD = 3.3 V			0.8	V
Input Leakage	I_{IH} at V_{IH} = 2.4 V			10	µA
	I_{IL} at V_{IL} = 0.8 V			10	µA
High Level Output Voltage (VOH)	I_{OH} = 1 mA	IOVDD − 0.60			V
Low Level Output Voltage (VOL)	I_{OL} = 1 mA			0.4	V
Input Capacitance				5	pF

POWER SUPPLY SPECIFICATIONS

Table 7.

Parameter	Test Conditions/Comments	Min	Typ	Max	Unit
SUPPLIES					
Voltage	AVDD	3.0	5.0	5.5	V
	DVDD	2.25	2.5	3.6	V
	PLLVDD	2.25	2.5	3.6	V
	IOVDD	3.0	5.0	5.5	V
	VSUPPLY	3.0	5.0	5.5	V
Analog Current—AVDD = 5.0 V					
Normal Operation			82		mA
Power-Down			1		µA
Analog Current—AVDD = 3.3 V					
Normal Operation			60		mA
Power-Down			1		µA
Digital Current—DVDD = 2.5 V					
Normal Operation	f_S = 48 kHz to 192 kHz		30		mA
Power-Down	No MCLK or I^2S		4		µA
PLL Current—PLLVDD = 2.5 V					
Normal Operation	f_S = 48 kHz to 192 kHz		5		mA
Power-Down			1		µA
IO Current—IOVDD = 3.3 V					
Normal Operation			4		mA
Power-Down			1		µA
QUIESCENT DISSIPATION—DITHER INPUT					
Operation	MCLK = 256 × f_S, 48 kHz				
All Supplies	AVDDx = 5.0 V, DVDD/PLLVDD = 2.5 V, IOVDD = 3.3 V		511		mW
All Supplies	AVDDx = 3.3 V, DVDD/PLLVDD = 2.5 V, IOVDD = 3.3 V		299		mW
Analog Supply	AVDDx = 5.0 V		410		mW
Analog Supply	AVDDx = 3.3 V		198		mW
Digital Supply	DVDD = 2.5 V		75		mW
PLL Supply	PLLVDD= 2.5 V		13		mW
I/O Supply	IOVDD = 3.3 V		13		mW
Power-Down, All Supplies			0		mW
POWER SUPPLY REJECTION RATIO					
Signal at Analog Supply Pins	1 kHz, 200 mV p-p		85		dB
	20 kHz, 200 mV p-p		85		dB

DIGITAL FILTERS

Table 8.

Parameter	Mode	Factor	Min	Typ	Max	Unit
DAC INTERPOLATION FILTER						
Pass Band	48 kHz mode, typical at 48 kHz	$0.4535 \times f_S$		22		kHz
	96 kHz mode, typical at 96 kHz	$0.3646 \times f_S$	35			kHz
	192 kHz mode, typical at 192 kHz	$0.3646 \times f_S$		70		kHz
Pass-Band Ripple	48 kHz mode, typical at 48 kHz				±0.01	dB
	96 kHz mode, typical at 96 kHz				±0.05	dB
	192 kHz mode, typical at 192 kHz				±0.1	dB
Transition Band	48 kHz mode, typical at 48 kHz	$0.5 \times f_S$		24		kHz
	96 kHz mode, typical at 96 kHz	$0.5 \times f_S$		48		kHz
	192 kHz mode, typical at 192 kHz	$0.5 \times f_S$		96		kHz
Stop Band	48 kHz mode, typical at 48 kHz	$0.5465 \times f_S$		26		kHz
	96 kHz mode, typical at 96 kHz	$0.6354 \times f_S$		61		kHz
	192 kHz mode, typical at 192 kHz	$0.6354 \times f_S$		122		kHz
Stop-Band Attenuation	48 kHz mode, typical at 48 kHz		68			dB
	96 kHz mode, typical at 96 kHz		68			dB
	192 kHz mode, typical at 192 kHz		68			dB
Propagation Delay	48 kHz mode, typical at 48 kHz	$25/f_S$		521		µs
	96 kHz mode, typical at 96 kHz	$11/f_S$		115		µs
	192 kHz mode, typical at 192 kHz	$8/f_S$		42		µs
	192 kHz low delay mode, typical at 192 kHz	$2/f_S$		10		µs

TIMING SPECIFICATIONS

$-40°C < T_A < +105°C$, DVDD = 2.5 V ± 10%.

Table 9.

Parameter	Description	Min	Typ	Max	Unit
INPUT MASTER CLOCK (MCLK) AND RESET					
t_{MH}	MCLK duty cycle, DAC clock source = PLL clock at $256 \times f_S$, $384 \times f_S$, $512 \times f_S$, and $768 \times f_S$	40		60	%
t_{MH}	DAC clock source = direct MCLK at $512 \times f_S$ (bypass on-chip PLL)	40		60	%
f_{MCLK}	MCLKI frequency, PLL mode	6.9		40.5	MHz
f_{MCLK}	Direct MCLK $512 \times f_S$ mode			27.1	MHz
f_{BCLK}	DBCLK frequency, PLL mode			27.0	MHz
t_{PDR}	Low	15			ns
t_{PDRR}	Recovery, reset to active output	300			ms
PLL					
Lock Time	MCLK input			10	ms
Lock Time	DLRCLK input			50	ms
$256 \times f_S$ VCO Clock, Output Duty Cycle, MCLKO Pin		40		60	%
SPI PORT	See Figure 14				
t_{CCH}	CCLK high	35			ns
t_{CCL}	CCLK low	35			ns
f_{CCLK}	CCLK frequency, $f_{CCLK} = 1/t_{CCP}$; only t_{CCP} shown in Figure 14			10	MHz
t_{CDS}	CDATA setup, time to CCLK rising	10			ns
t_{CDH}	CDATA hold, time from CCLK rising	10			ns
t_{CLS}	$\overline{\text{CLATCH}}$ setup, time to CCLK rising	10			ns
t_{CLH}	$\overline{\text{CLATCH}}$ hold, time from CCLK falling	10			ns
t_{CLHIGH}	$\overline{\text{CLATCH}}$ high, not shown in Figure 14	10			ns

Parameter	Description	Min	Typ	Max	Unit
t_{COE}	COUT enable from CCLK falling			30	ns
t_{COD}	COUT delay from CCLK falling			30	ns
t_{COH}	COUT hold from CCLK falling, not shown in Figure 14	30			ns
t_{COTS}	COUT tristate from CCLK falling			30	ns
I^2C	See Figure 2 and Figure 13				
f_{SCL}	SCL clock frequency			400	kHz
t_{SCLL}	SCL low	1.3			µs
t_{SCLH}	SCL high	0.6			µs
t_{SCS}	Setup time (start condition), relevant for repeated start condition	0.6			µs
t_{SCH}	Hold time (start condition), first clock generated after this period	0.6			µs
t_{SSH}	Setup time (stop condition)	0.6			µs
t_{DS}	Data setup time	100			ns
t_{SR}	SDA and SCL rise time			300	ns
t_{SF}	SDA and SCL fall time			300	ns
t_{BFT}	Bus-free time between stop and start	1.3			µs
DAC SERIAL PORT	See Figure 16				
t_{DBH}	DBCLK high, slave mode	10			ns
t_{DBL}	DBCLK low, slave mode	10			ns
t_{DLS}	DLRCLK setup, time to DBCLK rising, slave mode	10			ns
t_{DLH}	DLRCLK hold from DBCLK rising, slave mode	5			ns
t_{DLS}	DLRCLK skew from DBCLK falling, master mode	−8		+8	ns
t_{DDS}	DSDATAx setup to DBCLK rising	10			ns
t_{DDH}	DSDATAx hold from DBCLK rising	5			ns




Figure 2. I^2C Timing Diagram

ABSOLUTE MAXIMUM RATINGS

Table 10.

Parameter	Rating
Analog (AVDD)	−0.3 V to +5.5 V
I/O (IOVDD)	−0.3 V to +5.5 V
Digital (DVDD)	−0.3 V to +3.6 V
PLL (PLLVDD)	−0.3 V to +3.6 V
VSUPPLY	−0.3 V to +6.0 V
Input Current (Except Supply Pins)	±20 mA
Analog Input Voltage (Signal Pins)	−0.3 V to AVDD + 0.3 V
Digital Input Voltage (Signal Pins)	−0.3 V to IOVDD + 0.3 V
Operating Temperature Range (Case)	−40°C to +125°C
Storage Temperature Range	−65°C to +150°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

THERMAL RESISTANCE

θ_{JA} represents junction-to-ambient thermal resistance; θ_{JC} represents the junction-to-case thermal resistance. All characteristics are for a 4-layer board with a solid ground plane.

Table 11. Thermal Resistance

Package Type	θ_{JA}	θ_{JC}	Unit
80-Lead LQFP	42.3	10.0	°C/W

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

PIN CONFIGURATION AND FUNCTION DESCRIPTIONS




Figure 3. Pin Configuration

Table 12. Pin Function Descriptions

Pin No.	Type[1]	Mnemonic	Description
1	I	DAC_BIAS3	DAC Bias 3. AC couple with 470 nF to AGND3.
2	I	DAC_BIAS4	DAC Bias 4. AC couple with 470 nF to AVDD3.
3	PWR	AVDD3	Analog Power.
4	O	DAC13P	DAC13 Positive Output.
5	O	DAC13N	DAC13 Negative Output.
6	O	DAC14P	DAC14 Positive Output.
7	O	DAC14N	DAC14 Negative Output.
8	O	DAC15P	DAC15 Positive Output.
9	O	DAC15N	DAC15 Negative Output.
10	O	DAC16P	DAC16 Positive Output.
11	O	DAC16N	DAC16 Negative Output.
12	PWR	AVDD4	Analog Power.
13	GND	AGND4	Analog Ground.
14	GND	PLLGND	PLL Ground.
15	O	LF	PLL Loop Filter, Reference to PLLVDD.
16	PWR	PLLVDD	Apply 2.5 V to power PLL.
17	I	MCLKI/XTALI	Master Clock Input, Input to Crystal Inverter.
18	O	XTALO	Output from Crystal Inverter.
19	O	MCLKO	Master Clock Output.
20, 29, 41	PWR	DVDD	Digital Power, 2.5 V.
21, 26, 30, 40	GND	DGND	Digital Ground.

Pin No.	Type[1]	Mnemonic	Description
22, 39	PWR	IOVDD	Power for Digital Input and Output Pins, 3.3 V to 5 V.
23	I	VSENSE	2.5 V Output of Regulator, Collector of Pass Transistor. Bypass with 10 µF in parallel with 100 nF.
24	O	VDRIVE	Drive for Base of Pass Transistor.
25	I	VSUPPLY	5 V Input to Voltage Regulator, Emitter of Pass Transistor. Bypass with 10 µF in parallel with 100 nF.
27	I/O	DBCLK	Bit Clock for DACs.
28	I/O	DLRCLK	Frame Clock for DACs.
31	I	DSDATA8/SA	DAC15 and DAC 16 Serial Data Input/SA_MODE TDM State (see the Standalone Mode section, Table 15, and Table 16).
32	I	DSDATA7/SA	DAC13 and DAC 14 Serial Data Input/SA_MODE TDM State (see the Standalone Mode section, Table 15, and Table 16).
33	I	DSDATA6	DAC11 and DAC 12 Serial Data Input.
34	I	DSDATA5	DAC9 and DAC 10 Serial Data Input.
35	I	DSDATA4	DAC7 and DAC 8 Serial Data Input.
36	I	DSDATA3	DAC5 and DAC 6 Serial Data Input.
37	I	DSDATA2	DAC3 and DAC 4 Serial Data Input.
38	I	DSDATA1	DAC1 and DAC 2 Serial Data Input.
42	I	CDATA/ADDR1/SA	Control Data Input (SPI)/Address 1 (I^2C)/SA_MODE State (see the Standalone Mode section and Table 15).
43	I/O	COUT/SDA/SA	Control Data Output (SPI)/Control Data Input (I^2C)/SA_MODE State (see the Standalone Mode section and Table 15).
44	I	CCLK/SCL/SA	Control Clock Input (SPI)/Control Clock Input (I^2C)/SA_MODE State (see the Standalone Mode section and Table 15).
45	I	$\overline{\text{CLATCH}}$/ADDR0/SA	Control Chip Select (SPI) (Low Active)/Address 0 (I^2C)/SA_MODE State (see the Standalone Mode section and Table 15).
46	I	SA_MODE	Standalone Mode. This pin allows mode control of ADAU1966 using Pin 42 to Pin 45, Pin 31, and Pin 32 (high active, see Table 15 and Table 16).
47	I	PU/$\overline{\text{RST}}$	Power-Up/Reset (Low Active).
48	GND	AGND1	Analog Ground.
49	PWR	AVDD1	Analog Power.
50	O	DAC1P	DAC1 Positive Output.
51	O	DAC1N	DAC1 Negative Output.
52	O	DAC2P	DAC2 Positive Output.
53	O	DAC2N	DAC2 Negative Output.
54	O	DAC3P	DAC3 Positive Output.
55	O	DAC3N	DAC3 Negative Output.
56	O	DAC4P	DAC4 Positive Output.
57	O	DAC4N	DAC4 Negative Output.
58	PWR	AVDD2	Analog Power.
59	I	DAC_BIAS1	DAC Bias 1. AC couple with 470 nF to AVDD2.
60	I	DAC_BIAS2	DAC Bias 2. AC couple with 470 nF to AGND2.
61	GND	AGND2	Analog Ground.
62	O	CM	Common-Mode Reference Filter Capacitor Connection. Bypass with 10 µF in parallel with 100 nF to AGND2. This reference can be shut off in the PLL_CLK_CTRL1 register and the pin can be driven with an outside voltage source.
63	O	TS_REF	Voltage Reference Filter Capacitor Connection. Bypass with 10 µF in parallel with 100 nF to AGND2.
64	O	DAC5P	DAC5 Positive Output.
65	O	DAC5N	DAC5 Negative Output.
66	O	DAC6P	DAC6 Positive Output.
67	O	DAC6N	DAC6 Negative Output.
68	O	DAC7P	DAC7 Positive Output.
69	O	DAC7N	DAC7 Negative Output.
70	O	DAC8P	DAC8 Positive Output.

Pin No.	Type[1]	Mnemonic	Description
71	O	DAC8N	DAC8 Negative Output.
72	O	DAC9P	DAC9 Positive Output.
73	O	DAC9N	DAC9 Negative Output.
74	O	DAC10P	DAC10 Positive Output.
75	O	DAC10N	DAC10 Negative Output.
76	O	DAC11P	DAC11 Positive Output.
77	O	DAC11N	DAC11 Negative Output.
78	O	DAC12P	DAC12 Positive Output.
79	O	DAC12N	DAC12 Negative Output.
80	GND	AGND3	Analog Ground.

[1] I = input, O = output, I/O = input/output, PWR = power, GND = ground.

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 4. DAC Pass-Band Filter Response, 48 kHz




Figure 5. DAC Stop-Band Filter Response, 48 kHz




Figure 6. DAC Pass-Band Filter Response, 96 kHz




Figure 7. DAC Stop-Band Filter Response, 96 kHz

APPLICATION CIRCUITS

Typical application circuits are shown in Figure 8 to Figure 11. Recommended loop filters for DLRCLK and MCLKI/XTALI modes of the PLL reference are shown in Figure 8. Output filters for the DAC outputs are shown in Figure 9 and Figure 10, and an external regulator circuit is shown in Figure 11.




Figure 8. Recommended Loop Filters for DLRCLK or MCLKI/XTALI PLL Reference Modes




Figure 9. Typical DAC Output Passive Filter Circuit (Differential)




Figure 10. Typical DAC Output Active Filter Circuit (Differential)




Figure 11. Recommended 2.5 V Regulator Circuit

THEORY OF OPERATION

DIGITAL-TO-ANALOG CONVERTERS (DACS)

The 16 ADAU1966 digital-to-analog converter (DAC) channels are differential for improved noise and distortion performance and are voltage output for simplified connection. The DACs include on-chip digital interpolation filters with 68 dB stop-band attenuation and linear phase response, operating at an over-sampling ratio of 256× (48 kHz range), 128× (96 kHz range), or 64× (192 kHz range). Each channel has its own independently programmable attenuator, adjustable in 255 steps in increments of 0.375 dB. Digital inputs are supplied through eight serial data input pins (two channels on each pin), a common frame clock (DLRCLK), and a bit clock (DBCLK). Alternatively, any one of the TDM modes can be used to access up to 16 channels on a single TDM data line.

The ADAU1966 has a low propagation delay mode; this mode is an option for an f_S of 192 kHz and is enabled in Register DAC_CTRL0[2:1]. By setting these bits to b11, the propagation delay is reduced by the amount shown in Table 8. The shorter delay is achieved by reducing the amount of digital filtering; the negative impact of selecting this mode is reduced audio frequency response and increased out-of-band energy.

When AVDD is supplied with 5 V, each analog output pin has a nominal common-mode (CM) dc level of 2.25 V and swings ±8.49 V p-p (3 V rms differential) from a 0 dBFS digital input signal. An AVDD of 3.3 V generates a CM dc voltage of 1.5 V and allows differential audio swings of ±5.66 V p-p (2 V rms) from a 0 dBFS digital input signal. The differential analog outputs require only a single-order passive differential RC filter to provide the specified DNR performance; see Figure 9 for an example filter. The outputs can easily drive differential inputs on a separate PCB through cabling as well as differential inputs on the same PCB.

If more signal level is required or if a more robust filter is needed, a single op amp gain stage designed as a second-order, low-pass Bessel filter can be used to remove the high frequency out-of-band noise present on each pin of the differential outputs. The choice of components and design of this circuit is critical to yield the full DNR of the DACs (see the recommended passive and active circuits in Figure 9 and Figure 10). This filter can be built into an active difference amplifier to provide a single-ended output with gain, if necessary. Note that the use of op amps with low slew rate or low bandwidth can cause high frequency noise and tones to fold down into the audio band; exercise care when selecting these components.

The ADAU1966 offers control over the analog performance of the DACs; it is possible to program the registers to reduce the power consumption with the trade-off of lower SNR and THD + N. The reduced power consumption is the result of changing the internal bias current to the analog output amplifiers.

Register DAC_POWER1 to Register DAC_POWER4 present four basic settings for the DAC power vs. performance in each of the 16 channels: best performance, good performance, low power, and lowest power. Alternatively, in Register PLL_CLK_CTRL1[7:6], the LOPWR_MODE bits offer global control over the power and performance for all 16 channels. The default setting is b00. This setting allows the channels to be controlled individually using the DAC_POWERx registers. Setting b10 and Setting b11 select the low power and lowest power settings. The data presented in Table 13 shows the result of setting all 16 channels to each of the four settings. The SNR and THD + N specifications are shown in relation to the measured performance of a device at the best performance setting.

The voltage at CM, the common-mode reference pin, can be used to bias the external op amps that buffer the output signals (see the Power Supply and Voltage Reference section).

CLOCK SIGNALS

Upon powering the ADAU1966 and asserting the PU/$\overline{\text{RST}}$ pin high, the part starts in either standalone mode (SA_MODE) or program mode, depending on the state of SA_MODE (Pin 46). The clock functionality of SA_MODE is described in the Standalone Mode section. In program mode, the default for the ADAU1966 is for the MCLKO pin to feed a buffered output of the MCLKI signal. The default for the DLRCLK and DBCLK ports is slave mode; the DAC must be driven with a coherent set of MCLK, LRCLK, and BCLK signals to function.

The MCLKO pin can be programmed to provide different clock signals using Register Bits PLL_CLK_CTRL1[5:4]. The default, b10, provides a buffered copy of the clock signal that is driving the MCLKI pin. Two modes, b00 and b01, provide low jitter clock signals. The b00 setting yields a clock rate between 4 MHz and 6 MHz, and b01 yields a clock rate between 8 MHz and 12 MHz. Both of these clock frequencies are scaled as ratios of MCLK automatically inside the ADAU1966. As an example, an MCLK of 8.192 MHz and a setting of b00 yield an MCLKO of (8.192/2) = 4.096 MHz. Alternatively, an MCLK of 36.864 MHz and a setting of b01 yield an MCLKO frequency of (36.864/3) = 12.288 MHz. The setting b11 shuts off the MCLKO pin.

Table 13. DAC Power vs. Performance

Register Setting	Best Performance	Good Performance	Low Power	Lowest Power
Total AVDD Current	82 mA	73 mA	64 mA	54 mA
SNR	Reference	−0.2 dB	−1.5 dB	−14.2 dB
THD + N (−1 dbFS signal)	Reference	−1.8 dB	−3.0 dB	−5.8 dB

After the PU/$\overline{\text{RST}}$ pin has been asserted high, the PLL_CLK_CTRLx registers (0x00 and 0x01) can be programmed. The on-chip phase-locked loop (PLL) can be selected to use the clock appearing at the MCLKI/XTALI pin at a frequency of 256, 384, 512, or 768 times the sample rate (f_S), referenced to the 48 kHz mode from the master clock select (MCS) setting, as described in Table 14. In 96 kHz mode, the master clock frequency stays at the same absolute frequency; therefore, the actual multiplication rate is divided by 2. In 192 kHz mode, the actual multiplication rate is divided by 4. For example, if the ADAU1966 is programmed in 256 × f_S mode, the frequency of the master clock input is 256 × 48 kHz = 12.288 MHz. If the ADAU1966 is then switched to 96 kHz operation (by writing to DAC_CTRL0 [2:1]), the frequency of the master clock should remain at 12.288 MHz, which is 128 × f_S in this example. In 192 kHz mode, MCS becomes 64 × f_S.

The internal clock for the digital core varies by mode: 512 × f_S (48 kHz mode), 256 × f_S (96 kHz mode), or 128 × f_S (192 kHz mode). By default, the on-board PLL generates this internal master clock from an external clock.

The PLL should be powered and stable before the ADAU1966 is used as a source for quality audio. The PLL is enabled by reset and does not require writing to the I^2C or SPI port for normal operation.

With the PLL enabled, the performance of the ADAU1966 is not affected by jitter as high as a 300 ps rms time interval error (TIE). If the internal PLL is not used, it is best to use an independent crystal oscillator to generate the master clock.

If the ADAU1966 is to be used in direct MCLK mode, the PLL can be powered down in the PDN_THRMSENS_CTRL_1 register. For direct MCLK mode, a 512 × f_S (referenced to 48 kHz mode) master clock must be used as MCLK, and the CLK_SEL bit in the PLL_CLK_CTRL1 register must be set to b1.

The ADAU1966 PLL can also be programmed to run from an external LRCLK. When the PLLIN bits in the PLL_CLK_CTRL0 register are set to 01 and the appropriate loop filter is connected to the LF pin (see Figure 8), the ADAU1966 PLL generates all of the necessary internal clocks for operation with no external MCLK. This mode reduces the number of high frequency signals in the design, reducing EMI emissions.

It is possible to further reduce EMI emissions of the circuit by using the internal DBCLK generation setting of the BCLK_GEN bit in the DAC_CTRL1 register. With the BCLK_GEN bit set to b1 (internal) and the SAI_MS bit set to b0 (slave), the ADAU1966 generate its own DBCLK; this works with the PLL input set to either MCLKI/XTALI or DLRCLK. DLRCLK is the only required clock in DLRCLK PLL mode.

POWER-UP AND $\overline{\text{RST}}$

Power sequencing for the ADAU1966 should start with AVDD and IOVDD, followed by DVDD. It is very important that AVDD be settled at a regulated voltage and that IOVDD be within 10% of regulated voltage before applying DVDD. When using the ADAU1966 internal regulator, this timing occurs by default.

To guarantee proper startup, the PU/$\overline{\text{RST}}$ pin should be pulled low by an external resistor and then driven high after the power supplies have stabilized. The PU/$\overline{\text{RST}}$ can also be pulled high using a simple RC network.

Driving the PU/$\overline{\text{RST}}$ pin low puts the part into a very low power state (<3 µA). All functionality of the ADAU1966 is disabled until the PU/$\overline{\text{RST}}$ pin is asserted high. Once this pin is asserted high, the ADAU1966 requires 300 ms to stabilize. The MMUTE bit in the DAC_CTRL0 register must be toggled for operation.

The PUP bit in the PLL_CLK_CTRL0 register can be used to power down the ADAU1966. Engaging the master power-down puts the ADAU1966 in an idle state while maintaining the settings of all registers. Additionally, the power-down bits in the PDN_THRMSENS_CTRL1 register (TS_PDN, PLL_PDN, and VREG_PDN) can be used to power down individual sections of the ADAU1966.

The SOFT_RST bit in the PLL_CLK_CTRL0 register sets all of the control registers to their default settings while maintaining the internal clocks in default mode. The SOFT_RST bit does not power down the analog outputs; toggling this bit does not cause audible popping sounds at the differential analog outputs.

Proper startup of the ADAU1966 should proceed as follows:

1. Apply power to the ADAU1966 as described previously.
2. Assert the PU/$\overline{\text{RST}}$ pin high after power supplies have stabilized.
3. Set the PUP bit to b1.
4. Program all necessary registers for the desired settings.
5. Set the MMUTE bit to b0 to unmute all channels.

Table 14. MCS and f_S Modes

Sample Rate Select (FS) DAC_CTRL0[2:1]	Master Clock Select (MCS), PLL_CLK_CTRL0[2:1]							
	Setting 0, b00		Setting 1, b01		Setting 2, b10		Setting 3, b11	
	Ratio	MCLK (MHz)	Ratio	MCLK	Ratio	MCLK	Ratio	MCLK
32 kHz, b00	256 × f_S	8.192	384 × f_S	12.288	512 × f_S	16.384	768 × f_S	24.576
44.1 kHz, b00	256 × f_S	11.2896	384 × f_S	16.9344	512 × f_S	22.5792	768 × f_S	33.8688
48 kHz, b00	256 × f_S	12.288	384 × f_S	18.432	512 × f_S	24.576	768 × f_S	36.864
64 kHz, b01	128 × f_S	8.192	192 × f_S	12.288	256 × f_S	16.384	384 × f_S	24.576
88.2 kHz, b01	128 × f_S	11.2896	192 × f_S	16.9344	256 × f_S	22.5792	384 × f_S	33.8688
96 kHz, b01	128 × f_S	12.288	192 × f_S	18.432	256 × f_S	24.576	384 × f_S	36.864
128 kHz, b10 or b11	64 × f_S	8.192	96 × f_S	12.288	128 × f_S	16.384	192 × f_S	24.576
176.4 kHz, b10 or b11	64 × f_S	11.2896	96 × f_S	16.9344	128 × f_S	22.5792	192 × f_S	33.8688
192 kHz, b10 or b11	64 × f_S	12.288	96 × f_S	18.432	128 × f_S	24.576	192 × f_S	36.864

STANDALONE MODE

The ADAU1966 can operate without a typical I²C or SPI connection to a microcontroller. This standalone mode is made available by setting the SA_MODE (Pin 46) to high (IOVDD). All registers are set to default except the options shown in Table 15.

Table 15. SA_MODE Settings

Pin No.	Setting	Function
42	0	Master mode serial audio interface (SAI)
	1	Slave mode SAI
43	0	MCLK = 256 × f_S, PLL on
	1	MCLK = 384 × f_S, PLL on
44	0	AVDD = 5.0 V (CM = 2.25 V)
	1	AVDD = 3.3 V (CM = 1.50 V)
45	0	I²S SAI format
	1	TDM modes, determined by Pin 31 and Pin 32

When both SA_MODE and Pin 45 are set high, TDM mode is selected. Table 16 shows the available TDM modes; these modes are set by connecting Pin 31 (DSDATA8) and Pin 32 (DSDATA7) to GND or IOVDD.

Table 16. TDM Modes

Pin No.	Setting	Function
32:31	00	TDM4—DLRCLK pulse
	01	TDM8—DLRCLK pulse
	10	TDM16—DLRCLK pulse
	11	TDM8—DLRCLK 50% duty cycle

When the ADAU1966 is powered up in SA_MODE and the PU/$\overline{\text{RST}}$ pin is asserted high, the MCLKO pin provides a buffered version of the MCLKI pin, whether the source is a crystal or an active oscillator.

I²C CONTROL PORT

The ADAU1966 has an I²C-compatible control port that permits programming and reading back of the internal control registers for the DACs and clock system. The I²C interface of the ADAU1966 is a 2-wire interface consisting of a clock line, SCL, and a data line, SDA. SDA is bidirectional, and the ADAU1966 drives SDA either to acknowledge the master (ACK) or to send data during a read operation. The SDA pin for the I²C port is an open-drain collector and requires a 2 kΩ pull-up resistor. A write or read access occurs when the SDA line is pulled low while the SCL line is high, indicated by a start in Figure 12 and Figure 13. SDA is only allowed to change when SCL is low except when a start or stop condition occurs, as shown in Figure 12 and Figure 13. The first eight bits of the data-word consist of the device address and the R/$\overline{\text{W}}$ bit. The device address consists of an internal built-in address (0x04) and two address pins, ADDR1 and ADDR0. The two address bits allow four ADAU1966 devices to be used in a system. Initiating a write operation to the ADAU1966 involves sending a start condition and then sending the device address with the R/$\overline{\text{W}}$ bit set low. The ADAU1966 responds by issuing an acknowledge to indicate that it has been addressed. The user then sends a second frame telling the ADAU1966 which register is required to be written. Another acknowledge is issued by the ADAU1966. Finally, the user can send another frame with the eight data bits required to be written to the register. A third acknowledge is issued by the ADAU1966 after which the user can send a stop condition to complete the data transfer.

A read operation requires that the user first write to the ADAU1966 to point to the correct register and then read the data. This is achieved by sending a start condition followed by the device address frame, with the R/$\overline{\text{W}}$ bit low, and then the register address frame. Following the acknowledge from the ADAU1966, the user must issue a repeated start condition. The next frame is the device address with the R/$\overline{\text{W}}$ bit set high. On the next frame, the ADAU1966 outputs the register data on the SDA line. A stop condition completes the read operation.

Table 17. I²C Addresses

ADDR1	ADDR0	Slave Address
0	0	0x04
0	1	0x24
1	0	0x44
1	1	0x64




Figure 12. I²C Write Format




Figure 13. I²C Read Format

Table 18. I²C Abbreviations

Abbreviation	Condition
S	Start bit
P	Stop bit
AM	Acknowledge by master
AS	Acknowledge by slave

Table 19. Single Word I²C Write

S	Chip Address, R/$\overline{W}$ = 0	AS	Register Address	AS	Data-Word	AS	P

Table 20. Burst Mode I²C Write

S	Chip Address, R/$\overline{W}$ = 0	AS	Register Address	AS	Data-Word 1	AS	Data-Word 2	AS	Data-Word N	AS	P

Table 21. Single Word I²C Read

S	Chip Address, R/$\overline{W}$ = 0	AS	Register Address	AS	S	Chip Address, R/$\overline{W}$ = 1	AS	Data-Word	AM	P

Table 22. Burst Mode I²C Read

S	Chip Address, R/$\overline{W}$ = 0	AS	Register Address	AS	S	Chip Address, R/$\overline{W}$ = 1	AS	Data-Word 1	AM	Data-Word 2	AM	Data-Word N	AM	P

SERIAL CONTROL PORT: SPI CONTROL MODE

The ADAU1966 has an SPI control port that permits programming and reading back of the internal control registers for the DACs and clock system. A standalone mode is also available for operation without serial control; it is configured at reset using the SA_MODE pin. See the Standalone Mode section for details about SA_MODE.

By default, the ADAU1966 is in I²C mode, but it can be put into SPI control mode by pulling $\overline{\text{CLATCH}}$ low three times. This is done by performing three dummy writes to the SPI port (the ADAU1966 does not acknowledge these three writes). Beginning with the fourth SPI write, data can be written to or read from the IC. The ADAU1966 can be taken out of SPI control mode only by a full reset initiated by power cycling the IC.

The SPI control port of the ADAU1966 is a 4-wire serial control port. The format is similar to the Motorola SPI format except the input data-word is 24 bits wide. The serial bit clock and latch can be completely asynchronous to the sample rate of the DACs. Figure 14 shows the format of the SPI signal. The first byte is a global address with a read/write bit. For the ADAU1966, the address is 0x06, shifted left one bit due to the R/$\overline{\text{W}}$ bit. The second byte is the ADAU1966 register address, and the third byte is the data.

POWER SUPPLY AND VOLTAGE REFERENCE

The ADAU1966 is designed for 3.3 V or 5 V analog and 2.5 V digital supplies. To minimize noise pickup, the power supply pins should be bypassed with 100 nF ceramic chip capacitors placed as close to the pins as possible. A bulk aluminum electrolytic capacitor of at least 22 µF should also be provided for each rail on the same PC board as the codec. It is important that the analog supply be as clean as possible.

The ADAU1966 includes a 2.5 V regulator driver that requires only an external pass transistor and bypass capacitors to make a 2.5 V regulator from a 5 V or 3.3 V supply. The VSUPPLY and VSENSE pins should be decoupled with no more than 10 µF, in parallel with 100 nF high frequency bypassing. If the regulator driver is not used, connect VSUPPLY and VDRIVE to GND and leave VSENSE unconnected.

All digital inputs are compatible with TTL and CMOS levels. All outputs are driven from the 3.3 V or 5 V IOVDD supply and are compatible with TTL and 3.3 V CMOS levels.

The temperature sensor internal voltage reference (V_{TS_REF}) is brought out on the TS_REF pin and should be bypassed as close as possible to the chip with a parallel combination of 10 µF and 100 nF.

The internal band gap reference can be disabled in the PLL_CLK_CTRL1 register by setting VREF_EN to 0; the CM pin can be then be driven from an external source. This can be used to scale the DAC output to the clipping level of a power amplifier based on its power supply voltage.

The CM pin is the internal common-mode reference. It should be bypassed as close as possible to the chip, with a parallel combination of 10 µF and 100 nF. This voltage can be used to bias external op amps to the common-mode voltage of the analog input and output signal pins. The output current should be limited to less than 0.5 mA source and 2 mA sink.

SERIAL DATA PORTS—DATA FORMAT

The 16 DAC channels use a common serial bit clock (DBCLK) and a common left-right framing clock (DLRCLK) in the serial data port. The clock signals are all synchronous with the sample rate. The normal stereo serial modes are shown in Figure 15.

The DAC serial data mode defaults to I²S (1 BCLK delay) upon power-up and reset. The ports can also be programmed for left-justified and right-justified (24-bit and 16-bit) operation using DAC_CTRL0[7:6]. Stereo and TDM modes can be selected using DAC_CTRL0[5:3]. The polarity of DBCLK and DLRCLK is programmable according to the DAC_CTRL1[1] and DAC_CTRL1[5] bits. The serial ports are programmable as the clock masters according to the DAC_CTRL1[0] bit. By default, the serial port is in slave mode.

TIME-DIVISION MULTIPLEXED (TDM) MODES

The ADAU1966 serial ports also have several different TDM serial data modes. The ADAU1966 can support a single data line TDM16, a dual data line (TDM8), a quad data line (TDM4), or eight data lines (TDM2). The DLRCLK can be operated in both single-cycle pulse mode and a 50% duty cycle mode. Both 16 DBCLKs or 32 DBCLKs per channel are selectable for each mode.

The I/O pins of the serial ports are defined according to the serial mode that is selected. For a detailed description of the function of each pin in TDM and stereo modes, see Table 23.




Figure 14. Format of the SPI Signal

TEMPERATURE SENSOR

The ADAU1966 has an on-board temperature sensor that allows the user to read the temperature of the silicon inside the part. The temperature sensor readout has a range of −60°C to +140°C in 1°C steps. The PDN_THRMSENS_CTRL_1 register controls the settings of the sensor. The temperature sensor is powered on by default and can be shut off by setting the TS_PDN[2] bit to b1 in PDN_THRMSENS_CTRL_1. The temperature sensor can be run in either continuous operation or one-shot mode. The temperature sensor conversion mode is modified using Bit 5, THRM_MODE; the default is THRM_MODE = 1, one-shot mode. In one-shot mode, writing a 0 followed by writing a 1 to Bit 4, THRM_GO, results in a single reset and temperature conversion, placing the resulting temperature data in the THRM_TEMP_STAT register. In continuous operation mode, the data conversion takes place at a rate set by Bits[7:6], THRM_RATE, with a range of 0.5 sec to 4 sec between samples. Faster rates are possible using the one-shot mode.

Once a temperature conversion has been placed in the THRM_TEMP_STAT register, the data can be translated into degrees Celsius (°C) using the following steps:

1. Convert the binary or hexadecimal data read from THRM_TEMP_STAT into decimal form.
2. Subtract 60 from the converted THRM_TEMP_STAT data; this is the temperature of the silicon in °C.




Figure 15. Serial Audio Modes




Figure 16. DAC Serial Timing

Table 23. Pin Function Changes in Different Serial Audio Interface Modes

Signal	Stereo Modes (SAI = 0 or 1)	TDM4 Mode (SAI = 2)	TDM8 Mode (SAI = 3)	TDM16 Mode (SAI = 4)
DSDATA1	Channel 1/Channel 2 data in	Channel 1 to Channel 4 data in	Channel 1 to Channel 8 data in	Channel 1 to Channel 16 data in
DSDATA2	Channel 3/Channel 4 data in	Channel 5 to Channel 8 data in	Channel 9 to Channel 16 data in	Not used
DSDATA3	Channel 5/Channel 6 data in	Channel 9 to Channel 12 data in	Not used	Not used
DSDATA4	Channel 7/Channel 8 data in	Channel 13 to Channel 16 data in	Not used	Not used
DSDATA5	Channel 9/Channel 10 data in	Not used	Not used	Not used
DSDATA6	Channel 11/Channel 12 data in	Not used	Not Used	Not used
DSDATA7	Channel 13/Channel 14 data in	Not used	Not used	Not used
DSDATA8	Channel 15/Channel 16 data in	Not used	Not used	Not used
DLRCLK	DLRCLK in/DLRCLK out	TDM frame sync in/ TDM frame sync out	TDM frame sync in/ TDM frame sync out	TDM frame sync in/ TDM frame sync out
DBCLK	DBCLK in/DBCLK out	TDM DBCLK in/TDM DBCLK out	TDM DBCLK in/TDM DBCLK out	TDM DBCLK in/ TDM DBCLK out
Maximum Sample Rate	192 kHz	192 kHz	96 kHz	48 kHz

ADDITIONAL MODES

The ADAU1966 offers several additional modes for board level design enhancements. To reduce the EMI in board level design, serial data can be transmitted without an explicit DBCLK. See Figure 17 for an example of a DAC TDM data transmission mode that does not require a high speed DBCLK or an external MCLK. This configuration is applicable when the ADAU1966 master clock is generated by the PLL with the DLRCLK as the PLL reference frequency.

To relax the requirement for the setup time of the ADAU1966 in cases of high speed TDM data transmission, the ADAU1966 can latch in the data using the falling edge of DBCLK; see the BCLK_EDGE bit in the DAC_CTRL1 register. This effectively dedicates the entire BCLK period to the setup time. This mode is useful in cases where the source has a large delay time in the serial data driver. Figure 18 shows this inverted DBCLK mode of data transmission.




Figure 17. Serial DAC Data Transmission in TDM Format Without DBCLK (Applicable Only If PLL Locks to DLRCLK)




Figure 18. Inverted DBCLK Mode in DAC Serial Data Transmission (Applicable in Stereo and TDM, Useful for High Frequency TDM Transmission)

REGISTER SUMMARY

Table 24. ADAU1966 Register Summary

Reg	Name	Bits	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	Reset	RW
0x00	PLL_CLK_CTRL0	[7:0]	PLLIN		XTAL_SET		SOFT_RST	MCS		PUP	0x00	RW
0x01	PLL_CLK_CTRL1	[7:0]	LOPWR_MODE		MCLKO_SEL		PLL_MUTE	PLL_LOCK	VREF_EN	CLK_SEL	0x2A	RW
0x02	PDN_THRMSENS_CTRL_1	[7:0]	THRM_RATE		THRM_MODE	THRM_GO	RESERVED	TS_PDN	PLL_PDN	VREG_PDN	0xA0	RW
0x03	PDN_CTRL2	[7:0]	DAC08_PDN	DAC07_PDN	DAC06_PDN	DAC05_PDN	DAC04_PDN	DAC03_PDN	DAC02_PDN	DAC01_PDN	0x00	RW
0x04	PDN_CTRL3	[7:0]	DAC16_PDN	DAC15_PDN	DAC14_PDN	DAC13_PDN	DAC12_PDN	DAC11_PDN	DAC10_PDN	DAC09_PDN	0x00	RW
0x05	THRM_TEMP_STAT	[7:0]	TEMP								0x00	R
0x06	DAC_CTRL0	[7:0]	SDATA_FMT		SAI			FS		MMUTE	0x01	RW
0x07	DAC_CTRL1	[7:0]	BCLK_GEN	LRCLK_MODE	LRCLK_POL	SAI_MSB	RESERVED	BCLK_RATE	BCLK_EDGE	SAI_MS	0x00	RW
0x08	DAC_CTRL2	[7:0]	RESERVED	VREG_CTRL		BCLK_TDMC	DAC_POL	AUTO_MUTE_EN	DAC_OSR	DE_EMP_EN	0x06	RW
0x09	DAC_MUTE1	[7:0]	DAC08_MUTE	DAC07_MUTE	DAC06_MUTE	DAC05_MUTE	DAC04_MUTE	DAC03_MUTE	DAC02_MUTE	DAC01_MUTE	0x00	RW
0x0A	DAC_MUTE2	[7:0]	DAC16_MUTE	DAC15_MUTE	DAC14_MUTE	DAC13_MUTE	DAC12_MUTE	DAC11_MUTE	DAC10_MUTE	DAC09_MUTE	0x00	RW
0x0B	DACMSTR_VOL	[7:0]	DACMSTR_VOL								0x00	RW
0x0C	DAC01_VOL	[7:0]	DAC01_VOL								0x00	RW
0x0D	DAC02_VOL	[7:0]	DAC02_VOL								0x00	RW
0x0E	DAC03_VOL	[7:0]	DAC03_VOL								0x00	RW
0x0F	DAC04_VOL	[7:0]	DAC04_VOL								0x00	RW
0x10	DAC05_VOL	[7:0]	DAC05_VOL								0x00	RW
0x11	DAC06_VOL	[7:0]	DAC06_VOL								0x00	RW
0x12	DAC07_VOL	[7:0]	DAC07_VOL								0x00	RW
0x13	DAC08_VOL	[7:0]	DAC08_VOL								0x00	RW
0x14	DAC09_VOL	[7:0]	DAC09_VOL								0x00	RW
0x15	DAC10_VOL	[7:0]	DAC10_VOL								0x00	RW
0x16	DAC11_VOL	[7:0]	DAC11_VOL								0x00	RW
0x17	DAC12_VOL	[7:0]	DAC12_VOL								0x00	RW
0x18	DAC13_VOL	[7:0]	DAC13_VOL								0x00	RW
0x19	DAC14_VOL	[7:0]	DAC14_VOL								0x00	RW
0x1A	DAC15_VOL	[7:0]	DAC15_VOL								0x00	RW
0x1B	DAC16_VOL	[7:0]	DAC16_VOL								0x00	RW
0x1C	CM_SEL_PAD_STRGTH	[7:0]	RESERVED	RESERVED	PAD_DRV	RESERVED	RESERVED	RESERVED	CM_SEL	RESERVED	0x02	RW
0x1D	DAC_POWER1	[7:0]	DAC04_POWER		DAC03_POWER		DAC02_POWER		DAC01_POWER		0xAA	RW
0x1E	DAC_POWER2	[7:0]	DAC08_POWER		DAC07_POWER		DAC06_POWER		DAC05_POWER		0xAA	RW
0x1F	DAC_POWER3	[7:0]	DAC12_POWER		DAC11_POWER		DAC10_POWER		DAC09_POWER		0xAA	RW
0x20	DAC_POWER4	[7:0]	DAC16_POWER		DAC15_POWER		DAC14_POWER		DAC13_POWER		0xAA	RW

REGISTER DETAILS

PLL AND CLOCK CONTROL 0 REGISTER

Address: 0x00, Reset: 0x00, Name: PLL_CLK_CTRL0




Table 25. Bit Descriptions for PLL_CLK_CTRL0

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	PLLIN		PLL Input Select. Selects between MCLKI/XTALI or DLRCLK as the input to the PLL.	0x0	RW
		00	MCLKI or XTALI		
		01	DLRCLK		
		10	Reserved		
		11	Reserved		
[5:4]	XTAL_SET		XTAL Oscillator Setting. XTALO pin status.	0x0	RW
		00	XTAL Oscillator Enabled		
		01	Reserved		
		10	Reserved		
		11	XTALO Off		
3	SOFT_RST		Software Reset Control. This bit resets all circuitry inside the IC, except I^2C/SPI communications. All control registers are reset to default values, except 0x00 and 0x01. The PLL_CLK_CTRLx registers do not change state.	0x0	RW
		0	Normal Operation		
		1	Device in Reset		
[2:1]	MCS		Master Clock Select. MCLKI/XTALI pin functionality (PLL active), master clock rate setting. The following values are for the f_S rate window from 32 kHz to 48 kHz. See Table 14 for details when using other f_S selections.	0x0	RW
		00	256 × f_S MCLK (44.1 kHz or 48 kHz)		
		01	384 × f_S MCLK (44.1 kHz or 48 kHz)		
		10	512 × f_S MCLK (44.1 kHz or 48 kHz)		
		11	768 × f_S MCLK (44.1 kHz or 48 kHz)		
0	PUP		Master Power-Up Control. This bit must be set to 1 as the first register write to power up the IC.	0x0	RW
		0	Master Power-Down		
		1	Master Power-Up		

PLL AND CLOCK CONTROL 1 REGISTER

Address: 0x01, Reset: 0x2A, Name: PLL_CLK_CTRL1




Table 26. Bit Descriptions for PLL_CLK_CTRL1

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	LOPWR_MODE		Global Power/Performance Adjust. These bits adjust the power consumption and performance level for all 16 DAC channels at once. See the Digital-to-Analog Converters (DACs) section for more details.	0x0	RW
		00	I^2C Register Settings		
		01	Reserved		
		10	Low Power		
		11	Lowest Power		
[5:4]	MCLKO_SEL		MCLK Output Frequency. Frequency selection for MCLKO pin. See the Clock Signals section for more details.	0x2	RW
		00	MCLKO = 4 MHz to 6 MHz scaled by f_S		
		01	MCLKO = 8 MHz to 12 MHz scaled by f_S		
		10	MCLKO = Buffered MCLKI		
		11	MCLKO Pin Disabled		
3	PLL_MUTE		PLL Automute Enable/Lock. This bit enables the PLL lock automute function.	0x1	RW
		0	No DAC Automute		
		1	DAC Automute on PLL Unlock		
2	PLL_LOCK		PLL Lock Indicator.	0x0	R
		0	PLL Not Locked		
		1	PLL Locked		
1	VREF_EN		Internal Voltage Reference Enable. The internal voltage reference powers the common mode for the ADAU1966. Disabling this bit allows the user to drive the CM pin with an outside voltage source.	0x1	RW
		0	Disabled		
		1	Enabled		
0	CLK_SEL		DAC Clock Select. Selects between PLL or Direct MCLK mode.	0x0	RW
		0	MCLK from PLL		
		1	MCLK from MCLKI or XTALI		

BLOCK POWER-DOWN AND THERMAL SENSOR CONTROL 1 REGISTER

Address: 0x02, Reset: 0xA0, Name: PDN_THRMSENS_CTRL_1




Table 27. Bit Descriptions for PDN_THRMSENS_CTRL_1

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	THRM_RATE		Conversion Time Interval. When THERM_MODE = 0, the THERM_RATE bits control the time interval between temperature conversions.	0x2	RW
		00	4 sec/Conversion		
		01	0.5 sec/Conversion		
		10	1 sec/Conversion		
		11	2 sec/Conversion		
5	THRM_MODE		Continuous vs. One-Shot. Determines whether the temperature conversions occur continuously or only when commanded. To perform one-shot temperature conversions, set this bit to 1.	0x1	RW
		0	Continuous Operation		
		1	One-Shot Mode		
4	THRM_GO		One-Shot Conversion Mode. When in one-shot conversion mode, THERM_MODE = 1, the THERM_GO bit must be set to 0 followed by a write of 1. This sequence results in a single temperature conversion. The temperature data is available 120 ms after writing a 1 to this bit.	0x0	RW
		0	Reset		
		1	Convert temperature		
2	TS_PDN		Temperature Sensor Power-Down.	0x0	RW
		0	Temperature Sensor On		
		1	Temperature Sensor Power-Down		
1	PLL_PDN		PLL Power-Down.	0x0	RW
		0	PLL Normal Operation		
		1	PLL Power-Down		
0	VREG_PDN		Voltage Regulator Power-Down.	0x0	RW
		0	Voltage Regulator Normal Operation		
		1	Voltage Regulator Power-Down		

POWER-DOWN CONTROL 2 REGISTER

Address: 0x03, Reset: 0x00, Name: PDN_CTRL2




Table 28. Bit Descriptions for PDN_CTRL2

Bits	Bit Name	Settings	Description	Reset	Access
7	DAC08_PDN		Channel 8 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 8		
6	DAC07_PDN		Channel 7 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 7		
5	DAC06_PDN		Channel 6 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 6		
4	DAC05_PDN		Channel 5 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 5		
3	DAC04_PDN		Channel 4 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 4		
2	DAC03_PDN		Channel 3 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 2		
1	DAC02_PDN		Channel 2 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 2		
0	DAC01_PDN		Channel 1 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 1		

POWER-DOWN CONTROL 3 REGISTER

Address: 0x04, Reset: 0x00, Name: PDN_CTRL3




Table 29. Bit Descriptions for PDN_CTRL3

Bits	Bit Name	Settings	Description	Reset	Access
7	DAC16_PDN		Channel 16 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 16		
6	DAC15_PDN		Channel 15 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 15		
5	DAC14_PDN		Channel 14 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 14		
4	DAC13_PDN		Channel 13 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 13		
3	DAC12_PDN		Channel 12 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 12		
2	DAC11_PDN		Channel 11 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 11		
1	DAC10_PDN		Channel 10 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 10		
0	DAC09_PDN		Channel 9 Power-Down.	0x0	RW
		0	Normal Operation		
		1	Power-Down Channel 9		

THERMAL SENSOR TEMPERATURE READOUT REGISTER

Address: 0x05, Reset: 0x00, Name: THRM_TEMP_STAT

Thermal Sensor Temperature Readout. −60°C to +140°C range, 1°C step size. Read this register and convert the hexadecimal or binary TEMP value into decimal form; then subtract 60 from this decimal conversion. The result is the temperature in degrees Celsius.




Table 30. Bit Descriptions for THRM_TEMP_STAT

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	TEMP		Thermal Sensor Temperature Readout. −60°C to +140°C range, 1°C step size. To convert TEMP code to temperature, use the equation (TEMP − 60).	0x00	R

DAC CONTROL 0 REGISTER

Address: 0x06, Reset: 0x01, Name: DAC_CTRL0




Table 31. Bit Descriptions for DAC_CTRL0

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	SDATA_FMT		SDATA Format. Only used when SAI = 000.	0x0	RW
		00	I²S—1-BCLK Cycle Delay		
		01	Left-Justified—0-BCLK Cycle Delay		
		10	Right-Justified 24-bit Data—8-BCLK Cycle Delay		
		11	Right-Justified 16-bit Data—16-BCLK Cycle Delay		
[5:3]	SAI		Serial Audio Interface. When SAI = 000, the SDATA_FMT bits control stereo SDATA format.	0x0	RW
		000	Stereo (I²S, LJ, RJ)		
		001	TDM2—Octal Line		
		010	TDM4—Quad Line		
		011	TDM8—Dual Line		
		100	TDM16—Single Line (48 kHz)		
		101	Reserved		
		110	Reserved		
		111	Reserved		
[2:1]	FS		Sample Rate Select.	0x0	RW
		00	32 kHz/44.1 kHz/48 kHz		
		01	64 kHz/88.2 kHz/96 kHz		
		10	128 kHz/176.4 kHz/192 kHz		
		11	128 kHz/176.4 kHz/192 kHz Low Propagation Delay		
0	MMUTE		DAC Master Mute.	0x1	RW
		0	Normal Operation		
		1	All Channels Muted		

DAC CONTROL 1 REGISTER

Address: 0x07, Reset: 0x00, Name: DAC_CTRL1




Table 32. Bit Descriptions for DAC_CTRL1

Bits	Bit Name	Settings	Description	Reset	Access
7	BCLK_GEN		DBCLK Generation. When the PLL is locked to DLRCLK, it is possible to run the ADAU1966 without an external DBCLK.	0x0	RW
		0	Normal Operation—DBCLK		
		1	Internal DBCLK Generation		
6	LRCLK_MODE		DLRCLK Mode Select. Only Valid for TDM modes.	0x0	RW
		0	50% Duty Cycle DLRCLK		
		1	Pulse Mode		
5	LRCLK_POL		DLRCLK Polarity. Allows the swapping of data between channels.	0x0	RW
		0	Left/Odd channels are DLRCLK Low (Normal)		
		1	Left/Odd channels are DLRCLK High (Inverted)		
4	SAI_MSB		MSB Position.	0x0	RW
		0	MSB First DSDATA		
		1	LSB First DSDATA		
2	BCLK_RATE		DBCLK Rate. Number of DBCLK cycles per DLRCLK Frame. Used only for generating DBCLK in Master Mode operation (SAI_MS = 1).	0x0	RW
		0	32 Cycles per Frame		
		1	16 Cycles per Frame		
1	BCLK_EDGE		DBCLK Active Edge. Adjust the polarity of the DBCLK leading edge.	0x0	RW
		0	Latch in Rising Edge		
		1	Latch in Falling Edge		
0	SAI_MS		Serial Interface Master. Both DLRCLK and DBCLK become master when enabled.	0x0	RW
		0	DLRCLK/DBCLK Slave		
		1	DLRCLK/DBCLK Master		

DAC CONTROL 2 REGISTER

Address: 0x08, Reset: 0x06, Name: DAC_CTRL2




Table 33. Bit Descriptions for DAC_CTRL2

Bits	Bit Name	Settings	Description	Reset	Access
[6:5]	VREG_CTRL		Voltage Regulator Control. Select the Regulator Output Voltage.	0x0	RW
		00	Regulator Out = 2.5 V		
		01	Regulator Out = 2.75 V		
		10	Regulator Out = 3.0 V		
		11	Regulator Out = 3.3 V		
4	BCLK_TDMC		DBCLK Rate in TDM Mode. Number of DBCLK cycles per channel slot when in TDM mode.	0x0	RW
		0	32 BCLK cycles/channel slot		
		1	16 BCLK cycles/channel slot		
3	DAC_POL		DAC Output Polarity. This is a global switch of DAC polarity.	0x0	RW
		0	Noninverted DAC Output		
		1	Inverted DAC Output		
2	AUTO_MUTE_EN		Automute Enable. Automatically mutes the DACs when 1024 consecutive zero input samples are received. This is independent per channel.	0x1	RW
		0	Auto-Zero Input Mute Disabled		
		1	Auto-Zero Input Mute Enabled		
1	DAC_OSR		DAC Oversampling Rate. OSR Selection.	0x1	RW
		0	256 × f_S DAC Oversampling		
		1	128 × f_S DAC Oversampling		
0	DE_EMP_EN		De-Emphasis Enable.	0x0	RW
		0	No De-Emphasis/Flat		
		1	De-Emphasis Enabled		

DAC INDIVIDUAL CHANNEL MUTES 1 REGISTER

Address: 0x09, Reset: 0x00, Name: DAC_MUTE1




Table 34. Bit Descriptions for DAC_MUTE1

Bits	Bit Name	Settings	Description	Reset	Access
7	DAC08_MUTE		DAC8 Soft Mute.	0x0	RW
		0	DAC8 Normal Operation		
		1	DAC8 Mute		
6	DAC07_MUTE		DAC7 Soft Mute.	0x0	RW
		0	DAC7 Normal Operation		
		1	DAC7 Mute		
5	DAC06_MUTE		DAC6 Soft Mute.	0x0	RW
		0	DAC6 Normal Operation		
		1	DAC6 Mute		
4	DAC05_MUTE		DAC5 Soft Mute.	0x0	RW
		0	DAC5 Normal Operation		
		1	DAC5 Mute		
3	DAC04_MUTE		DAC4 Soft Mute.	0x0	RW
		0	DAC4 Normal Operation		
		1	DAC4 Mute		
2	DAC03_MUTE		DAC3 Soft Mute.	0x0	RW
		0	DAC3 Normal Operation		
		1	DAC3 Mute		
1	DAC02_MUTE		DAC2 Soft Mute.	0x0	RW
		0	DAC2 Normal Operation		
		1	DAC2 Mute		
0	DAC01_MUTE		DAC1 Soft Mute.	0x0	RW
		0	DAC1 Normal Operation		
		1	DAC1 Mute		

DAC INDIVIDUAL CHANNEL MUTES 2 REGISTER

Address: 0x0A, Reset: 0x00, Name: DAC_MUTE2




Table 35. Bit Descriptions for DAC_MUTE2

Bits	Bit Name	Settings	Description	Reset	Access
7	DAC16_MUTE		DAC16 Soft Mute.	0x0	RW
		0	DAC16 Normal Operation		
		1	DAC16 Mute		
6	DAC15_MUTE		DAC15 Soft Mute.	0x0	RW
		0	DAC15 Normal Operation		
		1	DAC15 Mute		
5	DAC14_MUTE		DAC14 Soft Mute.	0x0	RW
		0	DAC14 Normal Operation		
		1	DAC14 Mute		
4	DAC13_MUTE		DAC13 Soft Mute.	0x0	RW
		0	DAC13 Normal Operation		
		1	DAC13 Mute		
3	DAC12_MUTE		DAC12 Soft Mute.	0x0	RW
		0	DAC12 Normal Operation		
		1	DAC12 Mute		
2	DAC11_MUTE		DAC11 Soft Mute.	0x0	RW
		0	DAC11 Normal Operation		
		1	DAC11 Mute		
1	DAC10_MUTE		DAC10 Soft Mute.	0x0	RW
		0	DAC10 Normal Operation		
		1	DAC10 Mute		
0	DAC09_MUTE		DAC9 Soft Mute.	0x0	RW
		0	DAC9 Normal Operation		
		1	DAC9 Mute		

MASTER VOLUME CONTROL REGISTER

Address: 0x0B, Reset: 0x00, Name: DACMSTR_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 36. Bit Descriptions for DACMSTR_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DACMSTR_VOL		Master Volume Control.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 1 VOLUME CONTROL REGISTER

Address: 0x0C, Reset: 0x00, Name: DAC01_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 37. Bit Descriptions for DAC01_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC01_VOL		DAC Volume Control Channel 1.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 2 VOLUME CONTROL REGISTER

Address: 0x0D, Reset: 0x00, Name: DAC02_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 38. Bit Descriptions for DAC02_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC02_VOL		DAC Volume Control Channel 2.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 3 VOLUME CONTROL REGISTER

Address: 0x0E, Reset: 0x00, Name: DAC03_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 39. Bit Descriptions for DAC03_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC03_VOL		DAC Volume Control Channel 3.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 4 VOLUME CONTROL REGISTER

Address: 0x0F, Reset: 0x00, Name: DAC04_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 40. Bit Descriptions for DAC04_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC04_VOL		DAC Volume Control Channel 4.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 5 VOLUME CONTROL REGISTER

Address: 0x10, Reset: 0x00, Name: DAC05_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 41. Bit Descriptions for DAC05_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC05_VOL		DAC Volume Control Channel 5.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 6 VOLUME CONTROL REGISTER

Address: 0x11, Reset: 0x00, Name: DAC06_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 42. Bit Descriptions for DAC06_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC06_VOL		DAC Volume Control Channel 6.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 7 VOLUME CONTROL REGISTER

Address: 0x12, Reset: 0x00, Name: DAC07_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 43. Bit Descriptions for DAC07_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC07_VOL		DAC Volume Control Channel 7.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 8 VOLUME CONTROL REGISTER

Address: 0x13, Reset: 0x00, Name: DAC08_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 44. Bit Descriptions for DAC08_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC08_VOL		DAC Volume Control Channel 8.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 9 VOLUME CONTROL REGISTER

Address: 0x14, Reset: 0x00, Name: DAC09_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 45. Bit Descriptions for DAC09_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC09_VOL		DAC Volume Control Channel 9.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 10 VOLUME CONTROL REGISTER

Address: 0x15, Reset: 0x00, Name: DAC10_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 46. Bit Descriptions for DAC10_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC10_VOL		DAC Volume Control Channel 10.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 11 VOLUME CONTROL REGISTER

Address: 0x16, Reset: 0x00, Name: DAC11_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 47. Bit Descriptions for DAC11_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC11_VOL		DAC Volume Control Channel 11.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 12 VOLUME CONTROL REGISTER

Address: 0x17, Reset: 0x00, Name: DAC12_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 48. Bit Descriptions for DAC12_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC12_VOL		DAC Volume Control Channel 12.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 13 VOLUME CONTROL REGISTER

Address: 0x18, Reset: 0x00, Name: DAC13_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 49. Bit Descriptions for DAC13_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC13_VOL		DAC Volume Control Channel 13.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 14 VOLUME CONTROL REGISTER

Address: 0x19, Reset: 0x00, Name: DAC14_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 50. Bit Descriptions for DAC14_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC14_VOL		DAC Volume Control Channel 14.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 15 VOLUME CONTROL REGISTER

Address: 0x1A, Reset: 0x00, Name: DAC15_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 51. Bit Descriptions for DAC15_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC15_VOL		DAC Volume Control Channel 15.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

DAC 16 VOLUME CONTROL REGISTER

Address: 0x1B, Reset: 0x00, Name: DAC16_VOL

Each 1-bit step corresponds to a 0.375 dB change in volume. See Table 58 for a complete list of the volume settings.




Table 52. Bit Descriptions for DAC16_VOL

Bits	Bit Name	Settings	Description	Reset	Access
[7:0]	DAC16_VOL		DAC Volume Control Channel 16.	0x00	RW
		00000000	0 dB (default)		
		00000001	−0.375 dB		
		00000010	−0.750 dB		
		11111110	−95.250 dB		
		11111111	−95.625 dB		

COMMON-MODE AND PAD STRENGTH REGISTER

Address: 0x1C, Reset: 0x02, Name: CM_SEL_PAD_STRGTH




Table 53. Bit Descriptions for CM_SEL_PAD_STRGTH

Bits	Bit Name	Settings	Description	Reset	Access
5	PAD_DRV		Output Pad Drive Strength Control. Pad strength is stated for IOVDD = 5 V.	0x0	RW
		0	4 mA Drive for All Pads		
		1	8 mA Drive for All Pads		
1	CM_SEL		Common Mode Generation Selection.	0x1	RW
		0	Fixed 3.3 V AVDD CM Generation		
		1	Fixed 5 V AVDD CM Generation		

DAC POWER ADJUST 1 REGISTER

Address: 0x1D, Reset: 0xAA, Name: DAC_POWER1




Table 54. Bit Descriptions for DAC_POWER1

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	DAC04_POWER		DAC Power Control Channel 4.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[5:4]	DAC03_POWER		DAC Power Control Channel 3.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[3:2]	DAC02_POWER		DAC Power Control Channel 2.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[1:0]	DAC01_POWER		DAC Power Control Channel 1.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		

DAC POWER ADJUST 2 REGISTER

Address: 0x1E, Reset: 0xAA, Name: DAC_POWER2




Table 55. Bit Descriptions for DAC_POWER2

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	DAC08_POWER		DAC Power Control Channel 8.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[5:4]	DAC07_POWER		DAC Power Control Channel 7.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[3:2]	DAC06_POWER		DAC Power Control Channel 6.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[1:0]	DAC05_POWER		DAC Power Control Channel 5.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		

DAC POWER ADJUST 3 REGISTER

Address: 0x1F, Reset: 0xAA, Name: DAC_POWER3




Table 56. Bit Descriptions for DAC_POWER3

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	DAC12_POWER		DAC Power Control Channel 12.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[5:4]	DAC11_POWER		DAC Power Control Channel 11.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[3:2]	DAC10_POWER		DAC Power Control Channel 10.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[1:0]	DAC09_POWER		DAC Power Control Channel 9.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		

DAC POWER ADJUST 4 REGISTER

Address: 0x20, Reset: 0xAA, Name: DAC_POWER4




Table 57. Bit Descriptions for DAC_POWER4

Bits	Bit Name	Settings	Description	Reset	Access
[7:6]	DAC16_POWER		DAC Power Control Channel 16.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[5:4]	DAC15_POWER		DAC Power Control Channel 15.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[3:2]	DAC14_POWER		DAC Power Control Channel 14.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		
[1:0]	DAC13_POWER		DAC Power Control Channel 13.	0x2	RW
		00	Low Power		
		01	Lowest Power		
		10	Best Performance		
		11	Good Performance		


Table 58. Volume Table

Binary Value	Volume Attenuation (dB)
00000000	0
00000001	−0.375
00000010	−0.75
00000011	−1.125
00000100	−1.5
00000101	−1.875
00000110	−2.25
00000111	−2.625
00001000	−3
00001001	−3.375
00001010	−3.75
00001011	−4.125
00001100	−4.5
00001101	−4.875
00001110	−5.25
00001111	−5.625
00010000	−6
00010001	−6.375
00010010	−6.75
00010011	−7.125
00010100	−7.5
00010101	−7.875
00010110	−8.25
00010111	−8.625
00011000	−9
00011001	−9.375
00011010	−9.75
00011011	−10.125
00011100	−10.5
00011101	−10.875
00011110	−11.25
00011111	−11.625
00100000	−12
00100001	−12.375
00100010	−12.75
00100011	−13.125
00100100	−13.5
00100101	−13.875
00100110	−14.25
00100111	−14.625
00101000	−15
00101001	−15.375
00101010	−15.75
00101011	−16.125
00101100	−16.5
00101101	−16.875
00101110	−17.25
00101111	−17.625
00110000	−18
00110001	−18.375
00110010	−18.75
00110011	−19.125
00110100	−19.5
00110101	−19.875
00110110	−20.25
00110111	−20.625
00111000	−21
00111001	−21.375
00111010	−21.75
00111011	−22.125
00111100	−22.5
00111101	−22.875
00111110	−23.25
00111111	−23.625
01000000	−24
01000001	−24.375
01000010	−24.75
01000011	−25.125
01000100	−25.5
01000101	−25.875
01000110	−26.25
01000111	−26.625
01001000	−27
01001001	−27.375
01001010	−27.75
01001011	−28.125
01001100	−28.5
01001101	−28.875
01001110	−29.25
01001111	−29.625
01010000	−30
01010001	−30.375
01010010	−30.75
01010011	−31.125
01010100	−31.5
01010101	−31.875
01010110	−32.25
01010111	−32.625
01011000	−33
01011001	−33.375
01011010	−33.75
01011011	−34.125

Binary Value	Volume Attenuation (dB)
01011100	−34.5
01011101	−34.875
01011110	−35.25
01011111	−35.625
01100000	−36
01100001	−36.375
01100010	−36.75
01100011	−37.125
01100100	−37.5
01100101	−37.875
01100110	−38.25
01100111	−38.625
01101000	−39
01101001	−39.375
01101010	−39.75
01101011	−40.125
01101100	−40.5
01101101	−40.875
01101110	−41.25
01101111	−41.625
01110000	−42
01110001	−42.375
01110010	−42.75
01110011	−43.125
01110100	−43.5
01110101	−43.875
01110110	−44.25
01110111	−44.625
01111000	−45
01111001	−45.375
01111010	−45.75
01111011	−46.125
01111100	−46.5
01111101	−46.875
01111110	−47.25
01111111	−47.625
10000000	−48
10000001	−48.375
10000010	−48.75
10000011	−49.125
10000100	−49.5
10000101	−49.875
10000110	−50.25
10000111	−50.625
10001000	−51
10001001	−51.375
10001010	−51.75
10001011	−52.125
10001100	−52.5
10001101	−52.875
10001110	−53.25
10001111	−53.625
10010000	−54
10010001	−54.375
10010010	−54.75
10010011	−55.125
10010100	−55.5
10010101	−55.875
10010110	−56.25
10010111	−56.625
10011000	−57
10011001	−57.375
10011010	−57.75
10011011	−58.125
10011100	−58.5
10011101	−58.875
10011110	−59.25
10011111	−59.625
10100000	−60
10100001	−60.375
10100010	−60.75
10100011	−61.125
10100100	−61.5
10100101	−61.875
10100110	−62.25
10100111	−62.625
10101000	−63
10101001	−63.375
10101010	−63.75
10101011	−64.125
10101100	−64.5
10101101	−64.875
10101110	−65.25
10101111	−65.625
10110000	−66
10110001	−66.375
10110010	−66.75
10110011	−67.125
10110100	−67.5
10110101	−67.875
10110110	−68.25
10110111	−68.625
10111000	−69
10111001	−69.375

Binary Value	Volume Attenuation (dB)
10111010	−69.75
10111011	−70.125
10111100	−70.5
10111101	−70.875
10111110	−71.25
10111111	−71.625
11000000	−72
11000001	−72.375
11000010	−72.75
11000011	−73.125
11000100	−73.5
11000101	−73.875
11000110	−74.25
11000111	−74.625
11001000	−75
11001001	−75.375
11001010	−75.75
11001011	−76.125
11001100	−76.5
11001101	−76.875
11001110	−77.25
11001111	−77.625
11010000	−78
11010001	−78.375
11010010	−78.75
11010011	−79.125
11010100	−79.5
11010101	−79.875
11010110	−80.25
11010111	−80.625
11011000	−81
11011001	−81.375
11011010	−81.75
11011011	−82.125
11011100	−82.5
11011101	−82.875
11011110	−83.25
11011111	−83.625
11100000	−84
11100001	−84.375
11100010	−84.75
11100011	−85.125
11100100	−85.5
11100101	−85.875
11100110	−86.25
11100111	−86.625
11101000	−87
11101001	−87.375
11101010	−87.75
11101011	−88.125
11101100	−88.5
11101101	−88.875
11101110	−89.25
11101111	−89.625
11110000	−90
11110001	−90.375
11110010	−90.75
11110011	−91.125
11110100	−91.5
11110101	−91.875
11110110	−92.25
11110111	−92.625
11111000	−93
11111001	−93.375
11111010	−93.75
11111011	−94.125
11111100	−94.5
11111101	−94.875
11111110	−95.25
11111111	−95.625

OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MS-026-BEC

Figure 19. 80-Lead Low Profile Quad Flat Package [LQFP]
(ST-80-2)
Dimensions shown in millimeters

ORDERING GUIDE

Model[1, 2]	Temperature Range	Package Description	Package Option
ADAU1966WBSTZ	−40°C to +105°C	80-Lead LQFP	ST-80-2
ADAU1966WBSTZRL	−40°C to +105°C	80-Lead LQFP, 13″ Tape and Reel	ST-80-2
EVAL-ADAU1966Z		Evaluation Board	

[1] Z = RoHS Compliant Part.
[2] W = Qualified for Automotive Applications.

AUTOMOTIVE PRODUCTS

The ADAU1966W models are available with controlled manufacturing to support the quality and reliability requirements of automotive applications. Note that these automotive models may have specifications that differ from the commercial models; therefore, designers should review the Specifications section of this data sheet carefully. Only the automotive grade products shown are available for use in automotive applications. Contact your local Analog Devices account representative for specific product ordering information and to obtain the specific Automotive Reliability reports for these models.

I²C refers to a communications protocol originally developed by Philips Semiconductors (now NXP Semiconductors).

©2011–2013 Analog Devices, Inc. All rights reserved. Trademarks and registered trademarks are the property of their respective owners.
D09434-0-3/13(C)


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.