



Grove - Thumb Joystick

Release date : 9/20/2015

Version : 1.0

Wiki: [http://www.seeedstudio.com/wiki/Grove - Thumb Joystick](http://www.seeedstudio.com/wiki/Grove_-_Thumb_Joystick)

Bazaar: <http://www.seeedstudio.com/depot/Grove-Thumb-Joystick-p-935.html>

Document Revision History

Revision	Date	Author	Description
1.0	Sep 21, 2015	Victor.He	Create file

Contents

Document Revision History.....	2
1. Introduction	2
2. Features.....	3
3. Application ideas.....	4
4. Specifications	5
5. Usage.....	6
5.1 With Arduino.....	6
5.2 With Raspberry Pi	7
6. Resources	10
7. Support.....	11

Disclaimer

For physical injuries and possessions loss caused by those reasons which are not related to product quality, such as operating without following manual guide, natural disasters or force majeure, we take no responsibility for that.


Under the supervision of Seeed Technology Inc., this manual has been compiled and published which covered the latest product description and specification. The content of this manual is subject to change without notice.

Copyright

The design of this product (including software) and its accessories is under tutelage of laws. Any action to violate relevant right of our product will be penalized through law. Please consciously observe relevant local laws in the use of this product.

1. Introduction

Grove - Thumb Joystick is a Grove compatible module which is very similar to the 'analog' joystick on PS2 (PlayStation 2) controllers. The X and Y axes are two $\sim 10k$ potentiometers which control 2D movement by generating analog signals. The joystick also has a push button that could be used for special applications. When the module is in working mode, it will output two analog values, representing two directions. Compared to a normal joystick, its output values are restricted to a smaller range (i.e. 200~800), only when being pressed that the X value will be set to 1023 and the MCU can detect the action of pressing.



2. Features

- Grove Interface
- 5V/3.3V Compatible
- Analog Output

3. Application ideas

- Game Controller
- Robot remote

4. Specifications


Item	Min	Typical	Max	Unit
Working Voltage	4.75	5.0	5.25	V
Output Analog Value (X coordinate)	206	516	798	\
Output Analog Value (Y coordinate)	203	507	797	\

5. Usage

5.1 With [Arduino](#)

The Grove - Thumb Joystick is an analog device that outputs analog signal ranging from 0 to 1023. That requires us to use the analog port of Arduino to take the readings.

1. Connect the module to the A0/A1 of [Grove - Basic Shield](#) using the 4-pin grove cable.
2. Plug the Grove - Basic Shield into Arduino.
3. Connect Arduino to PC by using a USB cable.



4. Copy and paste code below to a new Arduino sketch. Please click [here](#) if you do not know how to upload.

```

/*
Thumb Joystick demo v1.0
by:http://www.seeedstudio.com
connect the module to A0&A1 for using;
*/


void setup() {
  Serial.begin(9600);
}

void loop() {

```

```
int sensorValue1 = analogRead(A0);
int sensorValue2 = analogRead(A1);
Serial.print("The X and Y coordinate is:");
Serial.print(sensorValue1, DEC);
Serial.print(",");
Serial.println(sensorValue2, DEC);
Serial.println(" ");
delay(200);
```

5. You can check the values of the output analog signals by opening the Serial Monitor.



The output value from the analog port of Arduino can be converted to the corresponding resistance using the formula: $R = (\text{float})(1023 - \text{sensorValue}) * 10 / \text{sensorValue}$.

5.2 With [Raspberry Pi](#)

1. You should have got a raspberry pi and a grovepi or grovepi+.
2. You should have completed configuring the development environment, otherwise follow [here](#).
3. Connection. Plug the sensor to grovepi socket D4 by using a grove cable.
4. Navigate to the demos' directory:

```
cd yourpath/GrovePi/Software/Python/
```

To see the code

```
nano grove_slide_potentiometer.py # "Ctrl+x" to exit #
```

```
import time
import grovepi

# Connect the Grove Thumb Joystick to analog port A0

# GrovePi Port A0 uses Arduino pins 0 and 1
# GrovePi Port A1 uses Arduino pins 1 and 2
# Don't plug anything into port A1 that uses pin 1
# Most Grove sensors only use 3 of their 4 pins, which is why the GrovePi
# shares Arduino pins between adjacent ports
# If the sensor has a pin definition SIG,NC,VCC,GND, the second (white)
# pin is not connected to anything

# If you wish to connect two joysticks, use ports A0 and A2 (skip A1)

# Uses two pins - one for the X axis and one for the Y axis
# This configuration means you are using port A0
xPin = 0
yPin = 1
grovepi.pinMode(xPin,"INPUT")
grovepi.pinMode(yPin,"INPUT")

# The Grove Thumb Joystick is an analog device that outputs analog signal
# ranging from 0 to 1023
# The X and Y axes are two ~10k potentiometers and a momentary push
# button which shorts the x axis

# My joystick produces slightly different results to the specifications
# found on the url above
# I've listed both here:

# Specifications
#   Min  Typ  Max  Click
#   X   206  516  798  1023
#   Y   203  507  797

# My Joystick
#   Min  Typ  Max  Click
#   X   253  513  766  1020-1023
#   Y   250  505  769
while True:
```

```
try:
    # Get X/Y coordinates
    x = grovepi.analogRead(xPin)
    y = grovepi.analogRead(yPin)

    # Calculate X/Y resistance
    Rx = (float)(1023 - x) * 10 / x
    Ry = (float)(1023 - y) * 10 / y

    # Was a click detected on the X axis?
    click = 1 if x >= 1020 else 0

    print "x =", x, " y =", y, " Rx =", Rx, " Ry =", Ry, " click =",
click
    time.sleep(.5)

except IOError:
    print "Error"}
```

5. Run the demo.

```
sudo python grove_thumb_joystick.py
```

6. Resources

[Grove-Thumb Joystick Eagle File](#)

[Analog Joystick Datasheet](#)

7. Support

[Ask questions on Seeed Forum.](#)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.