OMRON

Simple Fiber Amplifier E3X-SD/-NA

The Highest Level of Power and Precision in the Industry with "GIGA RAY" Giga Power Lighting Element

- Stable detection of minute objects even when the Sensor is covered with dust and oil in severe environments.
- Quick-tuning to automatically adjust light level and set threshold value.
- Use the one-key one-function feature for quick, easy operation.
- Reasonable price.

Ordering Information

Amplifier Units [Refer to *Dimensions* on page 13.] Digital Display and Direct Key Setting



CE

ltom	Appearance	Connection	Ratings and	Model	
nem	Appearance	method	Specifications	NPN output	PNP output
Standard models	and a	Pre-wired (2 m)		E3X-SD21 2M	E3X-SD51 2M
		Wire-saving connector *		E3X-SD7	E3X-SD9

*An Amplifier Unit Connector (sold separately) is required.

Bar Display and Adjuster Setting

ltem	Annearance	Connection	Ratings and	Model		
nem	Appearance	method	Specifications	NPN output	PNP output	
Standard models		Pre-wired (2 m)		E3X-NA11 2M	E3X-NA41 2M	
		Wire-saving connector *1		E3X-NA6	E3X-NA8	
High-speed detection models	The second secon	Pre-wired (2 m)	Response time: 20 μs	E3X-NA11F 2M	E3X-NA41F 2M	
Water-resistant models		Pre-wired (2 m)	Degree of protection:	E3X-NA11V 2M	E3X-NA41V 2M	
		Connector (M8) *2	IP66	E3X-NA14V	E3X-NA44V	

*1. An Amplifier Unit Connector (sold separately) is required.

*2. A Sensor I/O Connector (sold separately) is required.

		Note. I Totective seals	provided. [neler to biller	isions on page 17.]
Item Appearance		Cable length	No. of conductors	Model
Master Connector		2 m	3	E3X-CN11
Slave Connector			1	E3X-CN12

Amplifier Unit Connectors (sold separately) Note: Protective seals provided. [Refer to Dimensions on page 17.]

Ordering Precautions for Amplifier Units	Amplifier Units				Applicable Connecte	ors (sold separately)
Connectors	Туре	NPN	PNP	+	Master Connector	Slave Connector
A Connector is not provided with the Amplifier Unit.	Standard	E3X-SD7	E3X-SD9	•	E3X-CN11 (3-wire)	E3X-CN12 (1-wire)
Refer to the tables at the right when placing an order.	models	E3X-NA6	E3X-NA8	-		
	When Using 5 Amplifier Units					
	5 Amplifier Units			+	1 Master Connector -	+ 4 Slave Connectors

Sensor I/O Connectors (Models for Connectors: A Connector is not provided with the Amplifier Unit. Be sure to order a Connector separately.) [Refer to *Dimensions* on XS3.]

Size	Cable specifications	Appearance		Cable type		Model
		Straight		2 m		XS3F-M421-402-A
M8	Standard cable	connector	C Mr	5 m	Four-	XS3F-M421-405-A
		L-shaped		2 m cable	XS3F-M422-402-A	
		connector		5 m		XS3F-M422-405-A

Accessories (sold separately)

Mounting Brackets

A Mounting Bracket is not provided with the Amplifier Unit. Order a Mounting Bracket separately if required.

[Refer to Dimensions on page 17.]

Appearance	Applicable models	Model	Quantity
A CON	E3X-SD□ E3X-NA□ E3X-NA□F	E39-L143	1
	E3X-NA⊡V	E39-L148	

End Plate

End Plates are not provided with the Amplifier Unit. Order End Plates separately if required. [Refer to *Dimensions* on page 17.]



Ratings and Specifications

Amplifier Units

		Digital display and direct key setting	Bar display and adjuster setting				
	Туре	Standard models	Standard models	High-speed detection models	Water-resistant models		
Item	Model	E3X-SD	E3X-NA	E3X-NA□F	E3X-NA⊡V		
Light source (wavelength)	Red, 4-element LED (625 nm)			Red LED (680 nm)		
Power supply	voltage	12 to 24 VDC ±10%, ripple (p-p): 10% max.					
Power consu Current cons	mption/ umption	960 mW max. (Power supply voltage: 24 V, Current consumption: 40 mA max.) (Power supply voltage: 12 V, Current consumption: 80 mA max.)	960 mW max. (Current consumption: 40 mA max.)				
Control outpu	ıt	Open-collector output (NPN or PNP) Load power supply: 26.4 V max., Load current: 50 mA max. (Residual voltage: 1.5 V max.) Light-ON/Dark-ON mode selector	Open-collector output (NPN or PNP) Load power supply: 26.4 V max., Load current: 50 mA max. (Residual voltage: 1 V max.) Light-ON/Dark-ON mode selector.				
Response tim	ie	Operate or reset: 200 μs max. (*1)		Operate: 20 μs max. Reset: 30 μs max.	Operate or reset: 200 μs max. (*1)		
Sensitivity ad	justment	UP/DOWN direct key setting, teaching with/without a workpiece, automatic teaching	Shing 8-turn sensitivity adjuster (with indicator)				
Protection circuits		Power supply reverse polarity protection, output short-circuit protection, output reverse polarity protection	Power supply reverse polarity protection, output short-circuit protection				
Timer functio	n		No timer, OFF-delay timer;	or Timer selector (timer time	e: 40 ms (fixed))		
Mutual interfe	erence	Up to 5 Amplifiers (optically synchronized) (*2)		None	Up to 5 Amplifiers (optical- ly synchronized) (*2)		
Ambient illum	ination	Receiver side Incandescent lamp: 10,000 lux max. Sunlight: 20,000 lux max.					
Number of ga Amplifiers	ng-mounted	16 max. (The ambient temperature specification depends on the number of gang-mounted Amplifiers.)					
Ambient temp range	perature	Operating: Groups of 1 to 3 Amplifiers: -25°C to 55°C Groups of 4 to 11 Amplifiers: -25°C to 50°C Groups of 12 to 16 Amplifiers: -25°C to 45°C Storage: -30°C to 70°C (with no icing or condensation)					
Ambient hum	idity range	Operating and storage: 35% to 85% (with no cond	lensation)				
Insulation res	istance	20 MΩ. min. (at 500 VDC)					
Dielectric stre	ength	1,000 VAC at 50/60 Hz for 1 minute (*3)					
Vibration resi	stance	Destruction: 10 to 55 Hz with a 1.5-mm double am	plitude for 2 hours each in X	, Y and Z directions			
Shock resista	nce	Destruction: 500 m/s ² , for 3 times each in X, Y and	d Z directions				
Degree of protection		IEC 60529 IP50 (with Protective Cover attached)			IEC 60529 IP66 (with Protective Cover at- tached)		
Connection m	nethod	Pre-wired (standard cable length: 2 m), or connect	tor				
Weight (packe	ed state) (*4)	Pre-wired model: Approx. 100 g, Model with conne	ector: Approx. 55 g				
Material	Case	Polybutylene terephthalate (PBT)					
	Cover	Polycarbonate (PC)			Polyethersulfone (PES)		
Accessories		Instruction manual					

*1. When there are 8 or more E3X-NA Amplifiers mounted side-by-side, the response time will be 350 µs max.
*2. Mutual interference prevention is effective when E3X-SD/-NA-series Amplifiers are gang-mounted without other E3X-series Amplifiers.
*3. Water-resistant models and models with connectors have a dielectric strength of 500 VAC.
*4. Add 10 g for water-resistant models.

Amplifier Unit Connectors (Wire-saving Connectors)

Item	Model	E3X-CN11	E3X-CN12					
Rated current 2.5 A								
Rated vol	tage	i0 V						
Contact r	esistance	20 mΩ max. (20 mVDC max., 100 mA max.) (The above figure is for connection to the Amplifier Unit and the adjacent Connector. It does not include the conductor resistance of th cable.)						
Number o	of insertions	Destruction: 50 times (for connection to the Amplifier Unit and the ac	ljacent Connector)					
Motorial	Housing	Polybutylene terephthalate (PBT)						
Contact	Contact	Phosphor bronze/gold-plated nickel						
Weight (p	acked state)	Approx. 55 g	Approx. 25 g					

Sensing distance **Amplifier Unit** Sensing distance (Unit: mm) **Fiber Unit** E3X-SD E3X-NA E3X-NA V E3X-NA Screw-shaped model Sensing Standard **High-speed** Water-resistance Sensing Size Model method detection models direction models models МЗ Straight E32-T21R 2M 120 36 60 **Right angle** 160 280 E32-T11N 2M 530 Throughbeam E32-T11R 2M 560 160 280 M4 models E32-TC200 2M 800 240 400 Straight E32-T11L 2M 1,400 420 700 Right angle E32-C31N 2M 25 7.5 13 ΜЗ 30 10 15 E32-D21R 2M E32-C31 2M 80 26 40 Straight M4 30 10 E32-D211R 2M 15 Reflective E32-D11N 2M 170 50 90 Right angle E32-C11N 2M models 170 50 85 E32-D11R 2M 180 60 90 M6 E32-DC200 2M 300 100 150 Straight E32-CC200 2M 300 100 150 E32-D11L 2M 400 130 200

Amplifier Unit				Sensing distance (Unit: mm)			
Fiber Unit Flat model				E3X-SD E3X-NA	E3X-NA□F	E3X-NA□V	
Sensing method	Sensing direction	Size	Model	Standard models	High-speed detection models	Water-resistance models	
		Standard	E32-T15XR 2M	560	160	280	
Thursday	TOP VIEW	Small	E32-T25XR 2M	120	36	60	
I hrough-	Side view	Standard	E32-T15YR 2M	220	66	110	
models		Small	E32-T25YR 2M	60	18	30	
modelo	Eletview	Standard	E32-T15ZR 2M	220	66	110	
	Fiat view	Small	E32-T25ZR 2M	60	18	30	
		Standard	E32-D15XR 2M	180	60	90	
	TOP VIEW	Small	E32-D25XR 2M	30	10	15	
Reflective	Side view	Standard	E32-D15YR 2M	40	10	20	
models	Side view	Small	E32-D25YR 2M	8	2.4	4	
	Elet view	Standard	E32-D15ZR 2M	40	10	20	
	i-lat view	Small	E32-D25ZR 2M	8	2.4	4	

			Sens	ing distance (Unit	: mm)	
Fiber Unit Cylindrical model				E3X-SD E3X-NA	E3X-NA□F	E3X-NA□V
Sensing method	Sensing direction	Size	Model	Standard models	High-speed detection models	Water-resistance models
Thursday	Top view	φ1	E32-T223R 2M	120	36	60
I nrougn-	TOP VIEW	φ3	E32-T12R 2M	560	160	280
models	Side view	φ1	E32-T24R 2M	60	18	30
modelo		φ3	E32-T14LR 2M	220	66	110
		φ 1 .5	E32-D22B 2M	30	10	15
	Top view	φ2	E32-D32 2M	80	26	40
Reflective	TOP VIEW	40	E32-D22R 2M	30	10	15
models		ψο	E32-D32L 2M	160	50	80
	Side view	φ2	E32-D24R 2M	14	4.6	7
	Side view	φ6	E32-D14LR 2M	32	10	16

			Sens	ing distance (Unit	: mm)	
Fiber Unit			E3X-SD			
Model equi	pped with sleev	e	E3X-NA			
Sensing method	Sleeve size	Mounting size	Model	Standard models	High-speed detection models	Water-resistance models
	φ0.25 × 5	43	E32-T333-S5 1M	10	3	5
I nrougn-	φ0.5 × 40	ψΟ	E32-T33 1M	40	13.5	20
models	φ0.9 × 40	M3	E32-TC200F4R 2M	120	36	60
modolo	φ1.2 × 90	M4	E32-TC200BR 2M	560	160	280
	φ0.5 × 15	φ2	E32-D331 2M	3	1	1.5
Reflective	φ0.8 × 15	φ 3	E32-D33 2M	16	4	10
models	φ1.2 × 40	M3	E32-DC200F4R 2M	30	10	15
	φ2.5 × 90	M6	E32-DC200BR 2M	180	60	90

			Sens	ing distance (Unit	: mm)	
Fiber Unit Movable section (Flexibility)				E3X-SD E3X-NA	E3X-NA□F	E3X-NA□V
Sensing method	Shape	Size	Model	Standard models	High-speed detection models	Water-resistance models
	Screw-shaped	M3	E32-T21 2M	200	60	100
Thursday	model	M4	E32-T11 2M	720	200	360
I hrough-	Cylindrical	φ 1 .5	E32-T22B 2M	200	60	100
models	model	φ3	E32-T12B 2M	720	200	360
modolo	Flat model	Standard	E32-T15XB 2M	720	200	360
		Small	E32-T25XB 2M	150	40	75
	Corow abarad	M3	E32-D21 2M	30	10	15
	model	M4	E32-D21B 2M	70	20	35
Deflective	model	M6	E32-D11 2M	180	60	90
models	Cylindrical	φ 1 .5	E32-D22B 2M	30	10	15
models	model	φ3	E32-D221B 2M	70	20	35
	Elat model	Standard	E32-D15XB 2M	180	60	90
	i lat model	Small	E32-D25XB 2M	50	16	25

Amplifier Unit				Sensing distance (Unit: mm)		
Fiber Unit Heat-resistance model				E3X-SD E3X-NA	E3X-NA□F	E3X-NA□V
Sensing method	ng Operating d temperature		Model	Standard models	High-speed detection models	Water-resistance models
			E32-T51R 2M	400	120	225
	100°C	Lens	E32-T51R 2M + E39-F1	2,000	720	1,650
		High-power lens	E32-T51R 2M + E39-F16	4,000 粩	1,560	2,900
			E32-T51 2M	800	240	400
Through-	150°C	Lens	E32-T51 2M + E39-F1-33	2,400	720	1,400
beam		High-power lens	E32-T51 2M + E39-F16	4,000 *	3,120	4,000 *
models			E32-T54 2M	260	70	130
	200°C		E32-T81R-S 2M	360	100	180
		Lens	E32-T61-S 2M + E39-F1	4,000 *	1,800	3,000
	250°C		E32-T61-S 2M	600	180	300
	350 C	High-power lens	E32-T61-S 2M + E39-F16	4,000 *	2,340	3,900
	100°C		E32-D51R 2M	140	42	70
Reflective	150°C		E32-D51 2M	240	80	120
	200°C		E32-D81R 2M	90	27	45
models	350°C		E32-D61 2M	90	27	45
	400°C		E32-D73 2M	60	18	30

* The fiber length is 2 m on each side, so the sensing distance is given as 4,000 mm.

		Sens	ing distance (Unit	: mm)	
Fiber Unit Chemical-re	esistance / Oil-resistance mode	1	E3X-SD E3X-NA	E3X-NA□F	E3X-NA V
Sensing method	Туре	Model	Standard models	High-speed detection models	Water-resistance models
	φ5	E32-T12F 2M	3,200	960	1,600
	φ 7 .2	E32-T11F 2M	2,100	760	1,050
Through- beam	φ5 Heat-resistance	E32-T51F 2M	1,400	400	700
	φ5 Side view	E32-T14F 2M	400	120	200
models	M4 Chemical-resistance cable	E32-T11U 2M	720	200	360
	M4 Right angle Chemical-resistance cable	E32-T11NU 2M	400	120	210
	φ6	E32-D12F 2M	100	32	50
Reflective models	φ7 Side view	E32-D14F 2M	40	13	20
	M6 Chemical-resistance cable	E32-D11U 2M	180	60	90

			Sensing distance (Unit: mm)			
Fiber Unit				E3X-SD		
Vacuum-res	sistance model			E3X-NA		LJA-NALIV
Sensing method	Operating ambient temperature	Sensing direction	Model	Standard models	High-speed detection models	Water-resistance models
Through			E32-T51V 1M	200		100
heam	120°C	Top view	E32-T51V 1M + E39-F1V	1,200		600
models		Bight angle	E32-T54V 1M	130		65
modela	200°C	night angle	E32-T84SV 1M	500		250

Amplifier Unit				Sensi	Sensing distance (Unit: mm)		
Fiber Unit Long distance/Dust resistance (High-power), Detection through gaps (Narrow vision field)			r), Detection through gaps	E3X-SD E3X-NA	E3X-NA□F	E3X-NA⊡V	
Sensing method	sing hod Type direction/ Lens type		Model	Standard models	High-speed detection models	Water-resistance models	
	High-power	Top view	E32-T17L 10M	20,000 * 1	8,400	14,000	
	(integrated unit)	Side view	E32-T14 2M	3,600	1,080	1,800	
		High-power	E32-T11N 2M + E39-F1	3,700	1,110	2,100	
		Ultrahigh-power	E32-T11N 2M + E39-F16	4,000 *2	2,000	3,600	
		High-power	E32-T11R 2M + E39-F1	4,000 *2	1,260	2,100	
		Ultrahigh-power	E32-T11R 2M + E39-F16	4,000 *2	2,000	3,600	
		Side view	E32-T11R 2M + E39-F2	440	130	220	
		High-power	E32-TC200 2M + E39-F1	4,000 *2	1,800	3,000	
		Ultrahigh-power	E32-TC200 2M + E39-F16	4,000 *2	3,000	4,000 *2	
		Side view	E32-TC200 2M + E39-F2	700	210	350	
		High-power	E32-T11 2M + E39-F1	4,000 *2	1,200	2,000	
	High-power (with lens unit)	Ultrahigh-power	E32-T11 2M + E39-F16	4,000 *2	2,600	4,000 *2	
Through-		ough- High-power	Side view	E32-T11 2M + E39-F2	720	200	360
beam		High-power	E32-T11U 2M + E39-F1	3,600	1,080	2,000	
models		Ultrahigh-power	E32-T11U 2M + E39-F16	4,000 *2	2,600	4,000 * 2	
		Side view	E32-T11U 2M + E39-F2	660	198	330	
		High-power	E32-T11NU 2M + E39-F1	1,800	700	1,500	
		Ultrahigh-power	E32-T11NU 2M + E39-F16	4,000 *2	1,500	2,700	
		High-power	E32-T81R-S 2M + E39-F1	1,800	630	1,100	
		Ultrahigh-power	E32-T81R-S 2M + E39-F16	4,000 *2	1,300	2,300	
		Side view	E32-T81R-S 2M + E39-F2	280	84	140	
		High-power	E32-T61-S 2M + E39-F1	4,000 *2	1,800	3,000	
		Ultrahigh-power	E32-T61-S 2M + E39-F16	4,000 *2	2,340	3,900	
		Side view	E32-T61-S 2M + E39-F2	780	260	390	
	Narrow vision	Top view	E32-T22S 2M	2,000	600	1,000	
	field (aperture angle: 4°)	Side view	E32-T24S 2M	1,400	420	700	
Reflective models	High-power	Top view	E32-D16 2M	800	140	40 to 400	

*1. The fiber length is 10 m on each side, so the sensing distance is given as 20,000 mm.
*2. The fiber length is 2 m on each side, so the sensing distance is given as 4,000 mm.

Amplifier Unit			Sensing distance (Unit: mm)			
Fiber Unit				E3X-SD		
Minute obje	ect detection (Sr	nall-spot model)	E3X-NA		LUX-NALV
Sensing method	Spot diameter (mm)	Focal length (mm)	Model	Standard models	High-speed detection models	Water-resistance models
	φ0.1 to 0.6 (Variable)	6 to 15	E32-C42 1M + E39-F3A	Spot diameter of 0.1 to 0.6 mm at 6 to 15 mm		
	φ0.1	5	E32-C42S 1M	Spot diameter of 0.1 mm at 5 mm		
		7	E32-C41 1M + E39-F3A-5	Spot diameter of 0.1 mm at 7 mm		
	φ 0 .2	17	E32-C41 1M + E39-F3B	Spot diameter of 0.2 mm at 17 mm		
Reflective	+0 F	7	E32-C31 2M + E39-F3A-5	Spot diameter of 0.5 mm at 7 mm		at 7 mm
models	ψ0.5	17	E32-C31 2M + E39-F3B	Spot diameter of 0.5 mm at 17 mm		t 17 mm
	φ6	50	E32-L15 2M	Spot di	ameter of 6 mm at	50 mm
	φ4 Parallel light	0 to 20	E32-C31 2M + E39-F3C	Spot diameter of 4 mm max. at 0 to 20 mm		: 0 to 20 mm
	43	50	E32-C11N 2M + E39-F18	Spot diameter of 3 mm at 50 mm		
	φ3		E32-CC200 2M + E39-F18	Spot diameter of 3 mm at 50 mm		

			Sens	ing distance (Unit	: mm)	
Fiber Unit				E3X-SD	E3X-NA□F	E3X-NA⊡V
Area-sensi	ng (Area beam)			E3X-NA		
Sensing		Sensing	Madal	Standard	High-speed	Water-resistance
method	Area range	direction	Model	models	detection models	models
Through-	11 mm	Side view	E32-T16PR 2M	800	260	450
beam	111111	Flat view	E32-T16JR 2M	700	220	390
models	30 mm		E32-T16WR 2M	1,380	400	690
Reflective models	11 mm	Side view	E32-D36P1 2M	150	50	75

Amplifier Unit				Sensing distance (Unit: mm)			
Fiber Unit				E3X-SD			
Detection without background interference (Convergent-reflective)		E3X-NA					
Sensing	Sensing	Size	Model	Standard	High-speed	Water-resistance	
method	detection			models	detection models	models	
	Flat view	Elet view	Standard	E32-L16-N 2M	0 to 15	0 to 12	0 to 15
Pofloctivo		Small	E32-L24S 2M	0 to 4			
models	Top view		E32-L25L 2M	5.4 to 9	5.4 to 8	5.4 to 9	
				(Center 7.2)	(Center 7.2)	(Center 7.2)	
	Flat view		E32-L24L 2M		2 to 6 (Center 4)		

		Amplifier Unit	Sensing distance (Unit: mm)		
Fiber Unit			E3X-SD	E3X-NA E	
Detection of transparent objects (Retro-reflective)			E3X-NA		
Sensing method	Туре	Model	Standard models	High-speed detection models	Water-resistance models
	Square	E32-R16 5M + E39-R1 (Attached)	1,500	1,000	150 to 1,500
Retro-	Small	E32-R21 2M + E39-R3 (Attached)	10 to 250	250	10 to 250
reflective models	Film dotaction *2	E32-C31 2M + E39-F3R + E39-RP1	450	135	225
*1		E32-C31 2M + E39-F3R + E39-RSP1	220	65	110

*1. When using a highly reflective object, light reflected from the object may affect the Sensor.*2. Film detection may not be effective for some types of film. Confirm operation in advance.

			Amplifier Unit	Sens	ing distance (Unit	: mm)	
Fiber Unit				E3X-SD			
FPD / Semi	conductor / Sola	ar battery indust	try	E3X-NA	E3X-INA_F		
Sensing method	Application	Operating temperature	Model	Standard models	High-speed detection models	Water-resistance models	
	Glass	70°C	E32-L16-N 2M		0 to 15		
	substrate	700	E32-A08 2M		10 to 20		
	alignment	300°C	E32-A08H2 3M		10 to 20		
	Glass detection	70°C	E32-L16-N 2M		0 to 15		
	Glass	70°C	E32-A09 2M	-	15 to 38 (Center 25)	
	substrate	150°C	E32-A09H 2M	15 to 38 (Center 25)			
	mapping	300°C	E32-A09H2 2M	20 to 30 (Center 25)			
Reflective models	WET process	60°C	E32-L11FP 5M	8 to 20 mm from e (recommended: 1 19 to 31 mm from (recommended: 2	end of lens 1 mm) center point A of m 2 mm)	nounting hole	
		WET process	70°C	E32-L12FS 5M	8 to 20 mm from end of lens (recommended: 11 mm) 32 to 44 mm from center point A of mounting (recommended: 35 mm)		ounting hole
		85°C E32-L11FS 5M	E32-L11FS 5M	8 to 20 mm from end of lens (recommended: 11 mm) 32 to 44 mm from center point A of mounting hole (recommended: 35 mm)			
Thursday			E32-A03 2M	890	267	445	
i nrougn-	Wafer	70°C	E32-A03-1 2M	890	267	445	
models	mapping	70.0	E32-A04 2M	340	102	170	
			E32-A04-1 2M	340	102	170	

Amplifier Unit				Sens	ing distance (Unit	: mm)
Fiber Unit				E3X-SD	E3X-NA E	
Liquid-leve	detection mod	el		E3X-NA		
Sensing	Sensing	Pipe diameter	Model	Standard	High-speed	Water-resistance
memou	unection			IIIOueis	delection models	models
	Mounted to	No limit	E32-D36T 5M	Applicable pipe: Tr	ansparent (no restrie	ction on diameter)
Reflective	nine	68 to 10 mm	E32-1 25T 2M	Applicable pipe: T	ransparent pipe wit	h diameter of 8 to
models	pipo	φοιοτοπιπ		10 mm, recomme	nded pipe wall thick	mess: 1 mm
	Wet		E32-D82F1 4M		Wet model	

E3X-SD/-NA I/O Circuit Diagrams

Output form	Model	Output transistor operation mode	Timing charts	Operation selector	Output circuit
NPN	E3X-SD21 E3X-SD7 E3X-NA11	Light-ON	Incident light No incident light Operation ON indicator ON (orange) OFF Output ON transistor OFF Load Operate (relay) Reset (Between brown and black leads)	LIGHT ON (L-ON)	Operation indicator (orange) Photo- electric Sensor main circuit Unit of the sensor Black Control output Blue Blue S
Output E3X-N E3X-N E3X-N	E3X-NA6 E3X-NA11F E3X-NA11V E3X-NA14V	Dark-ON	Incident light No incident light Operation ON indicator (orange) OFF Output ON transistor OFF Load Operate (relay) Reset (Between brown and black leads)	DARK ON (D-ON)	M8 Connector Pin Arrangement (2) (3) (0) (3) (3) (4) (4) (4) (5) (5) (5) (6) (6) (7)
PNP	E3X-SD51 E3X-SD9 E3X-NA41	Light-ON	Incident light No incident light Operation ON Indicator ON (orange) OFF Output ON transistor OFF Load Operate (relay) Reset (Between blue and black leads)	LIGHT ON (L-ON)	Operation indicator (orange) Photo- electric Sensor main circuit Black Control output Black Control output Control output Black Control output Control output Black Control output Control output Control output Black Control output Control output
Output	E3X-NA8 E3X-NA41F E3X-NA41V E3X-NA41V E3X-NA44V	Dark-ON	Incident light No incident light Operation ON indicator (orange) OFF Output ON transistor OFF Load Operate (relay) Reset (Between blue and black leads)	DARK ON (D-ON)	M8 Connector Pin Arrangement (2) (3) Note: Pin 2 is not used. * Not present on the E3X-NA.

Note: Timing Charts for Timer Settings (T: Set Time)



Plug (Sensor I/O Connector)



Classification	Wire color	Connection pin	Application
	Brown	1	Power supply (+V)
DC	White	2	
DC	Blue	3	Power supply (0 V)
	Black	4	Output

Note: Pin 2 is not used.

Safety Precautions

🔥 WARNING

This product is not designed or rated for ensuring safety of persons either directly or indirectly.

Do not use it for such purposes.

Caution



Do not exceed the rated voltage. Excess voltage may result in malfunction or fire.

Do not use an AC power supply. Using an AC power supply may result in rupturing.



High-temperature environments may result in burn injury.



Precautions for Safe Use

The following precautions must be observed to ensure safety.

- 1. Do not use the product in locations where flammable or explosive gas is present.
- 2. Do not use the product in locations subject to splashing water, oil, or chemicals, or in locations subject to steam.
- 3. Do not attempt to disassemble, repair, or modify the product.
- 4. Do not apply voltage or current in excess of the rated ranges.
- 5. Do not use the product in atmospheres or environments that exceed product ratings.
- 6. Do not wire the product incorrectly, such as using incorrect power supply polarity.
- 7. Connect the load properly.
- 8. Do not short-circuit both ends of the load.
- 9. Do not use the product if the case is damaged.
- 10. When disposing of the product, dispose of it as industrial waste.
- 11. Do not use the product in locations subject to direct sunlight.
- 12. The surface temperature of the product may rise as a result of the ambient temperature, power supply, or other usage conditions. Use caution when performing maintenance and washing. Failure to do so may result in burn injury.

Precautions for Correct Use

Do not use the product in atmospheres or environments that exceed product ratings.

Amplifier Units

Designing

Communications Hole

The hole on the side of the Amplifier Unit is a communications hole for preventing mutual interference when Amplifier Units are mounted side-by-side. The E3X-MC11 Mobile Console (sold separately) cannot be used.

If an excessive amount of light is received via the Sensor, the mutual interference prevention function may not work. In this case, make the appropriate adjustments using the sensitivity adjuster.

Mutual interference prevention is effective when E3X-SD/-NA-series Amplifiers are gang-mounted without other E3Xseries Amplifiers.

Mounting

DIN Track Mounting/Removal

Mounting Amplifier Units

1. Mount the Amplifier Units one at a time onto the DIN track.



2. Slide the Amplifier Units together, line up the clips, and press the Amplifier Units together until they click into place.



Removing Amplifier Units

Slide Amplifier Units away from each other, and remove from the DIN track one at a time. (Do not attempt to remove Amplifier Units from the DIN track without separating them first.)

- Note 1. The specifications for ambient temperature will vary according to the number of Amplifier Units used together. For details, refer to *Ratings* and *Specifications*.
 - 2. Always turn OFF the power supply before mounting or removing Amplifier Units.

Fiber Connection and Disconnection

The E3X Amplifier Unit has a lock lever. Connect or disconnect the fibers to or from the E3X Amplifier Unit using the following procedures:

1. Connection

Open the Protective Cover, insert the fibers according to the fiber insertion marks on the side of the Amplifier Unit, and lower the lock lever.



Note: If one of the fibers from the Fiber Unit has a white line, such as with a Coaxial Sensor, that fiber is for the Emitter. Insert it into the Emitter section. Refer to Dimensions for the Fiber Unit to see if there is an Emitter fiber.

2. Disconnection

Remove the Protective Cover and raise the lock lever to pull out the fiber.



Note:To maintain the fiber properties, confirm that the lock is released before removing the fiber.

3. Precautions for Fiber Connection/Disconnection

Be sure to lock or unlock the lock lever within an ambient temperature range between -10° C and 40° C.

Operating Environment

Ambient Conditions

If dust or dirt adhere to the hole for optical communications, it may prevent normal communications. Be sure to remove any dust or dirt before using the Units.

Other

Protective Cover

Be sure to mount the Protective Cover before use.

Amplifier Units with Connectors

Mounting

Mounting Connectors

 Insert the Master or Slave Connector into the Amplifier Unit until it clicks into place.



- 2. Join Amplifier Units together as required after all the Master and Slave Connectors have been inserted.
- Attach the stickers (provided as accessories) to the sides of Master and Slave Connectors that are not connected to other Connectors.



Note: Attach the stickers to the sides with grooves.

Removing Connectors

- 1. Slide the slave Amplifier Unit for which the Connector is to be removed away from the rest of the group.
- After the Amplifier Unit has been separated, press down on the lever on the Connector and remove it. (Do not attempt to remove Connectors without separating them from other Amplifier Units first.)



Mounting End Plate (PFP-M)

Depending on how it is mounted, an Amplifier Unit may move during operation. In this case, use an End Plate. Before mounting an End Plate, remove the clip from the master Amplifier Unit using a nipper or similar tool.



The clip can also be removed using the following mechanism, which is incorporated in the construction of the section underneath the clip.

1. Insert the clip to be removed into the slit underneath the clip on another Amplifier Unit.



2. Remove the clip by rotating the Amplifier Unit.



Pull Strengths for Connectors (Including Cables) E3X-CN11: 30 N max. E3X-CN12: 12 N max.

Dimensions

(Unit: mm) Tolerance class IT16 applies to dimensions in this sheet unless otherwise specified.

Amplifier Units



Note: When using E39-L143 Mounting Brackets, there will be small gaps between the Amplifier Units if they are mounted side by side.



Note: When using E39-L143 Mounting Brackets, there will be small gaps between the Amplifier Units if they are mounted side by side.

14





Amplifier Unit Connectors (Wire-saving Connectors)



* E3X-CN11: 4 dia. cable / 3 conductors / Standard length: 2 m (Conductor cross section: 0.2 mm² (AWG24), Insulator diameter: 1.1 mm)

Slave Connector E3X-CN12





* E3X-CN12: 2.6 dia. cable / 1 conductor / Standard length: 2 m (Conductor cross section: 0.2 mm² (AWG24), Insulator diameter: 1.1 mm)

Accessories (sold separately)



Nomenclature



Operating Procedure

E3X-SD

1 Sensitivity Setting

The sensitivity can be set with the UP and DOWN Keys similar to using an adjuster knob. The sensitivity can also be easily set by using the following two teaching functions.

2-1. Teaching with/without a Workpiece

Two points (one with the workpiece and the other without) are detected, and the operating level is set to the midpoint. Light level is also automatically set to the optimal value.

Operation description	Button/Key
Press the TEACH button with the workpiece.	TEACH
Press the TEACH button without the workpiece.	TEACH

2-2. Automatic Teaching

Changes within a time are detected, and the operating level is set to the midpoint between the maximum and the minimum values of the changes. This setting is optimal for when the workpieces cannot be stopped. Execute automatic teaching again if the incident light level is not automatically set to the optimal value.

Operation description	Button/Key
Press the TEACH button for 3 s min. Let the workpiece pass while the button is pressed.	TEACH

E3X-NA

1 Displays

A bar display (with four green and one red) showing excess gain is provided in addition to the orange operation indicator. Use these when adjusting the light axis and setting the sensitivity at setup.

Display/indicator status (for L/ON)	Excess gain level	Description
Operation indicator	Approx. 120% min.	Stable incident light
	Approx. 110% to 120%	
	Approx. 90% to 110%	Unstable incident light or Unstable interrupted light
	Approx. 80% to 90%	Stable interrupted light
	Approx. 80% max.	

READ AND UNDERSTAND THIS DOCUMENT

Please read and understand this document before using the products. Please consult your OMRON representative if you have any questions or comments.

WARRANTY

OMRON's exclusive warranty is that the products are free from defects in materials and workmanship for a period of one year (or other period if specified) from date of sale by OMRON.

OMRON MAKES NO WARRANTY OR REPRESENTATION, EXPRESS OR IMPLIED, REGARDING NON-INFRINGEMENT, MERCHANTABILITY, OR FITNESS FOR PARTICULAR PURPOSE OF THE PRODUCTS. ANY BUYER OR USER ACKNOWLEDGES THAT THE BUYER OR USER ALONE HAS DETERMINED THAT THE PRODUCTS WILL SUITABLY MEET THE REQUIREMENTS OF THEIR INTENDED USE. OMRON DISCLAIMS ALL OTHER WARRANTIES, EXPRESS OR IMPLIED.

LIMITATIONS OF LIABILITY

OMRON SHALL NOT BE RESPONSIBLE FOR SPECIAL, INDIRECT, OR CONSEQUENTIAL DAMAGES, LOSS OF PROFITS OR COMMERCIAL LOSS IN ANY WAY CONNECTED WITH THE PRODUCTS, WHETHER SUCH CLAIM IS BASED ON CONTRACT, WARRANTY, NEGLIGENCE, OR STRICT LIABILITY.

In no event shall responsibility of OMRON for any act exceed the individual price of the product on which liability is asserted.

IN NO EVENT SHALL OMRON BE RESPONSIBLE FOR WARRANTY, REPAIR, OR OTHER CLAIMS REGARDING THE PRODUCTS UNLESS OMRON'S ANALYSIS CONFIRMS THAT THE PRODUCTS WERE PROPERLY HANDLED, STORED, INSTALLED, AND MAINTAINED AND NOT SUBJECT TO CONTAMINATION, ABUSE, MISUSE, OR INAPPROPRIATE MODIFICATION OR REPAIR.

SUITABILITY FOR USE

THE PRODUCTS CONTAINED IN THIS DOCUMENT ARE NOT SAFETY RATED. THEY ARE NOT DESIGNED OR RATED FOR ENSURING SAFETY OF PERSONS, AND SHOULD NOT BE RELIED UPON AS A SAFETY COMPONENT OR PROTECTIVE DEVICE FOR SUCH PURPOSES. Please refer to separate catalogs for OMRON's safety rated products.

OMRON shall not be responsible for conformity with any standards, codes, or regulations that apply to the combination of products in the customer's application or use of the product.

At the customer's request, OMRON will provide applicable third party certification documents identifying ratings and limitations of use that apply to the products. This information by itself is not sufficient for a complete determination of the suitability of the products in combination with the end product, machine, system, or other application or use.

The following are some examples of applications for which particular attention must be given. This is not intended to be an exhaustive list of all possible uses of the products, nor is it intended to imply that the uses listed may be suitable for the products:

- Outdoor use, uses involving potential chemical contamination or electrical interference, or conditions or uses not described in this document.
 Nuclear energy control systems, combustion systems, railroad systems, aviation systems, medical equipment, amusement machines, vehicles,
- safety equipment, and installations subject to separate industry or government regulations.
- · Systems, machines, and equipment that could present a risk to life or property.

Please know and observe all prohibitions of use applicable to the products.

NEVER USE THE PRODUCTS FOR AN APPLICATION INVOLVING SERIOUS RISK TO LIFE OR PROPERTY WITHOUT ENSURING THAT THE SYSTEM AS A WHOLE HAS BEEN DESIGNED TO ADDRESS THE RISKS, AND THAT THE OMRON PRODUCT IS PROPERLY RATED AND INSTALLED FOR THE INTENDED USE WITHIN THE OVERALL EQUIPMENT OR SYSTEM.

PERFORMANCE DATA

Performance data given in this document is provided as a guide for the user in determining suitability and does not constitute a warranty. It may represent the result of OMRON's test conditions, and the users must correlate it to actual application requirements. Actual performance is subject to the OMRON Warranty and Limitations of Liability.

CHANGE IN SPECIFICATIONS

Product specifications and accessories may be changed at any time based on improvements and other reasons.

It is our practice to change model numbers when published ratings or features are changed, or when significant construction changes are made. However, some specifications of the product may be changed without any notice. When in doubt, special model numbers may be assigned to fix or establish key specifications for your application on your request. Please consult with your OMRON representative at any time to confirm actual specifications of purchased products.

DIMENSIONS AND WEIGHTS

Dimensions and weights are nominal and are not to be used for manufacturing purposes, even when tolerances are shown.

ERRORS AND OMISSIONS

The information in this document has been carefully checked and is believed to be accurate; however, no responsibility is assumed for clerical, typographical, or proofreading errors, or omissions.

PROGRAMMABLE PRODUCTS

OMRON shall not be responsible for the user's programming of a programmable product, or any consequence thereof.

COPYRIGHT AND COPY PERMISSION

This document shall not be copied for sales or promotions without permission.

This document is protected by copyright and is intended solely for use in conjunction with the product. Please notify us before copying or reproducing this document in any manner, for any other purpose. If copying or transmitting this document to another, please copy or transmit it in its entirety.

This document provides information mainly for selecting suitable models. Please read the Instruction sheet carefully for information that the user must understand and accept before purchase, including information on warranty, limitations of liability, and precautions.

OMRON Corporation Industrial Tokyo, JAPAN Contact: www.ia.om	I Automation Company ron.com	Authorized Distributor:	
Regional Headquarters OMRON EUROPE B.V. Sensor Business Unit Carl-Benz-Str. 4, D-71154 Nufringen, Germany Tel: (49) 7032-811-0/Fax: (49) 7032-811-199	OMRON ELECTRONICS LLC One Commerce Drive Schaumburg, IL 60173-5302 U.S.A. Tel: (1) 847-843-7900/Fax: (1) 847-843-7787		
OMRON ASIA PACIFIC PTE. LTD. No. 438A Alexandra Road # 05-05/08 (Lobby 2), Alexandra Technopark, Singapore 119967 Tel: (65) 6835-3011/Fax: (65) 6835-2711	OMRON (CHINA) CO., LTD. Room 2211, Bank of China Tower, 200 Yin Cheng Zhong Road, PuDong New Area, Shanghai, 200120, China Tel: (86) 21-5037-2222/Fax: (86) 21-5037-2200	© OMRON Corporation 2010 All Rights Reserved. In the interest of product improvement, specifications are subject to change without notice. CSM_3_1_1010 Cat. No. E401-E1-01	0110



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный) **Факс:** 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.