DS26334DK/DS26324DK
3.3V, 16-Channel, E1/T1/J1 Short-/Long-Haul LIU Design Kit

www.maxim-ic.com

GENERAL DESCRIPTION

The DS26334DK/DS26324DK is a fully integrated design kit for the DS26334 and DS26324 3.3V, 16-channel, E1/T1/J1 line interface units (LIUs). This design kit contains all the necessary circuitry to evaluate the DS26334 and DS26324 in all modes of operation. The design kit also includes an on-board microprocessor to run real-time code for further part evaluation.

DESIGN KIT CONTENTS


DS26334DK Board with a DS26324 or DS26334
5V AC/DC Adapter
3ft USB Cable
Download:
- ChipView Software
- DS26334DK/DS26324DK.def Definition File
- DS26334DK/DS26324DK Data Sheet

ORDERING INFORMATION

PART	DESCRIPTION
DS26334DK	Design Kit Board for DS26334
DS26324DK	Design Kit Board for DS26324

FEATURES

- **Expedites New Designs by Eliminating First-Pass Prototyping**
- **Demonstrates Key Functions of the DS26334/DS26324**
- **Includes DS26334/DS26324 x 16-Port LIU, Transformers, 75Ω BNC Connectors, RJ-48 Connectors, and Termination Passives**
- **Communicates Directly with any PC with a USB or RS-232 Serial Interface**
- **High-Level Windows®-Based Software Provides Visual Access to All Registers**
- **Software-Controlled (Register) Mapped Configuration Switches Facilitate Real-Time Clock and Signal Routing**
- **Precision Test Points for All Clocks and Signals**
- **On-Board T1 and E1 Crystal Oscillators for Stable Clock Generation**
- **On-Board BERT for Testing and Pattern Generation**



Windows is a registered trademark of Microsoft Corp.

TABLE OF CONTENTS

COMPONENT LIST 3

BOARD FLOORPLAN 6

BASIC OPERATION 7

HARDWARE CONFIGURATION 7

QUICK START (HARDWARE SETTINGS—SINGLE POWER SUPPLY) 7
JTAG CONFIGURATION 7
Table 1. JTAG Connector (J6) Pinout 7
Figure 1. DS26334DK JTAG Chain 8
ADDRESS/DATA BUS CONNECTOR 8
Table 2. Address/Data Connector Pinout 8
TELECOM CLOCK AND DATA TEST POINTS 9
Table 3. Telecom Connector Pinout 9
ON-BOARD BIT ERROR-RATE TESTER (BERT) 9
Table 4. BERT Connector Pinout 9
PROM SPI CONFIGURATION 10
Figure 2. SPI Timing Diagram 10
Figure 3. SPI Configuration with PROM 11
Table 5. Configuration Memory 11

SOFTWARE CONFIGURATION 12

QUICK START (SOFTWARE—CHIPVIEW) 12

MEMORY MAP 12

Table 6. DS26334DK Relative Address Map 12
Table 7. General-Purpose FPGA Memory Map 12

ID REGISTERS 13

CONTROL REGISTERS 13

DS26334 INFORMATION 21

DS26324 INFORMATION 21

DS26334DK/DS26324DK INFORMATION 21

TECHNICAL SUPPORT 21

ERRATA 21

SCHEMATICS 21


COMPONENT LIST

DESIGNATION	QTY	DESCRIPTION	SUPPLIER/ PART NUMBER
C1, C4, C6, C7, C31, C33–C41, C43–C46, C49, C51–C54, C56–C58, C61–C93, C95–C108	66	0.1µF ±20%, 16V X7R ceramic capacitors (0603)	AVX 0603YC104MAT
C2, C3, C27, C37, C42, C48, C50, C55, C59, C60	10	1µF ±10%, 16V ceramic capacitors (1206)	Panasonic ECJ-3YB1C105K
C5, C16, C26, C30, C34, C35, C94	7	10µF ±20%, 10V ceramic capacitors (1206)	Panasonic ECJ-3YB1A106M
C8–C14, C17–C25	16	470pF ±10%, 100V ceramic capacitors (0603)	Panasonic ECJ-1VB2A471K
C15	1	6.8µF ±10%, 6.3V X5R ceramic capacitors (1206)	Panasonic ECJ-3YB0J685K
C28, C29, C32, C109, C110	5	68µF ±20%, 16V tantalum capacitors (D case)	Panasonic ECS-T1CD686R
C36, C38, C47	3	22pF ±5%, 25V ceramic capacitors (0603)	AVX 06033A220JAT
C39, C40	2	10pF ±5%, 50V ceramic capacitors (1206) (tall case)	Phycomp 1206CG100J9B200
D1, D20	2	Green LEDs (SMD)	Panasonic LN1351C
D2–D19	18	Red LEDs (SMD)	Panasonic LN1251C
D21, D22, D23	3	1A, 40V Schottky diodes	International Rectifier 10BQ040
H1–H4	4	KIT, 4-40 hardware 0.75 nylon standoff and 0.25 nylon screw	Not applicable 4-40KIT2
J1	1	DB9 right-angle connector (short case)	AMP 788750-2
J2	1	Black, single right angle (Type B)	Molex Not applicable
J3	1	2.5mm connector Power jack, right-angle PC board mount	Switchcraft RAPC712
J4	1	40-pin terminal strip (dual row, vertical)	Samtec TSW-120-07-T-D
J5, J7, J8, J28–J31, J34–J37, J40–J43, J49–J52	19	5-pin, 75Ω BNC connectors (vertical)	Cambridge CP-BNCPC-004
J6, J9–J25	18	14-pin headers (dual row, vertical)	Samtec TSW-107-14-T-D
J26, J27, J32, J33, J38, J39, J47, J48	8	2-pin headers, 0.100in centers (vertical)	Samtec TSW-102-07-T-S
J44, J45, J46	3	100-mil 3-position jumpers	Samtec Not applicable
J53, J54	2	8-pin 4-port RJ45 jacks (right angle)	Molex 43223-8140
L1	1	1.0µH ±20%, 2-pin SMT inductor	Coiltronics UP1B-1R0
R1, R20, R61, R90, R138	5	Resistors (0603) **DO NOT POPULATE**	—

DESIGNATION	QTY	DESCRIPTION	SUPPLIER/ PART NUMBER
R2, R23, R37, R38, R39, R42, R45, R47–R50, R52, R53, R55, R57–R60, R66–R69, R71, R72, R74–R76, R79, R80, R85, R88, R89, R91, R99, R103, R104, R105, R110	38	10kΩ ±5%, 1/16W resistors (0603)	Panasonic ERJ-3GEYJ103V
R3–R19, R21, R22, R24–R36, R41, R44, R46, R51, R63, R64, R65, R81, R82, R102, R109, R116, R120, R121, R122, R126, R130, R131, R132, R134–R137, R139, R140, R148, R151, R153	60	33Ω ±5%, 1/16W resistors (0603)	Panasonic ERJ-3GEYJ330V
R40, R70, R73, R77, R78, R83, R84, R86, R87, R92, R93, R95–R98, R100, R101, R106, R107, R108	20	330Ω ±5%, 1/16W resistors (0603)	Panasonic ERJ-3GEYJ331V
R43, R62	2	15kΩ ±5%, 1/16W resistors (0603)	Panasonic ERJ-3GEYJ153V
R54	1	Resistor (1206) **DO NOT POPULATE**	—
R56	1	470Ω ±5%, 1/16W resistor (0603)	Panasonic ERJ-3GEYJ471V
R94	1	51Ω ±5%, 1/16W resistor (0603)	Panasonic ERJ-3GEYJ510V
R111–R115, R117, R118, R119, R123, R124, R125, R127, R128, R129, R133, R141–R144, R146, R147, R149, R150, R152, R154–R161	32	60.4Ω ±1%, 1/16W resistors (0603)	Panasonic ERJ-3EKF60R4V
R145	1	22kΩ ±5%, 1/16W resistor (0603)	Panasonic ERJ-3GEYJ223V
SW1, SW2, SW6	3	4-pin single-pole switch	Panasonic EVQPAE04M
SW3, SW4, SW5, SW7	4	6-pin slide switches (DPDT, through hole)	Tyco Electronics SSA22
T1–T4	4	32-pin transmit/receive SMT transformers (1:2 and 1:1)	Pulse Engineering TX1475
U1	1	8-bit FIFO USB UART (32-pin LQFP)	FTDI FT245BM
U2	1	MCORE Microcontroller (144-pin LQFP)	Motorola MMC2107PV
U3, U10	2	128k x 8 SRAM (32-pin SO)	Cypress CY62128VL-70SC

DESIGNATION	QTY	DESCRIPTION	SUPPLIER/ PART NUMBER
U4	1	DS2174 EBERT (44-pin PLCC, 0°C to +70°C)	Dallas Semiconductor DS2174Q
U5	1	Spartan-II 2.5V FPGA, 200k gate (256-pin BGA)	Xilinx XC2S200-5FG256C
U6	1	3.3V, 16-channel, E1/T1/J1 long-haul LIU (256-pin BGA, 0°C to +70°C)	Dallas Semiconductor DS26334
U7	1	Dual RS-232 transmitter/receiver (150-mil, 16-pin SO)	Dallas Semiconductor DS232AR
U8, U11	2	High-speed buffers	Fairchild Semiconductor NC7SZ86
U9, U20	2	1.5W, 3.3V or adj, 1A linear regulators (16-pin TSSOP-EP)	Maxim MAX1793EUE-33
U12	1	PROM for FPGA (44-pin TQFP)	Xilinx XC18V02VQ44C
U13, U14, U18	3	Hex inverters (14-pin SO)	Toshiba TC74HC04AFN
U15	1	2.5V or adj linear regulator (8-pin μMAX/SO)	Maxim MAX1792EUA25
U16	1	Platform flash in-system programmable configuration PROM (2Mb, 20-pin TSSOP)	Xilinx XCF02SVO20C
U17	1	Quad 2-input NAND gate (14-pin SO)	Toshiba TC74HC00AFN
U19	1	Switch debouncer (4-pin SOT143)	Maxim MAX6816EUS-T
X1	1	6.00MHz low-profile crystal	Pletronics LP49-26-6.00M
X2	1	8.000MHz low-profile crystal	Ecliptek Corp. EC1-8.000M
Y1	1	Oscillator, crystal clock 5V, 2.048MHz	SaRonix NTH039A-2.0480
Y2	1	Oscillator, crystal clock 5V, 1.544MHz	SaRonix NTH039A-1.5440

BOARD FLOORPLAN



BASIC OPERATION

This design kit relies upon several supporting files, which are available for downloading on our website at www.maxim-ic.com/DS26334DK.

The support files are used with an evaluation program called ChipView, which is available for download at www.maxim-ic.com/telecom.

HARDWARE CONFIGURATION

Quick Start (Hardware Settings—Single Power Supply)

- For single power-supply operation, short jumpers J44, J45, and J46 between the 3.3V pin and the VLIU pin. This connects VDD of the DS26334/DS26324 to the 3.3V supply on the design kit.
- Ensure that the FLASH switch (SW3) is in the *RUN* position.
- Ensure that the FPGA switch (SW5) is in the *ON* position.
- Ensure that the SPI/PROM switch (SW7) is in the *OFF* position.
- If using the serial port, connect an RS-232 serial cable from DS26334DK (J1) to the PC.
- If using the USB port, connect a USB cable from DS26334DK (J2) to the PC.
- Connect AC/DC adapter with an AC power source and the DS26334DK (J3). PWR LED should be on.

JTAG Configuration


The JTAG chain is controlled by the connector JTAG CON (J6) and two on-board switches: FLASH (SW3) and ONCE/JTAG (SW4). Depending on the function, such as programming the internal microcontroller flash or performing boundary scan operations, the JTAG CON connector can be used and the switches can be configured to accomplish the desired task. For information on programming the internal flash of the on-board microcontroller, refer to the MMC2107 microcontroller user manual and board schematic.

For most purposes, having the complete JTAG chain is sufficient. Figure 1 shows the complete chain as well as what order the devices appear during boundary scan. Table 1 shows the pinout of the JTAG connector. Connect any JTAG cable to the connector to perform all operations. Note the JTAG chain changes depending on the switch SW4. The ONCE location of SW4 is used for programming the on-board microcontroller only.

Table 1. JTAG Connector (J6) Pinout

PIN	NAME
1	JTDI
2, 4, 6, 7	GND
3	JTDO
5	JTCLK
8	ALIGN KEY
9	BRD RST
10	JTMS
11	BRD V3.3
12	JDE
13	N.C.
14	JTRST

Figure 1. DS26334DK JTAG Chain



Address/Data Bus Connector

The DS26334DK has a connector (J4) to monitor all local bus activity for the design kit. All the signals can be captured with a high-impedance probe and displayed on an oscilloscope or logic analyzer. **Note:** If the FPGA switch (SW5) is in the "OFF" position, the on-board microcontroller will no longer drive any data onto the local bus. Therefore, the user can now connect the local bus of the DS26334/DS26324 into another system without making any modifications to the hardware. See Table 2 for specific pin information for connector J4.

Table 2. Address/Data Connector Pinout

PIN	NAME	FUNCTION		PIN	NAME	FUNCTION
1	A8	Local Address Bit 8		2	D0	Local Data Bit 0
3	A7	Local Address Bit 7		4	D1	Local Data Bit 1
5	A6	Local Address Bit 6		6	D2	Local Data Bit 2
7	A5	Local Address Bit 5		8	D3	Local Data Bit 3
9	A4	Local Address Bit 4		10	D4	Local Data Bit 4
11	A3	Local Address Bit 3		12	D5	Local Data Bit 5
13	A2	Local Address Bit 2		14	D6	Local Data Bit 6
15	A1	Local Address Bit 1		16	D7	Local Data Bit 7
17	A0	Local Address Bit 0		18	CLKE	SPI Clock Edge Select
19	MUX	Mux		20	RDY	Ready Handshake from LIU
21	CSFPGA	Chip Select FPGA		22	OE	Output Enable LIU
23	CSBERT	Chip Select DS2174		24	MOTEL	Motorola/Intel Select
25	CSLIU	Chip Select DS26334/DS26324		26	INT	Interrupt for DS26334/DS26324
27	ALELIU	Address Latch Enable		28	FPGAEN	FPGA Enable Pin
29	RD	Read Signal		30	UIN1	User Input 1
31	WR	Write Signal		32	UIN2	User Input 2
33	MODESEL	Mode Select		34, 36	3.3V	Board 3.3V
35	RSTLIU	Reset DS26334/DS26324		37–40	GND	Ground

Telecom Clock and Data Test Points

The DS26334DK has high-impedance test points for all the telecom signals that are related to the LIU. These signals are split up by port number and marked with easy to read silkscreen labels. Table 3 shows the telecom connector for port 1. The pinout for this connector is repeated for all 16 ports.

Table 3. Telecom Connector Pinout

PIN	NAME	FUNCTION
1	TCLK	Transmit Clock Input
2, 4, 6, 8, 10, 12, 14	GND	Ground
3	RCLK	Receive Clock Output
5	TPOS	Transmit Positive Data Input
7	RPOS	Receive Positive Data Output
9	TNEG	Transmit Negative Data Input
11	RNEG	Receive Positive Data Output
13	RLOS	Receive Loss-of-Signal Output

Note that the input signals in the telecom connector go from the connector to the on-board FPGA, then to the DS26334/DS26324. The FPGA was designed to perform specific signal routing functions such as looping back RPOS to TPOS on a particular port or transferring data from the on-board BERT. If you are using user-defined data and drive the signal on the connector, be sure to tri-state the input signal in the FPGA. **FAILURE TO DO SO COULD CAUSE DAMAGE TO THE FPGA**!

On-Board Bit Error-Rate Tester (BERT)

The DS26334DK has an on-board bit error-rate tester (BERT) to generate and detect errors in either pseudorandom or user-defined patterns. The BERT on the DS26334DK is the DS2174. A header for the relevant signals related to the BERT is located on the board (J22). See Table 4 for the pinout of the BERT connector. The BERT signals are routed into the FPGA and can be muxed into any of the 16 DS26334/DS26324 LIU ports under software control. For all questions concerning the operation of the on-board BERT, refer to the device data sheet available online at www.maxim-ic.com/telecom. If you are using user-defined data and driver the signal on the connector, be sure to tri-state the input signal in the FPGA. **FAILURE TO DO SO COULD CAUSE DAMAGE TO THE FPGA!**

Table 4. BERT Connector Pinout

PIN	NAME	FUNCTION
1	TCLK_EN	BERT TCLK Enable
2, 4, 6, 8, 10, 12, 14	GND	Ground
3	TCLKIN	BERT TCLK Input
5	TCLKO	BERT TCLK Output
7	RCLKIN	BERT RCLK Input
9	RCLKEN	BERT RCLK Enable
11	TDAT	BERT TDAT Output
13	RDAT	BERT RDAT Input

PROM SPI Configuration

In software mode, it is possible to configure the DS26334/DS26324 using a parallel interface or a serial peripheral interface (SPI). Most advanced microcontrollers have both a parallel interface and SPI interface such as the microcontroller on the DS26334DK. The command you send to the microcontroller through either the USB or serial port determines if that data is placed on the parallel or SPI bus. Refer to the data sheet for ChipView on the particular commands required to switch data ports.

A unique feature with the SPI port is that a PROM can be used to provide the LIU with the specific data needed for configuration. If the data in the PROM is formatted a certain way, it can seem as the PROM is acting like a controller with a SPI interface in master mode.

The most common PROMs to use for this type of application are those with an internal address accumulator. This feature for the PROM is important because the device must automatically jump to the next available address in the configuration memory. The Xilinx XC18V00 device family is a byte-wide nonvolatile memory with an autoincrement address function. The family of devices is available in 1Mb, 2Mb, and 4Mb densities. The PROM is also useful because the device can perform in-circuit programming with the JTAG port. Refer the data sheet for the XC18V00 for the JTAG codes for programming the configuration memory.

Figure 2 shows a general relationship of the timing for a SPI bus. For this case, all data is clocked into the slave device on the rising edge of SCLK. This feature can be configurable on the DS26334/DS26324.

Figure 2. SPI Timing Diagram




Figure 3 shows a simplified diagram of the XC18V00 device and the DS26334/DS26324 in SPI (serial) mode. Notice a few key points about this diagram. First, the CLK for the XC18V00 is the MCLK for the LIU, but this is not the SCLK for the SPI interface. The SCLK can be programmed as needed. See Table 5 for an example of the memory map. Second, the programming for this device begins when OE on the XC18V00 goes high. Therefore, consideration must be taken if some delay is necessary. Generally, it is sufficient for the OE pin to be connected to some power-up delay device. The OE delay is not necessary on this DK.

Figure 3. SPI Configuration with PROM




Table 5. Configuration Memory

ADDRESS	D7	D6	D5	D4	D3	D2	D1	D0
	CSB	SCLK	SDI	X	X	X	X	X
0x00	1	0	0	Start of Write Cycle				
0x01	0	0	0	Bit A0 (Always a "0" for a write)				
0x02	0	1	0					
0x03	0	0	1	Bit A1				
0x04	0	1	1					
0x05	0	0	0	Bit A2				
0x06	0	1	0					
0x07	0	0	0	Bit A3				
0x08	0	1	0					
0x09	0	0	0	Bit A4				
0x0A	0	1	0					
0x0B	0	0	0	Bit A5				
0x0C	0	1	0					
0x0D	0	0	0	Bit A6				
0x0E	0	1	0					
0x0F	0	0	0	Bit A7				
0x10	0	1	0					
0x11	0	0	0	Bit D0 (LSB)				
0x12	0	1	0					
0x13	0	0	1	Bit D1				
0x14	0	1	1					
0x15	0	0	1	Bit D2				
0x16	0	1	1					
0x17	0	0	0	Bit D3				
0x18	0	1	0					
0x19	0	0	0	Bit D4				
0x1A	0	1	0					
0x1B	0	0	1	Bit D5				
0x1C	0	1	1					
0x1D	0	0	1	Bit D6				
0x1E	0	1	1					
0x1F	0	0	0	Bit D7				
0x20	0	1	0					
0x21	1	0	X	End of Write Cycle				
0x22	1	X	X					

SOFTWARE CONFIGURATION

Quick Start (Software—ChipView)

- Perform steps in the Quick Start (Hardware Configuration).
- Load ChipView software.
- Select COM port.
- Select Register View.
- From the Programs menu, launch the host application named ChipView.exe. If the default installation options were used, click the Start button on the Windows toolbar and select Programs -> ChipView -> ChipView.
- Load the DS26334DK.def file.
- Make sure that all the register settings are correct for the proper function desired for the DS26334DK.
- Refer to the DS26334 and DS26324 data sheets for all questions pertaining to device functionality.

MEMORY MAP

The on-board microcontroller is configured to start the user address space at 0x81000000. All offsets given below are relative to the beginning of the user address space.

Table 6. DS26334DK Relative Address Map

REF DES	DEVICE	OFFSET
U5	General-Purpose FPGA Tx/Rx Clock, Data Switch/Mux	0x0000
U4	DS2174 BERT	0x1000
U6	DS26334/DS26324 16-Port T1/E1/J1 LIUs	0x2000

All device registers can be easily modified using the ChipView.exe host-based user-interface software.

Table 7. General-Purpose FPGA Memory Map

OFFSET	REGISTER NAME	TYPE	DESCRIPTION
0x00	BRDID	Read-Only	Board ID
0x02	DSIDH	Read-Only	Dallas Extended ID Upper Nibble
0x03	DSIDM	Read-Only	Dallas Extended ID Middle Nibble
0x04	DSIDL	Read-Only	Dallas Extended ID Lower Nibble
0x05	BRDREV	Read-Only	Board Rev
0x06	ASMREV	Read-Only	Assembly Rev
0x07	FPGAREV	Read-Only	FPGA Firmware Rev
0x08	CTRL1	Control	Control Register 1
0x0A	ABSP	Control	Address Bank Select Pointer
0x0B	BTCLK	Control	BERT TCLK Input
0x0C	BRCLK	Control	BERT RCLK Input
0x0D	BRDAT	Control	BERT RDAT Input
0x10	TCLK	Control	Indirect Register for TCLK Source Control
0x11	TPOS	Control	Indirect Register for TPOS Source Control
0x12	TNEG	Control	Indirect Register for TPOS Source Control

ID REGISTERS

BID: BOARD ID (Offset = 0X0000)

BID is read-only with a value of 0xD.

XBIDH: HIGH NIBBLE EXTENDED BOARD ID (Offset = 0X0002)

XBIDH is read-only with a value of 0x0.

XBIDM: MIDDLE NIBBLE EXTENDED BOARD ID (Offset = 0X0003)

XBIDM is read-only with a value of 0x1.

XBIDL: LOW NIBBLE EXTENDED BOARD ID (Offset = 0X0004)

XBIDL is read-only with a value of 0x6.

BREV: BOARD FAB REVISION (Offset = 0X0005)

BREV is read-only and displays the current fab revision.

AREV: BOARD ASSEMBLY REVISION (Offset = 0X0006)

AREV is read-only and displays the current assembly revision.

PREV: FPGA REVISION (Offset = 0X0007)

PREV is read-only and displays the current PLD firmware revision.

CONTROL REGISTERS

Register Name: **CTRL_1**
Register Description: **DS26334DK FPGA CONTROL REGISTER 1**
Register Offset: **0x08**

Bit #	7	6	5	4	3	2	1	0
Name	ENRLOS16	ENRLOS15	CLKE	SPI_SWAP	SPI	OE	MCLK1	MCLK0

Bit 7: ENRLOS16. This bit enables the RLOS16 LED. This should not be enabled when driving TECLK from the DS26334/DS26324.

If ENRLOS16 = LOW, the RLOS16 LED is not enabled.
If ENRLOS16 = HIGH, the RLOS16 LED is enabled and lights when RLOS16 is high.

Bit 6: ENRLOS15. This bit enables the RLOS15 LED. This should not be enabled when driving CLKA from the DS26334/DS26324.

If ENRLOS15 = LOW, the RLOS15 LED is not enabled.
If ENRLOS15 = HIGH, the RLOS15 LED is enabled and lights when RLOS15 is high.

Bit 5: CLKE. This bit sets the CLKE pin on the DS26334/DS26324. This is only active when SPI (Bit 0) is HIGH. If SPI (Bit 0) is low, CLKE is always low.

If CLKE = LOW, SDO is clocked out on the rising edge of SCLK.
If CLKE = HIGH, SDO is clocked out on the falling edge of SCLK.

Bit 4: SPI_SWAP. This bit sets the BSWP/A5 pin on the DS26334/DS26324. This is only active when SPI (Bit 0) is HIGH.

If SPI_SWAP = LOW, the SPI bus is LSB first.
If SPI_SWAP = HIGH, the SPI bus is MSB first.

Bit 3: SPI. This bit sets up the FPGA to use serial mode. This bit also changes the mode pin on the DS26334/DS26324.

If SPI = LOW, the parallel bus is used for all read/write access. This also sets the MODE pin on the DS26334/DS26324 to logic 1.
If SPI = HIGH, the SPI bus is used for all read/write access. This also sets the MODE pin on the DS26334/DS26324 to logic 0.

Bit 2: OE. This bit controls the OE pin to the DS26334.

Bits 1 and 0: MCLK1 and MCLK0. These bits control the MCLK pin to the DS26334/DS26324.

MCLK1	MCLK0	DESCRIPTION OF MCLK
0	0	MCLK = high-impedance mode
0	1	MCLK = on-board T1 oscillator
1	0	MCLK = on-board E1 oscillator
1	1	MCLK = user clock input

Register Name: **ABSP**
Register Description: **ADDRESS BANK SWAP POINTER**
Register Offset: **0x0A**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Bits 7 to 0: D7 to D0. These bits control the address bank for address 0x10 (TCLK N), 0x11 (TPOS), and 0x12 (TNEG).

ABSP	DESCRIPTION
0x00	Bank Address Value for Port 1
0x01	Bank Address Value for Port 2
0x02	Bank Address Value for Port 3
0x03	Bank Address Value for Port 4
0x04	Bank Address Value for Port 5
0x05	Bank Address Value for Port 6
0x06	Bank Address Value for Port 7
0x07	Bank Address Value for Port 8
0x08	Bank Address Value for Port 9
0x09	Bank Address Value for Port 10
0x0A	Bank Address Value for Port 11
0x0B	Bank Address Value for Port 12
0x0C	Bank Address Value for Port 13
0x0D	Bank Address Value for Port 14
0x0E	Bank Address Value for Port 15
0x0F	Bank Address Value for Port 16

Register Name: **BTCLK**
Register Description: **BERT TCLK SOURCE**
Register Offset: **0x0B**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Bits 7 to 0: D7 to D0. These bits control the source of the TCLK for the BERT.

BTCLK	DESCRIPTION
0x00	RCLK Port 1
0x01	RCLK Port 2
0x02	RCLK Port 3
0x03	RCLK Port 4
0x04	RCLK Port 5
0x05	RCLK Port 6
0x06	RCLK Port 7
0x07	RCLK Port 8
0x08	RCLK Port 9
0x09	RCLK Port 10
0x0A	RCLK Port 11
0x0B	RCLK Port 12
0x0C	RCLK Port 13
0x0D	RCLK Port 14
0x0E	RCLK Port 15
0x0F	RCLK Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334
0x14	TECLK DS26334
0x15	TCLKBERT OUT
0x16–0xFF	HI-Z

Register Name: **BRCLK**
Register Description: **BERT RCLK SOURCE**
Register Offset: **0x0C**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Bits 7 to 0: D7 to D0. These bits control the source of the RCLK for the BERT.

BTCLK	DESCRIPTION
0x00	RCLK Port 1
0x01	RCLK Port 2
0x02	RCLK Port 3
0x03	RCLK Port 4
0x04	RCLK Port 5
0x05	RCLK Port 6
0x06	RCLK Port 7
0x07	RCLK Port 8
0x08	RCLK Port 9
0x09	RCLK Port 10
0x0A	RCLK Port 11
0x0B	RCLK Port 12
0x0C	RCLK Port 13
0x0D	RCLK Port 14
0x0E	RCLK Port 15
0x0F	RCLK Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334/DS26324
0x14	TECLK DS26334/DS26324
0x15	TCLKBERT OUT
0x16–0xFF	HI-Z

Register Name: **BRDAT**
Register Description: **BERT RDAT SOURCE**
Register Offset: **0x0D**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Bits 7 to 0: D7 to D0. These bits control the source of the RDAT for the BERT. Note that the DS26334/DS26324 must be in single-rail mode for BERT to function properly.

BRDAT	DESCRIPTION
0x00	RPOS Port 1
0x01	RPOS Port 2
0x02	RPOS Port 3
0x03	RPOS Port 4
0x04	RPOS Port 5
0x05	RPOS Port 6
0x06	RPOS Port 7
0x07	RPOS Port 8
0x08	RPOS Port 9
0x09	RPOS Port 10
0x0A	RPOS Port 11
0x0B	RPOS Port 12
0x0C	RPOS Port 13
0x0D	RPOS Port 14
0x0E	RPOS Port 15
0x0F	RPOS Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334/DS26324
0x14	TECLK DS26334/DS26324
0x15	TCLKBERT OUT
0x16–0xFF	HI-Z

Register Name: **TCLK**
Register Description: **PORT TCLK SOURCE**
Register Offset: **0x10**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Note: *This is an indirect register that is related to ABSP (0x0A). See register description.*

Bits 7 to 0: D7 to D0. These bits control the source of the port TCLK for the DS26334/DS26324.

TCLK	DESCRIPTION
0x00	RCLK Port 1
0x01	RCLK Port 2
0x02	RCLK Port 3
0x03	RCLK Port 4
0x04	RCLK Port 5
0x05	RCLK Port 6
0x06	RCLK Port 7
0x07	RCLK Port 8
0x08	RCLK Port 9
0x09	RCLK Port 10
0x0A	RCLK Port 11
0x0B	RCLK Port 12
0x0C	RCLK Port 13
0x0D	RCLK Port 14
0x0E	RCLK Port 15
0x0F	RCLK Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334/DS26324
0x14	TECLK DS26334/DS26324
0x15	TCLKBERT OUT
0x16–0xFF	HI-Z

Register Name: **TPOS**
Register Description: **PORT TPOS SOURCE**
Register Offset: **0x11**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Note: *This is an indirect register that is related to ABSP (0x0A). See register description.*

Bits 7 to 0: D7 to D0. These bits control the source of the port TPOS for the DS26334/DS26324.

TPOS	DESCRIPTION
0x00	RPOS Port 1
0x01	RPOS Port 2
0x02	RPOS Port 3
0x03	RPOS Port 4
0x04	RPOS Port 5
0x05	RPOS Port 6
0x06	RPOS Port 7
0x07	RPOS Port 8
0x08	RPOS Port 9
0x09	RPOS Port 10
0x0A	RPOS Port 11
0x0B	RPOS Port 12
0x0C	RPOS Port 13
0x0D	RPOS Port 14
0x0E	RPOS Port 15
0x0F	RPOS Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334/DS26324
0x14	TECLK DS26334/DS26324
0x15	TDATBERT OUT
0x16–0xFF	HI-Z

Register Name: **TNEG**
Register Description: **PORT TNEG SOURCE**
Register Offset: **0x12**

Bit #	7	6	5	4	3	2	1	0
Name	D7	D6	D5	D4	D3	D2	D1	D0

Note: *This is an indirect register that is related to ABSP (0x0A). See register description.*

Bits 7 to 0: D7 to D0. These bits control the source of the port TNEG for the DS26334/DS26324.

TNEG	DESCRIPTION
0x00	RNEG Port 1
0x01	RNEG Port 2
0x02	RNEG Port 3
0x03	RNEG Port 4
0x04	RNEG Port 5
0x05	RNEG Port 6
0x06	RNEG Port 7
0x07	RNEG Port 8
0x08	RNEG Port 9
0x09	RNEG Port 10
0x0A	RNEG Port 11
0x0B	RNEG Port 12
0x0C	RNEG Port 13
0x0D	RNEG Port 14
0x0E	RNEG Port 15
0x0F	RNEG Port 16
0x10	1.544MHz On-board oscillator
0x11	2.048MHz On-board oscillator
0x12	User clock
0x13	CLKA DS26334/DS26324
0x14	TECLK DS26334/DS26324
0x15	Drive Logic “0”
0x16-0xFF	HI-Z

DS26334 INFORMATION

For more information about the DS26334, refer to the DS26334 data sheet available on our website at www.maxim-ic.com/DS26334.

DS26324 INFORMATION

For more information about the DS26324, refer to the DS26324 data sheet available on our website at www.maxim-ic.com/DS26324.

DS26334DK/DS26324DK INFORMATION

For more information about the DS26334DK/DS26324DK including software downloads, go to www.maxim-ic.com/DS26334DK.

TECHNICAL SUPPORT

For additional technical support, go to www.maxim-ic.com/support.

ERRATA

On page 18 of the schematic, EB0 and EB1 were swapped in the design on U3 and U10, respectively. These changes have been made to the board using jumper wires.

SCHEMATICS

The DS26334DK/DS26324DK schematics are featured in the following 25 pages.

Maxim/Dallas Semiconductor cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim/Dallas Semiconductor product. No circuit patent licenses are implied. Maxim/Dallas Semiconductor reserves the right to change the circuitry and specifications without notice at any time.

Maxim Integrated Products, 120 San Gabriel Drive, Sunnyvale, CA 94086 408-737-7600

© 2005 Maxim Integrated Products • Printed USA


The Maxim logo is a registered trademark of Maxim Integrated Products, Inc. The Dallas logo is a registered trademark of Dallas Semiconductor Corporation.


DS26334 DESIGN KIT
SCHEMATIC
DALLAS SEMICONDUCTOR / MAXIM
MAY 2005


TABLE OF CONTENTS

1. COVER PAGE
2. DS26334 CONTROL
3. DS26334 PORTS 1-4
4. DS26334 PORTS 5-8
5. DS26334 PORTS 9-12
6. DS26334 PORTS 13-16
7. LIU FRONT END PORTS 1-4
8. LIU FRONT END PORTS 5-8
9. LIU FRONT END PORTS 9-12
10. LIU FRONT END PORTS 13-16
11. RLOS, INT LEDs, PROG CLKS
12. EBERT x 1 / SPI PROM
13. FPGA CONTROL, FLASH CFG
14. FPGA BANK 1
15. FPGA BANK 2
16. USB AND JTAG CONN
17. ON BOARD MICRO
18. SRAM
19. TEST POINTS
20. LIU SERIES TERMINATION
21. DECOUPLING CAPS
22. MISC.
23. SIGNAL CROSS REF
24. PART CROSS REF P-1
25. PART CROSS REF P-2


TITLE: COVER PAGE	DATE:
ENGINEER: DS26334DK	PAGE: 1



LIU POWER (V_DUT) IS ISOLATED FROM BOARD SUPPLY (V3_3)
V_DUT
U6
DS26334_U
CONTROL
BGA
NA
DS26334
H1
MODESEL334 A3
MOTEL334 B3
CS334 P14
ALE334 N14
RD_LOCAL H14
WR_LOCAL G14
RDY334 C13
INT334 D7
OE334 R12
MUX_CLKE334 T14
JTCLK D14
JDS334OUT_SPI_PROM_IN A15
JFPGAOUT_DS334IN B15
JTMS B13
JTRST_B E15
RST334 B5
MCLK H12 MCLK334
SCANMODE R9 SCANMODE334
ADDRESS_LOCAL_<8..0>
DATA_<7..0>
TITLE: DS26334 CONTROL
DATE:
ENGINEER: DS26334DK
PAGE: 2


I7
BGA
NA
DS26334
U6
TRING01 E2
DS26334_U
PORT
RRING334_<16..1>
RTIP334_<16..1>
RCLK334_DUT<16..1>
RNEG334_DUT<16..1>
RPOS334_DUT<16..1>
RLOS334_<16..1>
A2
A1
D3
E3
F4
D2
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
E2
E1
F5
C3
F6
TRING334_<16..1>
TTIP334_<16..1>
TCLK334_<16..1>
TNEG334_<16..1>
TPOS334_<16..1>
I9
BGA
NA
DS26334
U6
TRING03 K2
DS26334_U
PORT
RRING334_<16..1>
RTIP334_<16..1>
RCLK334_DUT<16..1>
RNEG334_DUT<16..1>
RPOS334_DUT<16..1>
RLOS334_<16..1>
H2
H1
K3
K4
L3
J2
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
K2
K1
G9
J5
J6
TRING334_<16..1>
TTIP334_<16..1>
TCLK334_<16..1>
TNEG334_<16..1>
TPOS334_<16..1>
I8
BGA
NA
DS26334
U6
TRING02 F2
DS26334_U
PORT
RRING334_<16..1>
RTIP334_<16..1>
RCLK334_DUT<16..1>
RNEG334_DUT<16..1>
RPOS334_DUT<16..1>
RLOS334_<16..1>
C2
C1
G6
G5
F3
G2
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
F2
F1
G4
J14
G7
TRING334_<16..1>
TTIP334_<16..1>
TCLK334_<16..1>
TNEG334_<16..1>
TPOS334_<16..1>
I1
BGA
NA
DS26334
U6
TRING04 L2
DS26334_U
PORT
RRING334_<16..1>
RTIP334_<16..1>
RCLK334_DUT<16..1>
RNEG334_DUT<16..1>
RPOS334_DUT<16..1>
RLOS334_<16..1>
N2
N1
K5
M3
L4
M2
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
L2
L1
H6
G10
K6
TRING334_<16..1>
TTIP334_<16..1>
TCLK334_<16..1>
TNEG334_<16..1>
TPOS334_<16..1>
TITLE:
DS26334 PORTS 1-4
DATE:
ENGINEER:
DS26334DK
PAGE:
3




TITLE: DS26334 PORTS 5-8	DATE:
ENGINEER: DS26334DK	PAGE: 4



I8
BGA
NA
DS26334
U6
TRING09 M15
DS26334_U
PORT
RRING334_<16..1> 9 T15
RTIP334_<16..1> 9 T16
RCLK334_DUT<16..1> 9 L13
RNEG334_DUT<16..1> 9 M13
RPOS334_DUT<16..1> 9 M14
RLOS334_<16..1> 9 R14
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
M15 9 TRING334_<16..1>
M16 9 TTIP334_<16..1>
K11 9 TCLK334_<16..1>
L12 9 TNEG334_<16..1>
L11 9 TPOS334_<16..1>
I9
BGA
NA
DS26334
U6
TRING11 G15
DS26334_U
PORT
RRING334_<16..1> 11 J15
RTIP334_<16..1> 11 J16
RCLK334_DUT<16..1> 11 G13
RNEG334_DUT<16..1> 11 F13
RPOS334_DUT<16..1> 11 G12
RLOS334_<16..1> 11 K15
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
G15 11 TRING334_<16..1>
G16 11 TTIP334_<16..1>
F14 11 TCLK334_<16..1>
H11 11 TNEG334_<16..1>
G11 11 TPOS334_<16..1>
I7
BGA
NA
DS26334
U6
TRING10 L15
DS26334_U
PORT
RRING334_<16..1> 10 P15
RTIP334_<16..1> 10 P16
RCLK334_DUT<16..1> 10 K14
RNEG334_DUT<16..1> 10 L14
RPOS334_DUT<16..1> 10 K13
RLOS334_<16..1> 10 N15
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
L15 10 TRING334_<16..1>
L16 10 TTIP334_<16..1>
K12 10 TCLK334_<16..1>
J12 10 TNEG334_<16..1>
J11 10 TPOS334_<16..1>
I5
BGA
NA
DS26334
U6
TRING12 F15
DS26334_U
PORT
RRING334_<16..1> 12 D15
RTIP334_<16..1> 12 D16
RCLK334_DUT<16..1> 12 F12
RNEG334_DUT<16..1> 12 F11
RPOS334_DUT<16..1> 12 E14
RLOS334_<16..1> 12 H15
RRING
RTIP
RCLK
RNEG/CV
RPOS/RDATA
RLOS
TRING
TTIP
TCLK
TNEG
TPOS/DATA
F15 12 TRING334_<16..1>
F16 12 TTIP334_<16..1>
E12 12 TCLK334_<16..1>
E13 12 TNEG334_<16..1>
C14 12 TPOS334_<16..1>
TITLE: DS26334 PORTS 9-12
DATE:
ENGINEER: DS26334DK
PAGE: 5




TITLE: DS26334 PORTS 13-16		DATE:
ENGINEER: DS26334DK		PAGE: 6





TITLE: LIU FRONT END PORTS 1-4	DATE:
ENGINEER: DS26334DK	PAGE: 7


I36
TH
RJ45_4PORT
43223-8140
J54
RJ45
2:1
T2
TX1475
NA
SMT_XFMR
I55
I56
SMT_XFMR
NA
TX1475
1:1
TTIP334_<16..1>
TRING334_<16..1>
RTIP334_<16..1>
RRING334_<16..1>
C22
470PF
R158
R154
60.4
C105
.1UF
I24
TH
RJ45_4PORT
43223-8140
I51
SMT_XFMR
NA
TX1475
C25
R129
R127
C83
I49
I48
I54
I53
C23
R149
R147
C103
I12
I50
C24
I52
R142
R144
C93
TITLE:
LIU FRONT END PORTS 5-8
DATE:
ENGINEER:
DS26334DK
PAGE:
8





TITLE: LIU FRONT END PORTS 9-12	DATE:
ENGINEER: DS26334DK	PAGE: 9



I55
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J28
2:1
T4
I56
J27
TTIP334_<16..1>
TRING334_<16..1>
C11
470PF
I25
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J40
I26
J39
I28
SMT_XFMR
NA
TX1475
T4
2:1
C14
470PF
TTIP334_<16..1>
TRING334_<16..1>
TX1475
NA
SMT_XFMR
I58
I15
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J29
I59
SMT_XFMR
NA
TX1475
T4
1:1
R123
60.4
R118
60.4
C77
.1UF
RTIP334_<16..1>
RRING334_<16..1>
I45
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J41
I29
SMT_XFMR
NA
TX1475
T4
1:1
R141
60.4
R133
60.4
C88
.1UF
RTIP334_<16..1>
RRING334_<16..1>
I40
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J34
I41
J33
2:1
T4
C13
470PF
TTIP334_<16..1>
TRING334_<16..1>
I10
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J49
I11
J48
I13
SMT_XFMR
NA
TX1475
T4
2:1
C17
470PF
TTIP334_<16..1>
TRING334_<16..1>
TX1475
NA
SMT_XFMR
I43
I30
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J35
I44
SMT_XFMR
NA
TX1475
T4
1:1
R128
60.4
R125
60.4
C84
.1UF
RTIP334_<16..1>
RRING334_<16..1>
I60
CONN_BNC
75 OHM VERT
CP-BNCPC-004
CONN_BNC_5P
J50
1:1
T4
TX1475
NA
SMT_XFMR
I14
R143
60.4
R145
60.4
C96
.1UF
RTIP334_<16..1>
RRING334_<16..1>
TITLE:
LIU FRONT END PORTS 13-16
DATE:
ENGINEER:
DS26334DK
PAGE:
10




TITLE: RLOS, INT LEDs, PROG CLKS	DATE:
ENGINEER: DS26334DK	PAGE: 11









TITLE: EBERT x 1 / SPI PROM	DATE:
ENGINEER: DS26334DK	PAGE: 12



V2_5
C3 C14 D4 D13 E5 E12 M5 M12 N4 N13 P3 P14
VCCINT1 VCCINT2 VCCINT3 VCCINT4 VCCINT5 VCCINT6 VCCINT7 VCCINT8 VCCINT9 VCCINT10 VCCINT11 VCCINT12
V3_3
E8 VCCO1
F8 VCCO2
E9 VCCO3
F9 VCCO4
H11 VCCO5
H12 VCCO6
J11 VCCO7
J12 VCCO8
L9 VCCO9
M9 VCCO10
L8 VCCO11
M8 VCCO12
J5 VCCO13
J6 VCCO14
H5 VCCO15
H6 VCCO16
XILINX_PLD
200K
XC2S200-5FG256C
I3
U5
XC2S_FG256
CONTROL
TMS D3 JTMS
TDI A15 JFLASHOUT_FPGAIN
TCK C4 JTCLK
TDO B14 JFPGAOUT_DS334IN
PROGRAM* P15 PROGRAM_FPGA_A
CCLK D15 CCLK_A
DONE R14 DONE_FPGA_A
M0 N3
M1 P2
M2 R3
NC2 R4
NC1 P4
GND1 GND2 GND3 GND4 GND5 GND6 GND7 GND8 GND9 GND10 GND11 GND12 GND13 GND14 GND15 GND16 GND17 GND18 GND19 GND20 GND21 GND22 GND23 GND24 GND25 GND26 GND27 GND28 GND29 GND30 GND31 GND32 GND33 GND34 GND35 GND36
A1 A16 B2 B15 F6 F7 F10 F11 G6 G7 G8 G9 G10 G11 H7 H8 H9 H10 J7 J8 J9 J10 K6 K7 K8 K9 K10 K11 L6 L7 L10 L11 R2 R15 T1 T16
SERIAL CFG FLASH FOR FPGA
2MBIT
XCF02SV020C
I7
U16
V3_3
18 VCCINT
19 VCCO
20 VCCJ
ONCE_TDO_FLASHIN 4 JTDI
JTMS 5 JTMS
JTCLK 6 JTCK
11 GND
D0 1 CFG_DIN_A
CLK 3 CCLK_A
CE* 10 DONE_FPGA_A
CEO* 13 N/C
OE/RESET* 8 RESET_B
CF* 7 PROGRAM_FPGA_A
JTDO 17 JFLASHOUT_FPGAIN
XCFS_V020
FPGA_PROGRAM
STATUS LED
I27
U13
DONE_FPGA_A 9
7404
8 1
R108
330
2 2
D20
GREEN
V5_0
TITLE: FPGA CONTROL, FLASH CFG
DATE:
ENGINEER: DS26334DK
PAGE: 13





TITLE: FPGA BANK 1	DATE:
ENGINEER: DS26334DK	PAGE: 14




TITLE: FPGA BANK 2	DATE:
ENGINEER: DS26334DK	PAGE: 15



USB INTERFACE
BOARD JTAG HEADER
RS232 INTERFACE
V5_0
V3_3
R56
470
C41
.1UF
R43
15K
C47
22PF
J2
USB
VDD
DAT-
DAT+
GND
R44
33
R41
33
R62
15K
C36
22PF
I54
6.00MHZ
X1
C38
22PF
I55
ZCC0603_BL
I60
NA
FT245BM
U1
FT245BM_U
3V3OUT
USBDM
USBDP
RSTOUT#
XTIN
XTOUT
RESET#
EECS
EESK
EEDATA
TEST
AVCC
VCC1
VCC2
VCC1O
AGND
GND1
GND2
D0
D1
D2
D3
D4
D5
D6
D7
DATA_<7..0>
RD#
WR
TXE#
RXF#
SI_WU
PWREN#
RD_USB
WR_USB
TXE_USB
RXF_USB
SIWU_USB
PWREN_USB
I33
SWITCH
SSA2NDI
SW4
DPDT
JTMS_MIC
GND
JTDO
ONCE_TDO_FLASHIN
2JTMS
R55
10K
I6
NA
CONN_THRU-HOLE
HDR-TSW-107-14-T-D
J6
R48
10K
R47
10K
JTDI
JTCLK
GND
RESET
ALIGN KEY
JTMS_MIC
JDE_B
JTRST_B
CONN_14P
JTCLK
JTMS
R58
10K
R59
10K
SOIC16
NA
DS232AR
I71
U7
DS232
VPOS
VNEG
C1POS
C1NEG
C2POS
C2NEG
R1IN
R2IN
T1IN
T2IN
R1OUT
R2OUT
T1OUT
T2OUT
VCC
GND
C34
10UF
C26
10UF
C30
10UF
C35
10UF
PRT1_IN
SCI1_OUT
SCI1_IN
PRT1_OUT
CONN_DB9
NA
788750-2
163
J1
R50
10K
R45
10K
R49
10K
PRT1_OUT
PRT1_IN
CONN_DB9P
TITLE:
USB AND JTAG CONN
DATE:
ENGINEER:
DS26334DK
PAGE:
16


I33
144PIN_TQFP
MMC2107PV
U2
MMC2107
PORT
I4
144PIN_TQFP
MMC2107PV
U2
MMC2107
CONTROL
I2
I11
L1
1.0UH
R65
33
CLKOUT_MM2107
2 CLKOUT
RESET MICRO
I42
SW2
RESET_B
I46
U17
7400
I45
U13
7404
RESET
RESET_MIC
OSC_MCU
X2
8.000MHZ
I7
I9
C40
C39
10PF
RS4
DNP
XTAL
VSSSSYN
TIM_16H_8L
R75
10K
USER_LED1
USER_LED2
USER_IN1
USER_IN2
R72
R79
R38
R37
V3_3
V5_0
MICRODATA_<15..0>
MICROADD_<17..0>
CS2_BOARD
CS0_RAM
RESET_MIC
CLKOUT_MM2107
SCK
JDE_B
SS
SCI1_OUT
SCI1_IN
RUN_KIT_USR
INTERRUPT
OSC_MCU
JTCLK
JTRST_B
JTMS_MIC
TITLE:
ON BOARD MICRO
DATE:
ENGINEER:
DS26334DK
PAGE:
17



I37
U3
CY62128V
SOIC
CY62128VL-70SC
I11
U10
CY62128V
SOIC
CY62128VL-70SC
MICROADD_<17..0>
MICRODATA_<15..0>
V3_3
GND
FB0
FB1
OE
CS0_RAM
RUN_KIT_USR
TIM_16H_8L
MASTER
MODE
FULL
DRIVE
XTAL
W/ PLL
INTERNAL
FLASH EN
PD21
PD22
PD23
PD26
PD17
PD16
PD28
PD19
PD18
2RCON
ENABLE MICRO
I48
SWITCH
SSA22
I49
SWITCH
SSA22
SW5
DPDT
SW3
DPDT
FPGA_EN
FLASH_VPP
V5_0
R70
330
I52
RED
BOOT
INTERNAL
10K
TITLE:
SRAM
DATE:
ENGINEER:
DS26334DK
PAGE:
18



TITLE: TEST POINTS	DATE:
ENGINEER: DS26334DK	PAGE: 19





TITLE: LIU SERIES TERMINATION	DATE:
ENGINEER: DS26334DK	PAGE: 20




TITLE: DECOUPLING CAPS	DATE:
ENGINEER: DS26334DK	PAGE: 21

5V DC POWER SUPPLY
REVERSE BIAS PROTECTION










JTAG NOTES

SPLIT BOARD POWER SUPPLY
AND DUT POWER SUPPLY (V_DUT)



REVERSE BIAS PROTECTION





I1
0L_HARDWARE
.75STANDOFF_.25SCR
4-40KIT2

H1

I2
0L_HARDWARE
.75STANDOFF_.25SCR
4-40KIT2

H2

I3
0L_HARDWARE
.75STANDOFF_.25SCR
4-40KIT2

H3

I4
0L_HARDWARE
.75STANDOFF_.25SCR
4-40KIT2

H4

TITLE:	DATE:
ENGINEER: DS26334DK	PAGE: 22

*** Signal Cross-Reference for the entire design ***

```
ADDRESS_LOCAL_<8..0>  2B3 12C8 14D6 19A5
ALE334                12C1> 14B7<> 19A3<> 2C7<
CCLK_A                13B3<> 13B1<
CFG_DIN_A             13B1> 14B3<>
CLKOUT                14D7< 17D3<
CLKOUT_MM2107         17C1<> 17D4<
CS0_RAM               17C1<> 18D3< 18D6<
CS2_BOARD             14A4<> 17C1<>
CS334                 12C1> 14B7<> 19A3<> 2C7< 11C4<
CSFPGA                14B7<> 19A3<>
CS_BERT               14B7<> 19A3<> 12B8<
DATA_<7..0>           2B3 12B5 14C3 16C5 19B4
DONE_FPGA_A           13B3<> 13A3< 13B1<
E1_CLK                11B1< 15D6<
EB0                   14A4<> 17D3<> 18D7<
EB1                   14A4<> 17D3<> 18D3<
FLASH_VPP             18A7<> 17D7<
FPGA_CLKA             11D3<> 14C3<> 11C3<
FPGA_EN               14B7<> 18A8<> 19B3<>
FPGA_TECLK            11D3<> 14B3<> 11C3<
INT334                2B7> 14C3<> 19B3<> 11A8< 11D5<
INTERUPT              14B3<> 17B2<>
JDE_B                 16B2<> 17B1<>
JDS334OUT_SPI_PROM_IN  2B7> 12A2< 12D3<
JFLASHOUT_FPGAIN  13B1> 13C3<
JFPGAOUT_DS334IN  13C3> 2B7<
JTCLK                 12D3> 16C3<> 17B2<> 2B7< 13B3<
                    13C3< 16B2<
JTDI                  16C3<> 17D2<>
JTDO                  12D3> 16C4<> 12A1<
JTMS                  16C3<> 2B7< 12D3< 13B3< 13C3<
                    16B1<
JTMS_MIC              16B2<> 16C4<> 17B2<>
JTRST_B               16B2<> 17B2<> 2B7<
LED_RLOS15            11A8<> 11B4>
LED_RLOS16            11A8<> 11B4>
MCLK334               2C3< 11C4< 12C3<
MCLK_FPGA             14C3<> 11C3<
MICROADD_<17..0>  14B7 17B4 18B4 18B8
MICRODATA_<15..0>  14A5 17B8 18C2 18C5
MISO                  14B7<> 17A2<>
MODESEL334            14B3<> 19A3<> 2C7<
MOSI                  14B7<> 17A2<>
MOTEL334              14B3<> 19B3<> 2C7<
MUX_CLKE334           14B3<> 19A4<> 19B4<> 2B7<
OE                    14A4<> 17D7<> 18D3< 18D7<
OE334                 14B3<> 19B3<> 2B7<
ONCE_TDO_FLASHIN  16C4<> 17D2<> 13B3<
OSC_MCU               17B2<> 17B4<>
PD16                  17B8<> 18B3<
PD17                  17B8<> 18B3<
PD18                  17B8<> 18A4<
PD19                  17B8<> 18A2<
PD20                  17B8<>
PD21                  17C8<> 18B2<
PD22                  17C8<> 18B2<
PD23                  17C8<> 18B2<
PD24                  17C8<>
PD25                  17C8<>
PD26                  17C8<> 18B3<
PD27                  17C8<>
PD28                  17C8<> 18A2<
PD29                  17C8<>
PD30                  17C8<>
PD31                  17C8<>
PROGRAM_FPGA_A   13B1> 13B3<
PRT1_IN               16A6<> 16A8<
PRT1_OUT              16A6<> 16A6>
PWREN_USB             14D4<> 16B5>
RCLK334_<15..1>  19B6> 15A6 19B8< 19C2 19C4 19C6
                    19C8< 19D2 19D4 19D6 19D8< 20C6 20C6
                    20C8 20C8
RCLK334_DUT<15..1>  3B5< 3B8< 3C5< 3C8< 4B4< 4B8<
                    4C4< 4C8< 5B4< 5B8< 5C4< 5C8< 6B4<
                    6B8< 6C5< 6C8< 20C5 20C5 20C7 20C7
```

```
RCLKENABLE_BERT  14A6<> 19A8<> 12A6< 12D7<
RCLKIN_BERT           14A6<> 19A8<> 12D7<
RCON                  14A4<> 17D7<> 18A2<
RDAT_BERT             14A6<> 19A8<> 12D8<
RDY334                2B7> 14B3<> 19B4<>
RD_LOCAL              14B7<> 19A3<> 2C7< 12B8<
RD_USB                14A6<> 16C5>
RESET                 16B3<> 17A7<
RESET_B               13B1<> 17A8<> 21C6> 21C8> 21D3>
RESET_CFGPRM          12A3<> 12C3<>
RESET_MIC             17A6> 17C1<>
RLOS334_<16..1>  19B6> 3A4< 3A8< 3C4< 3C8< 4A4<
                    4A8< 4C4< 4C8< 5A4< 5A8< 5C4< 5C8<
                    6A4< 6A8< 6C4< 6C8< 11B5 11C5 11C8
                    19B8< 19C2 19C4 19C6 19C8< 19D2 19D4
                    19D6 19D8<
RLOS_15               14D4<> 11B5<
RLOS_16               14D4<> 11B5<
RNEG334_<16..1>  19B6> 15D4 19B8< 19C2 19C4 19C6
                    19C8< 19D2 19D4 19D6 19D8< 20A1 20A3
                    20B1 20B3
RNEG334_DUT<16..1>  3B5< 3B8< 3C5< 3C8< 4B4< 4B8<
                    4C4< 4C8< 5B4< 5B8< 5C4< 5C8< 6B4<
                    6B8< 6C5< 6C8< 20A3 20A4 20B3 20B4
RPOS334_<16..1>  19B6> 15D7 19B8< 19C2 19C4 19C6
                    19C8< 19D2 19D4 19D6 19D8< 20C1 20C1
                    20C3 20C3
RPOS334_DUT<16..1>  3B5< 3B8< 3C5< 3C8< 4B4< 4B8<
                    4C4< 4C8< 5B4< 5B8< 5C4< 5C8< 6B4<
                    6B8< 6C5< 6C8< 20C3 20C3 20C4 20C4
RRING334_<16..1>  7A1> 7A4> 7C1> 7C5> 8A1> 8A5>
                    8B5> 8C1> 9A1> 9A5> 9C1> 9C5> 10A1>
                    10A5> 10C1> 10C5> 3B4< 3B8< 3D5<
                    3D8< 4B4< 4B8< 4D4< 4D8< 5B4< 5B8<
                    5D4< 5D8< 6B4< 6B8< 6D4< 6D8<
RST334                11A5<> 14A3<> 19A3<> 2B7<
RTIP334_<16..1>  7B1> 7B4> 7C1> 7C5> 8A1> 8A5> 8C1>
                    8C5> 9A5> 9B1> 9C1> 9C5> 10A1> 10A5>
                    10C1> 10C5> 3B4< 3B8< 3C4< 3C8< 4B4<
                    4B8< 4C4< 4C8< 5B4< 5B8< 5C4< 5C8<
                    6B4< 6B8< 6C4< 6C8<
RUN_KIT_USR           17B3<> 18B6<
RW                    14A4<> 17D7<>
RXF_USB               14B3<> 16B5>
R_PB_CFG              12A2<> 12B2>
SCANMODE334           2C3< 11D5<
SCI1_IN               16A6> 17B4<>
SCI1_OUT              17C4<> 16A8<
SCK                   14B7<> 17C1<>
SIWU_USB              14D4<> 16B5>
SS                    14B7<> 17B1<>
T1_CLK                11B1< 15C7<
TA                    14A3<> 17D7<>
TCLK334_<16..1>  3B1> 3B5> 3C1> 3C5> 4B1> 4B5> 4C1>
                    4C5> 5B1> 5B5> 5C1> 5C5> 6B1> 6B5>
                    6C1> 6C5> 19B6> 15A4 19B8< 19C2 19C4
                    19C6 19C8< 19D2 19D4 19D6 19D8<
TCLKENABLE_BERT  14A5<> 19A8<> 12A6< 12B8<
TCLKIN_BERT           14A5<> 19A8<> 12B8<
TCLKOUT_BERT          14A6<> 19A8<> 12D5<
TDAT_BERT             14A6<> 19A8<> 12C5<
TEA                   14A3<> 17D7<>
TEST                  17C3<>
TIM_16H_8L            17D3<> 17A3< 18B5<
TNEG334_<16..1>  3B1> 3B5> 3C1> 3C5> 4B1> 4B5> 4C1>
                    4C5> 5B1> 5B5> 5C1> 5C5> 6B1> 6B5>
                    6C1> 6C5> 19B6> 15D5 19B8< 19C2 19C4
                    19C6 19C8< 19D2 19D4 19D6 19D8<
TPOS334_<16..1>  3B1> 3B5> 3C1> 3C5> 4B1> 4B5> 4C1>
                    4C5> 5B1> 5B5> 5C1> 5C5> 6B1> 6B5>
                    6C1> 6C5> 19B6> 14D5 15A7 19B8< 19C2
                    19C4 19C6 19C8< 19D2 19D4 19D6 19D8<
```

```
TRING334_<16..1>  3B1> 3B5> 3D1> 3D5> 4B1> 4B5>
                    4D1> 4D5> 5B1> 5B5> 5D1> 5D5> 6B1>
                    6B5> 6D1> 6D5> 7B1> 7B5> 7D1> 7D5>
                    8B1> 8B5> 8D1> 8D5> 9B1> 9B5> 9D1>
                    9D5> 10B1> 10B5> 10D1> 10D5>
TTIP334_<16..1>  3B1> 3B5> 3C1> 3C5> 4B1> 4B5> 4C1>
                    4C5> 5B1> 5B5> 5C1> 5C5> 6B1> 6B5>
                    6C1> 6C5> 7B1> 7B5> 7D1> 7D5> 8B1>
                    8B5> 8D1> 8D5> 9B1> 9B5> 9D1> 9D5>
                    10B1> 10B5> 10D1> 10D5>
TXE_USB               14B3<> 16B5<
USER_CLK              11A2<> 14C7<
USER_IN1              17B3<> 19B3<> 17A2<
USER_IN2              17B3<> 19B3<> 17A2<
USER_LED1             17B3<> 17A2<
USER_LED2             17B3<> 17A2<
VDDSYN                17D6<>
VDUT_CON              21D4<> 22A7<>
VSSSYN                17A4<
WR_LOCAL              12C1> 14A7<> 19A3<> 2B7< 12B8<
WR_USB                14A4<> 16B5>
XTAL                  17A3<> 17B2<>
```

TITLE:	DATE:
ENGINEER:	PAGE:

*** Part Cross-Reference for the entire design ***

C1	CAP1	21B6
C2	CAP1	21B7
C3	CAP1	21A5
C4	CAP1	21A6
C5	CAP1	21A3
C6	CAP1	21A5
C7	CAP1	21B4
C8	CAP1	9B2
C9	CAP1	9D2
C10	CAP1	9B6
C11	CAP1	10D6
C12	CAP1	9D6
C13	CAP1	10B6
C14	CAP1	10D2
C15	CAP1	21C4
C16	CAP1	21A3
C17	CAP1	10B2
C18	CAP1	7D6
C19	CAP1	7D2
C20	CAP1	7B2
C21	CAP1	7B6
C22	CAP1	8D6
C23	CAP1	8B6
C24	CAP1	8B2
C25	CAP1	8D2
C26	CAP1	16A7
C27	CAP1	21B7
C28	CAP1	21A4
C29	CAP1	21A4
C30	CAP1	16A8
C31	CAP1	21A6
C32	CAP1	21A4
C33	CAP1	21A7
C34	CAP1	16A8
C35	CAP1	16A6
C36	CAP1	16C8
C37	CAP1	21A7
C38	CAP1	16B8
C39	CAP1	17A4
C40	CAP1	17A4
C41	CAP1	16D7
C42	CAP1	21B8
C43	CAP1	21A8
C44	CAP1	21B5
C45	CAP1	21A8
C46	CAP1	21A6
C47	CAP1	16D7
C48	CAP1	21B7
C49	CAP1	21A5
C50	CAP1	21A7
C51	CAP1	21A7
C52	CAP1	21B5
C53	CAP1	21A4
C54	CAP1	21B4
C55	CAP1	21A8
C56	CAP1	21A4
C57	CAP1	21A5
C58	CAP1	21A6
C59	CAP1	21A7
C60	CAP1	21C1
C61	CAP1	21A7
C62	CAP1	21A6
C63	CAP1	21A7
C64	CAP1	21C1
C65	CAP1	21C2
C66	CAP1	21A5
C67	CAP1	21B5
C68	CAP1	21A6
C69	CAP1	21A6
C70	CAP1	21A5
C71	CAP1	21B6
C72	CAP1	21C1
C73	CAP1	21C2
C74	CAP1	9C1
C75	CAP1	9A1
C76	CAP1	9A5
C77	CAP1	10C5
C78	CAP1	9C5
C79	CAP1	21B2
C80	CAP1	21B2
C81	CAP1	21A3
C82	CAP1	21A2
C83	CAP1	8C2
C84	CAP1	10A5
C85	CAP1	21A2
C86	CAP1	21B3
C87	CAP1	21A3
C88	CAP1	10C2
C89	CAP1	21A3
C90	CAP1	21B2
C91	CAP1	21B3
C92	CAP1	21B1
C93	CAP1	8A1
C94	CAP1	21A5
C95	CAP1	21A2
C96	CAP1	10A1
C97	CAP1	21B3
C98	CAP1	21B1
C99	CAP1	21A2
C100	CAP1	21A1
C101	CAP1	21A1
C102	CAP1	21B2
C103	CAP1	8A5
C104	CAP1	7C5
C105	CAP1	8C5
C106	CAP1	7A1
C107	CAP1	7A5
C108	CAP1	7C2
C109	CAP1	21B1
C110	CAP1	21B1
D1	LED	22B7
D2	LED	18A7
D3	LED	11A7
D4	LED	11D7
D5	LED	11C7
D6	LED	11D7
D7	LED	11B7
D8	LED	11D7
D9	LED	11B7
D10	LED	11D7
D11	LED	11B7
D12	LED	11C7
D13	LED	11B7
D14	LED	11C7
D15	LED	11B7
D16	LED	11C7
D17	LED	11A7
D18	LED	11C7
D19	LED	11A7
D20	LED	13A2
D21	SCHOTTKYDIODE1	21D4
D22	SCHOTTKYDIODE1	22D8
D23	SCHOTTKYDIODE1	22A6
H1	4_40_HDWR	22B1
H2	4_40_HDWR	22B1
H3	4_40_HDWR	22A1
H4	4_40_HDWR	22A1
J1	CONN_DB9P	16A5
J2	USB_BCON_U	16D8
J3	POWER_JACK	22D8
J4	CONN_40P	19A5
J5	CONN_BNC_5P	11D1
J6	CONN_14P	16C3
J7	CONN_BNC_5P	11A2
J8	CONN_BNC_5P	11D1
J9	CONN_14P	19D7
J10	CONN_14P	19C7
J11	CONN_14P	19D7
J12	CONN_14P	19C5
J13	CONN_14P	19D5
J14	CONN_14P	19C5
J15	CONN_14P	19D5
J16	CONN_14P	19C3
J17	CONN_14P	19D3
J18	CONN_14P	19C3
J19	CONN_14P	19D2
J20	CONN_14P	19B1
J21	CONN_14P	19D1
J22	CONN_14P	19A7
J23	CONN_14P	19B7
J24	CONN_14P	19C7
J25	CONN_14P	19B7
J26	JMP_OPEN_2P	9B4
J27	JMP_OPEN_2P	10D8
J28	CONN_BNC_5P	10D7
J29	CONN_BNC_5P	10C7
J30	CONN_BNC_5P	9A3
J31	CONN_BNC_5P	9B3
J32	JMP_OPEN_2P	9D4
J33	JMP_OPEN_2P	10B8
J34	CONN_BNC_5P	10B7
J35	CONN_BNC_5P	10A7
J36	CONN_BNC_5P	9C3
J37	CONN_BNC_5P	9D3
J38	JMP_OPEN_2P	9B8
J39	JMP_OPEN_2P	10D4
J40	CONN_BNC_5P	10D3
J41	CONN_BNC_5P	10C3
J42	CONN_BNC_5P	9A8
J43	CONN_BNC_5P	9B8
J44	JMP3	22A8
J45	JMP3	22A7
J46	JMP3	22A7
J47	JMP_OPEN_2P	9D8
J48	JMP_OPEN_2P	10B4
J49	CONN_BNC_5P	10B3
J50	CONN_BNC_5P	10A3
J51	CONN_BNC_5P	9C8
J52	CONN_BNC_5P	9D8
J53	RJ45_8	7B4 7B7 7D4 7D8
J54	RJ45_8	8B4 8B8 8D4 8D8
L1	COIL_2P	17D6
R1	RES1	12A7
R2	RES1	12B7
R3	RES1	20C4
R4	RES1	20A4
R5	RES1	20C4
R6	RES1	20A4
R7	RES1	20C2
R8	RES1	20C4
R9	RES1	20C2
R10	RES1	20C7
R11	RES1	20A4
R12	RES1	20A2
R13	RES1	20D2
R14	RES1	20B2
R15	RES1	11C4
R16	RES1	20B2
R17	RES1	20C2
R18	RES1	20D2
R19	RES1	11C4
R20	RES1	11D4
R21	RES1	20C6
R22	RES1	20B2
R23	RES1	21C5
R24	RES1	20C6
R25	RES1	20D7
R26	RES1	20D6
R27	RES1	20C2
R28	RES1	20B4
R29	RES1	20D4
R30	RES1	20B4
R31	RES1	20D7
R32	RES1	20D4
R33	RES1	20B4
R34	RES1	20B4
R35	RES1	20A2
R36	RES1	20D7
R37	RES1	17A1
R38	RES1	17A1
R39	RES1	11D5
R40	RES1	22B7
R41	RES1	16C8
R42	RES1	11C4
R43	RES1	16D7
R44	RES1	16C8
R45	RES1	16A5
R46	RES1	11B2
R47	RES1	16C1
R48	RES1	16C1
R49	RES1	16A4
R50	RES1	16A5
R51	RES1	11D2
R52	RES1	17A7
R53	RES1	11A5
R54	RES1	17A4
R55	RES1	16C3
R56	RES1	16D5
R57	RES1	17A7
R58	RES1	16B2
R59	RES1	16B1
R60	RES1	18A2
R61	RES1	12A2
R62	RES1	16C7
R63	RES1	11C2
R64	RES1	11D2
R65	RES1	17D4
R66	RES1	18B3
R67	RES1	18B5
R68	RES1	18A2
R69	RES1	18A5
R70	RES1	18A7
R71	RES1	18B2
R72	RES1	17A1
R73	RES1	11A6
R74	RES1	18B2
R75	RES1	17A2
R76	RES1	18A4
R77	RES1	11C5
R78	RES1	11D5
R79	RES1	17A1
R80	RES1	18B3
R81	RES1	12C5
R82	RES1	12D5
R83	RES1	11B5
R84	RES1	11D5
R85	RES1	12B7
R86	RES1	11B5
R87	RES1	11D5
R88	RES1	18B2
R89	RES1	18B3
R90	RES1	12A7
R91	RES1	18A2
R92	RES1	11B5
R93	RES1	11D5
R94	RES1	11A2
R95	RES1	11B5
R96	RES1	11C5
R97	RES1	11A5
R98	RES1	11C5
R99	RES1	11A5
R100	RES1	11A6
R101	RES1	11C5
R102	RES1	11C4
R103	RES1	11C5
R104	RES1	12A5
R105	RES1	12A6
R106	RES1	11A6
R107	RES1	11C6
R108	RES1	13A2
R109	RES1	20A4
R110	RES1	12A3
R111	RES1	9A6
R112	RES1	9C2
R113	RES1	9A6
R114	RES1	9C2

TITLE:

DATE:

ENGINEER:

PAGE:

```
R115  RES1      9A2
R116  RES1      20C7
R117  RES1      9A2
R118  RES1      10C6
R119  RES1      9C6
R120  RES1      20C4
R121  RES1      20C7
R122  RES1      20C7
R123  RES1      10C6
R124  RES1      9C6
R125  RES1      10A6
R126  RES1      20D6
R127  RES1      8C2
R128  RES1      10A6
R129  RES1      8C2
R130  RES1      20D2
R131  RES1      20C6
R132  RES1      20A2
R133  RES1      10C2
R134  RES1      20B2
R135  RES1      20D2
R136  RES1      20D6
R137  RES1      20C6
R138  RES1      11D5
R139  RES1      20A2
R140  RES1      20D6
R141  RES1      10C2
R142  RES1      8A2
R143  RES1      10A2
R144  RES1      8A2
R145  RES1      21D5
R146  RES1      10A2
R147  RES1      8A6
R148  RES1      20D7
R149  RES1      8A6
R150  RES1      7C6
R151  RES1      20D4
R152  RES1      7C6
R153  RES1      20D4
R154  RES1      8C6
R155  RES1      7A6
R156  RES1      7A2
R157  RES1      7C2
R158  RES1      8C6
R159  RES1      7A6
R160  RES1      7A2
R161  RES1      7C2
SW1   PUSHBUTTON 11A5
SW2   PUSHBUTTON 17A8
SW3   SWITCH_DPDT_SLIDE_6P 18A6
SW4   SWITCH_DPDT_SLIDE_6P 16C4
SW5   SWITCH_DPDT_SLIDE_6P 18A8
SW6   PUSHBUTTON 12B3
SW7   SWITCH_DPDT_SLIDE_6P 12A2
T1    XFMR_QUADT1E1_TG83_U 7A3 7A7 7B3 7B6 7C3 7C7
            7D3 7D7
T2    XFMR_QUADT1E1_TG83_U 8A3 8A7 8B3 8B7 8C3 8C7
            8D3 8D7
T3    XFMR_QUADT1E1_TG83_U 9A3 9A7 9B2 9B7 9C3 9C7
            9D2 9D7
T4    XFMR_QUADT1E1_TG83_U 10A3 10A7 10B2 10B7 10C3
            10C7 10D3 10D7
U1    FT245BM_U 16C6
U2    MMC2107_1 17C2 17C6
U3    CY6212BV_2 18C7
U4    DS2174    12C7
U5    XC2S_FG256 13C6 14C5 15C5
U6    DS26334_U 2B5 3B3 3B7 3D3 3D7 4B3 4B7 4D3 4D7
            5B3 5B7 5D3 5D7 6B3 6B7 6D3 6D7
U7    DS232     16A7
U8    NC7SZ86_U 11D2
U9    MAX1793_U 21D7
U10   CY6212BV_2 18C3
U11   NC7SZ86_U 11D2
U12   XC18V02VQ44C 12D3
U13   74_04_U   11A7 11B7 11B8 13A3 17A6 22A2
U14   74_04_U   11C7 11C8 11D7 11D8
```

```
U15   MAX1792_1 21D3
U16   XCFS_VO20 13B2
U17   74_00     11B4 17A6 22B2
U18   74_04_U   11B7 11B8 11B8 11C7 11C7 11C8
U19   MAX6816_2 12B2
U20   MAX1793_U 21D5
X1    XTAL_U    16C7
X2    XTAL      17A4
Y1    OSC2      11B2
Y2    OSC2      11C2
```

TITLE:	DATE:
ENGINEER:	PAGE:


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.