19-0867; Rev 0; 9/07

EVALUATION KIT AVAILABLE

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

General Description

The MAX9517/MAX9524 are low-power video amplifiers with integrated reconstruction filters. Specially suited for standard-definition video signals, such as composite and luma, these devices are ideal for a wide range of applications such as cell phones and security/CCTV cameras. Video signals should be DC-coupled into the MAX9517 input and AC-coupled into the MAX9524 input.

The MAX9517/MAX9524 have two single-pole, single-throw (SPST) analog switches that can be used to route stereo audio, video, or digital signals. The reconstruction filter typically has ±1dB passband flatness at 9MHz and 52dB attenuation at 27MHz. The amplifiers have a gain of 2V/V, and the outputs can be DC-coupled to a load of 75Ω, which is equivalent to two video loads. The outputs can be AC-coupled to a load of 150Ω, which is equivalent to one video load.

The MAX9517/MAX9524 operate from a 2.7V to 3.6V single supply and are specified over the -40°C to +125°C automotive temperature range. The MAX9517/MAX9524 are available in a small 12-pin TQFN (3mm x 3mm) package.

Features

- **Integrated Reconstruction Filter for Standard-Definition Video**
- **9MHz, ±1dB Passband**
- **52dB Attenuation at 27MHz**
- **Dual SPST Switches**
- **Fixed Gain of 2V/V**
- **DC- or AC-Coupled Output**
- **2.7V to 3.6V Single-Supply Operation**

Applications

Security/CCTV Cameras

Mobile Phones/Cell Phones

Digital Still Cameras (DSC)

Camcorders (DVC)

Portable Media Players (PMP)

Ordering Information

PART	INPUT TYPE	PIN-PACKAGE	PKG CODE	TOP MARK
MAX9517ATC+	DC BIAS	12 TQFN-EP*	T1233+4	ABF
MAX9524ATC+	AC CLAMP	12 TQFN-EP*	T1233+4	ABE


Note: *All devices are specified over the -40°C to +125°C operating temperature range.*

+Denotes a lead-free package.

**EP = Exposed pad.*

Pin Configuration appears at end of data sheet.

Functional Diagrams



For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

ABSOLUTE MAXIMUM RATINGS

V_{DD} to GND .....-0.3V to +4V
VIDIN to GND .....-0.3V to +4V
COM_, NO_ to GND .....-0.3V to (V_{DD} + 0.3V)
$\overline{SHDN}$, IN_ to GND .....-0.3V to +4V
VIDOUT Short-Circuit Duration to V_{DD}, GND .....Continuous
Continuous Input Current
  VIDIN, IN_, $\overline{SHDN}$ .....±20mA
  COM_, NO_ .....±100mA
Peak Current
  COM_, NO_ (pulsed at 1ms, 10% duty cycle) .....±200mA
Continuous Power Dissipation (T_A = +70°C)
  12-Pin TQFN (derate 14.7mW/°C above +70°C) 1177mW
Operating Temperature Range .....-40°C to +125°C
Junction Temperature .....+150°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering 10s) .....+300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{DD} = $\overline{SHDN}$ = 3.3V, GND = 0V, no load, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Supply Voltage Range	V_{DD}	Guaranteed by PSRR		2.7		3.6	V
Supply Current	I_{DD}	MAX9517			3.5	7	mA
		MAX9524			4.25	8	
Shutdown Supply Current	I_{SHDN}	$V_{\overline{SHDN}}$ = GND				1	µA
VIDEO							
DC BUFFER INPUTS (MAX9517)							
Input Voltage Range	V_{IN}	Guaranteed by output-voltage swing	V_{DD} = 2.7V	0		1.05	V
			V_{DD} = 3V	0		1.2	
Input Current	I_{IN}	V_{IN} = 0V			3.5	10	µA
Input Resistance	R_{IN}				300		kΩ
DC Voltage Gain	A_V	R_L = 150Ω to GND	V_{DD} = 2.7V, 0 ≤ V_{IN} ≤ 1.05V	1.95	2.00	2.04	V/V
			V_{DD} = 3V, 0 ≤ V_{IN} ≤ 1.2V	1.95	2.00	2.04	
Output Level		Measured at V_{OUT}, VIDIN = 0.1µF to GND, R_L = 150Ω to GND		200	300	410	mV
Output-Voltage Swing		Measured at output, V_{DD} = 2.7V, 0 ≤ V_{IN} ≤ 1.05V, R_L = 150Ω to -0.2V			2.1		V_{P-P}
		Measured at output, V_{DD} = 2.7V, 0 ≤ V_{IN} ≤ 1.05V, R_L = 150Ω to V_{DD}/2			2.1		
		Measured at output, V_{DD} = 3V, 0 ≤ V_{IN} ≤ 1.2V, R_L = 150Ω to -0.2V			2.4		
		Measured at output, V_{DD} = 3V, 0 ≤ V_{IN} ≤ 1.2V, R_L = 150Ω to V_{DD}/2			2.4		
		Measured at output, V_{DD} = 3.135V, 0 ≤ V_{IN} ≤ 1.05V, R_L = 75Ω to -0.2V			2.1		
SYNC-TIP CLAMP INPUT (MAX9524)							
Sync-Tip Clamp Level	V_{CLP}	Sync-tip clamp		0.23		0.39	V
Input Voltage Range		V_{DD} = 2.7V to 3.6V				1.05	V_{P-P}
		V_{DD} = 3V to 3.6V				1.2	
Sync Crush		Sync-tip clamp, percentage reduction in sync pulse (0.3V_{P-P}), guaranteed by input clamping current measurement				2	%

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V, GND = 0V, no load, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Clamping Current		Sync-tip clamp			1	2	µA
Maximum Input Source Resistance					300		Ω
DC Voltage Gain (Note 2)	A_V	R_L = 150Ω to GND	V_{DD} = 2.7V, 0 ≤ V_{IN} ≤ 1.05V	1.95	2.00	2.04	V/V
			V_{DD} = 3V, 0 ≤ V_{IN} ≤ 1.2V	1.95	2.00	2.04	
Output Level		Measured at V_{OUT}, VIDIN = 0.1µF to GND, R_L = 150Ω to GND		0.21	0.30	0.39	V
Output-Voltage Swing		Measured at output, V_{DD} = 2.7V, V_{IN} = V_{CLP} to (V_{CLP} +1.05V), R_L = 150Ω to -0.2V			2.1		V_{P-P}
		Measured at output, V_{DD} = 2.7V, V_{IN} = V_{CLP} to (V_{CLP} +1.05V), R_L = 150Ω to V_{DD}/2			2.1		
		Measured at output, V_{DD} = 3V, V_{IN} = V_{CLP} to (V_{CLP} +1.2V), R_L = 150Ω to -0.2V			2.4		
		Measured at output, V_{DD} = 3V, V_{IN} = V_{CLP} to (V_{CLP} +1.2V), R_L = 150Ω to V_{DD}/2			2.4		
		Measured at output, V_{DD} = 3.135V, V_{IN} = V_{CLP} to (V_{CLP} +1.05V), R_L = 75Ω to -0.2V			2.1		
Output Short-Circuit Current		Short to GND (sourcing)			140		mA
		Short to V_{CC} (sinking)			70		
Output Resistance	R_{OUT}	V_{OUT} = 1.5V, -10mA ≤ I_{LOAD} ≤ +10mA			0.2		Ω
Output Leakage Current		$\overline{SHDN}$ = GND				1	µA
Power-Supply Rejection Ratio		2.7V ≤ V_{DD} ≤ 3.6V		48			dB
Standard-Definition Reconstruction Filter		±1dB passband flatness			9		MHz
		V_{VIDOUT} = $2V_{P-P}$, reference frequency is 100kHz	f = 5.5MHz		+0.15		dB
			f = 10MHz		-3		
			f = 27MHz		-52		
Differential Gain	DG	5-step modulated staircase of 129mV step size and 286mV_{P-P} subcarrier amplitude; f = 4.43MHz			1		%
Differential Phase	DP	5-step modulated staircase of 129mV step size and 286mV_{P-P} subcarrier amplitude; f = 4.43MHz			0.4		Degrees
2T Pulse-to-Bar K Rating		Bar time is 18µs, the beginning 2.5% and the ending 2.5% of the bar time are ignored, 2T = 200ns			0.6		K%
2T Pulse Response		2T = 200ns			0.2		K%
2T Bar Response		Bar time is 18µs, the beginning 2.5% and the ending 2.5% of the bar time are ignored, 2T = 200ns			0.2		K%

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V, GND = 0V, no load, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Nonlinearity		5-step staircase, f = 4.43MHz		0.5		%
Group Delay Distortion		100kHz ≤ f ≤ 5.5MHz, outputs are $2V_{P-P}$		12		ns
Peak Signal to RMS Noise		100kHz ≤ f ≤ 5.5MHz		71		dB
Power-Supply Rejection Ratio		f = 1MHz, $100mV_{P-P}$		29		dB
Output Impedance		f = 5.5MHz		4.8		Ω
All-Hostile Crosstalk		f = 4.43MHz		-64		dB
ANALOG SWITCHES						
Analog Signal Range	$V_{COM_}$, $V_{NO_}$		0		V_{DD}	V
On-Resistance (Note 3)	R_{ON}	V_{DD} = 2.7V, $I_{COM_}$ = 10mA, $V_{NO_}$ = 1.5V		1.7	5.0	Ω
On-Resistance Match Between Channels (Notes 3, 4)	ΔR_{ON}	V_{DD} = 2.7V, $I_{COM_}$ = 10mA, $V_{NO_}$ = 1.5V			0.4	Ω
On-Resistance Flatness (Note 5)	$R_{FLAT(ON)}$	V_{DD} = 2.7V, $I_{COM_}$ = 10mA, $V_{NO_}$ = 1.0V, 1.5V, 2.0V		0.5	1.5	Ω
NO_ Off-Leakage Current (Note 3)	$I_{NO_(OFF)}$	V_{DD} = 3.6V, $V_{COM_}$ = 0.3V, 3.3V; $V_{NO_}$ = 3.3V, 0.3V	-2		+2	nA
COM_ On-Leakage Current (Note 3)	$I_{COM_(ON)}$	V_{DD} = 3.6V, $V_{COM_}$ = 0.3V, 3.3V; $V_{NO_}$ = 0.3V, 3.3V, or unconnected	-2.5		+2.5	nA
Turn-On Time	t_{ON}	$V_{NO_}$ = 1.5V; R_L = 300Ω, C_L = 35pF, V_{IH} = 1.5V, V_{IL} = 0V			100	ns
Turn-Off Time	t_{OFF}	$V_{NO_}$ = 1.5V; R_L = 300Ω, C_L = 35pF, V_{IH} = 1.5V, V_{IL} = 0V			100	ns
Skew (Note 3)	t_{SKEW}	R_S = 39Ω, C_L = 50pF			2	ns
Charge Injection	Q	V_{GEN} = 1.5V, R_{GEN} = 0Ω, C_L = 1nF		10		pC
Off-Isolation	V_{ISO}	f = 10MHz; $V_{NO_}$ = $1V_{P-P}$; R_L = 50Ω, C_L = 5pF		-55		dB
		f = 1MHz; $V_{NO_}$ = $1V_{P-P}$; R_L = 50Ω, C_L = 5pF		-80		
On-Channel -3dB Bandwidth	BW	Signal = 0dBm, R_L = 50Ω, C_L = 5pF		300		MHz
Total Harmonic Distortion	THD	$V_{COM_}$ = $2V_{P-P}$, R_L = 600Ω		0.03		%
NO_ Off-Capacitance	$C_{NO_(OFF)}$	f = 1MHz		20		pF
Switch On-Capacitance	$C_{(ON)}$	f = 1MHz		50		pF
Switch-to-Switch	V_{CT}	f = 10MHz; $V_{NO_}$ = $1V_{P-P}$, R_L = 50Ω, C_L = 5pF		-80		dB
		f = 1MHz; $V_{NO_}$ = $1V_{P-P}$, R_L = 50Ω, C_L = 5pF		-110		
NO_-to-VIDOUT		Video circuit is on, switches are open; f = 10MHz; $V_{NO_}$ = $1V_{P-P}$		-55		dB
		Video circuit is on, switches are open; f = 1MHz; $V_{NO_}$ = $1V_{P-P}$		-80		

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V, GND = 0V, no load, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Note 1)


PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
CROSSTALK						
VIDOUT-to-NO_		Video circuit is on, f = 20kHz, VIDOUT = $2V_{P-P}$, R_L = 50Ω, C_L = 5pF		90		dB
VIDIN-to-COM		Video circuit is shutdown, f = 20kHz, $0.25V_{P-P}$ at VIDIN, R_L = 600Ω		100		dB
VIDOUT-to-COM		Video circuit is on, f = 20kHz, VIDOUT = $2V_{P-P}$, R_L = 50Ω, C_L = 5pF		90		dB
LOGIC SIGNAL (IN1 AND IN2)						
Logic-Low Threshold	V_{IL}				0.5	V
Logic-High Threshold	V_{IH}		1.4			V
Logic-Input Current	I_{IN}				10	µA
LOGIC SIGNAL ($\overline{SHDN}$)						
Logic-Low Threshold	V_{IL}				0.3 x V_{DD}	V
Logic-High Threshold	V_{IH}		0.7 x V_{DD}			V
Logic-Input Current	I_{IN}				10	µA

Note 1: All devices are 100% production tested at T_A = +25°C. Specifications over temperature limits are guaranteed by design.
Note 2: Voltage gain (A_V) is a two-point measurement in which the output-voltage swing is divided by the input-voltage swing.
Note 3: Guaranteed by design.
Note 4: $\Delta R_{ON} = R_{ON(MAX)} - R_{ON(MIN)}$.
Note 5: Flatness is defined as the difference between the maximum and minimum value of on-resistance as measured over the specified analog signal ranges.


Typical Operating Characteristics

(V_{DD} = $\overline{SHDN}$ = 3.3V. Video outputs have R_L = 150Ω connected to GND. T_A = +25°C, unless otherwise noted.)


SMALL-SIGNAL GAIN vs. FREQUENCY



SMALL-SIGNAL GAIN FLATNESS vs. FREQUENCY



LARGE-SIGNAL GAIN vs. FREQUENCY




Standard-Definition Video Filter Amplifiers with Dual SPST Switches


Typical Operating Characteristics (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V. Video outputs have R_L = 150Ω connected to GND. T_A = +25°C, unless otherwise noted.)


LARGE-SIGNAL GAIN FLATNESS vs. FREQUENCY




GROUP DELAY vs. FREQUENCY




POWER-SUPPLY REJECTION RATIO vs. FREQUENCY




QUIESCENT SUPPLY CURRENT vs. TEMPERATURE




VOLTAGE GAIN vs. TEMPERATURE




OUTPUT VOLTAGE vs. INPUT VOLTAGE (MAX9517)



DIFFERENTIAL GAIN AND PHASE




2T RESPONSE




Typical Operating Characteristics (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V. Video outputs have R_L = 150Ω connected to GND. T_A = +25°C, unless otherwise noted.)


12.5T RESPONSE




NTC-7 VIDEO TEST SIGNAL




PAL MULTIBURST RESPONSE




PAL COLOR BARS




FIELD SQUARE-WAVE RESPONSE




SWITCH INPUT-TO-INPUT CROSSTALK vs. FREQUENCY



SWITCH OUTPUT-TO-OUTPUT CROSSTALK vs. FREQUENCY



OUTPUT IMPEDANCE vs. FREQUENCY




Standard-Definition Video Filter Amplifiers with Dual SPST Switches


Typical Operating Characteristics (continued)

(V_{DD} = $\overline{SHDN}$ = 3.3V. Video outputs have R_L = 150Ω connected to GND. T_A = +25°C, unless otherwise noted.)


MAX9517
ENABLE RESPONSE




MAX9524
ENABLE RESPONSE



MAX9517
DISABLE RESPONSE



MAX9524
DISABLE RESPONSE



Pin Description

PIN	NAME	FUNCTION
1	N.C.	No Connection. Not internally connected.
2	COM1	Analog Switch 1 Common Terminal
3	COM2	Analog Switch 2 Common Terminal
4	VIDOUT	Video Output
5	GND	Ground
6	VIDIN	Video Input
7	NO2	Analog Switch 2 Normally Open Terminal
8	NO1	Analog Switch 1 Normally Open Terminal
9	$\overline{SHDN}$	Active-Low Shutdown Input. Connect to GND to place device in shutdown.
10	IN1	Analog Switch 1 Digital Control Input
11	IN2	Analog Switch 2 Digital Control Input
12	V_{DD}	Positive Power Supply. Bypass to GND with a 0.1µF capacitor.
—	EP	Exposed Paddle. Connect EP to GND. EP is also internally connected to GND.

Detailed Description

The MAX9517/MAX9524 consist of a lowpass filter and an output amplifier capable of driving a standard 150Ω video load to ground. The MAX9517 has an input buffer and the MAX9524 has an input sync-tip clamp. The MAX9517/MAX9524 both have two SPST analog switches that can be used to route audio, video, or digital signals. The output amplifiers provide a fixed gain of 2V/V.

The MAX9517/MAX9524 filter and amplify the video DAC output. External video signals, in which the DC bias is usually not known, can be AC-coupled to the MAX9524.

Input with DC Buffer (MAX9517)

The input of the MAX9517 can be directly connected to the video source if the signal is approximately between ground and 1V. This specification is commonly found at the output of most video DACs.

DC-coupling requires that the input signals are ground referenced so that the sync tip of composite or luma signals is within 50mV of ground.

Input with Sync-Tip Clamp (MAX9524)

When the bias of the incoming video signal is either unknown or not between ground and 1V (such as an external video source), use the MAX9524 to connect the video source through a 0.1µF capacitor.

The VIDIN input of the MAX9524 can only handle signals with a sync pulse, such as composite video and luma. An internal sync-tip clamp sets the internal DC level of the video signal.

Video Filter

The filter passband (±1dB) is typically 9MHz to make the device suitable for standard-definition video signals from all sources (including broadcast video and DVD). Broadcast video signals are channel limited: NTSC signals have 4.2MHz bandwidth, and PAL signals have 5MHz bandwidth. Video signals from a DVD player, however, are not channel limited; therefore, the bandwidth of DVD video signals can approach the Nyquist limit of 6.75MHz (recommendation ITU-R BT.601-5 specifies 13.5MHz as the sampling rate for standard-definition video). Therefore, the maximum bandwidth of the signal is 6.75MHz. To ease the filtering requirements, most modern video systems oversample by two times, clocking the video current DAC at 27MHz.

Outputs

The video output amplifiers can both source and sink load current, allowing output loads to be DC- or AC-coupled. The amplifier output stage needs around 300mV of headroom from either supply rail. The parts have an internal level shift circuit that positions the sync tip at approximately 300mV at the output.

If the supply voltage is greater than 3.135V (5% below a 3.3V supply), each amplifier can drive two DC-coupled video loads to ground. If the supply is less than 3.135V, each amplifier can drive only one DC-coupled or AC-coupled video load.

Shutdown

The MAX9517/MAX9524 draw less than 1µA supply current when $\overline{SHDN}$ is low. In shutdown, the amplifier output becomes high impedance.

SPST Analog Switches

Table 1. Logic for Analog Switches

IN_	SWITCH STATE
0	OFF
1	ON

Applications Information

Reducing Power Consumption in the Video DACs

The MAX9517/MAX9524 have high-impedance input buffers that can work with source resistances as high as 300Ω. To reduce power dissipation in the video DACs, the DAC output resistor can be scaled up in value. The reference resistor that sets the reference current inside the video DACs must also be similarly scaled up. For instance, if the output resistor is 37.5Ω, the DAC must source 26.7mA when the output is 1V. If the output resistor is increased to 300Ω, the DAC only needs to source 3.33mA when the output is 1V.

There is parasitic capacitance from the DAC output to ground. That capacitance in parallel with the DAC output resistor forms a pole that can potentially roll off the frequency response of the video signal. For example, 300Ω in parallel with 50pF creates a pole at 10.6MHz. To minimize this capacitance, reduce the area of the signal trace attached to the DAC output as much as possible, and place the MAX9517/MAX9524 as close as possible to the video DAC outputs.

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

AC-Coupling the Outputs

The outputs can be AC-coupled because the output stage can source and sink current as shown in Figure 1. Coupling capacitors should be 220µF or greater to keep the highpass filter formed by the 150Ω equivalent resistance of the video transmission line to a corner frequency of 4.8Hz or below. The frame rate of PAL systems is 25Hz, and the frame rate of NTSC systems is 30Hz. The corner frequency should be well below the frame rate.

Changing Between Video Output and Microphone Input on a Single Connector

A single pole on a mobile phone jack can be used for transmitting a video signal to a television or receiving the signal from the microphone of a headset. Figure 2 shows how the MAX9517 can transmit a video signal. Figure 3 shows how the MAX9517 can receive and pass on the signal from a microphone.

Switching Between Video and Digital Signals

The dual SPST analog switches and the high-impedance output of the video amplifier enable video transmission, digital transmission, and digital reception all on a single pole of a connector. Figures 4, 5, and 6 show the different configurations of the MAX9517.

Selecting Between Two Video Sources

The analog switches can multiplex between two video sources. For example, a mobile phone might have an application processor with an integrated video encoder and a mobile graphics processor with an integrated video encoder, each creating a composite video signal that is between 0 and 1V. Figure 7 shows this application in which the MAX9517 chooses between two internal video sources. The two analog switches can be used as a 2:1 multiplexer to select which video DAC output is actually filtered, amplified, and then driven out to the connector. Close switch 1 to select the video from the application processor. Close switch 2 to select the video from the mobile graphics processor.

Figure 8 shows the application in which the MAX9524 chooses between two external video sources with unknown DC bias.

Y/C Mixer with Chroma Mute

If the video application processor has two current output digital-to-analog converters (DACs) for luma (Y) and chroma (C), respectively, then the signals can be mixed together to create a composite video signal by summing the currents into a single resistor, as shown in Figure 9. The composite video signal should be AC-coupled into the MAX9524 because the composite video signal has a positive DC level shift. The sync-tip clamp of the MAX9524 will re-establish the DC bias level of the signal inside the chip.

The chroma current is connected to essentially a single-pole, double-throw (SPDT) switch. In one position, the switch routes the chroma current into the resistor. In the other position, the switch routes the chroma current into ground. For the Y/C mixer to work properly, the chroma current must be routed through analog switch 1 into the resistor.

If the chroma signal needs to be muted, then the chroma current is shunted to ground through analog switch 2. Analog switch 1 stays open. See Figure 10.




Figure 1. AC-Coupled Outputs




Figure 2. Video Output Configuration




Figure 3. Microphone Input Configuration

Standard-Definition Video Filter Amplifiers with Dual SPST Switches




Figure 4. Video Output Configuration




Figure 5. Digital Output Configuration




Figure 6. Digital Input Configuration




Figure 7. Selecting Between Two Internal Video Sources

Standard-Definition Video Filter Amplifiers with Dual SPST Switches




Figure 8. Selecting Between Two External Video Sources




Figure 9. Luma and Chroma Mixer Circuit (Chroma Current Routed into Resistor)




Figure 10. Luma and Chroma Mixer Circuit with Chroma Muted. Chroma Current is Shunted into Ground Through Analog Switch 2.

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Anti-Alias Filter

The MAX9524 can also provide anti-alias filtering with buffer before an analog-to-digital converter (ADC), which would be present in an NTSC/PAL video decoder, for example. Figure 11 shows an example application circuit for MAX9524. An external composite video signal is applied to IN, which is terminated with 75Ω to ground. The signal is AC-coupled to VIDIN because the DC level of an external video signal is usually not well specified.

Power-Supply Bypassing and Ground

The MAX9517/MAX9524 operate from a single-supply voltage down to 2.7V, allowing for low-power operation. Bypass V_{DD} to GND with a 0.1µF capacitor. Place all external components as close as possible to the device.




Figure 11. MAX9524 is Used as an Anti-Alias Filter with Buffer (Switches Can Route Other Signals)

Switch Test Circuits/Timing Diagrams




Figure 12. Switching Time

Switch Test Circuits/Timing Diagrams (continued)




Figure 13. Output Signal Skew

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Switch Test Circuits/Timing Diagrams (continued)




Figure 14. Charge Injection




Figure 15. On-Loss, Off-Isolation, and Crosstalk





Figure 16. Channel Off-/On-Capacitance


Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Typical Operating Circuits



Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Pin Configuration



Chip Information


PROCESS: BiCMOS

Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to **www.maxim-ic.com/packages**.)

12x16L QFN THIN.EPS



Standard-Definition Video Filter Amplifiers with Dual SPST Switches

Package Information (continued)

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information go to **www.maxim-ic.com/packages**.)

PKG	8L 3x3			12L 3x3			16L 3x3		
REF.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.
A	0.70	0.75	0.80	0.70	0.75	0.80	0.70	0.75	0.80
b	0.25	0.30	0.35	0.20	0.25	0.30	0.20	0.25	0.30
D	2.90	3.00	3.10	2.90	3.00	3.10	2.90	3.00	3.10
E	2.90	3.00	3.10	2.90	3.00	3.10	2.90	3.00	3.10
e	0.65 BSC.			0.50 BSC.			0.50 BSC.		
L	0.35	0.55	0.75	0.45	0.55	0.65	0.30	0.40	0.50
N	8			12			16		
ND	2			3			4		
NE	2			3			4		
A1	0	0.02	0.05	0	0.02	0.05	0	0.02	0.05
A2	0.20 REF			0.20 REF			0.20 REF		
k	0.25	-	-	0.25	-	-	0.25	-	-

EXPOSED PAD VARIATIONS								
PKG. CODES	D2			E2			PIN ID	JEDEC
	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.		
TQ833-1	0.25	0.70	1.25	0.25	0.70	1.25	0.35 x 45°	WEEC
T1233-1	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-1
T1233-3	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-1
T1233-4	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-1
T1633-2	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-2
T1633F-3	0.65	0.80	0.95	0.65	0.80	0.95	0.225 x 45°	WEED-2
T1633FH-3	0.65	0.80	0.95	0.65	0.80	0.95	0.225 x 45°	WEED-2
T1633-4	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-2
T1633-5	0.95	1.10	1.25	0.95	1.10	1.25	0.35 x 45°	WEED-2

NOTES:

1. DIMENSIONING & TOLERANCING CONFORM TO ASME Y14.5M-1994.
2. ALL DIMENSIONS ARE IN MILLIMETERS. ANGLES ARE IN DEGREES.
3. N IS THE TOTAL NUMBER OF TERMINALS.
4. THE TERMINAL #1 IDENTIFIER AND TERMINAL NUMBERING CONVENTION SHALL CONFORM TO JESD 95-1 SPP-012. DETAILS OF TERMINAL #1 IDENTIFIER ARE OPTIONAL, BUT MUST BE LOCATED WITHIN THE ZONE INDICATED. THE TERMINAL #1 IDENTIFIER MAY BE EITHER A MOLD OR MARKED FEATURE.
5. DIMENSION b APPLIES TO METALLIZED TERMINAL AND IS MEASURED BETWEEN 0.20 mm AND 0.25 mm FROM TERMINAL TIP.
6. ND AND NE REFER TO THE NUMBER OF TERMINALS ON EACH D AND E SIDE RESPECTIVELY.
7. DEPOPULATION IS POSSIBLE IN A SYMMETRICAL FASHION.
8. COPLANARITY APPLIES TO THE EXPOSED HEAT SINK SLUG AS WELL AS THE TERMINALS.
9. DRAWING CONFORMS TO JEDEC MO220 REVISION C.
10. MARKING IS FOR PACKAGE ORIENTATION REFERENCE ONLY.
11. NUMBER OF LEADS SHOWN ARE FOR REFERENCE ONLY.
12. WARPAGE NOT TO EXCEED 0.10mm.

—DRAWING NOT TO SCALE—

DALLAS SEMICONDUCTOR MAXIM

TITLE: PACKAGE OUTLINE
8, 12, 16L THIN QFN, 3x3x0.8mm

APPROVAL	DOCUMENT CONTROL NO.	REV.	
	21-0136	I	2/2

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2007 Maxim Integrated Products MAXIM is a registered trademark of Maxim Integrated Products, Inc.


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.