

## FEATURES

### Extremely low harmonic distortion (HD)

- 112 dBc HD2 @ 10 MHz
- 84 dBc HD2 @ 70 MHz
- 77 dBc HD2 @ 100 MHz
- 102 dBc HD3 @ 10 MHz
- 91 dBc HD3 @ 70 MHz
- 84 dBc HD3 @ 100 MHz

### Low input voltage noise: 2.2 nV/ $\sqrt{\text{Hz}}$

### High speed

- 3 dB bandwidth of 1.9 GHz,  $G = 1$
- Slew rate: 6000 V/ $\mu\text{s}$ , 25% to 75%
- Fast overdrive recovery of 1 ns

### 0.5 mV typical offset voltage

### Externally adjustable gain

### Differential-to-differential or single-ended-to-differential operation

### Adjustable output common-mode voltage

### Single-supply operation: 3.3 V to 5 V

## APPLICATIONS

### ADC drivers

### Single-ended-to-differential converters

### IF and baseband gain blocks

### Differential buffers

### Line drivers

## GENERAL DESCRIPTION

The ADA4937-x is a low noise, ultralow distortion, high speed differential amplifier. It is an ideal choice for driving high performance ADCs with resolutions up to 16 bits from dc to 100 MHz. The adjustable level of the output common mode allows the ADA4937-x to match the input of the ADC. The internal common-mode feedback loop also provides exceptional output balance as well as suppression of even-order harmonic distortion products.

With the ADA4937-x, differential gain configurations are easily realized with a simple external feedback network of four resistors that determine the closed-loop gain of the amplifier.

The ADA4937-x is fabricated using Analog Devices, Inc., proprietary silicon-germanium (SiGe), complementary bipolar process, enabling it to achieve very low levels of distortion with an input voltage noise of only 2.2 nV/ $\sqrt{\text{Hz}}$ . The low dc offset and excellent dynamic performance of the ADA4937-x make it well-suited for a wide variety of data acquisition and signal processing applications.

### Rev. C

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

## FUNCTIONAL BLOCK DIAGRAMS




Figure 1. ADA4937-1




Figure 2. ADA4937-2




Figure 3. Harmonic Distortion vs. Frequency

The ADA4937-x is available in a Pb-free, 3 mm  $\times$  3 mm, 16-lead LFCSP (ADA4937-1, single) or a Pb-free, 4 mm  $\times$  4 mm, 24-lead LFCSP (ADA4937-2, dual). The pinout has been optimized to facilitate PCB layout and minimize distortion. The ADA4937-x is specified to operate over the automotive ( $-40^{\circ}\text{C}$  to  $+105^{\circ}\text{C}$ ) temperature range and between 3.3 V and 5 V supplies.

## TABLE OF CONTENTS

|  |    |  |    |
|--|----|--|----|
| Features .....                                     | 1  | Analyzing an Application Circuit .....                                 | 18 |
| Applications .....                                 | 1  | Setting the Closed-Loop Gain .....                                     | 18 |
| General Description .....                          | 1  | Estimating the Output Noise Voltage .....                              | 18 |
| Functional Block Diagrams .....                    | 1  | Impact of Mismatches in the Feedback Networks .....                    | 19 |
| Revision History .....                             | 2  | Calculating the Input Impedance for an Application<br>Circuit .....    | 19 |
| Specifications .....                               | 3  | Input Common-Mode Voltage Range in Single-Supply<br>Applications ..... | 20 |
| 5 V Operation .....                                | 3  | Setting the Output Common-Mode Voltage .....                           | 20 |
| 3.3 V Operation .....                              | 5  | Power-Down Operation .....   | 20 |
| Absolute Maximum Ratings .....                     | 7  | Layout, Grounding, and Bypassing .....                                 | 22 |
| Thermal Resistance .....                           | 7  | High Performance ADC Driving .....                                     | 23 |
| ESD Caution .....                                  | 7  | 3.3 V Operation .....  | 25 |
| Pin Configurations and Function Descriptions ..... | 8  | Outline Dimensions .....   | 26 |
| Typical Performance Characteristics .....          | 9  | Ordering Guide .....   | 26 |
| Test Circuits .....                                | 16 |  |    |
| Terminology .....                                  | 17 |  |    |
| Theory of Operation .....                          | 18 |  |    |

## REVISION HISTORY

### 3/10—Rev. B to Rev. C

|  |    |
|--|----|
| Changes to Table 2, Power Supply Parameter ..... | 4  |
| Changes to Table 4, Power Supply Parameter ..... | 6  |
| Changes to Figure 43 .....                       | 15 |
| Added the Power-Down Operation Section .....     | 20 |

### 10/09—Rev. A to Rev. B

|  |    |
|--|----|
| Changes to General Description Section .....   | 1  |
| Changes to Table 1 .....   | 3  |
| Changes to Operating Temperature Range Parameter, Table 2 ..                               | 4  |
| Changes to Table 3 .....   | 5  |
| Changes to Figure 4 .....  | 7  |
| Changes to Figure 5 and Figure 6 .....   | 8  |
| Added EP Row to Table 7 and EP Row to Table 8 .....  | 8  |
| Added Figure 46, Figure 47, and Figure 48; Renumbered<br>Sequentially .....                | 15 |
| Changes to Table 9 .....   | 18 |
| Changes to Input Common-Mode Voltage Range in Single-<br>Supply Applications Section ..... | 20 |
| Changes to Ordering Guide .....  | 26 |

### 11/07—Rev. 0 to Rev. A

|   |           |
|---|-----------|
| Added the ADA4937-2 .....                                 | Universal |
| Changes to Features .....                                 | 1         |
| Changes to Specifications .....                           | 3         |
| Changes to Figure 4 .....                                 | 7         |
| Changes to Typical Performance Characteristics .....      | 9         |
| Inserted Figure 44 .....                                  | 15        |
| Added the Terminating a Single-Ended Input Section .....  | 19        |
| Changes to Table 10 and Table 11 .....                    | 21        |
| Changes to Layout, Grounding, and Bypassing Section ..... | 22        |
| Inserted Figure 59, Figure 60, and Figure 61 .....        | 22        |
| Updated Outline Dimensions .....                          | 26        |
| Changes to Ordering Guide .....                           | 26        |

### 5/07—Revision 0: Initial Version

# SPECIFICATIONS

## 5 V OPERATION

$T_A = 25^\circ\text{C}$ ,  $+V_S = 5\text{ V}$ ,  $-V_S = 0\text{ V}$ ,  $V_{OCM} = +V_S/2$ ,  $R_T = 61.9\ \Omega$ ,  $R_G = R_F = 200\ \Omega$ ,  $G = +1$ ,  $R_{L, dm} = 1\text{ k}\Omega$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted.

### $\pm D_{IN}$ to $\pm OUT$ Performance

Table 1.

| Parameter                                 | Test Conditions/Comments   | Min  | Typ        | Max  | Unit                         |
|---|--|------|------------|------|------------------------------|
| <b>DYNAMIC PERFORMANCE</b>                |  |      |            |      |                              |
| -3 dB Small Signal Bandwidth              | $V_{OUT, dm} = 0.1\text{ V p-p}$   |      | 1900       |      | MHz                          |
| Bandwidth for 0.1 dB Flatness             | $V_{OUT, dm} = 0.1\text{ V p-p}$   |      | 200        |      | MHz                          |
| Large Signal Bandwidth                    | $V_{OUT, dm} = 2\text{ V p-p}$   |      | 1700       |      | MHz                          |
| Slew Rate                                 | $V_{OUT, dm} = 2\text{ V p-p}$ ; 25% to 75%  |      | 6000       |      | V/ $\mu\text{s}$             |
| Settling Time                             | $V_{OUT, dm} = 2\text{ V p-p}$   |      | 7          |      | ns                           |
| Overdrive Recovery Time                   | $V_{IN} = 0\text{ V}$ to 1.5 V step; $G = 3.16$  |      | <1         |      | ns                           |
| <b>NOISE/HARMONIC PERFORMANCE</b>         |  |      |            |      |                              |
| See Figure 51 for distortion test circuit |  |      |            |      |                              |
| Second Harmonic                           | $V_{OUT, dm} = 2\text{ V p-p}$ ; 10 MHz  |      | -112       |      | dBc                          |
|   | $V_{OUT, dm} = 2\text{ V p-p}$ ; 70 MHz  |      | -84        |      | dBc                          |
|   | $V_{OUT, dm} = 2\text{ V p-p}$ ; 100 MHz   |      | -77        |      | dBc                          |
| Third Harmonic                            | $V_{OUT, dm} = 2\text{ V p-p}$ ; 10 MHz  |      | -102       |      | dBc                          |
|   | $V_{OUT, dm} = 2\text{ V p-p}$ ; 70 MHz  |      | -91        |      | dBc                          |
|   | $V_{OUT, dm} = 2\text{ V p-p}$ ; 100 MHz   |      | -84        |      | dBc                          |
| IMD                                       | $f_1 = 70\text{ MHz}$ ; $f_2 = 70.1\text{ MHz}$ ; $V_{OUT, dm} = 2\text{ V p-p}$   |      | -91        |      | dBc                          |
| Voltage Noise (RTI)                       | $f = 100\text{ kHz}$   |      | 2.2        |      | nV/ $\sqrt{\text{Hz}}$       |
| Input Current Noise                       | $f = 100\text{ kHz}$   |      | 4          |      | pA/ $\sqrt{\text{Hz}}$       |
| Noise Figure                              | $G = 4$ ; $R_T = 136\ \Omega$ ; $R_F = 200\ \Omega$ ; $R_G = 37\ \Omega$ ; $f = 100\text{ MHz}$                                    |      | 15         |      | dB                           |
| Crosstalk (ADA4937-2)                     | $f = 100\text{ MHz}$   |      | -72        |      | dB                           |
| <b>INPUT CHARACTERISTICS</b>              |  |      |            |      |                              |
| Offset Voltage                            | $V_{OS, dm} = V_{OUT, dm}/2$ ; $V_{DIN+} = V_{DIN-} = 2.5\text{ V}$  | -2.5 | $\pm 0.5$  | +2.5 | mV                           |
|   | $T_{MIN}$ to $T_{MAX}$ variation   |      | $\pm 1$    |      | $\mu\text{V}/^\circ\text{C}$ |
| Input Bias Current                        | $T_{MIN}$ to $T_{MAX}$ variation   | -30  | -21        | -10  | $\mu\text{A}$                |
|   | $T_{MIN}$ to $T_{MAX}$ variation   |      | 0.01       |      | $\mu\text{A}/^\circ\text{C}$ |
| Input Offset Current                      |  | -2   | +0.5       | +2   | $\mu\text{A}$                |
| Input Resistance                          | Differential   |      | 6          |      | M $\Omega$                   |
|   | Common mode  |      | 3          |      | M $\Omega$                   |
| Input Capacitance                         |  |      | 1          |      | pF                           |
| Input Common-Mode Voltage                 |  |      | 0.3 to 3.0 |      | V                            |
| CMRR                                      | $\Delta V_{OUT, dm}/\Delta V_{IN, cm}$ ; $\Delta V_{IN, cm} = \pm 1\text{ V}$  | -69  | -80        |      | dB                           |
| <b>OUTPUT CHARACTERISTICS</b>             |  |      |            |      |                              |
| Output Voltage Swing                      | Maximum $\Delta V_{OUT}$ ; single-ended output; $R_F = R_G = 10\text{ k}\Omega$  | 0.9  |            | 4.1  | V                            |
| Linear Output Current                     | Per amplifier; $R_{L, dm} = 20\ \Omega$ ; $f = 10\text{ MHz}$  |      | $\pm 70$   |      | mA                           |
| Output Balance Error                      | $\Delta V_{OUT, cm}/\Delta V_{OUT, dm}$ ; $\Delta V_{OUT, dm} = 1\text{ V}$ ; $f = 10\text{ MHz}$ ; see Figure 50 for test circuit |      | -61        |      | dB                           |

# ADA4937-1/ADA4937-2

## $V_{OCM}$ to $\pm OUT$ Performance

Table 2.

| Parameter   | Test Conditions/Comments  | Min                                 | Typ      | Max  | Unit                         |                  |
|---|---|-------------------------------------|----------|------|------------------------------|------------------|
| $V_{OCM}$ DYNAMIC PERFORMANCE                     |   |                                     |          |      |                              |                  |
| -3 dB Bandwidth                                   |   |                                     | 440      |      | MHz                          |                  |
| Slew Rate   | $V_{IN} = 1.5\text{ V to }3.5\text{ V}; 25\% \text{ to } 75\%$      |                                     | 1150     |      | V/ $\mu\text{s}$             |                  |
| Input Voltage Noise (RTI)                         | $f = 100\text{ kHz}$  |                                     | 7.5      |      | nV/ $\sqrt{\text{Hz}}$       |                  |
| $V_{OCM}$ INPUT CHARACTERISTICS                   |   |                                     |          |      |                              |                  |
| Input Voltage Range                               |   | 1.2                                 |          | 3.8  | V                            |                  |
| Input Resistance                                  |   | 8                                   | 10       | 12   | k $\Omega$                   |                  |
| Input Offset Voltage                              | $V_{OS,cm} = V_{OUT,cm}; V_{DIN+} = V_{DIN-} = +V_S/2$              |                                     | 2        | 7.1  | mV                           |                  |
| Input Bias Current                                |   |                                     | 0.5      |      | $\mu\text{A}$                |                  |
| $V_{OCM}$ CMRR                                    | $\Delta V_{OUT,dm}/\Delta V_{OCM}; \Delta V_{OCM} = \pm 1\text{ V}$ | -70                                 | -75      |      | dB                           |                  |
| Gain  | $\Delta V_{OUT,cm}/\Delta V_{OCM}; \Delta V_{OCM} = \pm 1\text{ V}$ | 0.97                                | 0.98     | 1.00 | V/V                          |                  |
| POWER SUPPLY                                      |   |                                     |          |      |                              |                  |
| Operating Range                                   |   | 3.0                                 |          | 5.25 | V                            |                  |
| Quiescent Current per Amplifier                   | Enabled   | 38.0                                | 39.5     | 42.0 | mA                           |                  |
|   | $T_{MIN}$ to $T_{MAX}$ variation                                    |                                     | 17       |      | $\mu\text{A}/^\circ\text{C}$ |                  |
| Power Supply Rejection Ratio                      | Powered down  | 0.02                                | 0.3      | 0.5  | mA                           |                  |
|   | $\Delta V_{OUT,dm}/\Delta V_S; \Delta V_S = 1\text{ V}$             | -70                                 | -90      |      | dB                           |                  |
| POWER-DOWN (PD)                                   |   |                                     |          |      |                              |                  |
| $\overline{\text{PD}}$ Input Voltage              | Powered down  |                                     | $\leq 1$ |      | V                            |                  |
|   | Enabled   |                                     | $\geq 2$ |      | V                            |                  |
| Turn-Off Time                                     |   |                                     | 1        |      | $\mu\text{s}$                |                  |
| Turn-On Time                                      |   |                                     | 200      |      | ns                           |                  |
| $\overline{\text{PD}}$ Bias Current per Amplifier | Enabled   | $\overline{\text{PD}} = 5\text{ V}$ | 10       | 30   | 50                           | $\mu\text{A}$    |
|   | Powered Down  | $\overline{\text{PD}} = 0\text{ V}$ | -300     | -200 | -150                         | $\mu\text{A}$    |
| OPERATING TEMPERATURE RANGE                       |   |                                     |          | -40  | +105                         | $^\circ\text{C}$ |

### 3.3 V OPERATION

$T_A = 25^\circ\text{C}$ ,  $+V_S = 3.3\text{ V}$ ,  $-V_S = 0\text{ V}$ ,  $V_{\text{OCM}} = +V_S/2$ ,  $R_T = 61.9\ \Omega$ ,  $R_G = R_F = 200\ \Omega$ ,  $G = 1$ ,  $R_{L,\text{dm}} = 1\ \text{k}\Omega$ , unless otherwise noted. All specifications refer to single-ended input and differential outputs, unless otherwise noted.

#### $\pm D_{\text{IN}}$ to $\pm O_{\text{UT}}$ Performance

Table 3.

| Parameter                                 | Test Conditions/Comments   | Min  | Typ        | Max  | Unit                         |
|---|--|------|------------|------|------------------------------|
| <b>DYNAMIC PERFORMANCE</b>                |  |      |            |      |                              |
| -3 dB Small Signal Bandwidth              | $V_{\text{OUT,dm}} = 0.1\text{ V p-p}$   |      | 1800       |      | MHz                          |
| Bandwidth for 0.1 dB Flatness             | $V_{\text{OUT,dm}} = 0.1\text{ V p-p}$   |      | 200        |      | MHz                          |
| Large Signal Bandwidth                    | $V_{\text{OUT,dm}} = 2\text{ V p-p}$   |      | 1300       |      | MHz                          |
| Slew Rate                                 | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 25% to 75%  |      | 4000       |      | V/ $\mu\text{s}$             |
| Settling Time                             | $V_{\text{OUT,dm}} = 2\text{ V p-p}$   |      | 7          |      | ns                           |
| Overdrive Recovery Time                   | $V_{\text{IN}} = 0\text{ V}$ to 1.0 V step; $G = 3.16$   |      | <1         |      | ns                           |
| <b>NOISE/HARMONIC PERFORMANCE</b>         |  |      |            |      |                              |
| See Figure 51 for distortion test circuit |  |      |            |      |                              |
| Second Harmonic                           | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 10 MHz  |      | -113       |      | dBc                          |
|   | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 70 MHz  |      | -85        |      | dBc                          |
|   | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 100 MHz   |      | -77        |      | dBc                          |
| Third Harmonic                            | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 10 MHz  |      | -95        |      | dBc                          |
|   | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 70 MHz  |      | -77        |      | dBc                          |
|   | $V_{\text{OUT,dm}} = 2\text{ V p-p}$ ; 100 MHz   |      | -71        |      | dBc                          |
| IMD                                       | $f_1 = 70\text{ MHz}$ ; $f_2 = 70.1\text{ MHz}$ ; $V_{\text{OUT,dm}} = 2\text{ V p-p}$   |      | -87        |      | dBc                          |
| Voltage Noise (RTI)                       | $f = 100\text{ kHz}$   |      | 2.2        |      | nV/ $\sqrt{\text{Hz}}$       |
| Input Current Noise                       | $f = 100\text{ kHz}$   |      | 4          |      | pA/ $\sqrt{\text{Hz}}$       |
| Noise Figure                              | $G = 4$ ; $R_T = 136\ \Omega$ ; $R_F = 200\ \Omega$ ; $R_G = 37\ \Omega$ ; $f = 100\text{ MHz}$  |      | 15         |      | dB                           |
| Crosstalk (ADA4937-2)                     | $f = 100\text{ MHz}$   |      | -72        |      | dB                           |
| <b>INPUT CHARACTERISTICS</b>              |  |      |            |      |                              |
| Offset Voltage                            | $V_{\text{OS,dm}} = V_{\text{OUT,dm}}/2$ ; $V_{\text{DIN+}} = V_{\text{DIN-}} = +V_S/2$  | -2.5 | $\pm 0.5$  | +2.5 | mV                           |
|   | $T_{\text{MIN}}$ to $T_{\text{MAX}}$ variation   |      | $\pm 1$    |      | $\mu\text{V}/^\circ\text{C}$ |
| Input Bias Current                        | $T_{\text{MIN}}$ to $T_{\text{MAX}}$ variation   | -50  | -20        | -10  | $\mu\text{A}$                |
|   | Differential   |      | 0.01       |      | $\mu\text{A}/^\circ\text{C}$ |
| Input Resistance                          | Differential   |      | 6          |      | M $\Omega$                   |
|   | Common mode  |      | 3          |      | M $\Omega$                   |
| Input Capacitance                         |  |      | 1          |      | pF                           |
| Input Common-Mode Voltage                 |  |      | 0.3 to 1.2 |      | V                            |
| CMRR                                      | $\Delta V_{\text{OUT,dm}}/\Delta V_{\text{IN,cm}}$ ; $\Delta V_{\text{IN,cm}} = \pm 1\text{ V}$  | -67  | -80        |      | dB                           |
| <b>OUTPUT CHARACTERISTICS</b>             |  |      |            |      |                              |
| Output Voltage Swing                      | Maximum $\Delta V_{\text{OUT}}$ ; single-ended output; $R_F = R_G = 10\ \text{k}\Omega$  | 0.8  |            | 2.5  | V                            |
| Linear Output Current                     | Per amplifier; $R_{L,\text{dm}} = 20\ \Omega$ ; $f = 10\text{ MHz}$  |      | $\pm 47$   |      | mA                           |
| Output Balance Error                      | $\Delta V_{\text{OUT,cm}}/\Delta V_{\text{OUT,dm}}$ ; $\Delta V_{\text{OUT,dm}} = 1\text{ V}$ ; $f = 10\text{ MHz}$ ; see Figure 50 for test circuit |      | -61        |      | dB                           |

# ADA4937-1/ADA4937-2

## $V_{OCM}$ to $\pm OUT$ Performance

Table 4.

| Parameter                                  | Test Conditions/Comments   | Min  | Typ      | Max  | Unit                           |
|--|--|------|----------|------|--------------------------------|
| $V_{OCM}$ DYNAMIC PERFORMANCE              |  |      |          |      |                                |
| -3 dB Bandwidth                            |  |      | 440      |      | MHz                            |
| Slew Rate                                  | $V_{IN} = 0.9\text{ V to } 2.4\text{ V}; 25\% \text{ to } 75\%$      |      | 900      |      | V/ $\mu\text{s}$               |
| Input Voltage Noise (RTI)                  | $f = 100\text{ kHz}$   |      | 7.5      |      | nV/ $\sqrt{\text{Hz}}$         |
| $V_{OCM}$ INPUT CHARACTERISTICS            |  |      |          |      |                                |
| Input Voltage Range                        |  | 1.2  |          | 2.1  | V                              |
| Input Resistance                           |  |      | 10       |      | k $\Omega$                     |
| Input Offset Voltage                       | $V_{OS, cm} = V_{OUT, cm}; V_{DIN+} = V_{DIN-} = 1.67\text{ V}$      |      | 2        | 7.1  | mV                             |
| Input Bias Current                         |  |      | 0.5      |      | $\mu\text{A}$                  |
| $V_{OCM}$ CMRR                             | $\Delta V_{OUT, dm}/\Delta V_{OCM}; \Delta V_{OCM} = \pm 1\text{ V}$ | -70  | -75      |      | dB                             |
| Gain                                       | $\Delta V_{OUT, cm}/\Delta V_{OCM}; \Delta V_{OCM} = \pm 1\text{ V}$ | 0.97 | 0.98     | 1.00 | V/V                            |
| POWER SUPPLY                               |  |      |          |      |                                |
| Operating Range                            |  | 3.0  |          | 5.25 | V                              |
| Quiescent Current per Amplifier            | Enabled  | 36   | 38       | 40   | mA                             |
|  | $T_{MIN}$ to $T_{MAX}$ variation                                     |      | 17       |      | $\mu\text{A}/^{\circ}\text{C}$ |
| Power Supply Rejection Ratio               | Powered down   | 0.02 | 0.2      | 0.5  | mA                             |
|  | $\Delta V_{OUT, dm}/\Delta V_S; \Delta V_S = 1\text{ V}$             | -70  | -90      |      | dB                             |
| POWER-DOWN ( $\overline{PD}$ )             |  |      |          |      |                                |
| $\overline{PD}$ Input Voltage              | Powered down   |      | $\leq 1$ |      | V                              |
|  | Enabled  |      | $\geq 2$ |      | V                              |
| Turn-Off Time                              |  |      | 1        |      | $\mu\text{s}$                  |
| Turn-On Time                               |  |      | 200      |      | ns                             |
| $\overline{PD}$ Bias Current per Amplifier | Enabled  | 10   | 20       | 30   | $\mu\text{A}$                  |
|  | Powered Down   | -200 | -120     | -100 | $\mu\text{A}$                  |
| OPERATING TEMPERATURE RANGE                |  | -40  |          | +105 | $^{\circ}\text{C}$             |

## ABSOLUTE MAXIMUM RATINGS

Table 5.

| Parameter                            | Rating          |
|--------------------------------------|-----------------|
| Supply Voltage                       | 5.5 V           |
| Power Dissipation                    | See Figure 4    |
| Storage Temperature Range            | -65°C to +125°C |
| Operating Temperature Range          | -40°C to +105°C |
| Lead Temperature (Soldering, 10 sec) | 300°C           |
| Junction Temperature                 | 150°C           |

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

### THERMAL RESISTANCE

$\theta_{JA}$  is specified for the device (including exposed pad) soldered to a high thermal conductivity 2s2p circuit board, as described in EIA/JESD51-7.

Table 6. Thermal Resistance

| Package Type                | $\theta_{JA}$ | Unit |
|-----------------------------|---------------|------|
| 16-Lead LFCSP (Exposed Pad) | 95            | °C/W |
| 24-Lead LFCSP (Exposed Pad) | 67            | °C/W |

### Maximum Power Dissipation

The maximum safe power dissipation in the ADA4937-x packages is limited by the associated rise in junction temperature ( $T_j$ ) on the die. At approximately 150°C, which is the glass transition temperature, the plastic changes its properties. Even temporarily exceeding this temperature limit can change the stresses that the package exerts on the die, permanently shifting the parametric performance of the ADA4937-x. Exceeding a junction temperature of 150°C for an extended period can result in changes in the silicon devices, potentially causing failure.

The power dissipated in the package ( $P_D$ ) is the sum of the quiescent power dissipation and the power dissipated in the package due to the load drive. The quiescent power is the voltage between the supply pins ( $V_S$ ) times the quiescent current ( $I_S$ ). The power dissipated due to the load drive depends upon the particular application. The power due to load drive is calculated by multiplying the load current by the associated voltage drop across the device. RMS voltages and currents must be used in these calculations.

Airflow increases heat dissipation, effectively reducing  $\theta_{JA}$ . In addition, more metal directly in contact with the package leads/exposed pad from metal traces, through holes, ground, and power planes reduces  $\theta_{JA}$ .

Figure 4 shows the maximum safe power dissipation in the package vs. the ambient temperature for the ADA4937-1 single 16-lead LFCSP (95°C/W), and the ADA4937-2 dual 24-lead LFCSP (67°C/W) on a JEDEC standard 4-layer board.



Figure 4. Maximum Power Dissipation vs. Temperature, 4-Layer Board


### ESD CAUTION



**ESD (electrostatic discharge) sensitive device.** Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

# ADA4937-1/ADA4937-2

## PIN CONFIGURATIONS AND FUNCTION DESCRIPTIONS




**NOTES**

1. EXPOSED PADDLE. THE EXPOSED PAD IS NOT ELECTRICALLY CONNECTED TO THE DEVICE. IT IS TYPICALLY SOLDERED TO GROUND OR A POWER PLANE ON THE PCB THAT IS THERMALLY CONDUCTIVE.

06591-1005

Figure 5. ADA4937-1 Pin Configuration



**NOTES**

1. EXPOSED PADDLE. THE EXPOSED PAD IS NOT ELECTRICALLY CONNECTED TO THE DEVICE. IT IS TYPICALLY SOLDERED TO GROUND OR A POWER PLANE ON THE PCB THAT IS THERMALLY CONDUCTIVE.

06591-1006

Figure 6. ADA4937-2 Pin Configuration

Table 7. ADA4937-1 Pin Function Descriptions

| Pin No.  | Mnemonic               | Description   |
|----------|------------------------|---|
| 1        | -FB                    | Negative Output for Feedback Component Connection.  |
| 2        | +IN                    | Positive Input Summing Node.  |
| 3        | -IN                    | Negative Input Summing Node.  |
| 4        | +FB                    | Positive Output for Feedback Component Connection.  |
| 5 to 8   | +V <sub>S</sub>        | Positive Supply Voltage.  |
| 9        | V <sub>OCM</sub>       | Output Common-Mode Voltage.   |
| 10       | +OUT                   | Positive Output for Load Connection.  |
| 11       | -OUT                   | Negative Output for Load Connection.  |
| 12       | $\overline{\text{PD}}$ | Power-Down Pin.   |
| 13 to 16 | -V <sub>S</sub>        | Negative Supply Voltage.  |
| EP       |                        | Exposed Paddle. The exposed pad is not electrically connected to the device. It is typically soldered to ground or a power plane on the PCB that is thermally conductive. |

Table 8. ADA4937-2 Pin Function Descriptions

| Pin No. | Mnemonic                | Description   |
|---------|-------------------------|---|
| 1       | -IN1                    | Negative Input Summing Node 1.  |
| 2       | +FB1                    | Positive Output Feedback Pin 1.   |
| 3, 4    | +V <sub>S1</sub>        | Positive Supply Voltage 1.  |
| 5       | -FB2                    | Negative Output Feedback Pin 2.   |
| 6       | +IN2                    | Positive Input Summing Node 2.  |
| 7       | -IN2                    | Negative Input Summing Node 2.  |
| 8       | +FB2                    | Positive Output Feedback Pin 2.   |
| 9, 10   | +V <sub>S2</sub>        | Positive Supply Voltage 2.  |
| 11      | V <sub>OCM2</sub>       | Output Common-Mode Voltage 2.   |
| 12      | +OUT2                   | Positive Output 2.  |
| 13      | -OUT2                   | Negative Output 2.  |
| 14      | $\overline{\text{PD2}}$ | Power-Down Pin 2.   |
| 15, 16  | -V <sub>S2</sub>        | Negative Supply Voltage 2.  |
| 17      | V <sub>OCM1</sub>       | Output Common-Mode Voltage 1.   |
| 18      | +OUT1                   | Positive Output 1.  |
| 19      | -OUT1                   | Negative Output 1.  |
| 20      | $\overline{\text{PD1}}$ | Power-Down Pin 1.   |
| 21, 22  | -V <sub>S1</sub>        | Negative Supply Voltage 1.  |
| 23      | -FB1                    | Negative Output Feedback Pin 1.   |
| 24      | +IN1                    | Positive Input Summing Node 1.  |
| EP      |                         | Exposed Paddle. The exposed pad is not electrically connected to the device. It is typically soldered to ground or a power plane on the PCB that is thermally conductive. |



## TYPICAL PERFORMANCE CHARACTERISTICS

$T_A = 25^\circ\text{C}$ ,  $+V_S = 5\text{ V}$ ,  $-V_S = 0\text{ V}$ ,  $V_{OUT, dm} = 2\text{ V p-p}$ ,  $V_{OCM} = +V_S/2$ ,  $R_T = 61.9\ \Omega$ ,  $R_G = R_F = 200\ \Omega$ ,  $G = 1$ ,  $R_{L, dm} = 1\text{ k}\Omega$ , unless otherwise noted. Refer to Figure 49 for the test setup circuit.




Figure 7. Small Signal Frequency Response for Various Gains,  $V_{OUT, dm} = 100\text{ mV p-p}$




Figure 10. Large Signal Frequency Response for Various Gains




Figure 8. Small Signal Frequency Response for Various Supplies,  $V_{OUT, dm} = 100\text{ mV p-p}$




Figure 11. Large Signal Frequency Response for Various Supplies




Figure 9. Small Signal Frequency Response for Various Temperatures,  $V_{OUT, dm} = 100\text{ mV p-p}$




Figure 12. Large Signal Frequency Response for Various Temperatures




Figure 13. Small Signal Frequency Response for Various Loads,  $V_{OUT, dm} = 100 \text{ mV p-p}$




Figure 16. Large Signal Frequency Response for Various Loads




Figure 14. Small Signal Frequency Response for Various Gains,  $V_S = 3.3 \text{ V}$ ,  $V_{OUT, dm} = 100 \text{ mV p-p}$




Figure 17. Large Signal Frequency Response for Various Gains,  $V_S = 3.3 \text{ V}$




Figure 15. Small Signal Frequency Response for Various Gains,  $V_{OUT, dm} = 100 \text{ mV p-p}$ ,  $R_F = 348 \Omega$




Figure 18. Large Signal Frequency Response for Various Gains,  $R_F = 348 \Omega$



Figure 19. Small Signal Frequency Response for Various  $V_{OCM}$

06591-019




Figure 22. Harmonic Distortion vs. Frequency and Gain

06591-022



Figure 20. 0.1 dB Flatness Response for Various Loads

06591-020




Figure 23. Harmonic Distortion vs. Frequency and Load

06591-023



Figure 21. Harmonic Distortion vs. Frequency and Supply Voltage

06591-021




Figure 24. Harmonic Distortion vs.  $V_{OUT}$  and Supply Voltage

06591-024




Figure 25. Harmonic Distortion vs.  $V_{OCM}$  and Frequency




Figure 28. 70 MHz Intermodulation Distortion




Figure 26. Harmonic Distortion vs.  $V_{OCM}$  and Frequency,  $V_S = 3.3 V$




Figure 29. CMRR vs. Frequency




Figure 27. Harmonic Distortion vs. Frequency and  $V_{OUT}$ ,  $V_S = 3.3 V$




Figure 30. Output Balance vs. Frequency




Figure 31. PSRR vs. Frequency,  $R_L = 200\Omega$

06591-031




Figure 34. Noise Figure vs. Frequency

06591-034




Figure 32. Return Loss ( $S_{11}$ ,  $S_{22}$ ) vs. Frequency

06591-032




Figure 35. Overdrive Recovery Time (Pulse Input)

06591-035




Figure 33. Spurious-Free Dynamic Range vs. Frequency and Load

06591-033




Figure 36. Overdrive Amplitude Characteristics (Triangle Wave Input)

06591-070

# ADA4937-1/ADA4937-2




Figure 37. Supply Current vs.  $\overline{PD}$  for Various Temperatures




Figure 40. Supply Current vs.  $\overline{PD}$  for Various Temperatures,  $V_S = 3.3 V$




Figure 38. Small Signal Pulse Response




Figure 41. Large Signal Pulse Response




Figure 39. Small Signal  $V_{OCM}$  Pulse Response




Figure 42. Large Signal  $V_{OCM}$  Pulse Response




Figure 43. PD Response vs. Time




Figure 46. Closed-Loop Output Impedance




Figure 44. Crosstalk vs. Frequency for ADA4937-2




Figure 47. 0.1% Settling Time




Figure 45. Voltage Spectral Noise Density, RTI




Figure 48. Open-Loop Gain and Phase vs. Frequency

## TEST CIRCUITS




Figure 49. Equivalent Basic Test Circuit

06591-046



Figure 50. Test Circuit for Output Balance

06591-047




Figure 51. Test Circuit for Distortion Measurements

06591-048



## TERMINOLOGY




Figure 52. Circuit Definitions

### Differential Voltage

Differential voltage refers to the difference between two node voltages. For example, the output differential voltage (or equivalently, output differential-mode voltage) is defined as

$$V_{OUT, dm} = (V_{+OUT} - V_{-OUT})$$

where  $V_{+OUT}$  and  $V_{-OUT}$  refer to the voltages at the +OUT and -OUT terminals with respect to a common reference.

### Common-Mode Voltage

Common-mode voltage refers to the average of two node voltages. The output common-mode voltage is defined as

$$V_{OUT, cm} = (V_{+OUT} + V_{-OUT})/2$$

### Output Balance

Output balance is a measure of how close the differential signals are to being equal in amplitude and opposite in phase. Output balance is most easily determined by placing a well-matched resistor divider between the differential voltage nodes and comparing the magnitude of the signal at the midpoint of the divider with the magnitude of the differential signal (see Figure 50). By this definition, output balance is the magnitude of the output common-mode voltage divided by the magnitude of the output differential mode voltage.

$$\text{Output Balance Error} = \left| \frac{V_{OUT, cm}}{V_{OUT, dm}} \right|$$

## THEORY OF OPERATION

The ADA4937-x differs from conventional op amps in that it has two outputs whose voltages move in opposite directions. Like an op amp, it relies on open-loop gain and negative feedback to force these outputs to the desired voltages. The ADA4937-x behaves much like a standard voltage feedback op amp, which makes it easier to perform single-ended-to-differential conversions, common-mode level shifting, and amplifications of differential signals. Also like an op amp, the ADA4937-x has high input impedance and low output impedance.

Two feedback loops control the differential and common-mode output voltages. The differential feedback loop, set with external resistors, controls only the differential output voltage. The common-mode feedback loop controls only the common-mode output voltage. This architecture makes it easy to set the output common-mode level to any arbitrary value. It is forced, by internal common-mode feedback, to be equal to the voltage applied to the  $V_{OCM}$  input without affecting the differential output voltage.

The ADA4937-x architecture results in outputs that are highly balanced over a wide frequency range without requiring tightly matched external components. The common-mode feedback loop forces the signal component of the output common-mode voltage to zero. This results in nearly perfectly balanced differential outputs that are identical in amplitude and are exactly 180° apart in phase.

## ANALYZING AN APPLICATION CIRCUIT

The ADA4937-x uses open-loop gain and negative feedback to force its differential and common-mode output voltages in such a way as to minimize the differential and common-mode error voltages. The differential error voltage is defined as the voltage between the differential inputs labeled +IN and -IN (see Figure 52). For most purposes, this voltage can be assumed to be zero. Similarly, the difference between the actual output common-mode voltage and the voltage applied to  $V_{OCM}$  can also be assumed to be zero. Starting from these two assumptions, any application circuit can be analyzed.

## SETTING THE CLOSED-LOOP GAIN

The differential-mode gain of the circuit in Figure 52 can be determined by

$$\left| \frac{V_{OUT, dm}}{V_{IN, dm}} \right| = \frac{R_F}{R_G}$$

This assumes that the input resistors ( $R_G$ ) and feedback resistors ( $R_F$ ) on each side are equal.

## ESTIMATING THE OUTPUT NOISE VOLTAGE

The differential output noise of the ADA4937-x can be estimated using the noise model in Figure 53. The input-referred noise voltage density,  $v_{nIN}$ , is modeled as a differential input, and the noise currents,  $i_{nIN-}$  and  $i_{nIN+}$ , appear between each input and ground. The noise currents are assumed to be equal and produce a voltage across the parallel combination of the gain and feedback resistances.  $v_{n, cm}$  is the noise voltage density at the  $V_{OCM}$  pin. Each of the four resistors contributes  $(4kTR_x)^{1/2}$ .

Table 9 summarizes the input noise sources, the multiplication factors, and the output-referred noise density terms.




Figure 53. ADA4937-x Noise Model

Table 9. Output Noise Voltage Density Calculations

| Input Noise Contribution   | Input Noise Term | Input Noise Voltage Density          | Output Multiplication Factor | Output Noise Voltage Density Term                   |
|----------------------------|------------------|--------------------------------------|------------------------------|---|
| Differential Input         | $v_{nIN}$        | $v_{nIN}$                            | $G_N$                        | $v_{nO1} = G_N(v_{nIN})$                            |
| Inverting Input            | $i_{nIN-}$       | $i_{nIN-} \times (R_{G2}    R_{F2})$ | $G_N$                        | $v_{nO2} = G_N[i_{nIN-} \times (R_{G2}    R_{F2})]$ |
| Noninverting Input         | $i_{nIN+}$       | $i_{nIN+} \times (R_{G1}    R_{F1})$ | $G_N$                        | $v_{nO3} = G_N[i_{nIN+} \times (R_{G1}    R_{F1})]$ |
| $V_{OCM}$ Input            | $v_{n, cm}$      | $v_{n, cm}$                          | $G_N(\beta_1 - \beta_2)$     | $v_{nO4} = G_N(\beta_1 - \beta_2)(v_{n, cm})$       |
| Gain Resistor $R_{G1}$     | $v_{nRG1}$       | $(4kTR_{G1})^{1/2}$                  | $G_N(1 - \beta_1)$           | $v_{nO5} = G_N(1 - \beta_1)(4kTR_{G1})^{1/2}$       |
| Gain Resistor $R_{G2}$     | $v_{nRG2}$       | $(4kTR_{G2})^{1/2}$                  | $G_N(1 - \beta_2)$           | $v_{nO6} = G_N(1 - \beta_2)(4kTR_{G2})^{1/2}$       |
| Feedback Resistor $R_{F1}$ | $v_{nRF1}$       | $(4kTR_{F1})^{1/2}$                  | 1                            | $v_{nO7} = (4kTR_{F1})^{1/2}$                       |
| Feedback Resistor $R_{F2}$ | $v_{nRF2}$       | $(4kTR_{F2})^{1/2}$                  | 1                            | $v_{nO8} = (4kTR_{F2})^{1/2}$                       |

Similar to the case of a conventional op amp, the output noise voltage densities can be estimated by multiplying the input-referred terms at +IN and -IN by the appropriate output factor, where:

$$G_N = \frac{2}{(\beta_1 + \beta_2)}$$
 is the circuit noise gain.

$$\beta_1 = \frac{R_{G1}}{R_{F1} + R_{G1}} \text{ and } \beta_2 = \frac{R_{G2}}{R_{F2} + R_{G2}}$$
 are the feedback factors.

When  $R_{F1}/R_{G1} = R_{F2}/R_{G2}$ , then  $\beta_1 = \beta_2 = \beta$ , and the noise gain becomes

$$G_N = \frac{1}{\beta} = 1 + \frac{R_F}{R_G}$$

Note that the output noise from  $V_{OCM}$  goes to zero in this case. The total differential output noise density,  $v_{nOD}$ , is the root-sum-square of the individual output noise terms.

$$v_{nOD} = \sqrt{\sum_{i=1}^8 v_{nOi}^2}$$

## IMPACT OF MISMATCHES IN THE FEEDBACK NETWORKS

As previously mentioned in the Setting the Closed-Loop Gain section), even if the external feedback networks ( $R_F/R_G$ ) are mismatched, the internal common-mode feedback loop still forces the outputs to remain balanced. The amplitudes of the signals at each output remain equal and 180° out of phase. The input-to-output differential mode gain varies proportionately to the feedback mismatch, but the output balance is unaffected.

As well as causing a noise contribution from  $V_{OCM}$ , ratio matching errors in the external resistors result in a degradation of the ability of the circuit to reject input common-mode signals, much the same as for a four-resistor difference amplifier made from a conventional op amp.

In addition, if the dc levels of the input and output common-mode voltages are different, matching errors result in a small differential-mode output offset voltage. When  $G = 1$ , with a ground referenced input signal and the output common-mode level set to 2.5 V, an output offset of as much as 25 mV (1% of the difference in common-mode levels) can result if 1% tolerance resistors are used. Resistors of 1% tolerance result in a worst-case input CMRR of approximately 40 dB, a worst-case differential-mode output offset of 25 mV due to 2.5 V level shift, and no significant degradation in output balance error.

## CALCULATING THE INPUT IMPEDANCE FOR AN APPLICATION CIRCUIT

The effective input impedance of a circuit depends on whether the amplifier is being driven by a single-ended or differential signal source. For balanced differential input signals, as shown in Figure 54, the input impedance ( $R_{IN, dm}$ ) between the inputs (+D<sub>IN</sub> and -D<sub>IN</sub>) is simply  $R_{IN, dm} = 2 \times R_G$ .




Figure 54. ADA4937-x Configured for Balanced (Differential) Inputs

For an unbalanced, single-ended input signal (see Figure 55), the input impedance is

$$R_{IN, cm} = \left( \frac{R_G}{1 - \frac{R_F}{2 \times (R_G + R_F)}} \right)$$




Figure 55. ADA4937-x Configured for Unbalanced (Single-Ended) Input

The input impedance of the circuit is effectively higher than it would be for a conventional op amp connected as an inverter because a fraction of the differential output voltage appears at the inputs as a common-mode signal, partially bootstrapping the voltage across the Input Gain Resistor  $R_G$ .

## Terminating a Single-Ended Input

This section explains how to properly terminate a single-ended input to the ADA4937-x. Using a simple example with an input source of 2 V and a source resistor of 50 Ω, four simple steps must be followed.

1. The input impedance must be calculated using the formula

$$R_{IN} = \left( \frac{R_G}{1 - \frac{R_F}{2 \times (R_G + R_F)}} \right) = \left( \frac{200}{1 - \frac{200}{2 \times (200 + 200)}} \right) = 267 \Omega$$




Figure 56. Single-Ended Input Impedance  $R_{IN}$

# ADA4937-1/ADA4937-2

- For the source termination to be 50 Ω, the termination resistor ( $R_T$ ) is calculated using  $R_T || R_{IN} = 50 \Omega$ , which makes  $R_T$  equal to 61.9 Ω.




Figure 57. Adding Termination Resistor  $R_T$

- To compensate for the imbalance of the gain resistors, a correction resistor ( $R_{TS}$ ) is added in series with the inverting Input Gain Resistor  $R_G$ .  $R_{TS}$  is equal to the Thevenin equivalent of the Source Resistance  $R_S || R_T$ .



Figure 58. Calculating Thevenin Equivalent

$R_{TS} = R_{TH} = R_S || R_T = 27.4 \Omega$ . Note that  $V_{TH}$  is not equal to  $V_S/2$ , which would be the case if the termination were not affected by the amplifier circuit.




Figure 59. Balancing Gain Resistor  $R_G$

- The feedback resistor is calculated to adjust the output voltage.
  - To make the output voltage  $V_{OUT} = 1 \text{ V}$ ,  $R_F$  must be calculated using the following formula:

$$R_F = \left( \frac{V_{OUT} \times (R_G + R_{TS})}{V_{TH}} \right) = \left( \frac{1 \times (200 + 27.4)}{1.1} \right) = 207 \Omega$$

- To make  $V_O = V_S = 2 \text{ V}$  to recover the loss due to the input termination,  $R_F$  should be

$$R_F = \left( \frac{V_{OUT} \times (R_G + R_{TS})}{V_{TH}} \right) = \left( \frac{2 \times (200 + 27.4)}{1.1} \right) = 414 \Omega$$




Figure 60. Complete Single-Ended-to-Differential System

## INPUT COMMON-MODE VOLTAGE RANGE IN SINGLE-SUPPLY APPLICATIONS

The ADA4937-x is optimized for level-shifting ground-referenced input signals. As such, the center of the input common-mode range is shifted approximately 1 V down from midsupply. For 5 V single-supply operation, the input common-mode range at the summing nodes of the amplifier is 0.3 V to 3.0 V, and 0.3 V to 1.2 V with a 3.3 V supply. To avoid clipping at the outputs, the voltage swing at the +IN and -IN terminals must be confined to these ranges.

## SETTING THE OUTPUT COMMON-MODE VOLTAGE

The  $V_{OCM}$  pin of the ADA4937-x is internally biased at a voltage approximately equal to the midsupply point,  $[(+V_S) + (-V_S)]/2$ . Relying on this internal bias results in an output common-mode voltage that is within about 100 mV of the expected value.

In cases where more accurate control of the output common-mode level is required, it is recommended that an external source, or resistor divider (10 kΩ or greater resistors), be used. The output common-mode offset listed in Table 2 and Table 4 assumes that the  $V_{OCM}$  input is driven by a low impedance voltage source.

It is also possible to connect the  $V_{OCM}$  input to a common-mode level (CML) output of an ADC. However, care must be taken to ensure that the output has sufficient drive capability. The input impedance of the  $V_{OCM}$  pin is approximately 10 kΩ. If multiple ADA4937-x devices share one reference output, it is recommended that a buffer be used.

Table 10 and Table 11 list several common gain settings, associated resistor values, input impedances, and output noise density values for both balanced and unbalanced input configurations.

## POWER-DOWN OPERATION

The ADA4937-x power-down pin features an internal 25 kΩ pull-up resistor to the positive supply ( $+V_S$ ). This ensures that, with the power-down pin left unconnected (floating), the ADA4937-x turns on. Applying a voltage of  $\leq 1 \text{ V}$  turns the ADA4937-x off.

**Table 10. Differential Ground-Referenced Input, DC-Coupled, 1 kΩ Load; See Figure 54**

| Nominal Gain (dB) | R <sub>F</sub> (Ω) | R <sub>G</sub> (Ω) | R <sub>IN, dm</sub> (Ω) | Differential Output Noise Density (nV/√Hz) |
|-------------------|--------------------|--------------------|-------------------------|--|
| 0                 | 200                | 200                | 400                     | 5.8  |
| 6                 | 402                | 200                | 400                     | 9.6  |
| 10                | 402                | 127                | 254                     | 12.1                                       |
| 14                | 402                | 80.6               | 161                     | 16.2                                       |

**Table 11. Single-Ended Ground-Referenced Input, DC-Coupled, R<sub>S</sub> = 50 Ω, R<sub>L</sub> = 1 kΩ; See Figure 55**

| Nominal Gain (dB) | R <sub>F</sub> (Ω) | R <sub>G1</sub> (Ω) | R <sub>T</sub> (Ω) | R <sub>IN, cm</sub> (Ω) | R <sub>G2</sub> (Ω) <sup>1</sup> | Differential Output Noise Density (nV/√Hz) |
|-------------------|--------------------|---------------------|--------------------|-------------------------|----------------------------------|--|
| 0                 | 200                | 200                 | 61.9               | 267                     | 226                              | 5.5  |
| 6                 | 402                | 200                 | 60.4               | 301                     | 228                              | 8.6  |
| 10                | 402                | 127                 | 66.5               | 205                     | 155                              | 10.1                                       |
| 14                | 402                | 80.6                | 76.8               | 138                     | 111                              | 12.2                                       |

<sup>1</sup> R<sub>G2</sub> = R<sub>G1</sub> + (R<sub>S</sub>||R<sub>T</sub>)

## LAYOUT, GROUNDING, AND BYPASSING

As a high speed device, the ADA4937-x is sensitive to the PCB environment in which it operates. Realizing its superior performance requires attention to the details of high speed PCB design. This section shows a detailed example of how the design issues of the ADA4937-1 were addressed.

The first requirement is a solid ground plane that covers as much of the board area around the ADA4937-1 as possible. However, the area near the feedback resistors ( $R_F$ ), input gain resistors ( $R_G$ ), and the input summing nodes (Pin 2 and Pin 3) should be cleared of all ground and power planes (see Figure 61). Clearing the ground and power planes minimizes any stray capacitance at these nodes and prevents peaking of the response of the amplifier at high frequencies.

The thermal resistance,  $\theta_{JA}$ , is specified for the device, including the exposed pad, soldered to a high thermal conductivity 4-layer circuit board, as described in EIA/JESD 51-7.




Figure 61. Ground and Power Plane Voiding in Vicinity of  $R_F$  and  $R_G$

Bypass the power supply pins as close to the device as possible and directly to a nearby ground plane. Use high frequency ceramic chip capacitors (1000 pF and 0.1  $\mu$ F) be used for each supply with the 1000 pF capacitor placed closer to the device; further away, provide low frequency bypassing using 10  $\mu$ F tantalum capacitors from each supply to ground.

Signal routing should be short and direct to avoid parasitic effects. Wherever complementary signals exist, provide a symmetrical layout to maximize balanced performance. When routing differential signals over a long distance, keep PCB traces close together and twist any differential wiring to minimize loop area. Doing this reduces radiated energy and makes the circuit less susceptible to interference.




Figure 62. Recommended PCB Thermal Attach Pad Dimensions (mm)




Figure 63. Cross-Section of 4-layer PCB Showing Thermal Via Connection to Buried Ground Plane (Dimensions in mm)

## HIGH PERFORMANCE ADC DRIVING

The ADA4937-x is ideally suited for broadband IF applications. The circuit in Figure 64 shows a front-end connection for an ADA4937-1 driving an AD9445, 14-bit, 105 MSPS ADC. The AD9445 achieves its optimum performance when driven differentially. The ADA4937-x eliminates the need for a transformer to drive the ADC and performs a single-ended-to-differential conversion and buffering of the driving signal.

The ADA4937-x is configured with a single 5 V supply and unity gain for a single-ended input to differential output. The 61.9  $\Omega$  termination resistor, in parallel with the single-ended input impedance of 267  $\Omega$ , provides a 50  $\Omega$  termination for the source. The additional 26  $\Omega$  (226  $\Omega$  total) at the inverting input balances the parallel impedance of the 50  $\Omega$  source and the termination resistor driving the noninverting input.

The signal generator has a symmetric, ground-referenced bipolar output. The  $V_{OCM}$  pin of the ADA4937-x remains unconnected allowing the internal divider to set the output common-mode voltage at midsupply; one half of the common-mode voltage is fed back to the summing nodes, biasing  $-IN$  and  $+IN$  at 1.25 V. For a common-mode voltage of 2.5 V, each ADA4937-x output swings between 2.0 V and 3.0 V, providing a 2 V p-p differential output.

The output of the amplifier is ac-coupled to the ADC through a second-order, low-pass filter with a cutoff frequency of 100 MHz. This reduces the noise bandwidth of the amplifier and isolates the driver outputs from the ADC inputs.

The AD9445 is configured for a 2 V p-p full-scale input by connecting the SENSE pin to AGND, as shown in Figure 64.




Figure 64. Driving an AD9445, 14-Bit, 105 MSPS ADC

# ADA4937-1/ADA4937-2

The circuit in Figure 66 shows a simplified front-end connection for an ADA4937-1 driving an AD9246, 14-bit, 125 MSPS ADC. The AD9246 achieves its optimum performance when driven differentially. The ADA4937-x performs the single-ended-to-differential conversion, eliminating the need for a transformer to drive the ADC.

The ADA4937-x is configured with a single 5 V supply and a gain of  $\sim 2$  V/V for a single-ended input to differential output. The  $76.8\ \Omega$  termination resistor, in parallel with the single-ended input impedance of  $137\ \Omega$ , provides a  $50\ \Omega$  ac termination for the source. The additional  $30\ \Omega$  ( $120\ \Omega$  total) at the inverting input balances the parallel ac impedance of the  $50\ \Omega$  source and the termination resistor driving the noninverting input.

The signal generator has a symmetric, ground-referenced bipolar output. The  $V_{OCM}$  pin of the ADA4937-x remains unconnected; therefore, the internal pull-ups set the output common-mode voltage to midsupply. A portion of this is fed back to the summing nodes, biasing  $-IN$  and  $+IN$  at  $0.55$  V. For a common-mode voltage of  $2.5$  V, each ADA4937-x output swings between  $2.0$  V and  $3.0$  V, providing a  $2$  V p-p differential output.

The output is ac-coupled to a single-pole, low-pass filter. This reduces the noise bandwidth of the amplifier and provides some level of isolation from the switched capacitor inputs of the ADC.

The AD9246 is set for a  $2$  V p-p full-scale input by connecting the SENSE pin to AGND. The inputs of the AD9246 are biased at  $1$  V by connecting the CML output, as shown in Figure 66.

The circuit was tested with a  $-1$  dBFS signal at various frequencies. Figure 65 shows a plot of the second- and third-order harmonic distortion (HD2/HD3) vs. frequency.




Figure 65. HD2/HD3 for Combination of ADA4937-x and AD9246 ADC




Figure 66. Driving an AD9246, 14-Bit, 125 MSPS ADC



### 3.3 V OPERATION

The ADA4937-x provides excellent performance in 3.3 V single-supply applications. Significant power savings can be realized when the ADA4937-x is used in combination with a low voltage ADC.

The circuit in Figure 67 is an example of the ADA4937-1 driving an AD9230, 12-bit, 250 MSPS ADC that is specified to operate with a single 1.8 V supply. The performance of the ADC is optimized when it is driven differentially, making the best use of the signal swing available within the 1.8 V supply. The ADA4937-x performs the single-ended-to-differential conversion, common-mode level-shifting, and buffering of the driving signal.

The ADA4937-x is configured with a single 3.3 V supply and a gain of 2 V/V for a single-ended input to differential output. The

59 Ω termination resistor, in parallel with the single-ended input impedance of 306 Ω, provides a 50 Ω termination for the source. The additional 26 Ω (226 Ω total) at the inverting input balances the parallel impedance of the 50 Ω source and the termination resistor that drives the noninverting input. The signal generator has a symmetric, ground-referenced bipolar output. The V<sub>OCM</sub> pin is connected to the CML output of the AD9230, and sets the output common mode of the ADA4937-x at 1.4 V. One third of the output common-mode voltage of the amplifier is fed back to the summing nodes, biasing -IN and +IN at ~0.5 V. For a common-mode voltage of 1.4 V, each ADA4937-x output swings between 1.09 V and 1.71 V, providing a 1.25 V p-p differential output.

A third-order, 125 MHz, low-pass filter between the ADA4937-x and the AD9230 reduces the noise bandwidth of the amplifier and isolates the driver outputs from the ADC inputs.




Figure 67. Driving an AD9230, 12-Bit, 250 MSPS ADC

08591-057

# ADA4937-1/ADA4937-2


## OUTLINE DIMENSIONS



\*COMPLIANT TO JEDEC STANDARDS MO-220-VEED-2 EXCEPT FOR EXPOSED PAD DIMENSION.

Figure 68. 16-Lead Lead Frame Chip Scale Package [LFCSP\_VQ]  
3 mm × 3 mm Body, Very Thin Quad  
(CP-16-2)  
Dimensions shown in millimeters

072208-A



COMPLIANT TO JEDEC STANDARDS MO-220-VGGD-2

Figure 69. 24-Lead Lead Frame Chip Scale Package [LFCSP\_VQ]  
4 mm × 4 mm Body, Very Thin Quad  
(CP-24-1)  
Dimensions shown in millimeters

072208-A

## ORDERING GUIDE

| Model <sup>1</sup> | Temperature Range | Package Description | Package Option | Ordering Quantity | Branding |
|--------------------|-------------------|---------------------|----------------|-------------------|----------|
| ADA4937-1YCPZ-R2   | -40°C to +105°C   | 16-Lead LFCSP_VQ    | CP-16-2        | 250               | H1S      |
| ADA4937-1YCPZ-RL   | -40°C to +105°C   | 16-Lead LFCSP_VQ    | CP-16-2        | 5,000             | H1S      |
| ADA4937-1YCPZ-R7   | -40°C to +105°C   | 16-Lead LFCSP_VQ    | CP-16-2        | 1,500             | H1S      |
| ADA4937-2YCPZ-R2   | -40°C to +105°C   | 24-Lead LFCSP_VQ    | CP-24-1        | 250               |          |
| ADA4937-2YCPZ-RL   | -40°C to +105°C   | 24-Lead LFCSP_VQ    | CP-24-1        | 5,000             |          |
| ADA4937-2YCPZ-R7   | -40°C to +105°C   | 24-Lead LFCSP_VQ    | CP-24-1        | 1,500             |          |

<sup>1</sup> Z = RoHS Compliant Part.

**NOTES**

**NOTES**



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.