RoHS

COMPLIANT


HALOGEN FREE

GREEN



Vishay Semiconductors

Fully Integrated Proximity Sensor With Infrared Emitter, I²C Interface, and Interrupt Function



DESCRIPTION

The VCNL3020 is a fully integrated proximity sensor. Fully integrated means that the infrared emitter is included in the package. It has 16 bit resolution. It includes a signal processing IC and features standard I²C communication interface. It features an interrupt function.

APPLICATIONS

- Proximity sensor for mobile devices (e.g. smart phones, touch phones, PDA, GPS) for touch screen locking, power saving, etc.
- Proximity / optical switch for consumer, computing and industrial devices and displays

FEATURES

- Package type: surface-mount
- Dimensions (L x W x H in mm): 4.90 x 2.40 x 0.83
- Integrated modules: infrared emitter (IRED), proximity sensor (PD), and signal conditioning IC
- Interrupt function
- Supply voltage range V_{DD}: 2.5 V to 3.6 V
- Supply voltage range IR anode: 2.5 V to 5 V
- Communication via I2C interface
- I²C bus H-level range: 1.7 V to 5 V
- Floor life: 72 h, MSL 4, according to J-STD-020
- Low stand by current consumption: 1.5 μA
- Material categorization: for definitions of compliance please see <u>www.vishay.com/doc?99912</u>

PROXIMITY FUNCTION

- Built-in infrared emitter and photo-pin-diode for proximity function
- 16 bit effective resolution for proximity detection range ensures excellent cross talk immunity
- Programmable LED drive current from 10 mA to 200 mA in 10 mA steps
- Excellent ambient light suppression by signal modulation
- Proximity distance up to 200 mm

PRODUCT SUMMARY										
PART NUMBER	OPERATING RANGE (mm)	OPERATING VOLTAGE RANGE (V)	I ² C BUS VOLTAGE RANGE (V)	LED PULSE CURRENT (1) (mA)	OUTPUT CODE	ADC RESOLUTION PROXIMITY / AMBIENT LIGHT				
VCNL3020	1 to 200	2.5 to 3.6	1.7 to 5	10 to 200	16 bit, I ² C	16 bit / -				

Note

(1) Adjustable through I²C interface

ORDERING INFORMATION				
ORDERING CODE	PACKAGING	VOLUME (1)	REMARKS	
VCNL3020-GS08	Tana and rool	MOQ: 3300 pcs	4.90 mm x 2.40 mm x 0.83 mm	
VCNL3020-GS18	Tape and reel	MOQ: 13 300 pcs	4.90 mm x 2.40 mm x 0.83 mm	

Note


(1) MOQ: minimum order quantity



ABSOLUTE MAXIMUM RATINGS (T _{amb} = 25 °C, unless otherwise specified)										
PARAMETER	TEST CONDITION	SYMBOL	MIN.	MAX.	UNIT					
Supply voltage		V_{DD}	-0.3	5.5	V					
Operation temperature range		T _{amb}	-25	+85	°C					
Storage temperature range		T _{stg}	-25	+85	°C					
Total power dissipation	T _{amb} ≤ 25 °C	P _{tot}		50	mW					
Junction temperature		Tj		100	°C					

BASIC CHARACTERIS	STICS (T _{amb} = 25 °C, unless o	therwise spe	ecified)			
PARAMETER	TEST CONDITION	SYMBOL	MIN.	TYP.	MAX.	UNIT
Supply voltage V _{DD}			2.5		3.6	V
Supply voltage IR anode			2.5		5	V
I ² C Bus H-level range			1.7		5	V
INT H-level range			1.7		5	V
INT low voltage	3 mA sink current				0.4	V
Current consumption	Standby current, no IRED-operation			1.5	2	μΑ
	2 measurements per second, IRED current 20 mA			5		μΑ
Current consumption	250 measurements per second, IRED current 20 mA			520		μΑ
proximity mode incl. IRED (averaged)	2 measurements per second, IRED current 200 mA			35		μΑ
	250 measurements per second, IRED current 200 mA			4		mA
I ² C clock rate range		f _{SCL}			3400	kHz


CIRCUIT BLOCK DIAGRAM



Note

nc must not be electrically connected
 Pads 6 and 7 are only considered as solder pads

TEST CIRCUIT



BASIC CHARACTERISTICS (T_{amb} = 25 °C, unless otherwise specified)




Fig. 1 - Idle Current vs. Ambient Temperature




Fig. 2 - Idle Current vs. V_{DD}




Fig. 3 - Proximity Value vs. Distance




Fig. 4 - Forward Current vs. Temperature




Fig. 5 - Relative Radiant Intensity vs. Wavelength






Fig. 6 - Relative Radiant Intensity vs. Angular Displacement








Fig. 8 - Relative Radiant Sensitivity vs. Angular Displacement (Proximity Sensor)

APPLICATION INFORMATION

VCNL3020 is a cost effective solution of proximity sensor with I²C bus interface. The standard serial digital interface is easy to access "Proximity Signal" without complex calculation and programming by external controller. Beside the digital output also a flexible programmable interrupt pin is available.

1. Application Circuit




Fig. 9 - Application Circuit (x) = Pin Number

Notes

- The interrupt pin is an open drain output. The needed pull-up resistor may be connected to the same supply voltage as the application controller and the pull-up resistors at SDA/SCL. Proposed value R2 should be >1 kΩ, e.g. 10 kΩ to 100 kΩ. Proposed value for R3 and R4, e.g. 2.2 kΩ to 4.7 kΩ, depend also on the I²C bus speed.
 For detailed description about set-up and use of the interrupt as well as more application related information see AN: "Designing VCNL3020 into an Application".
- IR_Cathode needs no external connection. The needed connection to the driver is done internally.




2. I²C Interface

The VCNL3020 contains seventeen 8 bit registers for operation control, parameter setup and result buffering. All registers are accessible via I²C communication. Figure 13 shows the basic I²C communication with VCNL3020.

The built in I²C interface is compatible with all I²C modes (standard, fast, and high speed).

 I^2C H-level range = 1.7 V to 5 V.

Please refer to the I²C specification from NXP for details.



Device Address

The VCNL3020 has a fix slave address for the host programming and accessing selection. The predefined 7 bit I^2C bus address is set to 0010 011 = 13h. The least significant bit (LSB) defines read or write mode. Accordingly the bus address is set to 0010 011x = 26h for write, 27h for read.

Register Addresses

VCNL3020 has seventeen user accessible 8 bit registers. The register addresses are 80h (register #0) to 90h (register #16).

REGISTER FUNCTIONS

Register #0 Command Register

Register address = 80h

The register #0 is for starting proximity measurements. This register contains a flag bit for data ready indication.

TABLE 1 -	TABLE 1 - COMMAND REGISTER #0									
Bit 7	Bit 6	Bit 5	Bit 5 Bit 4 Bit 3 Bit 2 Bit 1 Bit 0							
config_lock	n/a	prox_data_rdy	n/a	prox_od	n/a	prox_en	selftimed_en			
	Description									
config	g_lock	Read only bit. Value = 1								
prox_d	ata_rdy	Read only bit. Value = 1 when proximity measurement data is available in the result registers. This bit will be reset when one of the corresponding result registers (reg #7, reg #8) is read.								
prox	x_od			nd measurement fonversion for read		s #7(HB) and #8(L	.B).			
prox	x_en	R/W bit. Enables periodic proximity measurement								
selftim	ned_en		R/W bit. Enables state machine and LP oscillator for self timed measurements; no measurement is performed until the corresponding bit is set							

Note

• Beside prox_en first selftimed_en needs to be set. On-demand measurement mode is disabled if selftimed_en bit is set. For the selftimed_en mode changes in reading rates (reg #2) can be made only when b0 (selftimed_en bit) = 0.



Register #1 Product ID Revision Register

Register address = 81h. This register contains information about product ID and product revision.

Register data value of current revision = 21h.

TABLE 2 - PRODUCT ID REVISION REGISTER #1										
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0			
	Produ	uct ID		Revision ID						
			Descr	ription						
Prod	Product ID Read only bits. Value = 2									
Revis	sion ID	Read only bits. Value = 1								

Register #2 Rate of Proximity Measurement

Register address = 82h.

ABLE 3 -	PROXIMITY	RATE REGIS	STER #2				
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
	•	n/a		Rate of Proximity Measurement (no. of measurements per second)			
			Desc	ription			
Proxii	mity rate	001 - 3.90625 010 - 7.8125 m	surements/s	AULT)			

Note

Register #3 LED Current Setting for Proximity Mode

Register address = 83h. This register is to set the LED current value for proximity measurement.

The value is adjustable in steps of 10 mA from 0 mA to 200 mA.

This register also contains information about the used device fuse program ID.

TABLE 4 -	TABLE 4 - IR LED CURRENT REGISTER #3									
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0			
Fuse p	Fuse prog ID IR LED current value									
Description										
Fuse p	Fuse prog ID Read only bits. Information about fuse program revision used for initial setup/calibration of the device.									
IR LED cu	R/W bits. IR LED current = Value (dec.) x 10 mA. Valid Range = 0 to 20d. e.g. 0 = 0 mA , 1 = 10 mA,, 20 = 200 mA (2 = 20 mA = DEFAULT) LED Current is limited to 200 mA for values higher as 20d.						AULT)			

[•] If self_timed measurement is running, any new value written in this register will not be taken over until the mode is actualy cycled.



Register #7 and #8 Proximity Measurement Result Register

Register address = 87h and 88h. These registers are the result registers for proximity measurement readings.

The result is a 16 bit value. The high byte is stored in register #7 and the low byte in register #8.

TABLE 5 - PROXIMITY RESULT REGISTER #7									
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0		
	Description								
		Read only bits	. High byte (15:8)	of proximity meas	urement result				

TABLE 6 - PROXIMITY RESULT REGISTER #8									
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0		
	Description								
		Read only bit	s. Low byte (7:0) o	of proximity measu	rement result				

Register #9 Interrupt Control Register

Register address = 89h.

TABLE 7 -	INTERRUPT	CONTROL R	EGISTER #9						
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0		
	Int count exceed			INT_PROX_ ready_EN	n/a	INT_THRES_EN	INT_THRES_ SEL		
	Description								
Int coun	R/W bits. These bits contain the number of consecutive measurements needed above/below the threshold 000 - 1 count = DEFAULT 001 - 2 count 010 - 4 count 011 - 8 count 100 -16 count 101 - 32 count 110 - 64 count 111 - 128 count						below the		
INT_PROX	_ready_EN	R/W bit. Enable	R/W bit. Enables interrupt generation at proximity data ready						
INT_THI	RES_EN	R/W bit. Enables interrupt generation when high or low threshold is exceeded							
INT_THE	RES_SEL	R/W bit. 0: thres	sholds are applied	I to proximity mea	surements				



Register #10 and #11 Low Threshold

Register address = 8Ah and 8Bh. These registers contain the low threshold value. The value is a 16 bit word. The high byte is stored in register #10 and the low byte in register #11.

TABLE 8 - LOW THRESHOLD REGISTER #10									
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0		
	Description								
		R/W b	its. High byte (15:	8) of low threshold	d value				

TABLE 9 - LOW THRESHOLD REGISTER #11									
Bit 7 Bit 6 Bit 5 Bit 4 Bit 3 Bit 2 Bit 1 Bit 0									
Description									
R/W bits. Low byte (7:0) of low threshold value									

Register #12 and #13 High Threshold

Register address = 8Ch and 8Dh. These registers contain the high threshold value. The value is a 16 bit word. The high byte is stored in register #12 and the low byte in register #13.

TABLE 10 - HIGH THRESHOLD REGISTER #12										
Bit 7	Bit 7 Bit 6 Bit 5 Bit 4 Bit 3 Bit 2 Bit 1 Bit 0									
Description										
R/W bits. High byte (15:8) of high threshold value										

TABLE 11 - HIGH THRESHOLD REGISTER #13										
Bit 7	Bit 7 Bit 6 Bit 5 Bit 4 Bit 3 Bit 2 Bit 1 Bit 0									
Description										
R/W bits. Low byte (7:0) of high threshold value										

Register #14 Interrupt Status Register

Register address = 8Eh. This register contains information about the interrupt status indicates if high or low going threshold exceeded.

TABLE 12 - INTERRUPT STATUS REGISTER #14									
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0		
	n/a int_prox_ready n/a int_th_low int_th_hi								
	Description								
int_pro	int_prox_ready R/W bit. Indicates a generated interrupt for proximity								
int_th	int_th_low R/W bit. Indicates a low threshold exceed								
int_t	int_th_hi R/W bit. Indicates a high threshold exceed								

Note

 Once an interrupt is generated the corresponding status bit goes to 1 and stays there unless it is cleared by writing a 1 in the corresponding bit. The int pad will be pulled down while at least one of the status bit is 1.



Register #15 Proximity Modulator Timing Adjustment

Register address = 8Fh.

ABLE 13	3 - PROXIMIT	Y MODULATO	OR TIMING A	DJUSTMENT	#15			
Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0	
Modulation delay time			Proximity frequency		Modulation dead time			
			Desc	ription				
Modulation	on delay time	This function is	ng a delay time between IR LED signal and IR input signal evaluation. for compensation of delays from IR LED and IR photo diode. Also in respect to the etting different proximity signal frequency. Correct adjustment is optimizing measurement in interpret in interpret in its example.					
R/W bits. Settir			dz `					
Modulation	on dead time	This function is	for reducing of po	evaluation of IR signs ossible disturbance evel and should be	e effects.	of the IR signal. (DEFAULT = 1)	

Note

 The settings for best performance will be provided by Vishay. With first samples this is evaluated to: delay time = 0; dead time = 1 and proximity frequency = 0. With that register#15 should be programmed with 1 (= default value).

Register #16 Ambient IR Light Level Register

Register address = 90h.

This register is not intended to be used by customer.

3. IMPORTANT APPLICATION HINTS AND EXAMPLES

3.1 Receiver standby mode

In standby mode the receiver has the lowest current consumption of about 1.5 μ A. In this mode only the I²C interface is active. This is always valid, when there are no proximity measurement demands executed. Also the current sink for the IR-LED is inactive, so there is no need for changing register #3 (IR LED current).

3.2 Data Read

In order to get a certain register value, the register has to be addressed without data like shown in the following scheme. After this register addressing, the data from the addressed register is written after a subsequent read command.




Fig. 11 - Send Byte/Receive Byte Protocol

The stop condition between these write and read sequences is not mandatory. It works also with a repeated start condition.

Note

For reading out 2 (or more) subsequent registers like the result registers, it is not necessary to address each of the registers separately. After
one read command the internal register counter is increased automatically and any subsequent read command is accessing the next
register.




Example: read register "Proximity Result Register" #7 and #8:

Addressing:command: 26h, 87h (VCNL3020_I²C_Bus_Write_Adr., Proximity Result Register #7 [87])


Read register #7: command: 27h, data (VCNL3020_I2C_Bus_Read_Adr., {High Byte Data of Proximity Result register #7 [87])}

Read register #8: command: 27h, data (VCNL3020_12C_Bus_Read_Adr., {Low Byte Data of Proximity Result register #8 [88])}

PACKAGE DIMENSIONS in millimeters



TAPE AND REEL DIMENSIONS in millimeters



Drawing-No.: 9.700-5387.01-4

Issue: prel; 22.11.11



SOLDER PROFILE




Fig. 12 - Lead (Pb)-free Reflow Solder Profile According to J-STD-020

DRYPACK

Devices are packed in moisture barrier bags (MBB) to prevent the products from moisture absorption during transportation and storage. Each bag contains a desiccant.

FLOOR LIFE

Floor life (time between soldering and removing from MBB) must not exceed the time indicated on MBB label:

Floor life: 72 h

Conditions: T_{amb} < 30 °C, RH < 60 %

Moisture sensitivity level 4, according to J-STD-020.

DRYING

In case of moisture absorption devices should be baked before soldering. Conditions see J-STD-020 or label. Devices taped on reel dry using recommended conditions 192 h at 40 $^{\circ}$ C (+ 5 $^{\circ}$ C), RH < 5 $^{\circ}$ M.



Legal Disclaimer Notice

Vishay

Disclaimer

ALL PRODUCT, PRODUCT SPECIFICATIONS AND DATA ARE SUBJECT TO CHANGE WITHOUT NOTICE TO IMPROVE RELIABILITY, FUNCTION OR DESIGN OR OTHERWISE.

Vishay Intertechnology, Inc., its affiliates, agents, and employees, and all persons acting on its or their behalf (collectively, "Vishay"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.

Vishay makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product. To the maximum extent permitted by applicable law, Vishay disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability.

Statements regarding the suitability of products for certain types of applications are based on Vishay's knowledge of typical requirements that are often placed on Vishay products in generic applications. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary over time. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts. Product specifications do not expand or otherwise modify Vishay's terms and conditions of purchase, including but not limited to the warranty expressed therein.

Except as expressly indicated in writing, Vishay products are not designed for use in medical, life-saving, or life-sustaining applications or for any other application in which the failure of the Vishay product could result in personal injury or death. Customers using or selling Vishay products not expressly indicated for use in such applications do so at their own risk. Please contact authorized Vishay personnel to obtain written terms and conditions regarding products designed for such applications.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Vishay. Product names and markings noted herein may be trademarks of their respective owners.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов:
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001:
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: <u>org@eplast1.ru</u>

Адрес: 198099, г. Санкт-Петербург, ул. Калинина,

дом 2, корпус 4, литера А.