

## DESCRIPTION

Demonstration circuit 1294A shows adjustable linear regulators in parallel using LT3080. Architected as a precision current source and voltage follower, it allows this new regulator to be used in many applications requiring high current, adjustability to zero output, and no heat sink. Also the device brings out the collector of the pass transistor to allow low dropout operation when used with multiple supplies.

A key feature of the LT3080 is the capability to supply a wide output voltage range. By using a reference current through a single resistor, the output voltage can be programmed to any level between zero and 36V. The DC1294A has a reduced input voltage 25V due to input capacitor voltage rating, and is capable of delivering up to 4.4A output current by paralleling 4 LT3080s with only 20mΩ PCB ballast resistors. The DC1294A can be used as a high current linear regulator, post regulator for switching supply, vari-

able voltage supply or low output voltage power supply.

Internal protection circuitry includes current limiting and thermal limiting.

LT3080 regulator is offered in 8-lead MSOP (with an Exposed Pad for better thermal characteristics), a 3mm × 3mm DFN, 5-lead TO-220 and a simple-to-use 3-lead SOT-223 version.

The LT3080 datasheet gives a complete description of the part, operation and application information. The datasheet should be read in conjunction with this quick start guide for working on or modifying the demo circuit 1294A.

**Design files for this circuit board are available. Call the LTC factory.**

 , LTC and LT are registered trademarks of Linear Technology Corporation.

**Table 1. Performance Summary (  $T_A = 25^\circ\text{C}$  )**

PARAMETER	CONDITION	VALUE
Minimum Vin Voltage	Vout=3.3V	3.8V
Maximum Vin Voltage		25V
Minimum Vcontrol Voltage	Vout=3.3V	4.9V
Maximum Vcontrol Voltage		25V
Output Voltage		3.3V ±3%
Minimum Output Current		4mA
Maximum Output Current	Vin-Vout<2.5V	4.4A

## QUICK START PROCEDURE

The DC1294A is easy to set up to evaluate the performance of the LT3080. Refer to Figure 1. for proper measurement equipment setup and following the procedures below:

1. Apply 3.8V across  $V_{in}$  (to Gnd), and 4.9V across  $V_{control}$ . Draw 4.4A of load current. The measured  $V_{out}$  should be  $3.3V \pm 3\%$  (3.2V to 3.4V).

2. Vary  $V_{in}$  from 3.8V to 25V,  $V_{control}$  from 4.9V to 25V and the load current from 4mA to 4.4A.  $V_{out}$  should measure  $3.3V \pm 3\%$  (3.2V to 3.4V).

**Note: Make sure the power dissipation is limited below the thermal limit.**




Figure 1. Proper Measurement Equipment Setup




Figure 2. Measuring Input or Output Ripple

### INPUT VOLTAGE RANGE

The guaranteed  $V_{in}$  dropout voltage is 0.5V at 4.4A, the guaranteed  $V_{control}$  dropout voltage is 1.6V at 4.4A. The maximum  $V_{in}$  and maximum  $V_{control}$  is

reduced to 25V due to the input capacitor voltage rating.

### DUAL SUPPLY OR SINGLE SUPPLY

Use two separate supplies for  $V_{in}$  and  $V_{control}$ , a low dropout voltage can be achieved on the  $V_{in}$  pin and the power dissipation is minimized. Alternatively, Tying the  $V_{control}$  to  $V_{in}$  through a zero ohm jump resistor R1

on board, a single supply is sufficient to drive the demo circuit 1294A. **AVOID USING A LONG WIRE TO TIE VCONTROL AND VIN.**


### OUTPUT CURRENT

The output current will decrease at high input-to-output differential. The actual current output is further

limited by the thermal shutdown function, which is related to the board thermal dissipation.

### THERMAL IMAGE

An example thermal image shows the temperature distribution on board. The test is done in still air at room temperature with average 1.7W power dissipation in each LT3080.



### **BYPASS CAPACITOR**

Since the SET pin is a high impedance node, unwanted signals may couple into the SET pin and cause erratic behavior. This will be most noticeable when operating with minimum output capacitors at full load current. The easiest way to remedy this is to bypass the SET

pin with a small amount of capacitance from SET to ground, 10pF to 20pF is sufficient. A 0.01uF bypass capacitor is used on the demo board to provide a low-noise output. Please refer to datasheet for details.


### **PARALLEL OPERATION**

A small ballast resistor is required for parallel operation, such as 20mΩ. A short PCB trace can easily serve that purpose. Refer to the datasheet for trace length calculation. **THE BOTTOM PAD OF IC IS THE OUTPUT.** The bottom pad can be tied to the output pin

respectively, however, each bottom pad should isolated from the others, thus force the output current go through the ballast resistors.

# QUICK START GUIDE FOR DEMONSTRATION CIRCUIT 1294A

## ADJUSTABLE LDO LINEAR REGULATORS IN PARALLEL



<b>CUSTOMER NOTICE</b>		CONTRACT NO.	APPROVALS	DATE	TITLE	
LINEAR TECHNOLOGY HAS MADE A BEST EFFORT TO DESIGN A CIRCUIT THAT MEETS CUSTOMER-SUPPLIED SPECIFICATIONS; HOWEVER, IT REMAINS THE CUSTOMER'S RESPONSIBILITY TO VERIFY PROPER AND RELIABLE OPERATION IN THE ACTUAL APPLICATION. COMPONENT SUBSTITUTION AND PRINTED CIRCUIT BOARD LAYOUT MAY SIGNIFICANTLY AFFECT CIRCUIT PERFORMANCE OR RELIABILITY. CONTACT LINEAR TECHNOLOGY APPLICATIONS ENGINEERING FOR ASSISTANCE. THIS CIRCUIT IS PROPRIETARY TO LINEAR TECHNOLOGY AND SUPPLIED FOR USE WITH LINEAR TECHNOLOGY PARTS.		DRAWN	HELEN	6/18/07	DESIGNER	
		CHECKED			DESIGNER	
		ENGINEER	Tiger Zhou	6/18/07		
		DESIGNER				
		SCALE:	FILENAME:	SHEET 1	OF 1	

**LINEAR TECHNOLOGY**  
 6801 McCarty Blvd  
 Milpitas, CA 95035  
 Phone: (408)432-1000  
 Fax: (408)432-0077

**LT3080EDD, Adjustable LDO Linear Regulators in Parallel**  
 DC1294A

REV A

REV A



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.