2048 (H) x 2048 (V) Interline CCD Image Sensor

Description

The KAI–04070 Image Sensor is a 4-megapixel CCD in a 4/3 inch optical format. Based on the TRUESENSE 7.4 micron Interline Transfer CCD Platform, the sensor provides very high smear rejection and up to 82 dB linear dynamic range through the use of a unique dual-gain amplifier. A flexible readout architecture enables use of 1, 2, or 4 outputs for full resolution readout up to 28 frames per second, while a vertical overflow drain structure suppresses image blooming and enables electronic shuttering for precise exposure control.

Parameter	Typical Value
Architecture	Interline CCD, Progressive Scan
Total Number of Pixels	2128 (H) × 2112 (V)
Number of Effective Pixels	2080 (H) × 2080 (V)
Number of Active Pixels	2048 (H) × 2048 (V)
Pixel Size	7.4 μm (H) × 7.4 μm (V)
Active Image Size	15.2 mm (H) \times 15.2 mm (V), 21.4 mm (Diagonal), 4/3" Optical Format
Aspect Ratio	1:1
Number of Outputs	1, 2, or 4
Charge Capacity	44,000 electrons
Output Sensitivity	8.7 μV/e ⁻ (Low), 33 μV/e ⁻ (High)
Quantum Efficiency Pan (–ABA, –PBA, –QBA) R, G, B (–CBA) R, G, B (–FBA)	52% 38%, 42%, 43% 37%, 42%, 41%
Read Noise (f = 40 MHz)	12 e [−] rms
Dark Current Photodiode VCCD	3 e⁻/s 145 e⁻/s
Dark Current Doubling Temp. Photodiode VCCD	7°C 9°C
Dynamic Range High Gain Amp (40 MHz) Dual Amp, 2×2 Bin (40 MHz)	70 dB 82 dB
Charge Transfer Efficiency	0.999999
Blooming Suppression	> 1000 X
Smear	–115 dB
Image Lag	< 10 electrons
Maximum Pixel Clock Speed	40 MHz
Maximum Frame Rate Quad Output Dual Output Single Output	28 fps 14 fps 8 fps
Package	68 Pin PGA
Cover Glass	AR Coated, 2 Sides

ON

ON Semiconductor®

www.onsemi.com



Figure 1. KAI–04070 Interline CCD Image Sensor

Features

- Superior Smear Rejection
- Up to 82 dB Linear Dynamic Range
- Bayer Color Pattern, TRUESENSE Sparse Color Filter Pattern, and Monochrome Configurations
- Progressive Scan & Flexible Readout Architecture
- High Frame Rate
- High Sensitivity Low Noise Architecture
- Package Pin Reserved for Device Identification

Application

- Industrial Imaging and Inspection
- Traffic
- Surveillance

ORDERING INFORMATION

See detailed ordering and shipping information on page 2 of this data sheet.

devices.

Interline Transfer CCD image sensors, allowing a single

camera design to be leveraged in support of multiple

The sensor is available with the TRUESENSE Sparse Color Filter Pattern, a technology which provides a 2x improvement in light sensitivity compared to a standard color Bayer part.

The sensor shares common pin-out and electrical configurations with a full family of Truesense Imaging

ORDERING INFORMATION

Table 2. ORDERING INFORMATION – KAI–04070 IMAGE SENSOR

Part Number	Description	Marking Code	
KAI-04070-ABA-JD-BA	Monochrome, Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Standard Grade		
KAI-04070-ABA-JD-AE	Monochrome, Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Engineering Grade	KAI-04070-ABA	
KAI-04070-ABA-JR-BA	Monochrome, Telecentric Microlens, PGA Package, Taped Clear Cover Glass with AR Coating (Both Sides), Standard Grade	Serial Number	
KAI-04070-ABA-JR-AE	Monochrome, Telecentric Microlens, PGA Package, Taped Clear Cover Glass with AR Coating (Both Sides), Engineering Grade		
11KAI-04070-FBA-JD-BA	Gen2 Color (Bayer RGB), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Standard Grade	KAI-04070-FBA	
11KAI-04070-FBA-JD-AE	Gen2 Color (Bayer RGB), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Engineering Grade	Serial Number	
11KAI-04070-QBA-JD-BA	Gen2 Color (TRUESENSE Sparse CFA), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Standard Grade	KAI-04070-QBA	
11KAI-04070-QBA-JD-AE	Gen2 Color (TRUESENSE Sparse CFA), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Engineering Grade	Serial Number	
11KAI-04070-CBA-JD-BA*	Gen1 Color (Bayer RGB), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Standard Grade	KAI-04070-CBA	
11KAI-04070-CBA-JD-AE*	Gen1 Color (Bayer RGB), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Engineering Grade	Serial Number	
11KAI-04070-PBA-JD-BA*	Gen1 Color (TRUESENSE Sparse CFA), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Standard Grade	KAI-04070-PBA	
11KAI-04070-PBA-JD-AE*	Gen1 Color (TRUESENSE Sparse CFA), Telecentric Microlens, PGA Package, Sealed Clear Cover Glass with AR Coating (Both Sides), Engineering Grade	Serial Number	

*Note recommended for new designs.

Table 3. ORDERING INFORMATION – EVALUATION SUPPORT

Part Number	Description
G2-FPGA-BD-14-40-A-GEVK	FPGA Board for IT–CCD Evaluation Hardware
KAI-68PIN-HEAD-BD-A-GEVB	68 Pin Imager Board for IT-CCD Evaluation Hardware
LENS-MOUNT-KIT-A-GEVK	Lens Mount Kit for IT–CCD Evaluation Hardware
KAI-68PIN-N-PROBE-CARD-A-GEVB	68 Pin Probe Card (Narrow Socket)
KAI-68PIN-W-PROBE-CARD-A-GEVB	68 Pin Probe Card (Wide Socket)

See the ON Semiconductor *Device Nomenclature* document (TND310/D) for a full description of the naming convention used for image sensors. For reference documentation, including information on evaluation kits, please visit our web site at www.onsemi.com.

DEVICE DESCRIPTION

Architecture



Figure 2. Block Diagram

Dark Reference Pixels

There are 16 dark reference rows at the top and 16 dark rows at the bottom of the image sensor. The 24 dark columns on the left or right side of the image sensor should be used as a dark reference.

Under normal circumstances use only the center 22 columns of the 24 column dark reference due to potential light leakage.

Dummy Pixels

Within each horizontal shift register there are 12 leading additional shift phases. These pixels are designated as dummy pixels and should not be used to determine a dark reference level.

In addition, there is one dummy row of pixels at the top and bottom of the image.

Active Buffer Pixels

16 unshielded pixels adjacent to any leading or trailing dark reference regions are classified as active buffer pixels. These pixels are light sensitive but are not tested for defects and non-uniformities.

Image Acquisition

An electronic representation of an image is formed when incident photons falling on the sensor plane create electron-hole pairs within the individual silicon photodiodes. These photoelectrons are collected locally by the formation of potential wells at each photosite. Below photodiode saturation, the number of photoelectrons collected at each pixel is linearly dependent upon light level and exposure time and non-linearly dependent on wavelength. When the photodiodes charge capacity is reached, excess electrons are discharged into the substrate to prevent blooming.

ESD Protection

Adherence to the power-up and power-down sequence is critical. Failure to follow the proper power-up and power-down sequences may cause damage to the sensor. See Power-Up and Power-Down Sequence section.

Bayer Color Filter Pattern



Figure 3. Bayer Color Filter Pattern

TRUESENSE Sparse Color Filter Pattern



Figure 4. TRUESENSE Sparse Color Filter Pattern

Physical Description

Pin Description and Device Orientation



Figure 5. Package Pin Designations – Top View

Pin	Name	Description
1	V3B	Vertical CCD Clock, Phase 3, Bottom
3	V1B	Vertical CCD Clock, Phase 1, Bottom
4	V4B	Vertical CCD Clock, Phase 4, Bottom
5	VDDa	Output Amplifier Supply, Quadrant a
6	V2B	Vertical CCD Clock, Phase 2, Bottom
7	GND	Ground
8	VOUTa	Video Output, Quadrant a
9	Ra	Reset Gate, Standard (High) Gain, Quadrant a
10	RDab	Reset Drain, Quadrants a & b
11	H2SLa	Horizontal CCD Clock, Phase 2, Storage, Last Phase, Quadrant a
12	OGa	Output Gate, Quadrant a
13	H1Ba	Horizontal CCD Clock, Phase 1, Barrier, Quadrant a
14	H2Ba	Horizontal CCD Clock, Phase 2, Barrier, Quadrant a
15	H2Sa	Horizontal CCD Clock, Phase 2, Storage, Quadrant a
16	H1Sa	Horizontal CCD Clock, Phase 1, Storage, Quadrant a
17	R2ab	Reset Gate, Low Gain, Quadrants a & b
18	SUB	Substrate
19	H2Sb	Horizontal CCD Clock, Phase 2, Storage, Quadrant b
20	H1Sb	Horizontal CCD Clock, Phase 1, Storage, Quadrant b
21	H1Bb	Horizontal CCD Clock, Phase 1, Barrier, Quadrant b

Table 4. PACKAGE PIN DESCRIPTION

Table 4. PACKAGE PIN DESCRIPTION (continued)

Pin	Name	Description
22	H2Bb	Horizontal CCD Clock, Phase 2, Barrier, Quadrant b
23	H2SLb	Horizontal CCD Clock, Phase 1, Storage, Last Phase, Quadrant b
24	OGb	Output Gate, Quadrant b
25	Rb	Reset Gate, Standard (High) Gain, Quadrant b
26	RDab	Reset Drain, Quadrants a & b
27	GND	Ground
28	VOUTb	Video Output, Quadrant b
29	VDDb	Output Amplifier Supply, Quadrant b
30	V2B	Vertical CCD Clock, Phase 2, Bottom
31	V1B	Vertical CCD Clock, Phase 1, Bottom
32	V4B	Vertical CCD Clock, Phase 4, Bottom
33	V3B	Vertical CCD Clock, Phase 3, Bottom
34	ESD	ESD Protection Disable
35	V3T	Vertical CCD Clock, Phase 3, Top
36	DevID	Device Identification
37	V1T	Vertical CCD Clock, Phase 1, Top
38	V4T	Vertical CCD Clock, Phase 4, Top
39	VDDd	Output Amplifier Supply, Quadrant d
40	V2T	Vertical CCD Clock, Phase 2, Top
41	GND	Ground
42	VOUTd	Video Output, Quadrant d
43	Rd	Reset Gate, Standard (High) Gain, Quadrant d
44	RDcd	Reset Drain, Quadrants c & d
45	H2SLd	Horizontal CCD Clock, Phase 2, Storage, Last Phase, Quadrant d
46	OGd	Output Gate, Quadrant d
47	H1Bd	Horizontal CCD Clock, Phase 1, Barrier, Quadrant d
48	H2Bd	Horizontal CCD Clock, Phase 2, Barrier, Quadrant d
49	H2Sd	Horizontal CCD Clock, Phase 2, Storage, Quadrant d
50	H1Sd	Horizontal CCD Clock, Phase 1, Storage, Quadrant d
51	R2cd	Reset Gate, Low Gain, Quadrants c & d
52	SUB	Substrate
53	H2Sc	Horizontal CCD Clock, Phase 2, Storage, Quadrant c
54	H1Sc	Horizontal CCD Clock, Phase 1, Storage, Quadrant c
55	H1Bc	Horizontal CCD Clock, Phase 1, Barrier, Quadrant c
56	H2Bc	Horizontal CCD Clock, Phase 2, Barrier, Quadrant c
57	H2SLc	Horizontal CCD Clock, Phase 2, Storage, Last Phase, Quadrant c
58	OGc	Output Gate, Quadrant c
59	Rc	Reset Gate, Standard (High) Gain, Quadrant c
60	RDcd	Reset Drain, Quadrants c & d
61	GND	Ground
62	VOUTc	Video Output, Quadrant c
63	VDDc	Output Amplifier Supply, Quadrant c
64	V2T	Vertical CCD Clock, Phase 2, Top
65	V1T	Vertical CCD Clock, Phase 1, Top
66	V4T	Vertical CCD Clock, Phase 4, Top
67	V3T	Vertical CCD Clock, Phase 3, Top
68	ESD	EDS Protection Disable

1. Liked named pins are internally connected and should have a common drive signal.

IMAGING PERFORMANCE

Table 5. TYPICAL OPERATIONAL CONDITIONS

(Unless otherwise noted, the Imaging Performance Specifications are measured using the following conditions.)

Description	Condition	Notes
Light Source	Continuous Red, Green and Blue LED Illumination	1
Operation	Nominal Operating Voltages and Timing	

1. For monochrome sensor, only green LED used.

Specifications

Table 6. PERFORMANCE SPECIFICATIONS

Description	Symbol	Min	Nom	Max	Unit	Sampling Plan	Temperature Tested at (°C)
	Symbol	IVIIII.	NOIII.	IVIAX.	Onit	1 Idii	(0)
Dark Field Global Non-Liniformity	DSNU	_	_	2.0	m\/nn	Die	27 40
Bright Field Global Non-Uniformity (Note 1)	DONO	-	2.0	5.0	% rms	Die	27, 40
Bright Field Global Peak to Peak Non-Uniformity (Note 1)	PRNU	-	5.0	15.0	% pp	Die	27, 40
Bright Field Center Non-Uniformity (Note 1)		-	1.0	2.0	% rms	Die	27, 40
Maximum Photoresponse Non-Linearity High Gain (4,000 to 20,000 electrons) High Gain (4,000 to 40,000 electrons) Low Gain (8,000 to 80,000 electrons)	NL_HG1 NL_HG2 NL_LG1	- - -	2 3 6	- - -	%	Design	
Maximum Gain Difference between Outputs (Note 2)	ΔG	-	-	10	%	Design	
Horizontal CCD Charge Capacity	H _{Ne}	-	90	-	ke-	Design	
Vertical CCD Charge Capacity	V _{Ne}	-	60	-	ke-	Design	
Photodiode Charge Capacity (Note 3)	P _{Ne}	-	44	-	ke-	Die	27, 40
Floating Diffusion Capacity – High Gain	FNe_HG	40	-	-	ke-	Die	27, 40
Floating Diffusion Capacity – Low Gain	FNe_LG	160	-	-	ke-	Die	27, 40
Horizontal CCD Charge Transfer Efficiency	HCTE	0.999995	0.999999	-		Die	
Vertical CCD Charge Transfer Efficiency	VCTE	0.999995	0.999999	_		Die	
Photodiode Dark Current	I _{PD}	-	7	70	e/p/s	Die	40
Vertical CCD Dark Current	I _{VD}	-	140	400	e/p/s	Die	40
Image Lag	Lag	-	-	10	e-	Design	
Anti-Blooming Factor	X _{AB}	1,000	-	-		Design	
Vertical Smear	Smr	-	-115	-	dB	Design	
Read Noise (Note 4) High Gain Low Gain	n _{e-T}	-	12 45	-	e⁻ rms	Design	
Dynamic Range, Standard (Notes 4, 5)	DR	-	70.5	-	dB	Design	
Dynamic Range, Extended Linear Dynamic Range Mode (XLDR) (Notes 4, 5)	XLDR	_	82.5	_	dB	Design	
Output Amplifier DC Offset	V _{ODC}	-	9.0	-	V	Die	27, 40
Output Amplifier Bandwidth (Note 6)	f _{-3db}	-	250	-	MHz	Die	
Output Amplifier Impedance	R _{OUT}	-	127	-	Ω	Die	27, 40
Output Amplifier Sensitivity High Gain Low Gain	ΔV/ΔΝ	-	33 8.7		μV/e-	Design	

Table 6. PERFORMANCE SPECIFICATIONS (continued)

Description	Symbol	Min.	Nom.	Max.	Unit	Sampling Plan	Temperature Tested at (°C)
KAI-04070-ABA AND KAI-04070-PBA	AND KAI-04	070–QBA CO	ONFIGURATI	ONS	<u>I</u>	ļ	
Peak Quantum Efficiency	QE _{MAX}	-	52	-	%	Design	
Peak Quantum Efficiency Wavelength	λQE	_	500	-	nm	Design	
KAI-04070-FBA AND KAI-04070-QBA	GEN2 COLO	R CONFIGU	RATIONS				
Peak Quantum Efficiency Blue Green Red	QE _{MAX}	- - -	41 42 37	- - -	%	Design	
Peak Quantum Efficiency Wavelength Blue Green Red	λQE	- - -	460 535 610	- - -	nm	Design	
KAI-04070-CBA AND KAI-04070-PBA	GEN1 COLO	R CONFIGU	RATIONS (No	ote 7)			
Peak Quantum Efficiency Blue Green Red	QE _{MAX}	- - -	43 42 38	- - -	%	Design	
Peak Quantum Efficiency Wavelength Blue Green	λQE		470 540		nm	Design	

Red 1. Per color.

Value is over the range of 10% to 90% of linear signal level saturation. 2.

The operating value of the substrate voltage, V_{AB} , will be marked on the shipping container for each device. The value of V_{AB} is set such that the photodiode charge capacity is 440 mV. This value is determined while operating the device in the low gain mode. V_{AB} value assigned 3. is valid for both modes; high gain or low gain.

620

4. At 40 MHz.

5. Uses 20LOG (P_{Ne} / n_{e-T}). 6. Assumes 5 pF load.

7. This color filter set configuration (Gen1) is not recommended for new designs.

Linear Signal Range







Figure 7. Low Gain Linear Signal Range

TYPICAL PERFORMANCE CURVES

Quantum Efficiency

Monochrome with Microlens



Figure 8. Monochrome with Microlens Quantum Efficiency

Color (Bayer RGB) with Microlens(Gen2 and Gen1 CFA)



Figure 9. Color (Bayer RGB) with Microlens Quantum Efficiency

Color (TRUESENSE Sparse CFA) with Microlens (Gen2 and Gen1 CFA)



Figure 10. Color (TRUESENSE Sparse CFA) with Microlens Quantum Efficiency

Angular Quantum Efficiency

For the curves marked "Horizontal", the incident light angle is varied in a plane parallel to the HCCD. For the curves marked "Vertical", the incident light angle is varied in a plane parallel to the VCCD.

Monochrome with Microlens



Figure 11. Monochrome with Microlens Angular Quantum Efficiency

Color (Bayer RGB) with Microlens



Figure 12. Color (Bayer RGB) with Microlens Angular Quantum Efficiency



Dark Current vs. Temperature

Figure 13. Dark Current vs. Temperature

Power-Estimated

Power-Estimated – Full Resolution



Figure 14. Power – Full Resolution

Power-Estimated – 1/4 Resolution – 2×2 Binning









Figure 16. Power – 1/4 Resolution – Variable HCCD XLDR

Power-Estimated – 1/4 Resolution – 2×2 Binning using Constant HCCD XLDR



Figure 17. Power – 1/4 Resolution – Constant HCCD XLDR

Frame Rates

Frame Rates – Full Resolution

Frame rates are for low and high gain modes of operation.



Figure 18. Frame Rates – Full Resolution

Frame Rates -1/4 Resolution -2×2 Binning Frame rates are for low and high gain modes of operation.









Figure 20. Frame Rates - 1/4 Resolution - Variable HCCD ALI

Frame Rates -1/4 Resolution -2×2 Binning using Constant HCCD XLDR Frame rates for a constant HCCD mode of operation.



Figure 21. Frame Rates – 1/4 Resolution – Constant HCCD XLDR

DEFECT DEFINITIONS

Table 7. OPERATION CONDITIONS FOR DEFECT TESTING AT 40°C

Description	Condition	Notes
Operational Mode	One Output, using VOUTa, Continuous Readout	
HCCD Clock Frequency	20 MHz	
Pixels per Line	2,140	
Lines per Frame	2,112	
Line Time	115.0 μs	
Frame Time	242.9 ms	
Photodiode Integration Time (PD_Tint)	PD_Tint = Frame Time = 242.9 ms, No Electronic Shutter Used	
Temperature	40°C	
Light Source	Continuous Red, Green and Blue LED Illumination	1
Operation	Nominal Operating Voltages and Timing	

1. For monochrome sensor, only the green LED is used.

Table 8. DEFECT DEFINITIONS FOR TESTING AT 40°C

Description	Definition	Standard Grade	Notes
Major Dark Field Defective Bright Pixel	Defect ≥ 83 mV	40	1
Major Bright Field Defective Pixel	$-12\% \ge \text{Defect} \ge 12\%$	40	1
Minor Dark Field Defective Bright Pixel	Defect ≥ 41 mV	400	
Cluster Defect	A group of 2 to 10 contiguous major defective pixels, but no more than 2 adjacent defect horizontally.	8	2
Column Defect	A group of more than 10 contiguous major defective pixels along a single column.	0	2

1. For the color devices (KAI-04070-CBA and KAI-04070-PBA), a bright field defective pixel deviates by 12% with respect to pixels of the same color.2. Column and cluster defects are separated by no less than two (2) good pixels in any direction (excluding single pixel defects).

Table 9. OPERATION CONDITIONS FOR DEFECT TESTING AT 27°C

Description	Condition	Notes
Operational Mode	One Output, Using VOUTa, Continuous Readout	
HCCD Clock Frequency	20 MHz	
Pixels per Line	2,140	
Lines per Frame	2,112	
Line Time	115 µs	
Frame Time	242.9 ms	
Photodiode Integration Time (PD_Tint)	PD_Tint = Frame Time = 242.9 ms, No Electronic Shutter Used	
Temperature	27°C	
Light Source	Continuous Red, Green and Blue LED Illumination	1
Operation	Nominal Operating Voltages and Timing	

1. For monochrome sensor, only the green LED is used.

Table 10. DEFECT DEFINITIONS FOR TESTING AT 40°C

Description	Definition	Standard Grade	Notes
Major Dark Field Defective Bright Pixel	Defect \ge 27 mV	40	1
Major Bright Field Defective Pixel	$-12\% \ge Defect \ge 12\%$	40	1
Cluster Defect	A group of 2 to 10 contiguous major defective pixels, but no more than 2 adjacent defect horizontally.	8	2
Column Defect	A group of more than 10 contiguous major defective pixels along a single column.	0	2

1. For the color devices (KAI–04070–CBA and KAI–04070–PBA), a bright field defective pixel deviates by 12% with respect to pixels of the same color.

2. Column and cluster defects are separated by no less than two (2) good pixels in any direction (excluding single pixel defects).

Defect Map

The defect map supplied with each sensor is based upon testing at an ambient (27°C) temperature. Minor point

defects are not included in the defect map. All defective pixels are reference to pixel 1, 1 in the defect maps. See Figure 22 for the location of pixel 1, 1.

TEST DEFINITIONS

Test Regions of Interest

Image Area ROI:	Pixel (1, 1) to Pixel (2080, 2080)
Active Area ROI:	Pixel (17, 17) to Pixel (2064, 2064)
Center ROI:	Pixel (991, 991) to Pixel (1090, 1090)

Only the Active Area ROI pixels are used for performance and defect tests.

Overclocking

The test system timing is configured such that the sensor is overclocked in both the vertical and horizontal directions. See Figure 22 for a pictorial representation of the regions of interest.



Figure 22. Regions of Interest

Tests

Dark Field Global Non-Uniformity

This test is performed under dark field conditions. The sensor is partitioned into 256 sub regions of interest, each of which is 128 by 128 pixels in size. The average signal level of each of the 256 sub regions of interest is calculated. The signal level of each of the sub regions of interest is calculated using the following formula:

Signal of ROI[i] = (ROI Average in Counts -

- Horizontal Overclock Average in Counts) ·

· mV per Count

Units : mVpp (millivolts Peak to Peak)

where i = 1 to 256. During this calculation on the 256 sub regions of interest, the maximum and minimum signal levels

are found. The dark field global uniformity is then calculated as the maximum signal found minus the minimum signal level found.

Global Non-Uniformity

This test is performed with the imager illuminated to a level such that the output is at 70% of saturation (approximately 924 mV). Prior to this test being performed the substrate voltage has been set such that the charge capacity of the sensor is 1,320 mV. Global non-uniformity is defined as

 $Global Non-Uniformity = 100 \cdot \left(\frac{Active Area Standard Deviation}{Active Area Signal}\right)$

Units: % rms

Active Area Signal = Active Area Average – Dark Column Average

Global Peak to Peak Non-Uniformity

This test is performed with the imager illuminated to a level such that the output is at 70% of saturation (approximately 924 mV). Prior to this test being performed the substrate voltage has been set such that the charge capacity of the sensor is 1,320 mV. The sensor is partitioned into 256 sub regions of interest, each of which is 128 by 128 pixels in size. The average signal level of each of the 256 sub regions of interest (ROI) is calculated. The signal level of each of the sub regions of interest is calculated using the following formula:

Signal of ROI[i] = (ROI Average in Counts -

- Horizontal Overclock Average in Counts) \cdot

· mV per Count

Where i = 1 to 256. During this calculation on the 144 sub regions of interest, the maximum and minimum signal levels are found. The global peak to peak uniformity is then calculated as:

Global Uniformity =
$$100 \cdot \left(\frac{\text{Max. Signal} - \text{Min. Signal}}{\text{Active Area Signal}}\right)$$

Units : % pp

Center Non-Uniformity

This test is performed with the imager illuminated to a level such that the output is at 70% of saturation (approximately 924 mV). Prior to this test being performed the substrate voltage has been set such that the charge capacity of the sensor is 1,320 mV. Defects are excluded for the calculation of this test. This test is performed on the center 100 by 100 pixels of the sensor. Center uniformity is defined as:

 $Center \ ROI \ Uniformity \ = \ 100 \ \cdot \ \left(\frac{Center \ ROI \ Standard \ Deviation}{Center \ ROI \ Signal} \right)$

Units: % rms

Center ROI Signal = Center ROI Average - Dark Colum Average

Dark Field Defect Test

This test is performed under dark field conditions. The sensor is partitioned into 256 sub regions of interest, each of which is 128 by 128 pixels in size. In each region of interest, the median value of all pixels is found. For each region of interest, a pixel is marked defective if it is greater than or equal to the median value of that region of interest plus the defect threshold specified in the "Detect Definitions" section.

Bright Field Defect Test

This test is performed with the imager illuminated to a level such that the output is at approximately 924 mV. Prior to this test being performed the substrate voltage has been set such that the charge capacity of the sensor is 1,320 mV. The average signal level of all active pixels is found. The bright and dark thresholds are set as:

Dark Defect Threshold = Active Area Signal · Threshold

Bright Defect Threshold = Active Area Signal · Threshold

The sensor is then partitioned into 256 sub regions of interest, each of which is 128 by 128 pixels in size. In each region of interest, the average value of all pixels is found. For each region of interest, a pixel is marked defective if it is greater than or equal to the median value of that region of interest plus the bright threshold specified or if it is less than or equal to the median value of that region of interest minus the dark threshold specified.

- Example for major bright field defective pixels:
- Average value of all active pixels is found to be 924 mV
- Dark defect threshold: $924 \text{ mV} \cdot 12\% = 111 \text{ mV}$
- Bright defect threshold: $924 \text{ mV} \cdot 12\% = 111 \text{ mV}$
- Region of interest #1 selected. This region of interest is pixels 17, 17 to pixels 144, 144
 - Median of this region of interest is found to be 920 mV
 - Any pixel in this region of interest that is ≤ (920 - 111 mV) 809 mV in intensity will be marked defective
 - Any pixel in this region of interest that is ≥ (920 + 111 mV) 1,031 mV in intensity will be marked defective
- All remaining 144 sub regions of interest are analyzed for defective pixels in the same manner

OPERATION

Absolute Maximum Ratings

Absolute maximum rating is defined as a level or condition that should not be exceeded at any time per the

description. If the level or the condition is exceeded, the device will be degraded and may be damaged. Operation at these values will reduce MTTF.

Table 11. ABSOLUTE MAXIMUM RATINGS

Description	Symbol	Minimum	Maximum	Unit	Notes
Operating Temperature	T _{OP}	-50	70	°C	1
Humidity	RH	5	90	%	2
Output Bias Current	I _{OUT}	-	60	mA	3
Off-Chip Load	CL	-	10	pF	

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Noise performance will degrade at higher temperatures.

2. $T = 25^{\circ}C$. Excessive humidity will degrade MTTF.

3. Total for all outputs. Maximum current is -15 mA for each output. Avoid shorting output pins to ground or any low impedance source during operation. Amplifier bandwidth increases at higher current and lower load capacitance at the expense of reduced gain (sensitivity).

Table 12. ABSOLUTE MAXIMUM VOLTAGE RATINGS BETWEEN PINS AND GROUND

Description	Minimum	Maximum	Unit	Notes
VDDα, VOUTα	-0.4	17.5	V	1
RDα	-0.4	15.5	V	1
V1B, V1T	ESD – 0.4	ESD + 24.0	V	
V2B, V2T, V3B, V3T, V4B, V4T	ESD – 0.4	ESD + 14.0	V	
H1Sa, H1Ba, H2Sa, H2Ba, H2SLa, R1a, R2a, OGa	ESD – 0.4	ESD + 14.0	V	1
ESD	-10.0	0.0	V	
SUB	-0.4	40.0	V	2

1. α denotes a, b, c or d.

2. Refer to Application Note Using Interline CCD Image Sensors in High Intensity Visible Lighting Conditions

KAI-08050 Compatibility

The KAI–04070 is pin-for-pin compatible with a camera designed for the KAI–08050 image sensor with the following accommodations:

- To operate in accordance with a system designed for KAI–08050, the target substrate voltage should be set to be 2.0V higher than the value recorded on the KAI–04070 shipping container. This setting will cause the charge capacity to be limited to 20 ke⁻ (or 660 mV)
- On the KAI–04070, pins 17 (R2ab) and 51 (R2cd) should be left floating per the KAI–08050 Device Performance Specification

- The KAI-04070 will operate in only the high gain mode (33 µV/e⁻)
- All timing and voltages are taken from the KAI–08050 specification sheet
- The number of horizontal and vertical CCD clock cycles is reduced as appropriate

In addition, if the intent is to operate the KAI–04070 image sensor in a camera designed for the KAI–08050 sensor that has been modified to accept and process the full $40,000 \text{ e}^-(1,320 \text{ mV})$ output, the following changes to the RD bias must be made:

Table 13.

Pins	Names	KAI-08050	KAI-04070	
10, 26, 44, 60	RDa, RDb, RDc, RDd	12.0 V per the Specification	Increase to 12.6 V	

To make use of the low or dual gains modes the KAI-04070 voltages and timing specifications must be used.

Reset Pin, Low Gain (R2ab and R2cd)

The R2ab and R2bc (pins 17 and 51) each have an internal circuit to bias the pins to 4.3 V. This feature assures the device is set to operate in the high gain mode when pins 17

and 51 are not connected in the application to a clock driver (for KAI–08050 compatibility). Typical capacitor coupled drivers will not drive this structure.



Figure 23. Equivalent Circuit for Reset Gate, Low Gain (R2ab and R2cd)

Power-Up and Power-Down Sequence

Adherence to the power-up and power-down sequence is critical. Failure to follow the proper power-up and power-down sequences may cause damage to the sensor.



Notes:

- 1. Activate all other biases when ESD is stable and SUB is above 3 V.
- 2. Do not pulse the electronic shutter until ESD is stable.
- 3. VDD cannot be +15 V when SUB is 0 V.
- 4. The image sensor can be protected from an accidental improper ESD voltage by current limiting the SUB current to less than 10 mA. SUB and VDD must always be greater than GND. ESD must always be less than GND. Placing diodes between SUB, VDD, ESD and ground will protect the sensor from accidental overshoots of SUB, VDD and ESD during power on and power off. See the figure below.

Figure 24. Power-Up and Power-Down Sequence

The VCCD clock waveform must not have a negative overshoot more than 0.4 V below the ESD voltage.



Figure 25. VCCD Clock Waveform

Example of external diode protection for SUB, VDD and ESD. α denotes a, b, c or d.



Figure 26. Example of External Diode Protection

DC Bias Operating Conditions

TADIE 17. DO DIAO OF LIVATINO CONDITIONO
--

Description	Pins	Symbol	Min.	Nom.	Max.	Unit	Max. DC Current	Notes
Reset Drain	RDα	RD	12.4	12.6	12.8	V	10 μA	1, 9
Output Gate	OGα	OG	-2.2	-2.0	-1.8	V	10 μA	1
Output Amplifier Supply	VDDα	V _{DD}	14.5	15.0	15.5	V	11.0 mA	1, 2
Ground	GND	GND	0.0	0.0	0.0	V	–1.0 mA	
Substrate	SUB	V _{SUB}	5.0	V _{AB}	V _{DD}	V	50 μA	3, 8
ESD Protection Disable	ESD	ESD	-9.2	-9.0	Vx_L	V	50 μA	6, 7, 10
Output Bias Current	VOUTα	I _{OUT}	-3.0	-5.0	-10.0	mA	-	1, 4, 5

1. α denotes a, b, c or d.

2. The maximum DC current is for one output. $I_{DD} = I_{OUT} + I_{SS}$. See Figure 27. 3. The operating value of the substrate voltage, V_{AB} , will be marked on the shipping container for each device. The value of V_{AB} is set such that the photodiode charge capacity is the nominal P_{Ne} (see Specifications).
An output load sink must be applied to each VOUT pin to activate each output amplifier.

5. Nominal value required for 40 MHz operation per output. May be reduced for slower data rates and lower noise.

6. Adherence to the power-up and power-down sequence is critical. See Sequence section. 7. ESD maximum value must be less than or equal to $V1_L + 0.4$ V and $V2_L + 0.4$ V.

8. Refer to Application Note Using Interline CCD Image Sensors in High Intensity Visible Lighting Conditions.

9. 12.0 V may be used if the total output signal desired is 20,000 e⁻ or less.

10. Where Vx_L is the level set for V1_L, V2_L, V3_L, or V4_L in the application.



Figure 27. Output Amplifier

AC Operating Conditions

Table 15. CLOCK LEVELS

	Pins						
Description	(Note 1)	Symbol	Level	Min.	Nom.	Max.	Unit
Vertical CCD Clock, Phase 1	V1B, V1T	V1_L	Low	-8.2	-8.0	-7.8	V
		V1_M	Mid	-0.2	0.0	0.2	
		V1_H	High	11.5	12.0	12.5	
Vertical CCD Clock, Phase 2	V2B, V2T	V2_L	Low	-8.2	-8.0	-7.8	V
		V2_H	High	-0.2	0.0	0.2	
Vertical CCD Clock, Phase 3	V3B, V3T	V3_L	Low	-8.2	-8.0	-7.8	V
		V3_H	High	-0.2	0.0	0.2	
Vertical CCD Clock, Phase 4	V4B, V4T	V4_L	Low	-8.2	-8.0	-7.8	V
		V4_H	High	-0.2	0.0	0.2	
Horizontal CCD Clock, Phase 1 Storage	H1Sα	H1S_L	Low	-5.2	-4.0	-3.8	V
		H1S_A	Amplitude (Note 3)	3.8	4.0	5.2	
Horizontal CCD Clock, Phase 1 Barrier	Η1Βα	H1B_L	Low	-5.2	-4.0	-3.8	V
		H1B_A	Amplitude (Note 3)	3.8	4.0	5.2	
Horizontal CCD Clock, Phase 2 Storage	H2Sα	H2S_L	Low	-5.2	-4.0	-3.8	V
		H2S_A	Amplitude (Note 3)	3.8	4.0	5.2	
Horizontal CCD Clock, Phase 2 Barrier	Η2Βα	H2B_L	Low	-5.2	-4.0	-3.8	V
		H2B_A	Amplitude (Note 3)	3.8	4.0	5.2	
Horizontal CCD Clock, Last Phase	H2SLa	H2SL_L	Low	-5.2	-5.0	-4.8	V
(Note 2)		H2SL_A	Amplitude (Note 3)	4.8	5.0	5.2	
Reset Gate	R1α	R_L	Low	-3.2	-3.0	-2.8	V
		R_A	Amplitude	6.0	-	6.4	
Reset Gate 2	R2α	R2_L	Low	-2.0	-1.8	-1.6	V
		R2_A	Amplitude	6.0	-	6.4	
Electronic Shutter (Note 4)	SUB	VES	High	29.0	30.0	40.0	V

1. α denotes a, b, c or d.

2. Use separate clock driver for improved speed performance.

3. The horizontal clock amplitude should be set such that the high level reaches 0.0 V. Examples:

a. If the minimum horizontal low voltage of -5.2 V is used, then a 5.2 V amplitude clock is required for a clock swing of -5.2 V to 0.0 V. b. If the maximum horizontal low voltage of -3.8 V is used, then a 3.8 V amplitude clock is required for a clock swing of -3.8 V to 0.0 V. Poter to Application Note Using Intervine CCD Image Sensors in High Interprite Visible Lighting Conditions

4. Refer to Application Note Using Interline CCD Image Sensors in High Intensity Visible Lighting Conditions.

The figure below shows the DC bias (VSUB) and AC clock (VES) applied to the SUB pin. Both the DC bias and AC clock are referenced to ground.



Figure 28. DC Bias and AC Clock Applied to the SUB Pin

Capacitance

Table 16. CAPACITANCE

	V1B	V2B	V3B	V4B	V1T	V2T	V3T	V4T	GND	All Pins	Unit
V1B	Х	4	3	3	2	2	2	1	10	25	nF
V2B	Х	Х	1	3	1	1	1	1	10	20	nF
V3B	Х	Х	Х	5	2	1	2	1	6	23	nF
V4B	Х	Х	Х	Х	2	1	1	1	13	23	nF
V1T	Х	Х	Х	Х	Х	2	3	2	20	29	nF
V2T	Х	Х	Х	Х	Х	Х	5	3	4	21	nF
V3T	Х	Х	Х	Х	Х	Х	Х	2	9	24	nF
V4T	Х	Х	Х	Х	Х	Х	Х	Х	3	20	nF
VSUB	0.5	0.5	0.5	0.5	0.5	0.5	0.5	0.5	2.8	2.8	nF

	H2S	H1B	H2B	GND	All Pins	Unit
H1S	32	29	29	120	210	pF
H2S	Х	16	21	170	240	pF
H1B	Х	Х	7	155	210	pF
H2B	Х	Х	Х	165	235	pF

1. Tables show typical cross capacitance between pins of the device.

2. Capacitance is total for all like pins.

3. Capacitance values are estimated.

Device Identification

The device identification pin (DevID) may be used to determine which Truesense Imaging 7.4 micron pixel interline CCD sensor is being used.

Table 17. DEVICE IDENTIFICATION

Description	Pins	Symbol	Min.	Nom.	Max.	Unit	Max. DC Current	Notes
Device Identification	DevID	DevID	64,000	74,000	84,000	Ω	50 μA	1, 2, 3

1. Nominal value subject to verification and/or change during release of preliminary specifications.

2. If the Device Identification is not used, it may be left disconnected.

3. After Device Identification resistance has been read during camera initialization, it is recommended that the circuit be disabled to prevent localized heating of the sensor due to current flow through the R_DeviceID resistor.

Recommended Circuit

Note that V1 must be a different value than V2.





TIMING

Requirements and Characteristics

Table 18. REQUIREMENTS AND CHARACTERISTICS

Description	Symbol	Min.	Nom.	Max.	Unit	Notes
Photodiode Transfer	t _{PD}	1.0	-	_	μs	
VCCD Leading Pedestal	t _{3P}	4.0	-	-	μs	
VCCD Trailing Pedestal	t _{3D}	4.0	-	-	μs	
VCCD Transfer	t _V	2.0	-	-	μs	
VCCD Clock Cross-Over	V _{VCR}	75	-	100	%	1
VCCD Rise, Fall Times	t _{VR} , t _{VF}	5	-	10	%	1, 2
HCCD Delay	t _{HS}	2.0	-	-	μs	
HCCD Transfer	t _e	25.0	-	-	ns	
Shutter Transfer	t _{SUB}	2.0	-	-	μs	
Shutter Delay	t _{HD}	2.0	-	-	μs	
Reset Pulse	t _R	2.5	-	-	ns	
Reset – Video Delay	t _{RV}	-	2.2	-	ns	
H2SL – Video Delay	t _{HV}	-	3.1	-	ns	
Line Time	t _{LINE}	34.9	-	-	μs	Dual HCCD Readout
		61.5	-	-	μs	Single HCCD Readout
Frame Time	t _{FRAME}	36.9	-	-	ms	Quad HCCD Readout
		73.8	-	-	ms	Dual HCCD Readout
		129.9	-	-	ms	Single HCCD Readout
Line Time (XLDR Bin 2×2)	t _{LINE}	69.8	-	-	μs	Dual HCCD Readout
		123.0	-	-	μs	Single HCCD Readout
Frame Time (XLDR Bin 2×2)	t _{FRAME}	36.9	-	_	ms	Quad HCCD Readout
Constant HCCD Timing		73.7	-	-	ms	Dual HCCD Readout
		129.9	-	_	ms	Single HCCD Readout
Frame Time (XLDR Bin 2×2)	t _{FRAME}	29.8	_	-	ms	Quad HCCD Readout
Variable HCCD Timing		59.5	-	-	ms	Dual HCCD Readout
		101.7	-	-	ms	Single HCCD Readout

1. Refer to Figure 47: VCCD Clock Rise Time, Fall Time, and Edge Alignment. 2. Relative to the VCCD Transfer pulse width, t_V .

Timing Flow Charts

In the timing flow charts the number of HCCD clock cycles per row, NH, and the number of VCCD clock cycles per frame, NV, are shown in the following table.

Table 19. VALUES FOR NH AND NV WHEN OPERATING THE SENSOR IN THE VARIOUS MODES OF RESOLUTION

	Full Res	solution	1/4 Res	olution	XL	DR
	NV	NH	NV	NH	NV	NH
Quad	1056	1076	528	538	528	538
Dual VOUTa, VOUTc	1056	2152	528	1076	528	1076
Dual VOUTa, VOUTb	2112	1076	1056	538	1056	538
Single VOUTa	2112	2152	1056	1076	1056	1076

1. The time to read out one line t_{LINE} = Line Timing + NH / (Pixel Frequency).

2. The time to read out one frame $t_{FRAME} = NV \cdot t_{LINE} + Frame Timing.$

3. Line Timing: See Table 21: Line Timing.

4. Frame Timing: See Table 20: Frame Timing.

5. XLDR: eXtended Linear Dynamic Range.

No Electronic Shutter

In this case the photodiode exposure time is equal to the time to read out an image. This flow chart applies to both full and 1/4 resolution modes.



Figure 30. Timing Flow when Electronic Shutter is Not Used

Using the Electronic Shutter

This flow chart applies to both the full and 1/4 resolution modes. The exposure time begins on the falling edge of the electronic shutter pulse on the SUB pin. The exposure time

ends on the falling edge of the photodiode transfer (t_{PD}) of the V1T and V1B pins. The electronic shutter timing is shown in Figure 38.





Figure 31. Timing Flow Chart using the Electronic Shutter for Exposure Control

Timing Tables

Frame Timing

This timing table is for transferring charge from the photodiodes to the VCCD. See Figures 32 and 33 for frame timing diagrams.

	Full Re:	solution, Hig	h Gain or Lo	w Gain	1/4 Res	olution, Hig	h Gain or Lo	w Gain		1/4 Resolu	ion XLDR				
Device Pin	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa			
V1T	F	1T	F'	1B	F'	1T	F	IB	F'	1T	F1	IB			
V2T	F:	2T	F4	4B	F:	2T	F4	1B	F:	2T	F4	1B			
V3T	F	3T	F	3B	F	3T	F	3B	F	3T	F3	3B			
V4T	F4	4T	F	2B	F4	4T	F	2B	F4	4T	F2	F2B			
V1B		F1	IB			F1	IB		F1B						
V2B		F2	2B			F2	2B			F2	2B				
V3B		F3	3B			F3	3B			F3	3B				
V4B		F4	1B			F4	1B			F4	1B				
H1Sa		Р	1			P1	Q			P1	XL				
H1Ba		Р	1			P1	Q			P1	XL				
H2Sa		Р	2			P2	2Q			P2	XL				
H2Ba		Р	2			P2	2Q			P2	XL				
Ra		RHG	/RLG			RHGQ	/RLGQ			RX	XL				
H1Sb		Р	1		P1Q					P1	XL				
H1Bb	P1	P2	P1	P2	P1Q	P2Q	P1Q	P2Q	P1XL	P2XL	P1XL	P2XL			
H2Sb		P	2			P2	2Q			P2	XL				
H2Bb	P2	P1	P2	P1	P2Q	P1Q	P2Q	P1Q	P2XL	P1XL	P2XL	P1XL			
Rb	RHG/ RLG	(Note 1)	RHG/ RLG	(Note 1)	RHGQ/ RLGQ	(Note 1)	RHGQ/ RLGQ	(Note 1)	RXL	(Note 1)	RXL	(Note 1)			
R2ab		R2HG	/R2LG			R2HGQ	/R2LGQ			R2	XL				
H1Sc	F	'1	(No	te 1)	P	1Q	(No	te 1)	P1	XL	(Note 1)				
H1Bc	F	1	(No	te 1)	P	IQ	(No	te 1)	P1	XL	(Note 1)				
H2Sc	F	2	(No	te 1)	P2	2Q	(No	te 1)	P2	XL	(Not	te 1)			
H2Bc	F	2	(No	te 1)	P2	2Q	(No	te 1)	P2	XL	(Not	te 1)			
Rc	RHG	/RLG	(No	te 1)	RHGQ	/RLGQ	(No	te 1)	R	XL	(Not	te 1)			
H1Sd	F	'1	(No	te 1)	P	IQ	(No	te 1)	P1	XL	(Not	te 1)			
H1Bd	P1	P2	(No	te 1)	P1Q	P2Q	(No	te 1)	P1XL	P2XL	(Not	te 1)			
H2Sd	P	2	(No	te 1)	Pź	2Q	(No	te 1)	P2	XL	(Not	te 1)			
H2Bd	P2	P1	(No	te 1)	P2Q	P1Q	(No	te 1)	P2XL	P1XL	(Not	te 1)			
Rd	RHG/ RLG	(Note 1)	(No	te 1)	RHGQ/ RLGQ	(Note 1)	(No	te 1)	RXL	(Note 1)	(Not	te 1)			
R2cd	R2HG	/R2LG	(No	te 1)	R2HGQ	/R2LGQ	(No	te 1)	R2	XL	(Not	te 1)			
SHP (Note 2)		SH	P1			SH	PQ			(Not	te 4)				
SHD (Note 2)		SH	D1			SH	DQ			(Not	te 5)				

1. This clock should be held at its high level voltage (0 V) or held at +5.0 V for compatibility with TRUESENSE 5.5 micron Interline Transfer CCD family of products.

SHP and SHD are the sample clocks for the analog front end (AFE) signal processor.
 This note intentionally left empty.

Use SHPLG for the AFE processing the low gain signal. Use SHPHG for the AFE processing the high gain signal.
 Use SHDLG for the AFE processing the low gain signal. Use SHDHG for the AFE processing the high gain signal.

Line Timing

This timing is for transferring one line of charge from the VCCD to the HCCD. See Figure 34, Figure 35, Figure 36 and Figure 37 for line timing diagrams.

					T				1/4 Beeslutters VI DD						
	Full Res	solution, Hig	h Gain or Lo	ow Gain	1/4 Res	solution, Hig	h Gain or Lo	w Gain		1/4 Resolu	tion XLDR				
Device Pin	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa			
V1T	Ľ	1T	Ľ	1B	2 ×	L1T	2 ×	L1B	2 ×	L1T	2 ×	L1B			
V2T	L	2T	L	4B	2 ×	L2T	2 ×	L4B	2 ×	L2T	2 ×	L4B			
V3T	L	зт	L	3B	2 ×	L3T	2 ×	L3B	2 ×	L3T	2 × L3B				
V4T	L	4T	L	2B	2 ×	L4T	2 ×	L2B	2 ×	L4T	2 ×	L2B			
V1B		Ľ	IB			2 ×	L1B			2 ×	L1B				
V2B		L2	2B			2 ×	L2B			2 ×	L2B				
V3B		L	3B			2 ×	L3B			2 ×	L3B				
V4B		L	4B			2 ×	L4B			2 ×	L4B				
H1Sa		P	1L			P1	LQ			P1	XL				
H1Ba		P	1L			P1	LQ			P1	XL				
H2Sa		P	2L			P2	LQ			P2	XL				
H2Ba		P	2L			P2	LQ			P2	XL				
Ra		RHG	/RLG			RHGQ	/RLGQ			R۷	KL				
H1Sb		P	1L			P1	LQ			P1	XL				
H1Bb	P1L	P2L	P1L	P2L	P1LQ	P2LQ	P1LQ	P2LQ	P1XL	P2XL	P1XL	P2XL			
H2Sb		P	2L			P2	LQ			P2	XL				
H2Bb	P2L	P1L	P2L	P1L	P2LQ	P1LQ	P2LQ	P1LQ	P2XL	P1XL	P2XL	P1XL			
Rb	RHG/ RLG	(Note 1)	RHG/ RLG	(Note 1)	RHGQ/ RLGQ	(Note 1)	RHGQ/ RLGQ	(Note 1)	RXL	(Note 1)	RXL	(Note 1)			
R2ab		R2HG	/R2LG			R2HGQ	/R2LGQ			R2	XL				
H1Sc	P	1L	(No	te 1)	P1	LQ	(No	te 1)	P1	XL	(Not	te 1)			
H1Bc	P	1L	(No	te 1)	P1	LQ	(No	te 1)	P1	XL	(Note 1)				
H2Sc	P	2L	(No	te 1)	P2	LQ	(No	te 1)	P2	XL	(Not	te 1)			
H2Bc	P	2L	(No	te 1)	P2	LQ	(No	te 1)	P2	XL	(Not	te 1)			
Rc	RHG	/RLG	(No	te 1)	RHGQ	/RLGQ	(No	te 1)	R	XL	(Not	te 1)			
H1Sd	P	1L	(No	te 1)	P1	LQ	(No	te 1)	P1	XL	(Not	te 1)			
H1Bd	P1L	P2L	(No	te 1)	P1LQ	P2LQ	(No	te 1)	P1XL	P2XL	(Not	te 1)			
H2Sd	P	2L	(No	te 1)	P2	LQ	(No	te 1)	P2	XL	(Not	te 1)			
H2Bd	P2L	P1L	(No	te 1)	P2LQ	P1LQ	(No	te 1)	P2XL	P1XL	(Not	te 1)			
Rd	RHG/ RLG	(Note 1)	(No	te 1)	RHGQ/ RLGQ	(Note 1)	(No	te 1)	RXL	(Note 1)	(Not	te 1)			
R2cd	R2HG	/R2LG	(No	te 1)	R2HGQ	/R2LGQ	(No	te 1)	R2	2XL	(Not	te 1)			
SHP (Note 2)	2) SHP1					SH	PQ			(Not	e 4)				
SHD (Note 2)	HD SHD1					SH	DQ			(Not	(Note 5)				

Table 21. LINE TIMING

This clock should be held at its high level voltage (0 V) or held at +5.0 V for compatibility with TRUESENSE 5.5 micron Interline Transfer 1. CCD family of products.SHP and SHD are the sample clocks for the analog front end (AFE) signal processor.

The notation 2× L1B means repeat the L1B timing twice for every line. This sums two rows into the HCCD.
 Use SHPLG for the AFE processing the low gain signal. Use SHPHG for the AFE processing the high gain signal.
 Use SHDLG for the AFE processing the low gain signal. Use SHDHG for the AFE processing the high gain signal.

Pixel Timing

This timing is for transferring one pixel from the HCCD to the output amplifier.

Table 22. PIXEL TIMING

	Full Re:	solution, Hig	h Gain or Lo	ow Gain	1/4 Res	solution, Hig	h Gain or Lo	w Gain		1/4 Resolu	tion XLDR	Single VOUTa						
Device Pin	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa	Quad	Dual VOUTa VOUTc	Dual VOUTa VOUTb	Single VOUTa						
V1T		-8	V	•		-8	V	•		-8	•							
V2T		-8	V			-8	۶V			-8	V							
V3T		0	V			0	V			0	V							
V4T		0	V			0	V			0	V							
V1B		-8	V			-8	s V			-8	V							
V2B		0	V			0	V			0	V							
V3B		0	V			0	V			0	V							
V4B		-8	V			-8	۶V			-8	V							
H1Sa		Р	1			P1	IQ			P1	XL							
H1Ba		Р	1			P1	IQ			P1	XL							
H2Sa		Р	2			P2	2Q			P2	XL							
H2Ba		Р	2			P2	2Q		P2XL									
Ra		RHG	/RLG			RHGQ	/RLGQ		RXL									
H1Sb		Р	1			P1	IQ			P1	XL							
H1Bb	P1	P2	P1	P2	P1Q	P2Q	P1Q	P2Q	P1XL	P2XL	P1XL	P2XL						
H2Sb		P	2			. P2	2Q			. P2	XL							
H2Bb	P2	P1	P2	P1	P2Q	P1Q	P2Q	P1Q	P2XL	P1XL	P2XL	P1XL						
Rb	RHG/ RLG	(Note 1)	RHG/ RLG	(Note 1)	RHGQ/ RLGQ	(Note 1)	RHGQ/ RLGQ	(Note 1)	RXL	(Note 1)	RXL	(Note 1)						
R2ab		R2HG	/R2LG			R2HGQ	/R2LGQ			R2	XL							
H1Sc	F	1	(No	te 1)	P	1Q	(Not	te 1)	P1	XL	(No	te 1)						
H1Bc	F	1	(No	te 1)	P	1Q	(Not	te 1)	P1	XL	(No	te 1)						
H2Sc	F	2	(No	te 1)	P2	2Q	(Not	te 1)	P2	XL	(No	te 1)						
H2Bc	F	2	(No	te 1)	P2	2Q	(Not	te 1)	P2	XL	(No	te 1)						
Rc	RHG	/RLG	(No	te 1)	RHGQ	/RLGQ	(Not	te 1)	R	XL	(No	te 1)						
H1Sd	P	·1	(No	te 1)	P	1Q	(Not	te 1)	P1	XL	(No	te 1)						
H1Bd	P1	P2	(No	te 1)	P1Q	P2Q	(Not	te 1)	P1XL	P2XL	(No	te 1)						
H2Sd	P	2	(No	te 1)	P2	2Q	(Not	te 1)	P2	XL	(No	te 1)						
H2Bd	P2	P1	(No	te 1)	P2Q	P1Q	(Not	te 1)	P2XL	P1XL	(No	te 1)						
Rd	RHG/ RLG	(Note 1)	(No	te 1)	RHGQ/ RLGQ	(Note 1)	(Not	te 1)	RXL	(Note 1)	(No	te 1)						
R2cd	R2HG	/R2LG	(No	te 1)	R2HGQ	R2LGQ	(Not	te 1)	R2	2XL	(No	te 1)						
SHP (Note 2)		SH	P1			SH	PQ			(Not	e 4)							
SHD (Note 2)		SH	D1			SH	SHDQ (Note 5)											

1. This clock should be held at its high level voltage (0 V) or held at +5.0 V for compatibility with TRUESENSE 5.5 micron Interline Transfer CCD family of products.

2. SHP and SHD are the sample clocks for the analog front end (AFE) signal processor.

SHP and SHD are the sample clocks for the analog noncend (APE) signal processor.
 This note intentionally left empty.
 Use SHPLG for the AFE processing the low gain signal. Use SHPHG for the AFE processing the high gain signal.
 Use SHDLG for the AFE processing the low gain signal. Use SHDHG for the AFE processing the high gain signal.

Timing Diagrams

The charge in the photodiodes its transfer to the VCCD on the rising edge of the +12 V pulse and is completed by the falling edge of the +12 V pulsed on F1T and F1B. During the time period when F1T and F1B are at +12 V (t_{PD}) anti-blooming protection is disabled. The photodiode integration time ends on the falling edge of the +12 V pulse.





NOTE: See Table 20 for pin assignments.





Frame Timing - Single and Dual VOUTa/VOUTb Readout Modes

NOTE: See Table 20 for pin assignments.

Figure 33. Frame Timing Diagram Single and Dual VOUTa/VOUTb Readout Modes

		1			Line	Timing				
				٦	Time Dura	tion is 4 · t	V			
Device Pin	Pattern	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$. t _∨ . 2	$\frac{t_V}{2}$	0.)/
V1T	L1T		 					; ; ; ;	 	0V
'	L2T		1 1 1 1	1 1 1 1	ι ι ι Γ ·	<u>.</u> 		' ' '	"	0 V
¦	L3T		1 1 1 1	I I I I I	<u> </u>				I I I I	
'	L4T		<u> </u>	, , , ,			 	 	I I I I	
V1B	L1B		1 1 1 1	1 1 1 1	1 1 1 1	1 1 1 1	 	1 		0 V
V2B	L2B						 	, 	I I I I	8 V
'	L3B		<u> </u>	 	 		1 1 1 1 	 	 	
	L4B					, , , , , , ,		, , , ,	ļ	0 V 8 \
ont al	P1L	 	1 1 1 1 1	1 1 1 1 1		 	 	 	1 1 1 1 T	
Hor ize CI oc	P2L			 		 - -	 	 	 	0V
		$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	4 V
Frame or P	Pixel Timing	-			Line	Timing				Pixel Timin
	$\frac{t}{2}$	<u>e</u> 2								

Line Timing -Full Resolution - Quadrant and Dual VOUTa/VOUTc Readout Modes

NOTE: See Table 21 for pin assignments.



	1			Line	Timing				
			٦	Time Dura	tion is 4 · 1	ťγ			- - -
Pattern	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	t _V	. t _∨ . 2	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	0.14
L1B		, , , ,					-' 	I	0V
L4B		' ' '		<u>.</u> 	<u>.</u> 	<u>.</u> 	<u> </u> -	<u> </u>	- <mark>-</mark> 0 V
L3B			1	· ·		1 1 1 1 4	1 1 1 1 -1	1 1 1 1 1	
L2B		1 1 1 1	1 1 1 1	·	1 7 1 1	 		1 1 1 1	
L1B		 	 	I I I L	 1	 	' -, '	 	0 V
L2B		1 1 1 1	1 1 1		1 T 1 1	 		 	0 V
L3B		<u> </u>	- - 	· · · ·		- - - -	, , , , , , , , , , , , , , , , , , ,	 	
L4B	- 	 		- - - - - - -				ļ	0 V
P1L	1 1 1 1 1	1 1 1 1 1	1 1 1 1 1	1 1 1 1 1	 	1 1 1 1 1	I I I I I	1 1 1 T	
P2L	 	 		1 1 1 1	 	 	 	1 1 1 1	0V
	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	4 V
xel Timing	-			Line	Timing				Pixel Timing
	Pattern L1B L4B L3B L2B L1B L2B L3B L4B L4B P1L P2L	Pattern L1B L4B L3B L2B L2B L3B L2B L3B L2	Pattern $\frac{t_{V}}{2}$ $\frac{t_{V}}{2}$ L1B L4B L3B L2B L2B L2B L2B L2B L2B L2B L2	Pattern $\frac{t_V}{2}$ $\frac{t_V}{2}$ $\frac{t_V}{2}$ L1B L4B L3B L2B L2B L1B L2B L2B L2B L3B L2B L4B L4B L4B L4B L4B L4B L4B L4	Pattern $\frac{t_{\vee}}{2}$ $\frac{t_{\vee}}{2}$ $\frac{t_{\vee}}{2}$ $\frac{t_{\vee}}{2}$ $\frac{t_{\vee}}{2}$ L1B	Time Duration is 4 · t Pattern $\frac{t_v}{2}$ $\frac{t_v}{2}$ $\frac{t_v}{2}$ $\frac{t_v}{2}$ $\frac{t_v}{2}$ $\frac{t_v}{2}$ L1B	Time Duration is 4 · ty Pattern $\frac{t_y}{2}$ t	Ime Duration is 4 · ty Ime Duration is 4 · ty ty	Time Duration is 4 · ty Ity ty ty <th< td=""></th<>

Line Timing – Full Resolution – Single and Dual VOUTa/VOUTb Readout Modes

NOTE: See Table 21 for pin assignments.



	1/4 Resolution Line Timing																	
		-						Time	Durat	ion is	8 · t _V						>	
Device Pin	Pattern	$\frac{t_V}{2}$	$\frac{t_V}{2}$	t _V 2	t _V 2	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	t _V 2	$\frac{t_V}{2}$	t _V 2	. t _∨ . <u>2</u>	$\frac{t_V}{2}$	$\frac{t_V}{2}$. t _∨ . 2	$\frac{t_V}{2}$	t _V 2	1 1 1
V1T	L1T		, , ,	 	, , , , – –	, , , +	, , , ,	 		1		 		 	, , , ,	, , , ,	I	, , , ,
V2T	L2T		, , ,	, , ,	, , , ,	ι ι τ]	 - -	,		- - 	' ' '						1 1 1
V3T	L3T			 	<u> </u>	 1 1 1	-' 		, , , ,	·	 	; ; ; ; ;		 	' ' ' '		 	■ _
V4T	L4T		 	I I I I	⊢ – – I I I	 	• • • • • •	· · · ·	· · · ·			+ 				· · · ·	• • • ±	 -
V1B	L1B		1 1 1	 	1 1 1	 			1 1 1 1		1	 				i ī i	1 1 1 1	- - - - -
V2B	L2B		1 1 1 1	 		1 <u>1</u> 1 1	- - - - - - -		1 1 1 1	 	 	 		 	 		1 1 1 1	
V3B	L3B	' I ' I ' I		 	 		 	 	 		· ·	 			 		 	
V4B	L4B	' 	 		 	 +	 	 		·	, ,				 	 		
izont al ocks			 	 	ו ו ו ר	ι ι ι τ	 	 	ı ı ı			 	 	 	1 1 1 1 7	1 1 1 1 1	1 1 1 1 1	- - -
E I C I	P2L	' ' ' -	1 1 1	 	I I I	<u> </u>	 	 	·	<u> </u>		 		·	<u> </u>	 	' ' '	·
		$\frac{t_{\vee}}{2}$	¦ t _∨ ¦ 2	t _V 2	t _V 2	t _V 2	$\frac{t_V}{2}$	$\frac{t_V}{2}$	t _V 2	$\frac{t_V}{2}$	$\frac{t_V}{2}$, t _v	$\frac{t_V}{2}$	$\frac{t_V}{2}$	¦ t _∨ ¦ 2	. t _∨ 2	$\frac{t_V}{2}$	
ame or P	ixel Timing	t _e					1	/4 Res	solutio	n Line	Timin	g					,	Pix

Line Timing – Low Gain, High Gain and XLDR 1/4 Resolution – Quadrant and Dual VOUTa/VOUTc Readout Modes

NOTE: See Table 21 for pin assignments.

Figure 36. Line Timing Diagram – 1/4 Resolution – Quadrant and Dual VOUTa/VOUTc Readout Modes

		-					1	I/4 Re	solutio	n Line	Timin	g						1
		-						Time	Durat	tion is	$8 \cdot t_V$							- - -
Device Pin	Pattern	$\frac{t_V}{2}$. t _∨ . 2	. t _∨ 2	$\frac{t_V}{2}$	t _V 2	$\frac{t_V}{2}$	$\frac{t_V}{2}$	t _V 2	$\frac{t_V}{2}$. t _∨ . 2	. t _∨ 2	, t _∨ , <u>2</u>	, t _v	. t _∨ 2	. t _∨ 2	, t _V	0)
¦ V1T	L1B		 	 	 	, , , +			 		, , , ,	, , , ,	, , ,	 			т ! ! <u>+</u> !	
V2T	' L4B		 - -		י י ר – – י	1 1 1 1 1	' ' - -]		·	 	, , ,	 	1 1 1 1	 		<u>-</u> 8
V3T	L3B		ļ	' 	L 	 	 		 	 		<u>-</u> 	! 		 	 	1 1 1 1 	0\
V4T	L2B	-1	 	: : !	<u> </u>	+ ·	 - - -		; ; ; ;	 	· · · ·	: ; ; !		 	 		: ; ; 1	0 \
, V1B	L1B		 	I I I	 	 		- - - - - -	 		 	 	 	 	<u> </u>	 	1 1 1	0\
V2B	L2B		 	 	<u></u>	' <u> </u> 	' ' '		, , , , ,	' 	' 	, , , ,		' ' '	' ' '			0 \ 8
, V3B	L3B		<u>.</u>	 	 			· · ·	, , , , ,	 	· ·	 	 		 		L	0
'. V4B	,		 		 	 +	 	 		 	 	 	 	 	 	 		
zont al ocks			 	 	 	 	 	 	1 1 1 1	 	 	1 1 1 1 1	 	 	 	 	 	
Hor :: CI o	P2L		 	 	 	<u> </u>	 ! 		 	· 	 	 	 	 	<u>1</u> 1	· · ·	 	0 \
		$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$, t _v	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	$\frac{t_V}{2}$	4
Frame or P	ixel Timing	$\frac{1}{1}$					1	I/4 Re	solutio	n Line	Timin	ıg					>	Pixel Tin

Line Timing – Low Gain, High Gain and XLDR 1/4 Resolution – Single and Dual VOUTa/VOUTb Readout Modes

NOTE: See Table 21 for pin assignments.



Electronic Shutter Timing Diagrams

The electronic shutter pulse can be inserted at the end of any line of the HCCD timing. The HCCD should be empty when the electronic shutter is pulsed. A recommended position for the electronic shutter is just after the last pixel is read out of a line. The VCCD clocks should not resume until at least $t_V/2$ after the electronic shutter pulse has finished. The HCCD clocks can be run during the electronic shutter pulse as long as the HCCD does not contain valid image data.

For short exposures less than one line time, the electronic shutter pulse can appear inside the frame timing. Any electronic shutter pulse transition should be $t_V/2$ away from any VCCD clock transition.



Figure 38. Electronic Shutter Timing



Figure 39. Frame/Electrical Shutter Timing

Pixel Timing – Full Resolution – High Gain Pixel Timing

Use this timing to read out every pixel at high gain. If the sensor is to be permanently operated at high gain, the R2ab and R2cd pins can be left floating or set to any DC voltage between +3 V and +5 V. Note the R2ab and R2cd pins are

internally biased to +4.3 V when left floating. The SHP1 and SHD1 pulses indicate where the camera electronics should sample the video waveform. The SHP1 and SHD1 pulses are not applied to the image sensor.



Figure 40. Pixel Timing Diagram – Full Resolution – High Gain

Pixel Timing – Full Resolution – Low Gain Pixel Timing

Use this pixel timing to read out every pixel at low gain. If the sensor is to be permanently operated at low gain, the Ra, Rb, Rc and Rd pins should be set to any DC voltage between +3 V and +5 V. The SHP1 and SHD1 pulses indicate where the camera electronics should sample the video waveform. The SHP1 and SHD1 pulses are not applied to the image sensor.

Figure 41. Pixel Timing Diagram – Full Resolution – Low Gain

Pixel Timing – 1/4 Resolution – High Gain Pixel Timing

Use this timing to read out two pixels summed on the output amplifier sense node at high gain. If the sensor is to be permanently operated at high gain, the R2ab and R2cd pins can be left floating or set to any DC voltage between +3 V and +5 V. Note the R2ab and R2cd pins are internally biased to +4.3 V when left floating. The SHPQ and SHDQ pulses indicate where the camera electronics should sample

the video waveform. The SHPQ and SHDQ pulses are not applied to the image sensor.

The Ra, Rb, Rc, and Rd pins are pulsed at half the frequency of the horizontal CCD clocks. This causes two pixels to be summed on the output amplifier sense node. The SHPQ and SHDQ clocks are also half the frequency of the horizontal CCD clocks.

Figure 42. Pixel Timing Diagram – 1/4 Resolution – High Gain

Pixel Timing – 1/4 Resolution – Low Gain Pixel Timing

Use this timing to read out two pixels summed on the output amplifier sense node at low gain. If the sensor is to be permanently operated at low gain, the Ra, Rb, Rc and Rd pins can be set to any DC voltage between +3 V and +5 V. The SHPQ and SHDQ pulses indicate where the camera electronics should sample the video waveform. The SHPQ and SHDQ pulses are not applied to the image sensor.

The R2ab and R2cd pins are pulsed at half the frequency of the horizontal CCD clocks. This causes two pixels to be summed on the output amplifier sense node. The SHPQ and SHDQ clocks are also half the frequency of the horizontal CCD clocks.

XLDR Pixel Timing

To operate the sensor in extended linear dynamic range (XLDR) mode, the following pixel timing should be used. This mode requires two sets of analog front end (AFE) signal processing electronic units for each output. As shown in Figure 44 one AFE samples the pixel at low gain (SHPLG and SHDLG) and the other AFE samples the pixel at high gain (SHPHG and SHDHG).

Two HCCD pixels are summed on the output amplifier node to obtain enough charge to fully use the 82 dB range of the XLDR timing. Combined with two-line VCCD summing, a total of 160,000 electrons of signal $(4 \times 40,000)$ can be sampled with 12 electrons or less noise. Note that a linear dynamic range of 82 dB is very large. Ensure that the camera optics is capable of focusing an 82 dB dynamic range image on the sensor. Lens flare caused by inexpensive optics or even dust on the lens will limit the dynamic range.

The timing shown in Figure 46 shows the HCCD not being clocked at a constant frequency. If the HCCD cannot be clocked at a variable frequency, then the HCCD may be clocked at a constant frequency (Figure 45) at the expense of about 33% slower frame rate.

Figure 44. XLDR Timing – AFE Connections Block Diagram

Figure 45. Pixel Timing Diagram – 1/4 Resolution – XLDR – Constant HCCD Timing

Figure 46. Pixel Timing Diagram – 1/4 Resolution – XLDR – Variable HCCD Timing

Figure 47. VCCD Clock Rise Time, Fall Time and Edge Alignment

MECHANICAL INFORMATION

Completed Assembly

Notes:

- 1. See Ordering Information for marking code.
- No materials to interfere with clearance through guide holes.
 Units: mm.

Notes:

- 1. Optical center of image is nominally at the package center.
- 2. Units: mm.

Figure 49. Completed Assembly (2 of 2)

Notes:

- 1. Substrate = Schott D263T eco.
- 2. Dust, Scratch, Inclusion Specification: 10 µm maximum size in Zone A.

3. MAR coated both sides.

4. Spectral Transmission:

a. T > 98.0% 420–435 nm

b. T > 99.2% 435–630 nm

5. Units: mm.

Cover Glass Transmission

Figure 51. Cover Glass Transmission

REFERENCES

For information on ESD and cover glass care and cleanliness, please download the *Image Sensor Handling and Best Practices* Application Note (AN52561/D) from www.onsemi.com.

For information on environmental exposure, please download the *Using Interline CCD Image Sensors in High Intensity Lighting Conditions* Application Note (AND9183/D) from <u>www.onsemi.com</u>.

For information on soldering recommendations, please download the Soldering and Mounting Techniques Reference Manual (SOLDERRM/D) from www.onsemi.com. For quality and reliability information, please download the *Quality & Reliability* Handbook (HBD851/D) from <u>www.onsemi.com</u>.

For information on device numbering and ordering codes, please download the *Device Nomenclature* technical note (TND310/D) from <u>www.onsemi.com</u>.

For information on Standard terms and Conditions of Sale, please download <u>Terms and Conditions</u> from <u>www.onsemi.com</u>.

ON Semiconductor and the intervent and the intervent of the product of the property of the property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdt/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under tights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC products are associated with such unintended or unauthorized application. Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support:

Phone: 421 33 790 2910 Japan Customer Focus Center Phone: 81–3–5817–1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.

Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный) **Факс:** 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.