ChargePump™

General Description

The AAT3110 ChargePump™ is a MicroPower switched-capacitor voltage converter that delivers a regulated output. No external inductor is required for operation. Using three small capacitors, the AAT3110 can deliver up to 150mA to the voltage regulated output. The AAT3110 features very low quiescent current and high efficiency over a large portion of its load range making this device ideal for battery-powered applications. Furthermore, the combination of few external components and small package size keeps the total converter board area to a minimum in space restricted applications. The AAT3110 operates in an output-regulated voltage doubling mode. The regulator uses a pulse-skipping technique to provide a regulated output from a varying input supply. The AAT3110 contains a thermal management circuit to protect the device under continuous output short circuit conditions.

The AAT3110 is available in a surface mount 6-pin SOT23 or 8-pin SC70JW package and is rated from -40 to 85°C.

The AAT3110 ChargePump™ is a member of AnalogicTech's Total Power Management IC product family.

Features


- Step-up type voltage converter
- Input Range
  - AAT3110-5: 2.7V to 5V
  - AAT3110-3.3: 2.3V to 3.3V
- MicroPower consumption: 13µA
- 5V, 3.3V Regulated ±4% output
- 5V Output Current
  - 100mA with $V_{IN} \geq 3.0V$
  - 50mA with $V_{IN} \geq 2.7V$
- 3.3V Output Current
  - 150mA with $V_{IN} \geq 2.7V$
  - 100mA with $V_{IN} \geq 2.3V$
- High Frequency 750 kHz operation
- Shutdown mode draws less than 1µA
- Short-circuit/over-temperature protection
- 2kV ESD Rating
- SC70JW-8 or SOT23-6 package

Applications

- Cellular Phones
- Portable Communication Devices
- Handheld Electronics
- Digital Cameras
- PDAs
- Battery Back Up Supplies
- LED/Display Back Light Driver

Preliminary Information

Typical Operating Circuits




Pin Descriptions


Pin # SOT-23-6	Pin # SC70JW-8	Symbol	Function
1	1	V_{OUT}	Regulated output pin. Bypass this pin to ground with at least 6.8µF low ESR capacitor
2	2, 3, 4	GND	Ground connection
3	5	$\overline{SHDN}$	Shutdown input. Active low signal disables the converter.
4	6	C-	Flying capacitor negative terminal
5	7	V_{IN}	Input supply pin. Bypass this pin to ground with at least 6.8µF low ESR capacitor
6	8	C+	Flying capacitor positive terminal

Pin Configuration

SOT23-6



SC70JW-8



Absolute Maximum Ratings (T_A=25°C unless otherwise noted)

Symbol	Description	Value	Units
V_{IN}	V_{IN} to GND	-0.3 to 6	V
V_{OUT}	V_{OUT} to GND	-0.3 to 6	V
V_{SHDN}	SHDN to GND	-0.3 to 6	V
t_{SC}	Output to GND Short-Circuit Duration	Indefinite	s
T_J	Operating Junction Temperature Range	-40 to 150	°C
T_{LEAD}	Maximum Soldering Temperature (at leads, 10 sec)	300	°C
V_{ESD}	ESD Rating[1] — HBM	2000	V

Stresses above those listed in Absolute Maximum Ratings may cause permanent damage to the device. Functional operation at conditions other than the operating conditions specified is not implied. Only one Absolute Maximum rating should be applied at any one time.

Note 1: Human body model is a 100pF capacitor discharged through a 1.5kΩ resistor into each pin.

Thermal Information

Symbol	Description	Rating	Units
Θ_{JA}	Maximum Thermal Resistance (SOT23-6 or SC70JW-8)	150	°C/W
P_D	Maximum Power Dissipation (SOT23-6 or SC70JW-8)	667	mW

Note 2: Mounted on an FR4 board.

Electrical Characteristics (T_A = -40 to 85°C unless otherwise noted. Typical values are at T_A=25°C, C_{FLY}=1µF, C_{IN}=10µF, C_{OUT}=10µF)

AAT3110-5						
Symbol	**Description**	**Conditions**	**Min**	**Typ**	**Max**	**Units**
V_{IN}	Input Voltage	V_{OUT}=5.0V	2.7		V_{OUT}	V
I_Q	No Load Supply Current	2.7V < V_{IN} < 5V, I_{OUT}=0mA, $\overline{SHDN}$=V_{IN}		13	30	µA
V_{OUT}	Output Voltage	2.7V < V_{IN} < 5V, I_{OUT} ≤ 50mA	4.8	5	5.2	V
		3.0V < V_{IN} < 5V, I_{OUT} ≤ 100mA	4.8	5	5.2	V
I_{SHDN}	Shutdown Supply Current	2.7V < V_{IN} < 3.6V, I_{OUT} =0mA, V_{SHDN}=0		0.01	1	µA
		3.6V < V_{IN} < 5V, I_{OUT} =0mA, V_{SHDN}=0			2.5	
V_{RIPPLE}	Ripple Voltage	V_{IN} = 3V, I_{OUT} = 50mA		25		mV_{P-P}
		V_{IN} = 3V, I_{OUT} = 100mA		30		
η	Efficiency	V_{IN} = 3V, I_{OUT} = 50mA		83		%
f_{OSC}	Frequency	Oscillator Free Running		750		kHz
V_{IH}	$\overline{SHDN}$ Input Threshold High		1.4			V
V_{IL}	$\overline{SHDN}$ Input Threshold Low				0.3	V
I_{IH}	$\overline{SHDN}$ Input Current High	$\overline{SHDN}$ = V_{IN}	-1		1	µA
I_{IL}	$\overline{SHDN}$ Input Current Low	$\overline{SHDN}$ = GND	-1		1	µA
t_{ON}	V_{OUT} Turn-on time	V_{IN} = 3V, I_{OUT} = 0mA		0.2		ms
I_{SC}	Short-circuit current[3]	V_{IN} = 3V, V_{OUT} = GND, $\overline{SHDN}$ = 3V		300		mA

Note 3: Under short-circuit conditions, the device may enter overtemperature protection mode.

Electrical Characteristics


(T_A = -40 to 85°C unless otherwise noted. Typical values are at T_A=25°C, C_{FLY}=1µF, C_{IN}=10µF, C_{OUT}=10µF)

AAT3110-3.3						
Symbol	**Description**	**Conditions**	**Min**	**Typ**	**Max**	**Units**
V_{IN}	Input Voltage	V_{OUT}=3.3V	2.3		V_{OUT}	V
I_Q	No Load Supply Current	2.3V < V_{IN} < 3.3V, I_{OUT}=0mA		10	30	µA
V_{OUT}	Output Voltage	2.3V < V_{IN} < 3.3V, I_{OUT}=50mA	3.17	3.30	3.43	V
		2.5V < V_{IN} < 3.3V, I_{OUT}=100mA	3.17	3.30	3.43	V
I_{SHDN}	Shutdown Supply Current	2.3V < V_{IN} < 3.3V, I_{OUT} =0mA, V_{SHDN}=0		0.01	1	µA
V_{RIPPLE}	Ripple Voltage	V_{IN} = 2.3V, I_{OUT} = 50mA		20		mV_{P-P}
η	Efficiency	V_{IN} = 2.3V, I_{OUT} = 25mA		71		%
f_{OSC}	Frequency	Oscillator Free Running		750		kHz
V_{IH}	$\overline{SHDN}$ Input Threshold High		1.4			V
V_{IL}	$\overline{SHDN}$ Input Threshold Low				0.3	V
I_{IH}	$\overline{SHDN}$ Input Current High	$\overline{SHDN}$ = V_{IN}	-1		1	µA
I_{IL}	$\overline{SHDN}$ Input Current Low	$\overline{SHDN}$ = GND	-1		1	µA
t_{ON}	V_{OUT} Turn-on time	V_{IN} = 3V, I_{OUT} = 0mA		0.2		ms
I_{SC}	Short-circuit current	V_{IN} = 3V, V_{OUT} = GND, $\overline{SHDN}$ = 3V		300		mA


Typical Characteristics—AAT3110-5

(Unless otherwise noted, V_{IN} = 3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


Output Voltage vs. Output Current
AAT3110-5




Supply Current vs. Supply Voltage
AAT3110-5




Supply Current vs $V_{\overline{SHDN}}$
AAT3110-5




Efficiency vs. Supply Voltage
AAT3110-5



Efficiency vs. Load Current
AAT3110-5




Oscillator Frequency vs. Supply Voltage
AAT3110-5




Typical Characteristics—AAT3110-5

(Unless otherwise noted, V_{IN} = 3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


Startup Time with 50 mA Load
AAT3110-5




Startup Time with 100 mA Load
AAT3110-5




Load Transient Response for 50mA
AAT3110-5




Load Transient Response for 100mA
AAT3110-5



Output Ripple with I_{OUT}=50 mA
AAT3110-5




Output Ripple with I_{OUT}=100 mA
AAT3110-5




Typical Characteristics—AAT3110-5

(Unless otherwise noted, V_{IN} = 3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


V_{IN} vs. V_{IH}




V_{IN} vs. V_{IL}



V_{SHDN} Threshold vs. Supply Voltage AAT3110-5




Normalized Output Voltage vs Temperature




Typical Characteristics—AAT3110-3.3

(Unless otherwise noted, V_{IN} = 2.3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


Output Voltage vs. Output Current
AAT3110-3.3




Supply Current vs. Supply Voltage
AAT3110-3.3




Supply Current vs $V_{\overline{SHDN}}$
AAT3110-3.3




Efficiency vs. Supply Voltage
AAT3110-3.3



Efficiency vs. Output Current
AAT3110-3.3




Oscillator Frequency vs. Supply Voltage
AAT3110-3.3




Typical Characteristics—AAT3110-3.3

(Unless otherwise noted, V_{IN} = 2.3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


Startup Time with 50 mA Load
AAT3110-3.3




Startup Time with 100 mA Load
AAT3110-3.3




Load Transient Response for 50mA
AAT3110-3.3




Load Transient Response for 100mA
AAT3110-3.3



Output Ripple for 50mA Load
AAT3110-3.3




Output Ripple for 100mA Load
AAT3110-3.3




Typical Characteristics—AAT3110-3.3

(Unless otherwise noted, V_{IN} = 2.3V, C_{IN}=C_{OUT}=10µF, C_{FLY}=1µF, T_A = 25ºC)


V_{IN} vs. V_{IH}
AAT3110-3.3




V_{IN} vs. V_{IL}
AAT3110-3.3



V_{SHDN} Threshold vs. Supply Voltage
AAT3110-3.3



Functional Block Diagram



Functional Description

Operation (Refer to block diagram)

The AAT3110 uses a switched capacitor charge pump to boost an input voltage to a regulated output voltage. Regulation is achieved by sensing the charge pump output voltage through an internal resistor divider network. A switched doubling circuit is enabled when the divided output drops below a preset trip point controlled by an internal comparator. The charge pump switch cycling enables four internal switches at two non-overlapping phases. During the first phase, switches S1 and S4 are switched on (short) and switches S2 and S3 are off (open). The flying capacitor C_{FLY} is charged to a level approximately equal to input voltage V_{IN}. On the second phase, switches S1 and S4 are turned off (open), S2 and S3 are turned on (short). The low side of the flying capacitor C_{FLY} is connected to GND during the first phase. During the second phase, the flying capacitor C_{FLY} is switched so that the low side is connected to V_{IN}. The voltage at the high side of the flying capacitor C_{FLY} is bootstrapped to $2 \times V_{IN}$ and connected to output through a switch. For each cycle phase, charge from input node V_{IN} is transported from a lower voltage to a higher voltage. This cycle repeats itself until the output node voltage is high enough to exceed the preset input threshold of the control comparator. When the output voltage exceeds the internal trip point level, the switching cycle stops and the charge pump circuit is temporarily placed in an idle state. When idle, the AAT3110 has a quiescent current of 13µA or less. The closed loop feed back system containing the voltage sense circuit and control comparator allows the AAT3110 to provide a regulated output voltage to the limits of the input voltage and output load current. The switching signal, which drives the charge pump is created by an integrated oscillator within the control circuit block. The free running charge pump switching frequency is approximately 750kHz. The switching frequency under an active load is a function of V_{IN}, V_{OUT}, C_{OUT} and I_{OUT}.

For each phase of the switching cycle, the charge transported from V_{IN} to V_{OUT} can be approximated by the following formula:

$$V_{PHASE} \approx C_{FLY} \times (2 \times V_{IN} - V_{OUT})$$

The relative average current that the charge pump can supply to the output may be approximated by the following expression:

$$I_{OUT(AVG)} \propto C_{FLY} \times (2 \times V_{IN} - V_{OUT}) \times F_{SW}$$

The AAT3110 has complete output short circuit and thermal protection to safeguard the device under extreme operating conditions. An internal thermal protection circuit senses die temperature and will shut down the device if the internal junction temperature exceeds approximately 145°C. The charge pump will remain disabled until the fault condition is relieved.

Applications Information

External Capacitor Selection

Careful selection of the three external capacitors C_{IN}, C_{OUT} and C_{FLY} is very important because they will affect turn on time, output ripple and transient performance. Optimum performance will be obtained when low ESR (<100mΩ) ceramic capacitors are used for C_{IN} and C_{OUT} and C_{FLY}. In general, low ESR may be defined as less then 200mΩ. If desired for a particular application, low ESR Tantalum capacitors may be substituted; however optimum output ripple performance may not be realized. Aluminum Electrolytic capacitors are not recommended for use with the AAT3110 due the their inherent high ESR characteristic.

Typically as a starting point, a capacitor value of 10µF should be used for C_{IN} and C_{OUT} with 1µF C_{FLY} when the AAT3110 is used under maximum output load conditions. Lower values for C_{IN}, C_{OUT} and C_{FLY} may be utilized for light load current applications. Applications drawing a load current of 10mA or less may use a C_{IN} and C_{OUT} capacitor value as low as 1µF and a C_{FLY} value of 0.1µF. C_{IN} and C_{OUT} may range from 1µF for light loads to 10µF or more for heavy output load conditions. C_{FLY} may range from 0.01µF to 2.2µF or more. If C_{FLY} is increased, C_{OUT} should also be increased by the same ratio to minimize output ripple. As a basic rule, the ratio between C_{IN}, C_{OUT} and C_{FLY} should not exceed a ratio of 10 to 1. The compromise for lowering the value of C_{IN}, C_{OUT} and the flying capacitor C_{FLY} is the output ripple voltage may be increased. In any case, if the external capacitor values deviate greatly from the recommendation of C_{IN} = C_{OUT} = 10µF and C_{FLY} = 1µF, the AAT3110 output performance should be evaluated to assure the device meets the application requirements.

In applications where the input voltage source has very low impedance, it is possible to omit the C_{IN} capacitor. However, if C_{IN} is not used, circuit performance should be evaluated to assure desired operation is achieved. Under high peak current operating conditions that are typically experienced during circuit start up or when load demands create a large inrush current, poor output voltage regulation can result if the input supply source impedance is high, or if the value of C_{IN} is too low. This situation can be remedied by increasing the value of C_{IN}.

Capacitor Characteristics

Ceramic composition capacitors are highly recommended over all other types of capacitors for use with the AAT3110. Ceramic capacitors offer many advantages over their tantalum and aluminum electrolytic counterparts. A ceramic capacitor typically has very low ESR, is lower cost, has a smaller PCB footprint and is non-polarized. Low ESR ceramic capacitors help maximize charge pump transient response. Since ceramic capacitors are non-polarized, they are not prone to incorrect connection damage.

Equivalent Series Resistance (ESR): ESR is a very important characteristic to consider when selecting a capacitor. ESR is a resistance internal to a capacitor, which is caused by the leads, internal connections, size or area, material composition and ambient temperature. Typically capacitor ESR is measured in milliohms for ceramic capacitors and can range to more then several ohms for tantalum or aluminum electrolytic capacitors.

Ceramic Capacitor Materials: Ceramic capacitors less then 0.1µF are typically made from NPO or COG materials. NPO and COG materials typically have tight tolerance and are very stable over temperature. Large capacitor values are typically composed of X7R, X5R, Z5U or Y5V dielectric materials. Large ceramic capacitors, typically greater than 2.2µF are often available in low cost Y5V and Z5U dielectrics. If these types of capacitors are selected for use with the charge pump, the nominal value should be doubled to compensate for the capacitor tolerance which can vary more than ±50% over the operating temperature range of the device. A 10µF Y5V capacitor could be reduced to less than 5µF over temperature, this could cause problems for circuit operation. X7R and X5R dielectrics are much more desirable. The temperature tolerance of X7R dielectric is better than ±15%.

Capacitor area is another contributor to ESR. Capacitors that are physically large will have a lower ESR when compared to an equivalent material smaller capacitor. These larger devices can improve circuit transient response when compared to an equal value capacitor in a smaller package size.

Applications Information

Charge Pump Efficiency

The AAT3110 is a regulated output voltage doubling charge pump. The efficiency (η) can simply be defined as a linear voltage regulator with an effective output voltage that is equal to two times the input voltage. Efficiency (η) for an ideal voltage doubler can typically be expressed as the output power divided by the input power.

$$\eta = P_{OUT} / P_{IN}$$

In addition, with an ideal voltage doubling charge pump the output current may be expressed as half the input current. The expression to define the ideal efficiency (η) can be rewritten as:

$$\eta = P_{OUT}/P_{IN} = (V_{OUT} \times I_{OUT})/(V_{IN} \times 2I_{OUT}) = V_{OUT}/2V_{IN}$$

$$\eta(\%) = 100(V_{OUT} / 2V_{IN})$$

For a charge pump with an output of 5 volts and a nominal input of 3.0 volts, the theoretical efficiency is 83.3%. Due to internal switching losses and IC quiescent current consumption, the actual efficiency can be measured at 82.7%. These figures are in close agreement for output load conditions from 1mA to 100mA. Efficiency will decrease as load current drops below 0.05mA or when level of V_{IN} approaches V_{OUT}. Refer to the Typical Characteristics section for measured plots of efficiency versus input voltage and output load current for the given charge pump output voltage options.

Short Circuit and Thermal Protection

In the event of a short circuit condition, the charge pump can draw a much as 100mA to 400mA of current from V_{IN}. This excessive current consumption due to an output short circuit condition will cause a rise in the internal IC junction temperature. The AAT3110 has a thermal protection and shutdown circuit that continuously monitors the IC junction temperature. If the thermal protection circuit senses the die temperature exceeding approximately 145°C, the thermal shutdown will disable the charge pump switching cycle operation. The thermal limit system has 10°C of system hysteresis before the charge pump can reset. Once the over current event is removed from the output and the junction temperature drops below 135°C, the charge pump will then become active again. The thermal protection system will cycle on and off if an output short circuit condition persists. This will allow the AAT3110 to operate indefinitely a short circuit condition without damage to the device.

Output Ripple and Ripple Reduction

There are several factors that determine the amplitude and frequency of the charge pump output ripple, the values of C_{OUT} and C_{FLY}, the load current I_{OUT} and the level of V_{IN}. Ripple observed at V_{OUT} is typically a sawtooth waveform in shape. The ripple frequency will vary depending on the load current I_{OUT} and the level of V_{IN}. As V_{IN} increases the ability of the charge pump to transfer charge from the input to the output becomes greater, as it does, the peak-to-peak output ripple voltage will also increase.

The size and type of capacitors used for V_{IN}. C_{OUT} and C_{FLY} have an effect on output ripple. Since output ripple is associated with the R/C charge time constant of these two capacitors, the capacitor value and ESR will contribute to the resulting charge pump output ripple. This is why low ESR capacitors are recommended for use in charge pump applications. Typically, output ripple is not greater than $50mV_{P-P}$ when V_{IN} = 3.0V, V_{OUT} = 5.0V, C_{OUT} = 10µF and C_{FLY} = 1µF.

When the AAT3110 is used in light output load applications where I_{OUT} < 10mA, the flying capacitor C_{FLY} value can be reduced. The reason for this effect is when the charge pump is either under very light load conditions the transfer of charge across C_{FLY} is greater during each phase of the switching cycle. The result is higher ripple seen at the charge pump output. This effect will be reduced by decreasing the value of C_{FLY}. Caution should be observed when decreasing the flying capacitor. If the output load current rises above the nominal level for the reduced C_{FLY} value, charge pump efficiency can be compromised.

There are several methods that can be employed to reduce output ripple depending upon the requirements of a given application. The most simple and straightforward technique is to increase the value of the C_{OUT} capacitor. The nominal 10µF C_{OUT} capacitor can be increased to 22µF or more. Larger values for the C_{OUT} capacitor (22µF and greater) will by nature have lower ESR and can improve both high and low frequency components of the charge

Applications Information

and low frequency components of the charge pump output ripple response. If a higher value tantalum capacitor is used for C_{OUT} to reduce low frequency ripple elements, a small 1µF low ESR ceramic capacitor should be added in parallel to the tantalum capacitor (see Figure 1). The reason for this is tantalum capacitors typically have higher ESR than equivalent value ceramic capacitors and are less able to reduce high frequency components of the output ripple. The only disadvantage to using large values for the C_{OUT} capacitor is the AAT3110 device turn-on time and in-rush current may be increased.

If additional ripple reduction is desired, an R/C filter can be added to the charge pump output in addition to the C_{OUT} capacitor (see Figure 2). An R/C filter will reduce output ripple by primarily attenuating high frequency components of the output ripple waveform. The low frequency break point for the R/C filter will significantly depend on the capacitor value selected.

Layout Considerations

High charge pump switching frequencies and large peak transient currents mandate careful printed circuit board layout. As a general rule for charge pump boost converters, all external capacitors should be located as close as possible to the device package with minimum length trace connections. Maximize the ground plane around the AAT3110 charge pump and make sure all external capacitors are connected to the immediate ground plane. A local component side ground plane is recommended. If this is not possible due the layout design limitations, assure good ground connections by the use of large or multiple pcb via's.

Refer to the following AAT3110 evaluation board for an example of good charge pump layout design (Figures 3 through 5).




Figure 1: Application using tantalum capacitor




Figure 2: Application with output ripple reduction filter




Figure 3: Evaluation board top side silk screen layout / assembly drawing




Figure 4: Evaluation board component side layout




Figure 5: Evaluation board component side layout

Typical Application Circuits




Figure 6: Typical charge pump boost converter circuit




Figure 7: 5 Volt, 100mA supply powered from a USB port




Figure 8: 5 Volt LED or Display Driver from a Li-Ion Battery Source





Figure 9: 5 Volt, 200mA Step-Up Supply from a 3.0V to 5V Source.

Ordering Information

Output Voltage	Package	Marking	Part Number	
			Bulk	Tape and Reel
3.3V	SOT-23-6		N/A	AAT3110IGU-3.3-T1
5.0V	SOT-23-6		N/A	AAT3110IGU-5-T1
3.3V	SC70JW-8		N/A	AAT3110IJS-3.3-T1
5.0V	SC70JW-8		N/A	AAT3110IJS-5-T1


Package Information

SOT-23-6



Dim	Millimeters		Inches	
	Min	Max	Min	Max
A	0.95	1.45	0.037	0.057
A1	0.05	0.15	0.002	0.006
A2	0.90	1.30	0.035	0.051
b	0.35	0.50	0.0137	0.019
c	0.08	0.20	0.0031	0.0078
D	2.84	3.00	0.1118	0.118
E	1.50	1.70	0.059	0.0669
E1	2.60	3.00	0.102	0.118
e	0.95 BSC		0.0374 BSC	
e1	1.90 BSC		0.0748 BSC	
f	0.50 BSC		0.0197 BSC	
L	0.23	0.40	0.009	0.016
L1	0.10 BSC		0.039 BSC	
L2	0.60 BSC		0.0236 BSC	
t	0°	10°	0°	10°

SC70JW-8



Dim	Millimeters		Inches	
	Min	Max	Min	Max
E	2.10 BSC		0.083 BSC	
E1	1.75	2.00	0.069	0.079
L	0.23	0.40	0.009	0.016
A		1.10		0.043
A1	0	0.10		0.004
A2	0.70	1.00	0.028	0.039
D	2.00 BSC		0.079 BSC	
e	0.50 BSC		0.020 BSC	
b	0.15	0.30	0.006	0.012
c	0.10	0.20	0.004	0.008
Θ	0	8°	0	8°
Θ1	4°	10°	4°	10°

Advanced Analogic Technologies, Inc.
1250 Oakmead Parkway, Suite 310, Sunnyvale, CA 94086
Phone (408) 524-9684
Fax (408) 524-9689


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.