

TRON[®] In-Line Fuse Holders

HEB Series Single-Pole Breakaway & Non-Breakaway for 1³/₃₂" x 1 1¹/₂" Fuses



Non-Breakaway Fuse Holders

See page 2 for breakaway holders

Catalog Symbol: HEB

Description:

Water resistant, single-pole non-breakaway in-line fuse holders for 1³/₃₂" x 1 1¹/₂" midget fuses. Typical fuse types: BAF, DCM, FNM, FNQ and KTK.

Ratings:

Volts: 600V (or less)

Amps: Up to 30A*

Agency Information:

(1)UL Recognized, Guide IZLT2, File E14853

(2)CSA Certified, Class 6225-01, File 47235

(3)CE

Coupling Nut Torque: 10-20lb-in.

Part Number Explanation

Example: HEB-AK

- HEB = Holder series
- A = Loadside terminal (copper crimp for #12 copper wire)
- K = Lineside terminal (copper setscrew for two #6 copper wires)

Part Number Selection

From the table on page three, select the combination of desired loadside and lineside terminals for the application (define terminal type, wire size, number of wires per terminal and whether the terminal accepts solid and/or stranded conductors). Then in the right hand two columns, select either the non-breakaway or breakaway holder part number to order.

Available Part Numbers

HEB-AA⁽¹⁾ (2) (3), HEB-AB⁽²⁾, HEB-AC⁽²⁾,
HEB-AD⁽²⁾, HEB-AE⁽²⁾, HEB-AJ, HEB-AK, HEB-AL, HEB-AR,
HEB-AY, HEB-BA⁽²⁾, HEB-BB⁽²⁾, HEB-BC⁽²⁾, HEB-BD⁽²⁾,
HEB-CC⁽²⁾, HEB-DD⁽²⁾, HEB-JJ, HEB-JK, HEB-JL, HEB-JY,
HEB-LL, HEB-NN, HEB-PP⁽²⁾, HEB-QQ⁽²⁾, HEB-RR⁽²⁾,
HEB-SS, HEB-TT⁽²⁾, HEB-ZA.

Insulating Boots

For insulating boots, see page 2. Insulating boots are not included with non-breakaway holders and must be ordered separately. They come standard with the breakaway holders.

When insulating boots are utilized, extra heat retention requires that fuses are sized at a minimum of 200% of the RMS load current.

*Amp rating limited by conductor size.

Specification Data - Non-Breakaway & Loadside Breakaway

Conductor Terminals

| Terminal Type | Conductor Data | | | Catalog Symbol Load & Line (2) & (3) |
|---|----------------|------------------|----------------|--------------------------------------|
| | Size | No. Per Terminal | Solid Stranded | |
| Copper Crimp  | #12 to #8 | 1 | • • | A |
| | #12 | 2 | • • | |
| | #10 | 2 | • • | B |
| | #6 | 1 | • • | |
| | #8 | 2 | • • | C |
| | #4 | 1 | — • | |
| | #6 | 2 | • • | D |
| | #2 | 1 | — • | |
| | #4 | 2 | • • | E |
| | #20 to #18 | 1 | • • | |


Copper Setscrew

| | | | | |
|---|-----------|---|-----|---|
|  | #12 to #3 | 1 | • • | J |
| | | | | |
|  | #12 to #3 | 2 | • • | K |
| | | | | |

Solid Copper Terminal for Aluminum Wire Connector

| | | | | |
|---|-----------|---|-----|---|
|  | #8 to #12 | 1 | • — | S |
| | #10 to #4 | 1 | — • | |

Aluminum Crimp

| | | | | |
|---|--------|---|-----|---|
|  | #8 | 1 | — • | N |
| | #6 | 1 | • — | |
| | #6 | 1 | — • | P |
| | #4 | 1 | • — | |
| | #3, #4 | 1 | — • | Q |
| | #2 | 1 | • — | |
| | #1, #2 | 1 | — • | R |
| | #1/0 | 1 | — • | |

Aluminum Setscrew

| | | | | |
|---|-----------|---|-----|---|
|  | #12 to #2 | 1 | • • | L |
| | | | | |
|  | #12 to #3 | 2 | • • | Y |
| | | | | |

Breakaway Fuse Holders

Catalog Symbol: HEB

Description:

Single-pole breakaway in-line fuse holders for $\frac{13}{32}$ " x $1 \frac{1}{2}$ " midget fuses. Typical fuse types: BAF, DCM, FNM, FNQ AND KTK.

Ratings:

Volts: 600V (or less)

Amps: Up to 30A*

Agency Information:

(1)UL Recognized, Guide IZLT2, File E14853

(2)CSA Certified, Class 6225-01, File 47235

(3)CE

Coupling Nut Torque: 10-20lb-in.

Part Number Explanation

Example: HEB-AW-RYC

- HEB = Holder series
- AW = Loadside terminal (copper crimp for #12 copper wire)
- RYC = Lineside terminal (copper setscrew for two #6 copper wires)

Part Number Selection

From the table on page three, select the combination of desired loadside and lineside terminals for the application (define terminal type, wire size, number of wires per terminal and whether the terminal accepts solid and/or stranded conductors). Then in the right hand two columns, select either the non-breakaway or breakaway holder part number to order.

Available Part Numbers

Breakaway Units:

(Includes fuse holder, breakaway part and insulating boots):







HEB-AW-RLA, HEB-AW-RLC-A⁽¹⁾ ⁽²⁾ ⁽³⁾, HEB-AW-RLC-B, HEB-AW-RLC-C, HEB-AW-RLC-J, HEB-AW-RYA, HEB-AW-RYC, HEB-BW-RLC-A, HEB-BW-RLC-B, HEB-BW-RYC, HEB-JW-RLC-J, HEB-JW-RYC, HEB-KW-RLC-J, HEB-KW-RYC, HEB-LW-RLA, HEB-LW-RLC-J, HEB-LW-RYA

Fuse Holder Only: HEB-AW⁽²⁾, HEB-BW⁽²⁾, HEB-DW⁽²⁾, HEB-JW, HEB-LW

Breakaway Part: RLC-A, RLC-B, RLC-C, RLC-J, RYC, RLA, RYA

Specification Data - Lineside Breakaway

Breakaway Receptacles

| Terminal Type | Conductor Data | | | | Catalog Symbol |
|--|--------------------------------------|------------------|-------|----------|----------------|
| | Size | No. Per Terminal | Solid | Stranded | |
| Copper Crimp  | #12 to #8 | 1 | • | • | -RLC-A |
| | #6 | 1 | • | • | -RLC-B |
| | #4 | 1 | • | • | -RLC-C |
| Copper Setscrew  | #12 to #2 | 1 | • | • | -RLC-J |
| | | | | | |
|  | #12 to #3 | 2 | • | • | -RYC |
| Aluminum Setscrew  | #12 to #2 | 1 | • | • | -RLA |
| | | | | | |
|  | #12 to #3 | 2 | • | • | -RYA |
| Solid Breakaway  | (Required with Breakaway Receptacle) | | | W | |

Insulating Boots



| Part Numbers | Type |
|--------------|------------------|
| 2A0660 | Single conductor |
| 2A0661 | Two conductor |

Two insulating boots come standard with the breakaway holders (example: HEB-AW-RLC-A). The insulating boots are not included with the non-breakaway holders (example: HEB-AA) or the individual pieces of the breakaway holders (example: HEB-AW, RLC-A). Two insulating boots must be ordered for each holder when ordering them separately. When insulating boots are utilized, extra heat retention requires that fuses are sized at a minimum of 200% of the RMS load current.

*Amp rating limited by conductor size.

For HEB Holders Only

Directions: To select complete holder P/N, work from left to right starting with loadside terminal options and then lineside terminal options. Then determine breakaway or non-breakaway style.

| Loadside Terminal | | | | | Lineside Terminal | | | | | Available P/N's | |
|---------------------------------------|-------------------------|---------------------------|------------|---------------|---------------------------------------|-------------------------|---------------------------|------------|---------------|---|---------------------------------------|
| Terminal Type | Wire Size | No. of Wires per Terminal | Solid Wire | Stranded Wire | Terminal Type | Wire Size | No. of Wires per Terminal | Solid Wire | Stranded Wire | Non-Breakaway P/N (Boots not included) | Breakaway P/N (Boots included) |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | HEB-AA ⁽¹⁾⁽²⁾ (3) | HEB-AW-RLC-A ⁽¹⁾⁽²⁾ (3) |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | HEB-AB ⁽²⁾ | HEB-AW-RLC-B |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Crimp | #4 #8 | 1 2 | N Y | Y Y | HEB-AC ⁽²⁾ | HEB-AW-RLC-C ⁽⁴⁾ |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Crimp | #2 #6 | 1 2 | N Y | Y Y | HEB-AD ⁽²⁾ | N/A |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Crimp | 2/0 #3 | 1 2 | N N | Y Y | HEB-AE ⁽²⁾ | N/A |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Setscrew | #12 to #3 | 1 | Y | Y | HEB-AJ | HEB-AW-RLC-J |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Copper Setscrew | #12 to #3 | 2 | Y | Y | HEB-AK | HEB-AW-RYC |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Aluminum Setscrew | #12 to #2 | 1 | Y | Y | HEB-AL | HEB-AW-RLA |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Aluminum Setscrew | #12 to #2 | 2 | Y | Y | HEB-AY | HEB-AW-RYA |
| Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | Aluminum Crimp | #1, #2 | 1 | N | Y | HEB-AR | N/A |
| Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | HEB-BA ⁽²⁾ | HEB-BW-RLC-A |
| Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | HEB-BB ⁽²⁾ | HEB-BW-RLC-B |
| Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | Copper Crimp | #4 #8 | 1 2 | N Y | Y Y | HEB-BC ⁽²⁾ | N/A |
| Copper Crimp | #6 #10 | 1 2 | Y Y | Y Y | Copper Crimp | #2 #6 | 1 2 | N Y | Y Y | HEB-BD ⁽²⁾ | N/A |
| Copper Crimp | #4 #8 | 1 2 | N Y | Y Y | Copper Crimp | #4 #8 | 1 2 | N Y | Y Y | HEB-CC ⁽²⁾ | N/A |
| Copper Crimp | #2 #6 | 1 2 | N Y | Y Y | Copper Crimp | #2 #6 | 1 2 | N Y | Y Y | HEB-DD ⁽²⁾ | N/A |
| Copper Crimp | #20, #18 | 1 | Y | Y | Copper Crimp | #12 to #8 #12 | 1 2 | Y Y | Y Y | HEB-ZA | N/A |
| Copper Setscrew | #12 to #3 | 1 | Y | Y | Copper Setscrew | #12 to #3 | 1 | Y | Y | HEB-JJ | HEB-JW-RLC-J |
| Copper Setscrew | #12 to #3 | 1 | Y | Y | Copper Setscrew | #12 to #3 | 2 | Y | Y | HEB-JK | HEB-JW-RYC |
| Copper Setscrew | #12 to #3 | 1 | Y | Y | Aluminum Setscrew | #12 to #2 | 1 | Y | Y | HEB-JL | N/A |
| Copper Setscrew | #12 to #3 | 1 | Y | Y | Aluminum Setscrew | #12 to #2 | 2 | Y | Y | HEB-JY | N/A |
| Aluminum Setscrew | #12 to #2 | 1 | Y | Y | Aluminum Setscrew | #12 to #2 | 1 | Y | Y | HEB-LL | HEB-LW-RLA |
| Aluminum Crimp | #8 #6 | 1 1 | N Y | Y N | Aluminum Crimp | #8 #6 | 1 1 | N Y | Y N | HEB-NN | N/A |
| Aluminum Crimp | #6 #4 | 1 1 | N Y | Y N | Aluminum Crimp | #6 #4 | 1 1 | N Y | Y N | HEB-PP ⁽²⁾ | N/A |
| Aluminum Crimp | #3, #4 #2 | 1 1 | N Y | Y N | Aluminum Crimp | #3, #4 #2 | 1 1 | N Y | Y N | HEB-QQ ⁽²⁾ | N/A |
| Aluminum Crimp | #1, #2 | 1 | N | Y | Aluminum Crimp | #1, #2 | 1 | N | Y | HEB-RR ⁽²⁾ | N/A |
| Aluminum Crimp | 1/0 | 1 | N | Y | Aluminum Crimp | 1/0 | 1 | N | Y | HEB-TT ⁽²⁾ | N/A |
| Solid Terminal for aluminum connector | #8 to #12 #10 to #14 | 1 1 | Y N | N Y | Solid Terminal for aluminum connector | #8 to #12 #10 to #14 | 1 1 | Y N | N Y | HEB-SS | N/A |

(1) UL Recognized, Guide IZLT2, File E14853

(2) CSA Certified, Class 6225-01, File 47235

(3) CE

(4) HEB-AW-RLC-C is for (1) #4 stranded wire only.

Contact your local Cooper Bussmann representative for other possible terminations not listed.

The only controlled copy of this Data Sheet is the electronic read-only version located on the Cooper Bussmann Network Drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Cooper Bussmann reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Cooper Bussmann also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.