

TPS73x01DRBEVM-518

This user's guide describes the characteristics, operation, and use of the TPS73x01DRBEVM-518 evaluation module. This document includes setup instructions, a schematic diagram, thermal guidelines, a bill of materials (BOM), and printed circuit board (PCB) layout drawings.

Contents

1	Overview	2
2	Setup	2
3	Operation	3
4	Thermal Guidelines	3
5	Board Layout, Schematic, and Parts List	4

List of Figures

1	Assembly Layer	6
2	Top Layer Routing	7
3	Bottom Layer Assembly	8
4	Bottom Layer Routing	8
5	TPS73x01DRBEVM-518 Schematic.....	9

List of Tables

1	Device Summary	2
2	Related Documentation	2
3	Maximum Input Voltage	4
5	TPS73x01DRBEVM-518 Bill of Materials	10

1 Overview

This document describes the characteristics, operation, and use of the TPS73x01DRBEVM-518 evaluation module (EVM). This EVM demonstrates the capabilities and features of Texas Instruments' [TPS73201DRB](#), [TPS73601DRB](#), and [TPS73701DRB](#) low-dropout (LDO) linear regulators. These regulators, each available in a 3-mm × 3-mm SON package, are capable of 250-mA, 400-mA, and 1-A output currents, respectively. The TPS73x01DRBEVM-518 module helps designers evaluate the operation and performance of the TPS73201, TPS73601, and TPS73701 LDO devices in a variety of configurations. The output voltage from the LDO device can be selected by a jumper to obtain 1.8 V, 2.5 V, 2.8 V, 3.0 V or 3.3 V. [Table 1](#) summarizes the LDOs that are suitable for use with this EVM.

Table 1. Device Summary

Device	Package Size	Description
TPS73201DRB	3-mm × 3-mm SON	Cap-Free, NMOS, 250-mA Low Dropout Regulator with Reverse Current Protection
TPS73601DRB	3-mm × 3-mm SON	Cap-Free, NMOS, 400-mA Low Dropout Regulator with Reverse Current Protection
TPS73701DRB	3-mm × 3-mm SON	1-A Low Dropout Regulator with Reverse Current Protection

1.1 Related Documentation from Texas Instruments

The following related documents are available through the Texas Instruments web site at <http://www.ti.com>.

Table 2. Related Documentation

Part Number	Literature Number
TPS73201	SBVS037
TPS73601	SBVS038
TPS73701	SBVS067

2 Setup

This section describes the jumpers and connectors on the EVM as well as how to properly connect, set up, and use the TPS73x01DRBEVM-518.

2.1 Input/Output Connector Descriptions

2.1.1 J1: VIN

This connector is the positive input supply voltage. The leads to the input supply should be twisted and kept as short as possible to minimize electromagnetic interference (EMI) transmission. Additional bulk capacitance should be added between J1 and J2 if the supply leads are greater than 6 inches (15,24 cm). An additional 47-μF or greater capacitor improves the transient response of the TPS73x01DRB and helps to reduce ringing on the input when long supply wires are used. The TPS73x01DRBEVM-518 has a footprint (C4) on the EVM available for this purpose.

2.1.2 J3: VOUT

This jumper is the positive connection from the output. Connect this pin to the positive input of the load.

2.1.3 J2: GND

This jumper is the return connection for the input power supply of the regulator.

2.1.4 J4: GND

This point is the return connection for the output.

2.1.5 JP1: ENABLE

This jumper is used to enable or disable the output of the TPS73x01DRB. Placing a shorting jumper between pins 1 and 2 (*ON* position) enables the TPS73x01DRB. Placing the shorting jumper between pins 2 and 3 (*OFF* position) disables the TPS73x01DRB.

2.1.6 JP2: V_{OUT} Selection

This jumper sets the desired output voltage from the TPS73x01DRB. Placing a shorting jumper between the appropriate pins gives the corresponding outputs.

WARNING

1. The Jumper JP2 should only be changed from one place to another when the power is off.
2. The user should not touch the jumper JP2 while the power is applied to the EVM since the output voltage may change due to the noise pick-up in the feedback path.

3 Operation

This section provides information about the operation of the TPS73x01DRBEVM.

3.1 Configuration and Initial Operation

Connect the positive input power supply to J1. Connect the input power return (ground) to J2. The TPS73x01DRB has an absolute maximum input voltage of 6.0 V. The recommended maximum operating voltage is 5.5 V. The actual highest input voltage may be less than 5.5 V as a result of thermal conditions. See the [Thermal Considerations](#) section of this manual to determine the highest input voltage for maintaining a safe junction temperature.

Connect the desired load between J3 (positive lead) and J4 (negative or return lead). Configure jumper JP2 for the desired output voltage.

4 Thermal Guidelines

This section presents guidelines for the thermal management of the TPS73x01DRBEVM-518 board.

4.1 Thermal Considerations

Thermal management is a key design component of any power converter, and is especially important when power dissipation in the LDO is high. To better help you design the TPS73x01DRB family into your applications, the following formula should be used to approximate the maximum power dissipation (P_{DMax}) at a particular ambient temperature:

$$T_J = T_A + P_D \times \theta_{JA} \quad (1)$$

where:

- T_J is the junction temperature
- T_A is the ambient temperature
- P_D is the power dissipation in the IC
- θ_{JA} is the thermal resistance from junction to ambient

All temperatures are in degrees Celsius.

The measured thermal resistance from junction to ambient for the TPS73x01EVM has a typical value of 40°C/W. The recommended maximum operating junction temperature specified in the product data sheet for the TPS73x01 family is +125°C. With these two pieces of information, the maximum power dissipation can be found by using Equation (1).

Example 1. Sample Calculation

What is the maximum input voltage that can be applied to a TPS73701DRB with a 1.8-V output voltage if the ambient temperature is +85°C and the full 1 A of load current is required?

Given:

$$T_J = +125^\circ\text{C}, T_A = +85^\circ\text{C}, \theta_{JA} = 40^\circ\text{C/W}$$

Using Equation 1, we substitute in the given values above and find that the maximum power dissipation for the part is $P_D = 1 \text{ W}$.

$$125^\circ\text{C} = 85^\circ\text{C} + P_D(40^\circ\text{C/W})$$

This result means that the total power dissipation of the TPS73701DRB must be less than 1 W. Now the input voltage can be calculated.

$$P_D = (V_{IN} - V_{OUT}) \times I_{OUT} = (V_{IN} - 1.8 \text{ V}) \times 1 \text{ A} = 1 \text{ W}$$

So the maximum input voltage would need to be 2.8 V or less in order to maintain a safe junction temperature.

Similar analysis can be performed to determine the maximum input voltage at room temperature (+25°C) or +85°C to provide full output current while maintaining the junction temperature at or below +125°C. The answer depends on the desired output voltage, as Table 3 shows.

Table 3. Maximum Input Voltage

Output Voltage V_{OUT}	TPS73701DRB		TPS73601DRB		TPS73201DRB	
	Ambient Temperature		Ambient Temperature		Ambient Temperature	
	+25°C	+85°C	+25°C ⁽¹⁾	+85°C	+25°C ⁽¹⁾	+85°C ⁽¹⁾
1.8 V	4.3 V	2.8 V	5.5 V	4.3 V	5.5 V	5.5 V
2.5 V	5.0 V	3.5 V	5.5 V	5.0 V	5.5 V	5.5 V
2.8 V	5.3 V	3.8 V	5.5 V	5.3 V	5.5 V	5.5 V
3.0 V	5.5 V	4.0 V	5.5 V	5.5 V	5.5 V	5.5 V
3.3 V	5.5 V ⁽¹⁾	4.3 V	5.5 V	5.5 V ⁽¹⁾	5.5 V	5.5 V

⁽¹⁾ Limited by recommended operating maximum temperature, not thermal resistance.

5 Board Layout, Schematic, and Parts List

This section provides the TPS73x01DRBEVM-518 board layout and illustrations. It also provides the TPS73x01DRBEVM-518 schematic and bill of materials.

5.1 PCB Layout

Figure 1 through Figure 4 show the layout for the TPS73x01DRBEVM-518 PCB.

NOTE: Board layouts are not to scale. These figures are intended to show how the board is laid out; they are not intended to be used for manufacturing TPS73x01DRBEVM-518 PCBs.




Figure 1. Assembly Layer




Figure 2. Top Layer Routing




Figure 3. Bottom Layer Assembly




Figure 4. Bottom Layer Routing

5.2 Schematic and BOM

Figure 5 illustrates the TPS73x01DRBEVM-518 schematic. Table 4 lists the bill of materials for this EVM.




Figure 5. TPS73x01DRBEVM-518 Schematic

Table 4. TPS73x01DRBEVM-518 Bill of Materials^{(1) (2) (3)}

-01	-02	-03	Ref Des ⁽⁴⁾	Value	Description	Size	Part Number	Mfr
1	1	1	C1	10 μ F	Capacitor, ceramic, 6.3 V, X5R, 10%	0603	Std	Std
1	1	1	C2	2.2 μ F	Capacitor, ceramic, 10 V, X5R, 10%	0603	Std	Std
0	0	0	C3	—	Capacitor, ceramic, 16 V, X5R, 10%	0603	Std	Std
0	0	0	C4	47 μ F	Capacitor, aluminum, 16 V, $\pm$ 20%	0.260 $\times$ 0.307 inch	EEEVFK1C470P	Panasonic
4	4	4	J1, J2, J3, J4	PEC02S AAN	Header, male 2-pin, 100-mil spacing	0.100 inch $\times$ 2	PEC02SAAN	Sullins
1	1	1	JP1	PEC03S AAN	Header, 3-pin, 100-mil spacing	0.100 inch $\times$ 3	PEC03SAAN	Sullins
1	1	1	JP2	PEC05D AAN	Header, male 2x5-pin, 100-mil spacing	0.100 inch $\times$ 5 $\times$ 2	PEC05DAAN	Sullins
1	1	1	R1	44.2 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	1	1	R2	88.7 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	1	1	R3	41.2 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	1	1	R4	33.2 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	1	1	R5	29.4 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	1	1	R6	25.5 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	0	0	U1	TPS7320 1DRB	IC, Cap-free, NMOS, 250-mA LDO regulator with reverse current Protection	QFN-8	TPS73201DRB	Texas Instruments
0	1	0	U1	TPS7360 1DRB	IC, Cap-free, NMOS, 400-mA LDO regulator with reverse current Protection	QFN-8	TPS73601DRB	Texas Instruments
0	0	1	U1	TPS7370 1DRB	IC, 1-A LDO regulator with reverse current protection	QFN-8	TPS73701DRB	Texas Instruments
2	2	2	—	—	Shunt, 100-mil black	0.1	929950-00	3M
1	1	1	N/A	—	PCB, FR-4, 2-layer, SMOBC, 1.620 in $\times$ 1.500 in $\times$.062 in	—	HPA518**	Any

⁽¹⁾ These assemblies are ESD sensitive. ESD precautions must be observed.

⁽²⁾ These assemblies must be clean and free from flux and all contaminants. Use of no-clean flux is not acceptable.

⁽³⁾ These assemblies must comply with workmanship standards IPC-A-610 Class 2.

⁽⁴⁾ Components can be substituted with equivalent manufacturer components except where indicated with **.

EVALUATION BOARD/KIT IMPORTANT NOTICE

Texas Instruments (TI) provides the enclosed product(s) under the following conditions:

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. Persons handling the product(s) must have electronics training and observe good engineering practice standards. As such, the goods being provided are not intended to be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including product safety and environmental measures typically found in end products that incorporate such semiconductor components or circuit boards. This evaluation board/kit does not fall within the scope of the European Union directives regarding electromagnetic compatibility, restricted substances (RoHS), recycling (WEEE), FCC, CE or UL, and therefore may not meet the technical requirements of these directives or other related directives.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE.

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge.

EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

TI currently deals with a variety of customers for products, and therefore our arrangement with the user **is not exclusive**.

TI assumes **no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein**.

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please contact the TI application engineer or visit www.ti.com/esh.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used.

FCC Warning

This evaluation board/kit is intended for use for **ENGINEERING DEVELOPMENT, DEMONSTRATION, OR EVALUATION PURPOSES ONLY** and is not considered by TI to be a finished end-product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC rules, which are designed to provide reasonable protection against radio frequency interference. Operation of this equipment in other environments may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

EVM WARNINGS AND RESTRICTIONS

It is important to operate this EVM within the input voltage range of 1.7 V to 5.5 V and the output voltage range of 1.2 V to 3.3 V.

Exceeding the specified input range may cause unexpected operation and/or irreversible damage to the EVM. If there are questions concerning the input range, please contact a TI field representative prior to connecting the input power.

Applying loads outside of the specified output range may result in unintended operation and/or possible permanent damage to the EVM. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative.

During normal operation, some circuit components may have case temperatures greater than +85°C. The EVM is designed to operate properly with certain components above +85°C as long as the input and output ranges are maintained. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors. These types of devices can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during operation, please be aware that these devices may be very warm to the touch.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2009, Texas Instruments Incorporated



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.