MACX MCR-EX-SL-NAM-2RO(-SP)

Intrinsically safe NAMUR isolating amplifier with two relay outputs

INTERFACE

Data sheet 103465_en_00

© PHOENIX CONTACT - 08/2008

1 Description

The NAMUR **MACX MCR-EX-SL-NAM-2RO(-SP)** isolating amplifier has been designed for intrinsically safe operation of the proximity sensors (as per EN 60947-5-6 (NAMUR)) and the floating and resistance circuit mechanical contacts installed in the Ex area.

The input circuit is monitored for line faults (breakage and short circuit (LFD)) (can be switched on/off). Errors are indicated via a red flashing LED (as per NE 44) and the relevant output relay is de-energized. Error messages are also transmitted to the power and error evaluation module via the DIN rail connector.

The output side has two N/O contact relays. Both can be operated as signal outputs. Output 2 can also be used as an error message output (can be adjusted via the DIP switch). The switch can be used to set the direction (open or closed circuit current behavior). The relay status is indicated via a yellow LED. The modules can be installed in zone 2 with the "n" (EN 60079-15) protection type.

1.1 Properties

- Input for NAMUR proximity sensor or switch, [Ex ia] IIC
- Two relay signal outputs (N/O contact); output 2 can be used as an error message output
- Line fault detection (LFD)
- Option of phase reversal
- 3-way electrical isolation
- SIL 2 according to EN 61508
- Installation in Zone 2 permissible
- Power supply and error message possible via the DIN rail connector

INSPIRING INNOVATIONS

 With screw (MACX MCR-EX-SL-NAM-2RO) or spring-cage connection (MACX MCR-EX-SL-NAM-2RO-SP)

	λ	
	!	Λ.
_		

WARNING: Explosion hazard

The module is an associated item of electrical equipment for intrinsically safe circuits. It is designed for use in zone 2, if specific conditions are observed.

When installing and operating the device, the applicable safety directives (including national safety directives), accident prevention regulations, as well as general technical regulations, must be observed.

\triangle	WARNING: Explosion hazard Be sure to observe the safety regulations and installation notes on page 5.
i	Make sure you always use the latest documentation. It can be downloaded at <u>www.download.phoenixcontact.com</u> .
	A conversion table is available on the Internet at <u>www.download.phoenixcontact.com/general/7000_en_00.pdf</u> .
i	This data sheet is valid for all products listed on the following page:



Table of contents

1	Description	. 1
2	Ordering data	. 2
3	Technical data	. 2
4	Safety regulations and installation notes	. 5
5	Installation	. 6
6	Configuration	. 8
7	Comparison of safety data	10
8	Switch on	10
9	Safety-related applications (SIL 2)	11

2 Ordering data

NAMUR isolating amplifiers

Description	Туре	Order No.	Pcs./Pkt.
Intrinsically safe NAMUR isolating amplifier, with two relay outputs and screw connection	MACX MCR-EX-SL-NAM-2RO	2865450	1
Intrinsically safe NAMUR isolating amplifier, with two relay outputs and spring-cage connection	MACX MCR-EX-SL-NAM-2RO-SP	2924061	1
Accessories			
Description	Туре	Order No.	Pcs./Pkt.
DIN rail connector (T-BUS), 5-pos., for bridging the supply voltage, can be snapped onto NS 35/ DIN rails according to EN 60715	ME 6.2 TBUS-2 1.5/5-ST-3.81 GN	2869728	10
Power and error evaluation module, including the relevant DIN rail connector ME 17.5 TBUS 1.5/5-ST-3.81 GN			
Screw connection Spring-cage connection	MACX MCR-PTB MACX MCR-PTB-SP	2865625 2924184	1 1
For additional accessories, please refer to the "INTERFACE" cat	alog from Phoenix Contact.		

3 Technical data

Input	
Input	Intrinsically safe, designed for protection type Ex-i [Ex ia] IIC
Available input sources	 NAMUR proximity switches according to EN 60947-5-6 or Switch contacts with open circuit (not for safety-related applications, SIL 2) or Switch contacts with resistance circuit
Switching hysteresis	< 0.2 mA

Control circuit	
Non-load voltage	8 V DC ±10%
Switching points according to EN 60947-5-6	I < 1.2 mA (blocking)
	I > 2.1 mA (conductive)
Line fault detection	Break 0.05 mA < I _{IN} < 0.35 mA
	Short circuit 100 Ω < R _{sensor} < 360 Ω
	Activated/deactivated via DIP switch
Switching output	
Switching output	Relay, 2 x N/O contacts
Switching behavior	Can be inverted using DIP switch
Switching frequency	20 Hz (without load)
Maximum switching voltage	250 V AC (2 A) 120 V DC (0.2 A) 30 V (2 A)
Maximum switching power	500 VA
Contact material	AgSnO ₂ , gold-plated
Service life	
Mechanical	10 ⁷ cycles
Recommended minimum load	5 V/10 mA
General data	
Supply voltage range	19.2 V DC 30 V DC
Current consumption, maximum	30 mA (24 V DC)
Power dissipation	< 950 mW
Electrical isolation	
Input/output	375 V (peak value according to EN 60079-11)
Input/power supply	375 V (peak value according to EN 60079-11)
Input/power supply, DIN rail connector	300 V _{rms} (rated insulation voltage, surge voltage category II, pollution degree 2, safe isolation as per EN 61010, EN 50178) 1.5 kV AC (50 Hz, 1 min., test voltage)
Output 1/output 2/input, power supply, DIN rail connector	300 Vrms (rated insulation voltage, surge voltage category III; pollution degree 2, safe isolation as per EN 61010, EN 50178) 2.5 kV AC (50 Hz, 1 min., test voltage)
Ambient temperature	
Operation	-20°C +60°C (any mounting position)
Storage/transport	-40°C +80°C
Permissible humidity (operation)	10% 95% (no condensation)
Status indicator	Green LED (PWR, supply voltage)
	Red LED (LE, line errors)
	Yellow LED (OUT, switching state)
Housing material	PBT
Color	Green
Degree of protection	IP20
Width x length x height	12.5 mm x 114.5 mm x 104 mm (with connection terminal block)
Inflammability class according to UL 94	VO
Design	Terminal block housing for mounting on DIN rails
Conformance	
EMC directive 2004/108/EC	EN 61000-6-2, EN 61000-6-4, EN 61326-1
Ex directive (ATEX)	EN 60079-0, EN 60079-11, EN 60079-15

Safety data according to ATEX for intrinsically safe circ	cuits
Maximum voltage U _o	9.6 V
Maximum current I _o	10 mA
Maximum power P _o	25 mW
Maximum inner inductance L _i	Negligible
Maximum inner capacitance C _i	11 nF
Gas group	IIC IIB
Maximum external inductance L _o	100 mH 5 mH 1 mH 10 μ H 100 mH 5 mH 1 mH 10 μ H
Maximum external capacitance Co	510 nF 840 nF 1.2 μF 3.6 μF 2.7 μF 4.4 μF 6.3 μF 26 μF
Safety-related maximum voltage Um	253 V AC (125 V DC)
Certificates	
ATEX	🖼 II (1) GD [Ex ia] IIC, IIB IBExU 07 ATEX 1069
	₩ II (3) G Ex nAC II T4 X
IECEx approval	[Ex ia] IIC; [Ex ia D]; Ex nAC IIC T4
	IECEX IBE 08.0001X
UL USA/Canada	Applied for
Functional safety (SIL)	SIL 2 according to EN 61508
Connection data MACX MCR-EX-SL-NAM-2RO	
Conductor cross-section	
Solid (minimum/maximum)	$0.2 \text{ mm}^2/2.5 \text{ mm}^2$
Stranded (minimum/maximum)	$0.2 \text{ mm}^2/2.5 \text{ mm}^2$
AWG/kcmil (minimum/maximum)	24/14
Stripping length	7 mm
Connection method	Pluggable screw connection
Tightening torque	0.5 Nm, minimum/0.6 Nm, maximum
Connection data MACX MCR-EX-SL-NAM-2RO-SP	
Conductor cross-section	
Solid (minimum/maximum)	0.2 mm ² /1.5 mm ²
Stranded (minimum/maximum)	0.2 mm ² /1.5 mm ²
AWG/kcmil (minimum/maximum)	24/16
Stripping length	8 mm
Connection method	Spring-cage connection

4 Safety regulations and installation notes

4.1 Installation and operation

Follow the installation instructions.



NOTE: Installation, operation, and maintenance may only be carried out by qualified specialist personnel.

When installing and operating the device, the applicable safety directives (including national safety directives), accident prevention regulations, as well as general technical regulations must be observed.



NOTE: The circuits inside the device must not be accessed.

Do not repair the device yourself, but replace it with an equivalent device. Repairs may only be carried out by the manufacturer.



NOTE: The device is designed to meet IP20 protection when:

- It is installed outside potentially explosive areas.
- The environment is clean and dry.

Install the device in a suitable housing with a suitable degree of protection in accordance with IEC 60529 in order to protect it from mechanical and electrical damage.

For the safety data, please refer to the operating instructions and certificates (EC type-examination, other approvals, if necessary).



NOTE: The load connected to the relay outputs should be limited to the values listed in the technical data.

4.2 Safety regulations for installation in potentially explosive areas

Regulations for intrinsically safe circuits



WARNING: Explosion hazard

When carrying out **measurements** on the intrinsically safe side, be sure to observe the relevant regulations regarding the connection of intrinsically safe equipment.

Only use devices approved for use in intrinsically safe circuits.



WARNING: Explosion hazard

If the **device has been used in nonintrinsically safe circuits,** it must **not** be used again in intrinsically safe circuits. Clearly label the module as being non-intrinsically safe.

Installation in Zone 2



WARNING: Explosion hazard

The device is associated equipment of the "Ex-i" protection type and suitable for installation in Zone 2.

Observe the specified conditions for use in potentially explosive areas.



WARNING: Explosion hazard

Install the device in suitable **housing with a minimum of IP54 degree of protection**. Observe the requirements of IEC 60079-14/ EN 60079-14, e.g., steel housing with a wall thickness of 3 mm.



WARNING: Explosion hazard

Disconnect the block power supply before:

- Snapping it on or disconnecting it.
- Connecting or disconnecting cables of nonintrinsically safe circuits.



WARNING: Explosion hazard

Only use category 3G modules (ATEX 94/9/EC).

Installation in areas with a danger of dust explosions



WARNING: Explosion hazard The device is **not** designed for installation in

areas with a danger of dust explosions.

Connection to the **intrinsically safe circuit in areas with a danger of dust explosions** (zones 20, 21, and 22) is **only** permitted if the equipment connected to this circuit is approved for this zone (e.g., category 1D, 2D or 3D). 4.3 Use in safety-related applications (SIL 2)

When using the MACX MCR-EX-SL-NAM-2RO(-SP) in safety-related applications, observe the instructions in Section 9, as the requirements differ for safety-related functions.

5 Installation



NOTE: Electrostatic discharge

The device contains components that can be damaged or destroyed by electrostatic discharge. When handling the device, observe the necessary safety precautions against electrostatic discharge (ESD) according to EN 61340-5-1 and EN 61340-5-2.

5.1 Basic circuit diagram



Figure 1 Basic circuit diagram with connection terminal blocks





Figure 2 Design

- 1 COMBICON plug connectors
- 2 PWR LED (green), for indicating the power supply
- 3 LED LF1/LF2 (red), for indicating line faults on the sensor cable
- 4 LED OUT1 (yellow), for indicating switching state of relay output 1
- 5 LED OUT2 (yellow), for indicating switching state of relay output 2
- 6 Switch DIP1 ... DIP4
- 7 Metal lock for fixing on the DIN rail
- 8 Connection option for DIN rail connector

5.3 Dimensions



5.4 Mounting

\triangle

WARNING: Explosion hazard

If the **module has been used in non**intrinsically safe circuits, it must **not** be used again in intrinsically safe circuits.

Clearly label the module as being non-intrinsically safe.



Figure 4 Assembly and removal

- Mount the module on a 35 mm DIN rail according to EN 60715.
- When using the DIN rail connector, first place it into the DIN rail (see A – C, Figure 4). It is used to bridge the voltage supply and for error messages.
 Please also ensure you observe the direction of the module and DIN rail connector when snapping into position:

Snap-on foot below (2) and connector left (1).

- Install the module in suitable housing to meet the requirements for the protection class.
- Before startup, check that the NAMUR isolating amplifier is operating and wired correctly, especially with regard to the wiring and labeling of the intrinsically safe circuits.

5.5 Connecting the cables

- Pluggable screw terminal blocks (on MACX MCR-EX-SL-NAM-2RO); litz wires provided with ferrules.
- Pluggable spring-cage terminal blocks (on MACX MCR-EX-SL-NAM-2RO-SP); litz wires provided with ferrules.
- Lay intrinsically safe and non-intrinsically safe cables separately.
- Permissible cable cross-section: 0.2 mm² to 2.5 mm².

– Screw connection:

- Insert the wire into the corresponding connection terminal block.
- Use a screwdriver to tighten the screw in the opening above the connection terminal block.

- Spring-cage connection:

- Insert a screwdriver in the opening above the connection terminal block.
- Insert the wire into the corresponding connection terminal block.

5.6 Voltage supply

modules.

NOTE: Never connect the supply voltage directly to the DIN rail connector. It is not permitted to draw power from the DIN rail connector or from individual MACX-MCR-EX

The modules can be powered via the connection terminal blocks 1.1 (+24 V) and 1.2 (GND) or via the DIN rail connector (ME 6.2 TBUS-..., order no. 2869728).

Depending on the number of modules to be powered, the voltage is either fed via the

MACX MCR-EX-SL-NAM-2RO(-SP) or the power and error evaluation module MACX MCR-PTB(-SP) on the DIN rail connector.

Supply via the module

Where the total current consumption of the aligned modules does not exceed 400 mA, the power can be supplied directly at the connection terminal blocks of the module. A 400 mA fuse should be connected upstream.

The voltage supply is provided at the connection terminal blocks 1.1 (+24 V) and 1.2 (GND).

Infeed via the power and error evaluation module MACX MCR-PTB(-SP)

The supply voltage is fed in via the module MACX MCR-PTB(-SP) to the DIN rail connectors. The supply voltage can be provided as either simple or redundant.

The module MACX MCR-PTB(-SP) has integrated error evaluation. An auxiliary supply failure or fuse error is registered to a relay contact and displayed via a flashing LED.

Collection line faults of all modules connected via the DIN rail connectors are also signaled.

6 Configuration

In the default state upon delivery, all DIP switches are set to the position "I".



(Not permitted for safety-related applications, SIL 2)

6.1 Line fault detection (switch DIP2)

WARNING: For safety-related applications, **only** the switch position "**DIP2 = II**" is **permitted**.

Line fault detection is enabled or disabled using switch DIP2. When line fault detection is enabled, the relay drops out in the event of a cable interrupt or short circuit to the sensor so that the output is set to the safe, non-conductive state. The red LED (LF) flashes.

Operating range for the

via floating relay output.

- Cable break alarm $50 \ \mu\text{A} > \text{I} > 350 \ \mu\text{A}$
- Short circuit alarm $100 \Omega > R > 360 \Omega$

If the module is connected to a power module MACX MCR-PTB(-SP) via a DIN rail connector, a group error message is also sent to the higher-level evaluation unit



NOTE: For **switch contacts with open circuit** (Figure 5), line fault detection (DIP2 = I) must be disabled or the corresponding resistance circuit must be provided directly at the switch contact (Figure 6, e. g. UKK 5-2R/NAMUR (Order No. 2941662) with D-UKK 3/5 (Order No. 2770024)).





circuit

with resistance

Figure 5 Switch contact with open circuit

(Not permitted for safety-related applications, SIL 2)

6.2 Phase reversal (switch DIP1)

The phase reversal function is enabled or disabled using switch DIP1.

Output relay	Normal phase (I)	Inverted phase (II)	
Switched if	l > 2.1 mA	l < 1.2 mA	
In normal position when	l < 1.2 mA	l > 2.1 mA	

6.3 Output OUT2 (switch DIP3/DIP4)



DIP4 Operating mode OUT2 = II Signal duplicator

= I Error indicator

= || = ||

Disabled

6.4 Truth table



WARNING: For safety-related applications, **only** the switch position "**DIP2 = II**" is **permitted**.

WARNING: Only switch contacts with resistance circuit are **permitted** at the input for safety-related applications (see Figure 6).

	Sensor in Input Input circuit			D	IP	Relay contact output (N/O contact)				LED	LF
						OUT1	OUT2			OUT	LED
	Switch	NAMUR	State	1	2		Signal duplicator	Error indicator	Disconnected	Yellow	Red
	Open	Blocking	OK	-	Ι	Open	Open	Open	Open		
WR R	Closed	Conductive	OK	-	Ι	Closed	Closed	Open	Open	Х	
ex-s	Open	Blocking	OK	=	Η	Closed	Closed	Open	Open	Х	
ICH III	Closed	Conductive	OK		Ι	Open	Open	Open	Open		
PCK P		Blocking	OK	Ι	II	Open	Open	Open	Open		
		Conductive	OK	-	=	Closed	Closed	Open	Open	Х	
		Any	Open circuit	Ι	=	Open	Open	Closed	Open		Х
		Any	Short circuit	I	II	Open	Open	Closed	Open		Х
41 5.2 5.1		Blocking	OK	II	II	Closed	Closed	Open	Open	Х	
1		Conductive	OK	Ш	Π	Open	Open	Open	Open		
ſ		Any	Open circuit	II	II	Open	Open	Closed	Open		Х
		Any	Short circuit	Ш	Π	Open	Open	Closed	Open		Х

DIP2 = I	Line fault detection disabled (not permitted for safety-related applications, SIL 2)
DIP2 = II	Line fault detection enabled
DIP1 = I	Normal phase
DIP1 = II	Inverted phase
DIP4 = II	Signal duplicator
$DIP\;3=II+DIP4=I$	Error indicator
DIP3 = II + DIP4 = II	Disabled

PWR LED = Supply voltage

LED OUT1 = Switching state of relay output 1 LED OUT2 = Switching state of relay output 2

LF LED = Line fault on the sensor cable

7 Comparison of safety data



WARNING: Explosion hazard

Compare the safety data before connecting a module located in the intrinsically safe area to the MACX MCR-EX-SL-NAM-2RO(-SP).

Safety data for

Field devices: Isolation amplifier: U_{i,} I_{i,} P_i, L_i, C_i U_{o,} I_{o,} P_o, L_o, C_o

For the values for U_o , I_o , P_o , L_o and C_o , please refer to "Safety data according to ATEX for intrinsically safe circuits" on page 4.

Requirements for intrinsic safety (simple circuits):

 $U_i \ge U_o$ $I_i \ge I_o$

 $\boldsymbol{P}_i \geq \boldsymbol{P}_o$

 $L_i + L_c \leq L_o$

 $\boldsymbol{C}_i + \boldsymbol{C}_c \leq \boldsymbol{C}_o$

(L_c and C_c depend on the cables/lines used).

8 Switch on

NOTE: Around 5 seconds after switching on the main power, the module is ready for use. It depends on the operating conditions as to whether the module reaches its specified accuracy immediately or whether there is a warm-up period.

The greatest possible accuracy is achieved when the unit has been running for around 2 hours.

9 Safety-related applications (SIL 2)

9.1 Wiring

Input

Permitted for safety-related applications:

- NAMUR sensor (according to EN 60947-5-6)
- Switch contact with resistance circuit (1 k Ω serial and 10 k Ω parallel (tolerance ±10%)) (Note: The resistance circuit regulates the behavior of a

NAMUR sensor)

WARNING: Switch contacts without resistance circuit are not permitted for safety-related applications.

Output

The safety-related function at the output is dependent on the position of switch DIP1.

- I = Normal In the event of a 0-signal (NAMUR sensor operation high resistance, therefore lower current in the input circuit) the output (N/O contact) switches to the "non-conductive" state.
- II = Inverse In the event of a 1-signal at the input, the function output switches to the "non-conductive" state.

9.2 Diagnostic function of switch DIP2

For safety applications, line fault detection is enabled, i.e., the DIP2 switch is in the "II" position.



WARNING: The "DIP 2 = I" switch position is **not** permitted for safety-related applications.

When line fault detection is enabled, the red LED indicates any faults that occur. If a line fault is detected, the output is disabled ("non-conductive"). This behavior is not dependent on the position of the DIP1, DIP3 and DIP4 switches.

9.3 Safe state

The "safe state" means that the output is in a non-conductive state, i.e., the relay contact is open.

9.4 **Response times**

Following a state change at the input, the output enters the safe state in \leq 40 ms.

9.5 Operating mode of the safety function

Operating mode as per EN 61508: "Low demand mode"

Failure behavior and required response 9.6

- 1. The safe state is entered in the event that a line fault is detected or the supply voltage fails (see Section 9.3).
- 2. The safe state is reached by removing the connection terminal blocks.

Startup and restart

Behavior	Description
Startup or restart of the device	The output enters the state without oscillation (according to the truth table on page 9). A reset is not required.
What happens when a line fault is detected and what must the user do?	The fault is indicated by the red LED and the output enters the "non-conductive" state regardless of the input signal and the operating mode (normal or inverse mode). The user must remove the line fault (short circuit or break in the sensor cable). The device output is not blocked when fault detection is triggered (no lock or reset). Undefined line states that occur during repairs can switch the output. The user must prevent this from happening by disconnecting the supply voltage or removing the connection terminal blocks. Other options that have the same result and do not present an additional hazard are permitted.
The line fault is removed.	The user must ensure that a defined state is entered using the truth table on page 9. The device is restarted in the same way as during initial startup. The device then behaves as described under "Startup or restart of the device".

9.7 Safety integrity requirements

Failure rates

- Type A device (according to EN 61508-2)
- Safety Integrity Level (SIL) 1 and 2

Non-inverted operation:

λ_{sd}	λ _{su} *	λ_{dd}	λ_{du}	SFF [†]	DC_S^{\ddagger}	DC _D ‡
6 FIT**	249 FIT	7 FIT	64 FIT	78%	2.4%	9%

- * The SU (Safe Undetected) category includes failures that do not cause a spurious trip.
- [†] SFF = Safe Failure Fraction
- [‡] DC = **D**iagnostic **C**overage (safe or dangerous)
- ^{**} FIT = Failure in Time (1 FIT = 1 failure/ 10^9 h)

PFD_{AVG} values

T[PROOF] =	1 year	2 years	5 years
PFD _{AVG} * =	3.09E-04	6.17E-04	1.54E-03

PFD = Probability of Failure on Demand

Inverted operation:

λ_{sd}	λ_{su}^{*}	λ_{dd}	λ_{du}	SFF [†]	DC_S^{\ddagger}	DC _D ‡
1 FIT**	248 FIT	6 FIT	62 FIT	78%	0.4%	8%

The SU (Safe Undetected) category includes failures that do not cause a spurious trip.

- [†] SFF = **S**afe **F**ailure **F**raction
- [‡] DC = **D**iagnostic **C**overage
- ^{**} FIT = **F**ailure in **T**ime (1 FIT = 1 failure/ 10^9 h)

PFD_{AVG} values

T[PROOF] =	1 year	2 years	5 years
PFD _{AVG} * =	3.01E-04	6.02E-04	1.50E-03

* PFD = Probability of Failure on Demand

The boxes marked in white mean that the calculated PFD_{AVG} values are within the allowed range for SIL 2 according to table 2 of EN 61508-1, but do not fulfill the requirement to not claim more than 10% of this range, i.e., to be better than or equal to 1.00E-03.

The boxes marked in gray mean that the calculated PFD_{AVG} values are within the allowed range for SIL 2 according to table 2 of EN 61508-1, and do fulfill the requirement to not claim more than 10% of this range, i.e., to be better than or equal to 1.00E-03.

Failure limit

The operating mode is based on low demand mode. The percentage of the device at PFH/PFD for the overall safety loop is less than 10%.



Figure 7 Safety loop

Conditions

- The failure rates of the components used remain constant throughout the period of use.
- Propagation of errors by the device in the system is not taken into consideration.
- The repair time (= replacement) should take eight hours.
- The failure rates of the external power supply are not taken into consideration.
- The average temperature at which the device is to be used is +40°C. This is based on standard industrial conditions.

The failure rates given refer to an ambient temperature of $+40^{\circ}$ C. For an ambient temperature of $+60^{\circ}$ C, you will need to multiply the failure rates by a factor of 2.5. The factor of 2.5 is based on empirical values gathered.

9.8 Proof test

- 1. Carry out the appropriate steps to prevent incorrect use.
- 2. An appropriate signal is applied at the input of the MACX MCR-EX-SL-NAM-2RO in order to obtain the non-conductive state at the output. Check whether the output is non-conductive.
- 3. Restore the safety circuit to full functionality.
- 4. Return to normal operation.

With this test, around 99% of possible "du" ("dangerous undetected") errors are uncovered in the repeater power supply.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный) Факс: 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.