

DOGM240-6 GRAPHIC

Issue 5.2019

240x64 INCL. CONTROLLER UC1611s

available in low quantities !
flat: 6.5mm with LED b./l. mounted

EA DOGM240W-6 +
EA LED94X40-W



EA DOGM240B-6 +
EA LED94X40-W



EA DOGM240W-6 +
EA LED94X40-A

TECHNICAL DATA

- * CONTROLLER UC1611s WITH INTEGRATED GRAFIC-RAM
- * HIGH-CONTRAST LCD SUPERTWIST DISPLAY (STN AND FSTN) WITH 15µm DOT GAP
- * OPTIONAL LED BACKLIGHTS IN VARIOUS COLORS
- * 240x64 DOTS (CORRESPONDS TO 8x40 CHARS OR 4x20 LARGE CHARS)
- * POWER SUPPLY: SINGLE SUPPLY 2,7..3,3V (typ. 500 µA)
- * NO ADDITIONAL VOLTAGES REQUIRED
- * THREE DIFFERENT INTERFACES: 3-WIRE SPI, 4-WIRE SPI AND I²C
- * OPERATING TEMPERATURE RANGE -20..+70°C (STORAGE -30..+80°C)
- * LED BACKLIGHTING 10 to 150mA
- * NO MOUNTING REQUIRED: SIMPLY SOLDER ONTO PCB

ORDERING CODE

GRAPHICS DISPLAY, 240x64, 94x40 mm

x: W = white background (FSTN pos. transfective)

B = blue background (STN neg. transmissive)

S = black background (FSTN neg. transmissive)

N = superwhite background (FSTN pos. reflective, cannot be backlit)

LED BACKLIGHT, WHITE

LED BACKLIGHT, AMBER

LED BACKLIGHT, DUO COLOR GREEN/RED

LED BACKLIGHT, 3 COLORS GREEN/RED/WHITE

EA DOGM240x-6

EA LED94X40-W

EA LED94X40-A

EA LED94X40-GR

EA LED94X40-ERW

ACCESSORIES

USB TEST BOARD FOR PC (WINDOWS 2000, XP, VISTA)

TOUCH PANEL, 4-WIRE, ANALOG, STICK-ON

ZIF CONNECTOR FOR TOUCH PANEL, BOTTOM CONTACT

10 CHARACTER SETS e.g. 6x8,8x8,8x16,CYRILLIC, FONT EDITOR

SOCKET 4.8mm HEIGHT (2 pcs. ARE NECESSARY)

EA 9780-4USB

EA TOUCH240-4

EA WF100-04S

EA USBSTICK-FONT

EA FL-20P

PINOUT

The EA DOGM240-6, a 240x64 dots graphics display, is a new addition to ELECTRONIC ASSEMBLY's EA DOG series. It, too, has pins that allow it to be mounted quickly and easily.

CONTRAST ADJUSTMENT

The contrast can be set by means of a command for all the displays in the EA DOGM- Series. The contrast setting of the display must be set once by the software, and is then kept constant throughout the entire operating temperature range (-20..+70°C), thanks to the integrated temperature compensation.

| Pin | Symbol | Level Function | Pin | Symbol | Level Function |
|-----|--------|----------------------|-----|----------|-------------------------------|
| 1 | NC | (A1+: LED backlight) | 21 | VB0+ | - Voltage Converter |
| 2 | NC | (A2+: LED backlight) | 22 | VB1+ | - Voltage Converter |
| 3 | NC | (A3+: LED backlight) | 23 | VB1- | - Voltage Converter |
| 4 | | | 24 | VB0- | - Voltage Converter |
| 5 | | | 25 | VA0+ | - Voltage Converter |
| 6 | | | 26 | VA1+ | - Voltage Converter |
| 7 | | | 27 | VA1- | - Voltage Converter |
| 8 | | | 28 | VA0- | - Voltage Converter |
| 9 | | | 29 | VLCD | - Power LC Drive |
| 10 | | | 30 | VDD | H Power Supply +2,7..3,3V |
| 11 | | | 31 | VSS | L Power Supply 0V (GND) |
| 12 | | | 32 | VSS | |
| 13 | | | 33 | BM0 | H / L Config Serial Interface |
| 14 | | | 34 | CD | H / L L= Command, H= Data |
| 15 | | | 35 | CS1 (A3) | H Chip Select (high low) |
| 16 | | | 36 | CS0 (A2) | L Chip Select (active low) |
| 17 | | | 37 | RST | L Reset (active low) |
| 18 | NC | (C1-: LED backlight) | 38 | SCK (D0) | H / L Serial Clock |
| 19 | NC | (C2-: LED backlight) | 39 | SDA (D3) | H / L Serial Data |
| 20 | NC | (C3-: LED backlight) | 40 | D13 | H / L Config Serial Interface |





CHARACTER SET AND FONT EDITOR (ACCESSORY)

With the ordering code EA USBSTICK-FONT a memory stick comes with various character sets, especially made for this display. An import function allows additionally to use Windows fonts. With the FontEditor it is easy to generate for example Cyrillic, Greek and Arabic fonts. The preview function shows immediately the size and style in simulation window.

When the testboard EA 9780-4USB is connected to the USB port, you can see the character (or any predefined text) live on the display !

4 DIFFERENT TECHNOLOGIES

See below for an overview of available technologies STN and FSTN. See also an recommendation to combine with backlights and their usability:

| Displaytyp | Technologie | optionale Beleuchtung | Lesbarkeit | Displayfarbe unbeleuchtet | Displayfarbe mit Beleuchtung | empfohlene Beleuchtung |
|--|---------------------------|--|-------------------------------------|---------------------------|---|------------------------|
|  | FSTN pos. transflektiv | mit und ohne Beleuchtungskörper zu verwenden | auch bei abgeschalteter Bel. lesbar | schwarz auf weiß | schwarz auf Beleuchtungsfarbe | alle |
|  | STN neg. blau transmissiv | nur beleuchtet zu verwenden | --- | --- | Beleuchtungsfarbe auf blauem Hintergrund | weiß, amber |
|  | FSTN neg. transmissiv | nur beleuchtet zu verwenden | --- | --- | Beleuchtungsfarbe auf schwarzem Hintergrund | alle |
|  | FSTN pos. reflektiv | keine Beleuchtung möglich | ohne Beleuchtung bestens lesbar | schwarz auf weiß | --- | --- |

4 DIFFERENT BACKLIGHTS


Four different backlight types are available to match equipments design as much as possible. Incl. 2- and 3-color green/red. The most effective and brightest one is the white one EA LED94X40-W.



| LED backlight (each path) | Forward voltage | Current max. |
|-------------------------------|--------------------|-----------------|
| | typ | |
| white EA LED94x40-W | 6.4 V | 15 mA |

EA LED94X49-W (white) - the super bright one


With the white backlight, there are 3 separate LED paths containing 2 LEDs in series each. We are using high-quality LEDs from NICHIA. To operate the backlight with longest life time, we recommend a current source (e.g. CAT4238TD). Life time typ. 80,000 hours.



| LED backlight (each path) | Forward voltage | Current | Limiting resistor (ohm) | |
|-------------------------------|--------------------|---------|----------------------------|------|
| | typ | | @3,3 V | @5 V |
| amber EA LED94x40-A | 2.1 V | 80 mA | 18 | 39 |

EA LED94X40-A (amber) - the cost effective one


With the amber backlight, there are 3 separate LED paths containing 4 parallel LEDs, that can be switched in parallel or in series to suit the system's voltage. Life time typ. 100,000 hours.



| LED backlight (each color) | Forward voltage | Current | Limiting resistor (ohm) |
|-------------------------------|--------------------|---------|-------------------------------|
| | typ | | |
| full color EA LED94x40-GR | 2.1 V | 120 mA | 25 |

EA LED94X40-GR (green/red) - for warnings


The duo-color backlight has common anode and two terminals for driving the red and / or the green color. Life time typ. 100,000 hours.



EA LED94X40-ERW (green/red/white) - the versatile


Bright white LEDs (brand: NICHIA) providing best readability under all conditions. The 3-color backlight has common anode (AERW) and three terminals for driving the red , green and white LED path. Life time typ. 80,000 hours.

| LED backlight color | Forward voltage | Current | Limiting resistor (ohm) |
|------------------------|--------------------|---------|-------------------------------|
| | typ | | |
| Green | 3.0 V | 90 mA | 24 |
| Red | 2.1 V | 90 mA | 33 |
| White | 3.0 V | 90 mA | 24 |



APPLICATION EXAMPLE LED DRIVER FOR 3.3V

Based on white backlight EA LED94x40-W with the help of current source CAT4238.



Important: Do never connect the backlight LEDs directly to a 5V/3.3V supply as this may immediately destroy the LEDs. Please note that derating applies at temperatures exceeding +25°C.

USB-TEST BOARD EA 9780-4USB

For easy startup, an USB test board is available that can be connected to a PC. It comes with an USB cable and a Windows software. This allows text and images (BMP) to be displayed directly on the plugged-in display. You will find more information on the test board in the EA 9780-4USB's data sheet.



SIMULATION WITH WINDOWS


A simulator window also displays the contents of the display. The software can simulate all the displays and colors even without the hardware. You can download the software for free from our website:

https://www.lcd-module.de/fileadmin/downloads/startdog_v45.zip

SOCKET EA FL-20P

With the help of the single-row female connector stripe EA FL20-P the mounting of the display is detachable. In addition the overall height can be adjusted.

2 pieces are required each display!



DATA TRANSFER

The EA DOGM240-6 supports three serial modes. The data transfer of the two SPI-Modes is unidirectional, that means data can only be written, not read back. Compared to other displays, a busy query is not necessary. The clock-pulse rate of the CLK line can be up to 8MHz, depending on the supply voltage and interface mode.

More detailed information on timing can be found on page 64 to 66 of the data sheet of the UC1611s controller on our website at http://www.lcd-module.de/fileadmin/eng/pdf/zubehoer/uc1611s_v1_0.pdf



| Serial Modes | | |
|--------------|-----|-------------------|
| BM0 | D13 | Description |
| 0 | 0 | 4-wire, 8-Bit SPI |
| 1 | 0 | 3-wire, 9-Bit SPI |
| 1 | 1 | 2-wire, I2C |

4 WIRE, 8-BIT SPI-MODE

Falling edge on Pin CS0 (or rising edge on PIN CS1) is used for chip select and bus cycle reset. During each write cycle, 8 bits of data, MSB first, are latched on eight rising CLK edges into an 8-bit data holder.

If CD=0 (reading at D0), the byte will be decoded as command. If CD=1, this 8-bit will be treated as data byte.



The clock-pulse rate of the CLK line can be up to 8 MHz, depending on power supply and wiring.



3 WIRE, 9-BIT SPI-MODE

Falling edge on PIN CS0 (or rising edge on PIN CS1) is used for chip select and bus cycle reset. First of all the CD-Bit is transferred to select whether data (H) or command (L) is followed up within the next 8 bit (MSB first)

The clock-pulse rate of the CLK line can be up to 8 MHz, depending on power supply and wiring.




2 WIRE, I²C-MODE

Pin A2 and A3 is used to configure the device address. That means up to 4 displays can use the same I²C bus.

The I²C mode has a bidirectional data transfer, i.e. data can be read back from the display's ram. The clock-pulse rate of the CLK line can be up to 1.7 MHz, depending on power supply and wiring. Please be informed, that the pins SDA+SCK contain an internal resistance of 600 to 1000 Ohm, or even more (Important, because of the LO-level while reading data and the ACK-Bit).

Important: After the commands to set page or column adress you always have to read a dummy byte.




| A2=VSS / A3=VSS (like application example) | |
|---|---------------|
| Adr | Function |
| \$70 | Write Command |
| \$71 | Read Status |
| \$72 | Write Data |
| \$73 | Read Data |

| A2=VDD / A3=VDD | |
|-----------------|---------------|
| Adr | Function |
| \$7C | Write Command |
| \$7D | Read Status |
| \$7E | Write Data |
| \$7F | Read Data |

| A2=VDD / A3=VSS | |
|-----------------|---------------|
| Adr | Function |
| \$74 | Write Command |
| \$75 | Read Status |
| \$76 | Write Data |
| \$77 | Read Data |

| A2=VSS / A3=VDD | |
|-----------------|---------------|
| Adr | Function |
| \$78 | Write Command |
| \$79 | Read Status |
| \$7A | Write Data |
| \$7B | Read Data |




DOGM240-6 GRAPHIC

TOUCH PANEL EA TOUCH240-4 (OPTIONAL)

An analog touch panel is available as an accessory. It has a self-adhesive material on its rear surface and is simply stuck onto the display. The connection is made by means of a 4-pin flexible cable for a ZIF connector (e.g. EA WF100-04S) with a grid of 1.0 mm. Bending radius is defined with min. 5mm. For optimum readability we recommend that you use a backlight with the display.


Interfacing to a processor can be either done by an external touch panel controller or with a controller that is featured with analogue inputs. The touch panel is similar to a potentiometer: connecting a voltage of e.g. 3.3V to the pins *Top-Bottom* read out a voltage on pin near to the Y-coordinate of X-coordinate will result be supplied to *Left-Right* done at *Top* or *Bottom*. The pinout of the



the pins *Top-Bottom* read out a voltage on pin near to the Y-coordinate of X-coordinate will result be supplied to *Left-Right* done at *Top* or *Bottom*.

connecting cable is shown in the drawing.

| Specification | | | |
|------------------|--------|------|--------------------|
| Specification | min | max | Unit |
| Top-Bottom | 100 | 180 | Ω |
| Left-Right | 1300 | 2200 | Ω |
| Voltage | 3 | 12 | V |
| Current | 5 | 25 | mA |
| Linearity | | 3 | % |
| Force | 90 | 120 | g |
| Contact Bounce | 5 | 10 | ms |
| Op. Temperatur | -20 | +60 | $^{\circ}\text{C}$ |
| Stor. Temperatur | -20 | +70 | $^{\circ}\text{C}$ |
| Transmission | 75 | 85 | % |
| Life Time | 100000 | | Cycles |



ZIF CONNECTOR EA WF100-04S

As an accessory for the touch panel we do provide a ZIF connector (4 pins) with pitch 1.0mm (SMD type). This connector is a „bottom side contact“ type




TABLE OF COMMANDS (OVERVIEW)

| Command | Command Code | | | | | | | | | | Function | Default |
|------------------------------|--------------|------------------|----|------------|----|----------|----------|----|----|------------------------|---|---------|
| | CD | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | | | |
| (1) Write Data Byte | 1 | data bit D[7..0] | | | | | | | | | Write one byte to memory | N/A |
| (4) Set Column Address LSB | 0 | 0 | 0 | 0 | 0 | CA[3..0] | | | | | Set the SRAM column address CA=0..239 | 0x00 |
| Set Column Address MSB | | 0 | 0 | 0 | 1 | CA[7..4] | | | | | | |
| (10) Set Page Address LSB | 0 | 0 | 1 | 1 | 0 | PA[3..0] | | | | | Set the SRAM page address PA=0..15 in black and white mode | 0x00 |
| Set Page Address MSB | 0 | 0 | 1 | 1 | 1 | 0 | PA[6..4] | | | | | |
| (15) Set RAM Address Control | 0 | 1 | 0 | 0 | 0 | 1 | AC[2..0] | | | | AC0: 0=stop increment at end ,1=warp around AC1: 0=column, 1=page increment AC2: Set page increment: 0= +1, 1= -1 | 0x01 |
| (31) Set Window Start Column | 0 | 1 | 1 | 1 | 1 | 0 | 1 | 0 | 0 | 0 | Set Start Column of Window Function | 0x00 |
| | | WPC0[7..0] | | | | | | | | | | |
| (32) Set Window Start Page | 0 | 1 | 1 | 1 | 1 | 0 | 1 | 0 | 1 | 1 | Set Start Page of Window Function | 0x00 |
| | | 0 | 0 | WPP0[5..0] | | | | | | | | |
| (33) Set Window End Column | 0 | 1 | 1 | 1 | 1 | 0 | 1 | 1 | 1 | 0 | Set End Column of Window Function | 0xFF |
| | | WPC1[7..0] | | | | | | | | | | |
| (34) Set Window End Page | 0 | 1 | 1 | 1 | 1 | 0 | 1 | 1 | 1 | 1 | Set End Page of Window Function | 0x4F |
| | | 0 | 0 | WPP1[5..0] | | | | | | | | |
| (35) Set Window program mode | 0 | 1 | 1 | 1 | 1 | 1 | 0 | 0 | C4 | C4: 0=inside 1=outside | 0x00 | |

Further information, please download the datasheet of the controller UC1611s from our homepage:

http://www.lcd-module.de/fileadmin/eng/pdf/zubehoer/uc1611s_v1_0.pdf

INITIALISATION EXAMPLE (6:00 VIEW ANGLE)

| Initialisation example (bottom view) | | | | | | | | | | | |
|--------------------------------------|----|----|----|----|----|----|----|----|----|------|--|
| Command | CD | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Hex | Remark |
| [28] Set COM End | 0 | 1 | 1 | 1 | 1 | 0 | 0 | 0 | 1 | \$F1 | Set last COM electrode to 63 (number of COM electrodes - 1) |
| | | 0 | 0 | 1 | 1 | 1 | 1 | 1 | 1 | \$3F | |
| [29] Set partial display start | 0 | 1 | 1 | 1 | 1 | 0 | 0 | 1 | 0 | \$F2 | Set Display start line to 0 |
| | | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | \$00 | |
| [30] Set partial display end | 0 | 1 | 1 | 1 | 1 | 0 | 0 | 1 | 1 | \$F3 | Set Display end line to 63 |
| | | 0 | 0 | 1 | 1 | 1 | 1 | 1 | 1 | \$3F | |
| [11] Set Potentiometer | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 1 | \$81 | Set Contrast |
| | | 1 | 0 | 1 | 1 | 0 | 1 | 1 | 1 | \$B7 | |
| [21] Set LCD mapping control | 0 | 1 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | \$C0 | set bottom view |
| | | 0 | 0 | 0 | 0 | 0 | 0 | 1 | 0 | \$02 | |
| [17] Set line rate | 0 | 1 | 0 | 1 | 0 | 0 | 0 | 1 | 1 | \$A3 | 9.4 kilo-lines per second |
| [27] Set LCD bias ratio | 0 | 1 | 1 | 1 | 0 | 1 | 0 | 0 | 1 | \$E9 | Set bias ratio to 10. |
| [20] Set display enable | 0 | 1 | 0 | 1 | 0 | 1 | 0 | 0 | 1 | \$A9 | Enable display in black and white mode |
| [23] Set display pattern | 0 | 1 | 1 | 0 | 1 | 0 | 0 | 0 | 1 | \$D1 | |

0 --- Column address --- 239

| | |
|----------|--------|
| D0 D7 | Page 0 |
| D0 D7 | Page 1 |
| D0 D7 | Page 2 |

GRAPHIC RAM

The EA DOGM240-6 has integrated a RAM to store 4 complete display contents. One byte contains 8 dots. The complete datasheet for the controller UC1611s can be downloaded on our homepage:

http://www.lcd-module.de/fileadmin/eng/pdf/zubehoer/uc1611s_v1_0.pdf

| | |
|----------|--------|
| D0 D7 | Page 5 |
| D0 D7 | Page 6 |
| D0 D7 | Page 7 |

12:00 VIEW ANGLE, TOP VIEW

If the display is read mostly from above (on the front of a laboratory power supply unit e.g.), the preferred angle of viewing can be set to 12 o'clock. This rotates the display by 180°. A slightly different initialization setup is required for this.




6:00 o'clock (Bottom View)




12:00 o'clock (Top View)

| Initialisation example (changes for top view) | | | | | | | | | | | |
|--|----|----|----|----|----|----|----|----|----|------|--------------|
| Command | CD | D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | Hex | Remark |
| [21] Set LCD Mapping Control | 0 | 1 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | \$C0 | Set top view |
| | | 0 | 0 | 0 | 0 | 0 | 1 | 0 | 0 | \$04 | |

DIMENSIONS EA DOGM240-6



DIMENSIONS EA LED94X40



MOUNTING / ASSEMBLING

First, clip the display and backlight modules together by gently pushing the display pins through the corresponding holes on the backlight module. Then insert the entire module into the socket, or into the soldering holes on the pcb. The backlight pins (6 pins at the bottom) must be soldered on the top side as well to ensure good contact between the modules.

Important:

- The display and the backlight do have in summary 3 protective films. There are some on the top and the bottom of the display and also one on the backlight. These must be removed.
- LC displays are generally not suited for wave or reflow soldering. Temperatures of over 80°C can cause lasting damage.
- Make sure that either display nor backlight will never come into contact with any kind of liquid like Fluxer, Cleaner, Water.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.