

### DESCRIPTION

The MP20051 is a low-dropout linear regulator that supplies up to 1A current with a 140mV dropout voltage. The externally-adjustable output voltage has a range of 0.8V to 5V from an input voltage of 2.5V to 5.5V.

An internal PMOS pass element allows for a low 110µA ground current, making the MP20051 suitable for battery-powered devices. Other features include low-power shutdown, and short-circuit and thermal protection. The MP20051 is available in 3mm x 3mm 8-pin QFN and SOIC8E packages.

### FEATURES


- Up to 1A Output Current
- Low 140mV Dropout at 1A
- Low 110µA Ground Current
- Output Voltage Available from 0.8V to 5V
- Low Noise: 13µV<sub>RMS</sub> typical (10Hz to 100kHz)
- 63dB PSRR @1kHz
- Stable with Ceramic Capacitor
- Excellent Load/Line Transient Response
- Current Limiting and Thermal Protection
- Available in 3mm x 3mm 8-pin QFN and SOIC8E Packages

### APPLICATIONS

- Notebook Computers
- Cordless Telephones
- Cellular Phones
- Wireless Communication Equipment
- Hand-Held Instruments

All MPS parts are lead-free and adhere to the RoHS directive. For MPS green status, please visit MPS website under Quality Assurance. "MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.

### TYPICAL APPLICATION



## ORDERING INFORMATION

Part Number	Package	Top Marking
MP20051DQ*	QFN-8 (3mm x 3mm)	See Below
MP20051DN**	SOIC8E	See Below

\* For Tape & Reel, add suffix –Z (e.g. MP20051DQ–Z);  
For RoHS Compliant Packaging, add suffix –LF (e.g. MP20051DQ–LF–Z)

\*\* For Tape & Reel, add suffix –Z (e.g. MP20051DN–Z);  
For RoHS Compliant Packaging, add suffix –LF (e.g. MP20051DN–LF–Z)

### TOP MARKING (MP20051DQ)

**ABRY**  
**LLL**

ABR: product code of MP20051DQ;

Y: year code;

LLL: lot number;

### TOP MARKING (MP20051DN)

**MP20051**  
**LLLLLLLL**  
**MPSYWW**

MP20051: product code of MP20051DN;


MPS: MPS prefix:

Y: year code;

WW: week code:

LLLLLLL: lot number;

## PACKAGE REFERENCE

**ABSOLUTE MAXIMUM RATINGS<sup>(1)</sup>**

VIN, EN, FB to GND .....	-0.3V to +6V
OUT to GND .....	-0.5V to ( $V_{IN}$ + 0.5V)
Continuous Power Dissipation .....	( $T_A$ =25°C) <sup>(2)</sup>
QFN8 (3x3mm).....	2.0W
SOIC8E .....	2.0W
Junction Temperature .....	150°C
Storage Temperature Range .....	-65°C to 150°C
Lead Temperature (Soldering, 10sec).....	260°C

**ESD SUSCEPTIBILITY<sup>(3)</sup>**

HBM (Human Body Mode).....	2kV
MM (Machine Mode) .....	200V

**Recommended Operating Conditions<sup>(4)</sup>**

Supply Input Voltage.....	2.5V to 5.5V
Enable Input Voltage .....	0V to 5.5V
Operating Junction Temp. ( $T_J$ ). -40°C to +125°C	

**Thermal Resistance<sup>(5)</sup>       $\theta_{JA}$        $\theta_{JC}$** 

QFN-8 (3mmx3mm) .....	50	12 ... °C/W
SOIC8E .....	50	10 ... °C/W

**Notes:**

- 1) Exceeding these ratings may damage the device.
- 2) The maximum allowable power dissipation is a function of the maximum junction temperature  $T_J$  (MAX), the junction-to-ambient thermal resistance  $\theta_{JA}$ , and the ambient temperature  $T_A$ . The maximum allowable continuous power dissipation at any ambient temperature is calculated by  $P_D$  (MAX) =  $(T_J$  (MAX)- $T_A$ )/ $\theta_{JA}$ . Exceeding the maximum allowable power dissipation will cause excessive die temperature, and the regulator will go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
- 3) Devices are ESD sensitive. Handling precaution recommended.
- 4) The device is not guaranteed to function outside of its operating conditions.
- 5) Measured on JESD51-7, 4-layer PCB.

**ELECTRICAL CHARACTERISTICS** **$V_{IN} = V_{OUT} + 0.5V$  or  $V_{IN} = 2.5V$ ,  $EN = V_{IN}$ , Typical values are at  $T_A = 25^\circ C$ , unless otherwise specified**

Parameter	Condition	Min	Typ	Max	Units
Input Voltage		2.5		5.5	V
Input Under Voltage Lockout	$V_{IN}$ rising	1.95		2.25	V
Hysteresis of UVLO			160		mV
FB Voltage	$V_{OUT} = 0.8V$ , $I_{OUT} = 1mA$	0.784	0.8	0.816	V
Output Voltage Accuracy	$I_{OUT} = 1mA$ , $T_A = 25^\circ C$	-2		2	%
	$I_{OUT} = 1mA$ , $-40 \leq T_A \leq 85^\circ C$	-3		3	
Maximum Output Current	Continuous, $V_{IN} \geq 2.5V$ , $V_{OUT} = 2.5V$	1			A
Short-Circuit Current Limit	$V_{OUT} = 0$ , $V_{IN} \geq 2.5V$		1.6		A
In-Regulation Current Limit	$V_{OUT} = 2.5V$ , $V_{OUT}$ within 4% of normal output voltage $V_{IN} = 5.5V$	1.4	2.2	3.0	A
Ground Current	$I_{OUT} = 0.1mA$ , $V_{OUT} = 2.5V$		110		$\mu A$
	$I_{OUT} = 1A$ , $V_{OUT} = 2.5V$		600		
Dropout Voltage <sup>(6)</sup>	$I_{OUT} = 1A$ , $V_{OUT} = 2.5V$	140	280		mV
	$I_{OUT} = 750m$ , $V_{OUT} = 2.5V$	105	210		
	$I_{OUT} = 500mA$ , $V_{OUT} = 2.5V$	70	140		
Line Regulation <sup>(7)</sup>	$V_{OUT} = 2.5V$ , $V_{IN}$ from $V_{OUT} + 0.5V$ to $5.5V$ , $I_{OUT} = 100mA$	-0.15		0.15	%/V
Load Regulation <sup>(8)</sup>	$I_{OUT}$ from 100mA to 1A, $V_{OUT} = 2.5V$		0.3		%
Output Voltage Noise	$I_{OUT} = 100mA$ , f ranges from 10Hz to 100kHz	$V_{OUT} = 1.1V$	13		$\mu V_{RMS}$
		$V_{OUT} = 3.3V$	35		
		$V_{OUT} = 5V$	55		
PSRR	$V_{IN} = 2.5V$ , $V_{OUT} = 1.1V$ , $I_{OUT} = 1A$	f=100Hz	65		dB
		f=1kHz	63		
		f=10kHz	63		
		f=1MHz	33		
Shutdown Supply Current	$V_{IN} = +5.5V$		0.2		$\mu A$
EN Pin Current, Enabled	$V_{IN} = V_{EN} = +5.5V$		0.2		$\mu A$
Feedback Pin Current	$V_{IN} = +5.5V$ , $V_{FB} = 6V$		0.02		$\mu A$
Startup Time	$V_{OUT(NOM)} = 2.5V$ , $C_{OUT} = 4.7\mu F$ , $V_{OUT} = 0\%$ to 90% $V_{OUT(NOM)}$		45		$\mu s$
EN PIN Threshold	EN Logic High	1.5			V
	EN Logic Low			0.4	
Thermal Shutdown Temperature	Typical thermal hysteresis = $20^\circ C$		150		$^\circ C$

**Notes:**

- 6) Dropout Voltage is defined as the input to output differential when the output voltage drops 100mV below its nominal value.

$$7) \text{ Line Regulation} = \frac{\left| V_{OUT[V_{IN(MAX)}]} - V_{OUT[V_{IN(MIN)}]} \right|}{\left[ V_{IN(MAX)} - V_{IN(MIN)} \right] \times V_{OUT(NOM)}} \times (\%) / V$$










$$8) \text{ Load Regulation} = \frac{\left| V_{OUT[I_{OUT(MAX)}]} - V_{OUT[I_{OUT(MIN)}]} \right|}{V_{OUT(NOM)}} \times (\%)$$

## PIN FUNCTIONS

Pin #	Name	Pin Function
1, 2	VOUT	Regulator output. Bypass with a standard 4.7 $\mu$ F ceramic capacitor to GND. Connect all the pins together externally.
3	FB	Feedback Input. Connect FB to the center point of the external resistor divider. The feedback threshold voltage is 0.8V.
4	GND Exposed pad	Ground. Connect exposed pad to GND plane for optimal thermal performance.
5	EN	Regulator Enable Control Input. Drive EN above 1.5V to turn on the MP20051. Drive EN below 0.4V to turn it off. Do not float the EN pin.
6	NC	No Connection. Leave this NC pin open.
7, 8	VIN	Regulator Input. Supply voltage ranges from 2.5V to 5.5V. Bypass with 2.2 $\mu$ F capacitor. These pins must be externally connected for proper operation even if they are internally connected.




## TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = 2.5V$ ,  $V_{OUT} = 1.1V$ ,  $C_{IN}=2.2\mu F$ ,  $C_{OUT}=4.7\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.



**TYPICAL PERFORMANCE CHARACTERISTICS (continued)**

$V_{IN} = 2.5V$ ,  $V_{OUT} = 1.1V$ ,  $C_{IN}=2.2\mu F$ ,  $C_{OUT}=4.7\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.


**Load Regulation****Output Voltage Accuracy vs. Temperature****PSRR Vs. Frequency**

## TYPICAL PERFORMANCE CHARACTERISTICS (continued)

$V_{IN} = 2.5V$ ,  $V_{OUT} = 1.1V$ ,  $C_{IN}=2.2\mu F$ ,  $C_{OUT}=4.7\mu F$ ,  $T_A = 25^\circ C$ , unless otherwise noted.


### Input Power Start Up

$V_{IN}=2.5V$ ,  $V_{OUT}=1.1V$ ,  $I_{OUT}=1A$ ,  
with Resistor Load




### Input Power Shutdown

$V_{IN}=2.5V$ ,  $V_{OUT}=1.1V$ ,  $I_{OUT}=1A$ ,  
with Resistor Load




### EN Start Up

$V_{EN}=2.5V$ ,  $V_{OUT}=1.1V$ ,  $I_{OUT}=1A$ ,  
with Resistor Load




### EN Shutdown

$V_{EN}=2.5V$ ,  $V_{OUT}=1.1V$ ,  $I_{OUT}=1A$ ,  
with Resistor Load




### Line Transient

$V_{IN}=2.5V$  to  $4V$ ,  $V_{OUT}=1.1V$ ,  
 $I_{OUT}=10mA$ , with Resistor Load




### Line Transient

$V_{IN}=2.5V$  to  $4V$ ,  $V_{OUT}=1.1V$ ,  
 $I_{OUT}=1A$ , with Resistor Load




### Load Transient


$V_{IN}=2.5V$ ,  $V_{OUT}=1.1V$ ,  
 $I_{OUT}=10mA$  to  $1A$ , with Resistor Load



### Over Current Protection Steady State

$V_{IN}=2.5V$ ,  $V_{OUT}=1.1V$



**FUNCTIONAL BLOCK DIAGRAM****Figure 1—Functional Block Diagram**

## OPERATION

The MP20051 is a low-dropout linear regulator that can supply up to 1A current, which makes it suitable for very low voltage, low quiescent, low noise, and high PSRR applications such as wireless LAN transceivers, notebook computers, smartphones, and other low-power electronics.

The MP20051 uses an internal PMOS as the pass element and includes both thermal shutdown and an internal current-limiting circuit.

### Dropout Voltage

Dropout voltage is the minimum input to output differential voltage required for the regulator to maintain an output voltage within 100mV of its nominal value. Because the PMOS pass element behaves as a low-value resistor, the dropout voltage of MP20051 is only 140mV.

### Shutdown

The MP20051 can be switched ON or OFF by a logic input at the EN pin: Logic high turns the regulator on and logic low turns it off. Tie the EN pin to VIN if the application does not require the shutdown feature. Do not float the EN pin.

### Current Limit

The MP20051 includes a current limit structure that monitors and controls the PMOS gate voltage to limit the guaranteed maximum output current to 1.6A.

### Thermal Protection

Thermal protection turns off the PMOS when the junction temperature exceeds 150°C, allowing the IC to cool. When the IC's junction temperature drops by 20°C, the PMOS will turn on again. Thermal protection limits total power dissipation in the MP20051. For reliable operation, limit the junction temperature to a maximum of 125°C.

### Load-Transient Considerations

The output response of the load-transient consists of a transient response and DC shift—the MP20051's excellent load regulation effectively limits the DC shift. The output voltage transient depends on the output capacitor's value and ESR. Increasing the capacitance and decreasing the ESR will improve the transient response.

## APPLICATION INFORMATION

### Setting the Output Voltage

The MP20051 has an externally-set output voltage with a range of 0.8V to 5V given a 2.5V to 5.5V input. Set the output voltage using a resistive voltage divider from the output voltage to the FB pin. The result of the voltage divider at the FB pin is:

$$V_{FB} = V_{OUT} \frac{R2}{R1 + R2}$$

Where  $V_{FB}$  is the feedback threshold voltage ( $V_{FB} = 0.8V$ ), and  $V_{OUT}$  is the output voltage. Thus the output voltage is:

$$V_{OUT} = 0.8 \times \frac{R1 + R2}{R2}$$

$R2$  can go as high as 100kΩ, but typical applications use 10kΩ. After selecting  $R2$ ,  $R1$  is determined by:

$$R1 = R2 \times \left( \frac{V_{OUT} - V_{FB}}{V_{FB}} \right)$$

For example, for a 1.1V output voltage,  $R2$  is 10kΩ, and  $R1$  is 3.75kΩ. You can select a standard 3.75kΩ (±1%) resistor for  $R1$ .

### Power Dissipation

The power dissipation for any package depends on the thermal resistance of the case and circuit board, the temperature differential between the junction and ambient air, and the rate of air flow. The power dissipation across the device can be represented by the equation:

$$P = (V_{IN} - V_{OUT}) \times I_{OUT}$$

The allowable power dissipation can be calculated using the following equation:

$$P_{(MAX)} = (T_{Junction} - T_{Ambient}) / \theta_{JA}$$




Where  $(T_{Junction} - T_{Ambient})$  is the temperature differential between the junction and the surrounding environment,  $\theta_{JA}$  is the thermal resistance from the junction to the ambient environment. Connecting the exposed GND pad to a large ground pad or plane helps to channel away heat.

### Output Capacitor Selection



The MP20051 is specifically designed to work with a standard ceramic output capacitor to save space and improve performance. Use a 4.7µF ceramic capacitor for most applications. Larger output capacitors will improve load transient response and reduce noise at the cost of increased size.

## PACKAGE INFORMATION

QFN-8 (3mm×3mm)









PIN 1 ID OPTION A  
0.30x45° TYP.  
PIN 1 ID OPTION B  
R0.20 TYP.



## NOTE:

- 1) ALL DIMENSIONS ARE IN MILLIMETERS.
- 2) EXPOSED PADDLE SIZE DOES NOT INCLUDE MOLD FLASH.
- 3) LEAD COPLANARITY SHALL BE 0.08 MILLIMETER MAX.
- 4) DRAWING CONFORMS TO JEDEC MO-229, VARIATION VEEC-2.
- 5) DRAWING IS NOT TO SCALE.

## SOIC8E



## NOTE:

- 1) CONTROL DIMENSION IS IN INCHES. DIMENSION IN BRACKET IS IN MILLIMETERS.
- 2) PACKAGE LENGTH DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS.
- 3) PACKAGE WIDTH DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSIONS.
- 4) LEAD COPLANARITY (BOTTOM OF LEADS AFTER FORMING) SHALL BE 0.004" INCHES MAX.
- 5) DRAWING CONFORMS TO JEDEC MS-012, VARIATION BA.
- 6) DRAWING IS NOT TO SCALE.

**NOTICE:** The information in this document is subject to change without notice. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

#### Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помошь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помошь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: [org@eplast1.ru](mailto:org@eplast1.ru)

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.