800mA LDO REGULATOR
R1170X series

■ OUTLINE

The R1170 Series are positive voltage regulator ICs by CMOS process. The R1170 Series have features of high ripple rejection, low dropout voltage, high output voltage accuracy, low consumption current. Each of these ICs consists of a voltage reference unit, an error amplifier, resistor net for setting output voltage, a current limit circuit at short mode, a chip enable circuit, and thermal-shunt circuit. Output Voltage of R1170 is fixed in the IC.

Low consumption current by the merit of CMOS process and built-in transistors with low ON-resistance make low dropout voltage and chip enable function prolong the battery life. These regulators are remarkable improvement on the current regulators in terms of ripple rejection, input transient response, and load transient response.

Maximum Output Current is large for its compact size.

Thus, the R1170 Series are suitable for various power sources for portable appliances.

Since the packages for these ICs are the SOT-89-5 package or HSON6, high density mounting of the ICs on boards is possible.

■ FEATURES


- ●Ultra-Low Supply Current• • • • • • • • TYP. 80μA
- ●Low Standby Current • • • • • • • • • • • • TYP. 0.1μA
- ●Output Current • • • • • • • • • • • • • • • • MIN. 800mA(V_{IN}=V_{OUT}+1.0V)
- ●Output Voltage • • • • • • • • • • • • • Stepwise setting with a step of 0.1V in the range of 1.5V to 4.0V
- ●High Output Voltage Accuracy• • • • ±2.0%
- ●Low Dropout Voltage• • • • • • • • • • • • TYP. 0.12V(V_{OUT}=3.0V, I_{OUT}=300mA)
- ●Line Regulation• • • • • • • • • • • • TYP. 0.05%/V
- ●Small Package • • • • • • • • • • • • • • • • SOT-89-5, HSON6
- ●Built-in Current Limit Circuit
- ●Built-in Thermal Shunt Circuit
- ●Low Temperature-drift Coefficient of Output Voltage • • • • • • • • • TYP.±100ppm/°C

■ APPLICATIONS


- ●Local Power source for Notebook PC.
- ●Local Power source for portable appliances, cameras, and videos.
- ●Local Power source for equipment of battery-use.
- ●Local Power source for home appliances.

■ BLOCK DIAGRAMS

R1170H Series



R1170D Series



■ SELECTION GUIDE


The output voltage, the chip-enable polarity, the taping type can be selected at the user's request. The selection can be made with the part number as follows;

R1170X XXXX-XX ← Part Number
↑ ↑ ↑ ↑
a b c d


Code	Contents
a	Package Type; H: SOT89-5, D: HSON-6P
b	Designation of Output Voltage(VOUT) Stepwise setting with 0.1V increment in the range from 1.5V to 4.0V
c	Designation of option; A: Built-in Chip Enable Circuit, Active at "L" B: Built-in Chip Enable Circuit, Active at "H"
d	Designation of Taping Type; T1 or T2 (SOT89-5), TR(HSON-6) (Refer to Taping Specifications)

■ PIN CONFIGURATION

● SOT-89-5



● HSON-6P



■ PIN DESCRIPTION

SOT89-5

Pin No.	Symbol	Description
1	$\overline{CE}$ or CE	Chip Enable Pin Voltage Regulator Output Pin
2	GND	Ground Pin
3	NC	No Connection
4	V_{DD}	Input Pin
5	V_{OUT}	Voltage Regulator Output Pin

HSON-6P

Pin No.	Symbol	Description
1	V_{OUT}	Voltage Regulator Output Pin
2	V_{OUT}	Voltage Regulator Output Pin
3	$\overline{CE}$ or CE	Chip Enable Pin Voltage Regulator Output Pin
4	GND	Ground Pin
5	V_{DD}	Input Pin
6	V_{DD}	Input Pin

■ ABSOLUTE MAXIMUM RATINGS

Item	Symbol	Rating	Unit
Input Voltage	V_{IN}	7.0	V
Input Voltage(CE or CE Input Pin)*Note	V_{CE}	-0.3 ~ V_{IN}+0.3	V
Output Voltage	V_{OUT}	-0.3 ~ V_{IN}+0.3	V
Output Current	I_{OUT}	1.2	A
Power Dissipation	P_D	Internally limited	
Operating Temperature	T_{opt}	-40 ~ 85	°C
Storage Temperature	T_{stg}	-55 ~ 125	°C

■ ELECTRICAL CHARACTERISTICS

●R1170XxxxA

(Topt=25°C)

Item	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input Voltage	V_{IN}				6.0	V
Supply Current1	I_{SS1}	V_{IN}-V_{OUT}=1.0V V_{CE}=GND		80	160	μA
Standby Current	Istb	V_{IN}=V_{CE}=6.0V		0.1	1.0	μA
Output voltage	V_{OUT}	V_{IN}-V_{OUT}=1.0V I_{OUT}=100mA	x0.98		x1.02	V
Output Current	I_{OUT1}	V_{IN}-V_{OUT}=1.0V	800			mA
Load regulation	ΔV_{OUT}/ ΔI_{OUT}	V_{IN}-V_{OUT}=1.0V 1mA≤I_{OUT}≤300mA		30	100	mV
Dropout Voltage	V_{DIF}	I_{OUT}=300mA	Refer to Dropout Voltage Table			
Line regulation	ΔV_{OUT}/ ΔV_{IN}	I_{OUT}=100mA V_{OUT}+0.5V≤V_{IN}≤8.0V		0.05	0.30	%/V
Ripple Rejection	RR	f=1kHz,Ripple 0.5Vp-p V_{IN}-V_{OUT}=1.0V		50		dB
Output Voltage Temperature Coefficient	ΔV_{OUT}/ ΔT	I_{OUT}=10mA -40°C ≤ Topt ≤ 85°C		±100		ppm /°C
Short Current Limit	I_{LIM}	V_{OUT}=0V		40		mA
Pull-up resistance for $\overline{CE}$ pin	R_{PU}		1.25	2.50	5.00	MΩ
$\overline{CE}$ Input Voltage "H"	V_{CEH}		1.50		V_{IN}	V
$\overline{CE}$ Input Voltage "L"	V_{CEL}		0.00		0.25	V
Thermal Shutdown Detector Threshold Temperature	T_{TSD}	Junction Temperature		150		°C
Thermal Shutdown Released Temperature	T_{TSR}	Junction Temperature		120		°C

●R1170xxxxB


(Topt=25°C)

Item	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input voltage	V_{IN}				6.0	V
Supply Current1	I_{SS1}	V_{IN}-V_{OUT}=1.0V V_{CE}=V_{IN}		80	160	μA
Standby Current	Istb	V_{IN}=6.0V, V_{CE}=GND		0.1	1.0	μA
Reference Voltage for Adjustable Voltage Regulator	V_{OUT}	V_{IN}-V_{OUT}=1.0V I_{OUT}=100mA	x0.98		x1.02	V
Output Current	I_{OUT1}	V_{IN}-V_{OUT}=1.0V	800			mA
Load regulation	ΔV_{OUT}/ ΔI_{OUT}	V_{IN}-V_{OUT}=1.0V 1mA≤I_{OUT}≤300mA		30	100	mV
Dropout Voltage	V_{DIF}	I_{OUT}=300mA	Refer to Dropout Voltage Table			
Line regulation	ΔV_{OUT}/ ΔV_{IN}	I_{OUT}=100mA V_{OUT}+0.5V≤V_{IN}≤8.0V		0.05	0.30	%/V
Ripple Rejection	RR	f=1kHz,Ripple 0.5Vp-p		50		dB
Output Voltage Temperature Coefficient	ΔV_{OUT}/ ΔT	-40°C≤Topt≤85°C		±100		ppm /°C
Short Current Limit	I_{LIM}	V_{OUT}=0V		40		mA
Pull-down resistance for CE pin	R_{PD}		1.25	2.5	5	MΩ
CE Input Voltage “H”	V_{CEH}		1.5		V_{IN}	V
CE Input Voltage “L”	V_{CEL}		0		0.25	V
Thermal Shutdown Detector Threshold Temperature	T_{TSD}	Junction Temperature		150		°C
Thermal Shutdown Released Temperature	T_{TSR}	Junction Temperature		120		°C


●Dropout Voltage by Output Voltage (Topt=25°C)

Output Voltage V_{OUT}(V)	Dropout Voltage (V)	
	TYP.	MAX.
V_{OUT}=1.5	0.35	0.45
V_{OUT}=1.6	0.30	0.35
V_{OUT}=1.7	0.25	0.30
1.8≤V_{OUT}≤2.0	0.20	0.25
2.1≤V_{OUT}≤2.4	0.15	0.20
2.5≤V_{OUT}≤4.0	0.12	0.18


■ TEST CIRCUITS




Standard Test Circuit



Supply Current Test Circuit



Test Circuit for Ripple Rejection, Input Transient Response



Test Circuit for Load Transient Response

■ Technical Notes on External Components and Typical Application

Phase Compensation

In these ICs, phase compensation is made with Output capacitor for securing stable operation even if the load current is varied. For this purpose, use as much as 10μF Capacitor as C_L.


If you use a tantalum type capacitor and ESR value of the capacitor is large, output might be unstable. Evaluate your circuit with considering frequency characteristics. Further, refer to the Typical Characteristics No.12.

Mounting on PCB

Make V_{DD} and GND lines sufficient. If the impedance of these is high, current flows, the noise might be picked up or be a cause of unstable operation. Further use as much as 10μF Capacitor between V_{DD} pin and GND pin as close as possible.

Set an Output capcitor between V_{OUT} pin and GND pin for phase compensation as close as possible. (Refer to the example of typical application)

Example of the typical application of R1170HxxxB




CI=10μF(Ceramic), CL=10μF(Ceramic)


■ TYPICAL CHARACTERISTICS

1)Output Voltage vs. Output Current(Topt=25°C)


R1170X151B




R1170X201B



R1170X301B




R1170X401B




2)Output Voltage vs. Input Voltage(Topt=25°C)


R1170X151B




R1170X201B



R1170X301B




R1170X401B




3)Dropout Voltage vs. Output Current


R1170X151B




R1170X201B



R1170X301B



R1170X401B




4)Output Voltage vs. Temperature

R1170X151B

V_{IN}=2.5V


I_{OUT}=10mA



R1170X201B

V_{IN}=3V


I_{OUT}=10mA



R1170X301B

V_{IN}=4V


I_{OUT}=10mA



R1170X401B


V_{IN}=5V

I_{OUT}=10mA




5)Supply Current vs. Input Voltage(Topt=25°C)


R1170X151B




R1170X201B



R1170X301B




R1170X401B




6)Supply Current vs. Temperature


R1170X151B




R1170X201B



R1170X301B




R1170X401B




7)Dropout Voltage vs. Set Output Voltage(Topt=25°C)

R1170XXXXB




8)Ripple Rejection vs. Frequency


R1170X151B VIN=2.5V+0.5Vp-p IOUT=100mA




R1170X201B VIN=3V+0.5Vp-p IOUT=100mA




R1170X301B VIN=4V+0.5Vp-p IOUT=100mA





R1170X401B VIN=5V+0.5Vp-p IOUT=100mA




9)Ripple Rejection vs. Input Voltage










10)Input Transient Response (Topt=25°C)










11)Load Transient ResponseTopt=25°C)







12)Stable Area(Topt=25°C,VIN=Set Output Voltage+1V,CIN=Ceramic 10μF)




As an output capacitor for this IC, Ceramic capacitor is recommendable. However, other low ESR type capacitor can be used with this IC.

For your reference, noise level is tested with the circuit as shown above, and if the noise level is 40μV or less than 40μV, the ESR values are plotted as stable area. Upper limit is described in the next four graphs, or ESR vs. Output Current. (Hatched area is the stable area.)


R1170X151B

C OUT=Ceramic 10uF




R1170X151B

C OUT =Ceramic 4.7uF




R1170X301B

COUT=Ceramic 10uF



R1170X301B

C OUT=Ceramic 4.7uF




Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.