

LM611 Operational Amplifier and Adjustable Reference

Check for Samples: [LM611](#)

FEATURES

OP AMP

- **Low Operating Current:** 300 μA (op amp)
- **Wide Supply Voltage Range:** 4V to 36V
- **Wide Common-Mode Range:** V^- to $(V^+ - 1.8\text{V})$
- **Wide Differential Input Voltage:** $\pm 36\text{V}$
- **Available in Low Cost 8-pin DIP**
- **Available in Plastic Package Rated for Military Temperature Range Operation**

REFERENCE

- **Adjustable Output Voltage:** 1.2V to 6.3V
- **Tight Initial Tolerance Available:** $\pm 0.6\%$
- **Wide Operating Current Range:** 17 μA to 20 mA
- **Reference Floats Above Ground**
- **Tolerant of Load Capacitance**

APPLICATIONS

- **Transducer Bridge Driver**
- **Process and Mass Flow Control Systems**
- **Power Supply Voltage Monitor**
- **Buffered Voltage References for A/D's**

Connection Diagrams




Figure 1. Hermetic Dual-In-Line Package




Figure 2. Plastic Surface Mount Narrow Package



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

All trademarks are the property of their respective owners.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of the Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 1998–2013, Texas Instruments Incorporated



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

Absolute Maximum Ratings⁽¹⁾⁽²⁾

Voltage on Any Pins Except V_R (referred to V^- pin)	36V (Max)
See ⁽³⁾	-0.3V (Min)
Current through Any Input Pin and V_R Pin	± 20 mA
Differential Input Voltage	
Military and Industrial	± 36 V
Commercial	± 32 V
Storage Temperature Range	$-65^{\circ}\text{C} \leq T_J \leq +150^{\circ}\text{C}$
Maximum Junction Temperature	150°C
Thermal Resistance, Junction-to-Ambient ⁽⁴⁾	
N Package	100°C/W
D Package	150°C/W
Soldering Information Soldering (10 seconds)	
N Package	260°C
D Package	220°C
ESD Tolerance ⁽⁵⁾	± 1 kV

- (1) Absolute maximum ratings indicate limits beyond which damage to the component may occur. Electrical specifications do not apply when operating the device beyond its rated operating conditions.
- (2) If Military/Aerospace specified devices are required, please contact the Texas Instruments Sales Office/ Distributors for availability and specifications.
- (3) More accurately, it is excessive current flow, with resulting excess heating, that limits the voltages on all pins. When any pin is pulled a diode drop below V^- , a parasitic NPN transistor turns ON. No latch-up will occur as long as the current through that pin remains below the Maximum Rating. Operation is undefined and unpredictable when any parasitic diode or transistor is conducting.
- (4) Junction temperature may be calculated using $T_J = T_A + P_D \theta_{JA}$. The given thermal resistance is worst-case for packages in sockets in still air. For packages soldered to copper-clad board with dissipation from one op amp or reference output transistor, nominal θ_{JA} is 90°C/W for the N package and 135°C/W for the D package.
- (5) Human body model, 100 pF discharged through a 1.5 k Ω resistor.

Operating Temperature Range

LM611AI, LM611I, LM611BI	$-40^{\circ}\text{C} \leq T_J \leq +85^{\circ}\text{C}$
LM611AM, LM611M	$-55^{\circ}\text{C} \leq T_J \leq +125^{\circ}\text{C}$
LM611C	$0^{\circ}\text{C} \leq T_J \leq 70^{\circ}\text{C}$

Electrical Characteristics⁽¹⁾

These specifications apply for $V^- = \text{GND} = 0\text{V}$, $V^+ = 5\text{V}$, $V_{\text{CM}} = V_{\text{OUT}} = 2.5\text{V}$, $I_{\text{R}} = 100\text{ }\mu\text{A}$, FEEDBACK pin shorted to GND, unless otherwise specified. Limits in standard typeface are for $T_{\text{J}} = 25^\circ\text{C}$; limits in **boldface type** apply over the **Operating Temperature Range**.

Symbol	Parameter	Conditions	Typical ⁽²⁾	LM611AM LM611AI Limits ⁽³⁾	LM611M LM611BI LM611I LM611C Limits ⁽³⁾	Units
I _S	Total Supply Current	R _{LOAD} = ∞, 4V ≤ V ⁺ ≤ 36V (32V for LM611C)	210 221	300 320	350 370	μA max μA max
V _S	Supply Voltage Range		2.2 2.9	2.8 3	2.8 3	V min V min
			46 43	36 36	32 32	V max V max
OPERATIONAL AMPLIFIER						
V _{OS1}	V _{OS} Over Supply	4V ≤ V ⁺ ≤ 36V (4V ≤ V ⁺ ≤ 32V for LM611C)	1.5 2.0	3.5 6.0	5.0 7.0	mV max mV max
V _{OS2}	V _{OS} Over V _{CM}	V _{CM} = 0V through V _{CM} = (V ⁺ − 1.8V), V ⁺ = 30V, V [−] = 0V	1.0 1.5	3.5 6.0	5.0 7.0	mV max mV max
$\frac{V_{OS3}}{\Delta T}$	Average V _{OS} Drift	See ⁽³⁾	15			μV/°C max
I _B	Input Bias Current		10 11	25 30	35 40	nA max nA max
I _{OS}	Input Offset Current		0.2 0.3	4 5	4 5	nA max nA max
$\frac{I_{OS1}}{\Delta T}$	Average Offset Drift Current		4			pA/°C
R _{IN}	Input Resistance	Differential	1800			MΩ
		Common-Mode	3800			MΩ
C _{IN}	Input Capacitance	Common-Mode	5.7			pF
e _n	Voltage Noise	f = 100 Hz, Input Referred	74			nV/ $\sqrt{\text{Hz}}$
I _n	Current Noise	f = 100 Hz, Input Referred	58			fA/ $\sqrt{\text{Hz}}$
CMRR	Common-Mode Rejection-Ratio	V ⁺ = 30V, 0V ≤ V _{CM} ≤ (V ⁺ − 1.8V) CMRR = 20 log (ΔV _{CM} /ΔV _{OS})	95 90	80 75	75 70	dB min dB min
PSRR	Power Supply Rejection-Ratio	4V ≤ V ⁺ ≤ 30V, V _{CM} = V ⁺ /2, PSRR = 20 log (ΔV ⁺ /ΔV _{OS})	110 100	80 75	75 70	dB min dB min
A _V	Open Loop Voltage Gain	R _L = 10 kΩ to GND, V ⁺ = 30V, 5V ≤ V _{OUT} ≤ 25V	500 50	100 40	94 40	V/mV min
SR	Slew Rate	V ⁺ = 30V ⁽⁴⁾	0.70 0.65	0.55 0.45	0.50 0.45	V/μs
GBW	Gain Bandwidth	C _L = 50 pF	0.80 0.50			MHz
V _{O1}	Output Voltage Swing High	R _L = 10 kΩ to GND V ⁺ = 36V (32V for LM611C)	V ⁺ − 1.4 V ⁺ − 1.6	V ⁺ − 1.7 V ⁺ − 1.9	V ⁺ − 1.8 V ⁺ − 1.9	V min V min
V _{O2}	Output Voltage Swing Low	R _L = 10 kΩ to V ⁺ V ⁺ = 36V (32V for LM611C)	V [−] + 0.8 V [−] + 0.9	V [−] + 0.9 V [−] + 1.0	V [−] + 0.95 V [−] + 1.0	V max V max
I _{OUT}	Output Source Current	V _{OUT} = 2.5V, V _{+IN} = 0V, V _{−IN} = −0.3V	25 15	20 13	16 13	mA min mA min

- (1) Military RETS 611AMX electrical test specification is available on request. The LM611AMJ/883 can also be procured as a Standard Military Drawing.
- (2) Typical values in standard typeface are for $T_{\text{J}} = 25^\circ\text{C}$; values in **boldface type** apply for the full operating temperature range. These values represent the most likely parametric norm.
- (3) All limits are specified at room temperature (standard type face) or at operating temperature extremes (**bold face type**).
- (4) Slew rate is measured with op amp in a voltage follower configuration. For rising slew rate, the input voltage is driven from 5V to 25V, and the output voltage transition is sampled at 10V and 20V. For falling slew rate, the input voltage is driven from 25V to 5V, and output voltage transition is sampled at 20V and 10V.

Electrical Characteristics⁽¹⁾ (continued)

These specifications apply for $V^- = \text{GND} = 0\text{V}$, $V^+ = 5\text{V}$, $V_{\text{CM}} = V_{\text{OUT}} = 2.5\text{V}$, $I_{\text{R}} = 100\ \mu\text{A}$, FEEDBACK pin shorted to GND, unless otherwise specified. Limits in standard typeface are for $T_{\text{J}} = 25^\circ\text{C}$; limits in **boldface type** apply over the **Operating Temperature Range**.

Symbol	Parameter	Conditions	Typical ⁽²⁾	LM611AM LM611AI Limits ⁽³⁾	LM611M LM611BI LM611I LM611C Limits ⁽³⁾	Units
I _{SINK}	Output Sink Current	V _{OUT} = 1.6V, V _{+IN} = 0V, V _{-IN} = 0.3V	17 9	14 8	13 8	mA min mA min
I _{SHORT}	Short Circuit Current	V _{OUT} = 0V, V _{+IN} = 3V, V _{-IN} = 2V, Source	30 40	50 60	50 60	mA max mA max
		V _{OUT} = 5V, V _{+IN} = 2V, V _{-IN} = 3V, Sink	30 32	60 80	70 90	mA max mA max
VOLTAGE REFERENCE						
V _R	Reference Voltage	See ⁽⁵⁾	1.244	1.2365 1.2515 (±0.6%)	1.2191 1.2689 (±2.0%)	V min V max
$\frac{\Delta V_R}{\Delta T_J}$	Average Temperature Drift	See ⁽⁶⁾	10	80	150	PPM/°C max
$\frac{\Delta V_R}{\Delta T_J}$	Hysteresis	Hyst = (V _{ro'} – V _{ro})/ΔT _J ⁽⁷⁾	3.2			μV/°C
$\frac{\Delta V_R}{\Delta I_R}$	V _R Change with Current	V _R (100 μA) – V _R (17 μA)	0.05 0.1	1 1.1	1 1.1	mV max mV max
		V _R (10 mA) – V _R (100 μA) ⁽⁸⁾	1.5 2.0	5 5.5	5 5.5	mV max mV max
R	Resistance	ΔV _R (10→0.1 mA)/9.9 mA ΔV _R (100→17 μA)/83 μA	0.2 0.6	0.56 13	0.56 13	Ω max Ω max
$\frac{\Delta V_R}{V_{RO}}$	V _R Change with High V _{RO}	V _R (V _{ro} = V _r) – V _R (V _{ro} = 6.3V) (5.06V between Anode and FEEDBACK)	2.5 2.8	7 10	7 10	mV max mV max
$\frac{\Delta V_R}{\Delta V^+}$	V _R Change with V ⁺ Change	V _R (V ⁺ = 5V) – V _R (V ⁺ = 36V) (V ⁺ = 32V for LM611C)	0.1 0.1	1.2 1.3	1.2 1.3	mV max mV max
		V _R (V ⁺ = 5V) – V _R (V ⁺ = 3V)	0.01 0.01	1 1.5	1 1.5	mV max mV max
$\frac{\Delta V_R}{\Delta V_{ANODE}}$	V _R Change with V _{ANODE} Change	V ⁺ = V ⁺ max, ΔV _R = V _R (@ V _{ANODE} = V ⁻ = GND) – V _R (@ V _{ANODE} = V ⁺ – 1.0V)	0.7 3.3	1.5 3.0	1.6 3.0	mV max mV max
I _{FB}	FEEDBACK Bias Current	I _{FB} ; V _{ANODE} ≤ V _{FB} ≤ 5.06V	22 29	35 40	50 55	nA max nA max
e _n	V _R Noise	10 Hz to 10,000 Hz, V _{RO} = V _R	30			μV _{RMS}

(5) V_{R} is the cathode-feedback voltage, nominally 1.244V.

(6) Average reference drift is calculated from the measurement of the reference voltage at 25°C and at the temperature extremes. The drift, in ppm/ $^\circ\text{C}$, is $10^6 \cdot \Delta V_{\text{R}} / (V_{\text{R}[25^\circ\text{C}]} \cdot \Delta T_{\text{J}})$, where ΔV_{R} is the lowest value subtracted from the highest, $V_{\text{R}[25^\circ\text{C}]}$ is the value at 25°C , and ΔT_{J} is the temperature range. This parameter is ensured by design and sample testing.

(7) Hysteresis is the change in V_{R} caused by a change in T_{J} , after the reference has been “dehysteresized”. To dehysteresize the reference; that is minimize the hysteresis to the typical value, its junction temperature should be cycled in the following pattern, spiraling in toward 25°C : 25°C , 85°C , -40°C , 70°C , 0°C , 25°C .

(8) Low contact resistance is required for accurate measurement.

Typical Performance Characteristics (Reference)

$T_J = 25^\circ\text{C}$, FEEDBACK pin shorted to $V^- = 0\text{V}$, unless otherwise noted




Figure 3.




Figure 4.




Figure 5.




Figure 6.




Figure 7.




Figure 8.

Typical Performance Characteristics (Reference) (continued)

$T_J = 25^\circ\text{C}$, FEEDBACK pin shorted to $V^- = 0\text{V}$, unless otherwise noted




Figure 9.




Figure 10.




Figure 11.




Figure 12.




Figure 13.




Figure 14.

Typical Performance Characteristics (Reference) (continued)

$T_J = 25^\circ\text{C}$, FEEDBACK pin shorted to $V^- = 0\text{V}$, unless otherwise noted




Figure 15.




Figure 16.




Figure 17.




Figure 18.










Figure 19.

Typical Performance Characteristics (Op Amps)

$V^+ = 5V$, $V^- = \text{GND} = 0V$, $V_{CM} = V^+/2$, $V_{OUT} = V^+/2$, $T_J = 25^\circ\text{C}$, unless otherwise noted



Typical Performance Characteristics (Op Amps) (continued)

$V^+ = 5V$, $V^- = GND = 0V$, $V_{CM} = V^+/2$, $V_{OUT} = V^+/2$, $T_J = 25^\circ C$, unless otherwise noted




Figure 26.




Figure 27.




Figure 28.




Figure 29.




Figure 30.




Figure 31.

Typical Performance Characteristics (Op Amps) (continued)

$V^+ = 5V$, $V^- = GND = 0V$, $V_{CM} = V^+/2$, $V_{OUT} = V^+/2$, $T_J = 25^\circ C$, unless otherwise noted




Figure 32.




Figure 33.




Figure 34.




Figure 35.




Figure 36.










Figure 37.

Typical Performance Characteristics (Op Amps) (continued)

$V^+ = 5V$, $V^- = GND = 0V$, $V_{CM} = V^+/2$, $V_{OUT} = V^+/2$, $T_J = 25^\circ C$, unless otherwise noted



Typical Performance Distributions




Figure 44.




Figure 45.




Figure 46.




Figure 47.




Figure 48.




Figure 49.

Typical Performance Distributions (continued)




Figure 50.




Figure 51.





Figure 52.

APPLICATION INFORMATION

VOLTAGE REFERENCE

Reference Biasing

The voltage reference is of a shunt regulator topology that models as a simple zener diode. With current I_r flowing in the 'forward' direction there is the familiar diode transfer function. I_r flowing in the reverse direction forces the reference voltage to be developed from cathode to anode. The applied voltage to the cathode may range from a diode drop below V^- to the reference voltage or to the avalanche voltage of the parallel protection diode, nominally 7V. A 6.3V reference with $V^+ = 3V$ is allowed.



**Figure 53. Voltages Associated with Reference
(Current Source I_r is External)**

The reference equivalent circuit reveals how V_r is held at the constant 1.2V by feedback, and how the FEEDBACK pin passes little current.

To generate the required reverse current, typically a resistor is connected from a supply voltage higher than the reference voltage. Varying that voltage, and so varying I_r , has small effect with the equivalent series resistance of less than an ohm at the higher currents. Alternatively, an active current source, such as the LM134 series, may generate I_r .




Figure 54. Reference Equivalent Circuit




Figure 55. 1.2V Reference

Capacitors in parallel with the reference are allowed. See the [Reference AC Stability Range curve](#) for capacitance values—from 20 μA to 3 mA any capacitor value is stable. With the reference's wide stability range with resistive and capacitive loads, a wide range of RC filter values will perform noise filtering.

Adjustable Reference

The FEEDBACK pin allows the reference output voltage, V_{ro} , to vary from 1.24V to 6.3V. The reference attempts to hold V_r at 1.24V. If V_r is above 1.24V, the reference will conduct current from Cathode to Anode; FEEDBACK current always remains low. If FEEDBACK is connected to Anode, then $V_{ro} = V_r = 1.24\text{V}$. For higher voltages FEEDBACK is held at a constant voltage above Anode—say 3.76V for $V_{ro} = 5\text{V}$. Connecting a resistor across the constant V_r generates a current $I = R1/V_r$ flowing from Cathode into FEEDBACK node. A Thevenin equivalent 3.76V is generated from FEEDBACK to Anode with $R2 = 3.76/I$. Keep I greater than one thousand times larger than FEEDBACK bias current for $<0.1\%$ error— $I \geq 32\text{ }\mu\text{A}$ for the military grade over the military temperature range ($I \geq 5.5\text{ }\mu\text{A}$ for a 1% untrimmed error for a commercial part.)





Figure 56. Thevenin Equivalent of Reference with 5V Output



$$R1 = V_r / I = 1.24 / 32\mu = 39k$$

$$R2 = R1 \{ (V_{ro}/V_r) - 1 \} = 39k \{ (5/1.24) - 1 \} = 118k$$

Figure 57. Resistors R1 and R2 Program Reference Output Voltage to be 5V

Understanding that V_r is fixed and that voltage sources, resistors, and capacitors may be tied to the FEEDBACK pin, a range of V_r temperature coefficients may be synthesized.




Figure 58. Output Voltage has Negative Temperature Coefficient (TC) if R2 has Negative TC




Figure 59. Output Voltage has Positive TC if R1 has Negative TC





Figure 60. Diode in Series with R1 Causes Voltage Across R1 and R2 to be Proportional to Absolute Temperature (PTAT)

Connecting a resistor across Cathode-to-FEEDBACK creates a 0 TC current source, but a range of TCs may be synthesized.



$$I = V_r/R1 = 1.24/R1$$

Figure 61. Current Source is Programmed by R1




Figure 62. Proportional-to-Absolute-Temperature Current Source




Figure 63. Negative –TC Current Source

Hysteresis

The reference voltage depends, slightly, on the thermal history of the die. Competitive micro-power products vary—always check the data sheet for any given device. Do not assume that no specification means no hysteresis.

OPERATIONAL AMPLIFIER

The amp or the reference may be biased in any way with no effect on the other, except when a substrate diode conducts (see ⁽¹⁾ under [Electrical Characteristics](#)). The amp may have inputs outside the common-mode range, may be operated as a comparator, or have all terminals floating with no effect on the reference (tying inverting input to output and non-inverting input to V^- on unused amp is preferred). Choosing operating points that cause oscillation, such as driving too large a capacitive load, is best avoided.

Op Amp Output Stage

The op amp, like the LM124 series, has a flexible and relatively wide-swing output stage. There are simple rules to optimize output swing, reduce cross-over distortion, and optimize capacitive drive capability:

1. **Output Swing:** Unloaded, the 42 μA pull-down will bring the output within 300 mV of V^- over the military temperature range. If more than 42 μA is required, a resistor from output to V^- will help. Swing across any load may be improved slightly if the load can be tied to V^+ , at the cost of poorer sinking open-loop voltage gain.
2. **Cross-over Distortion:** The LM611 has lower cross-over distortion (a 1 V_{BE} deadband versus 3 V_{BE} for the LM124), and increased slew rate as shown in the [Typical Performance Characteristics curves](#). A resistor pull-up or pull-down will force class-A operation with only the PNP or NPN output transistor conducting, eliminating cross-over distortion.
3. **Capacitive Drive:** Limited by the output pole caused by the output resistance driving capacitive loads, a pull-down resistor conducting 1 mA or more reduces the output stage NPN r_e until the output resistance is that of the current limit 25 Ω . 200 pF may then be driven without oscillation.

Op Amp Input Stage

The lateral PNP input transistors, unlike those of most op amps, have BV_{EBO} equal to the absolute maximum supply voltage. Also, they have no diode clamps to the positive supply nor across the inputs. These features make the inputs look like high impedances to input sources producing large differential and common-mode voltages.

Typical Applications




Figure 64. Ultra Low Noise 10.000V Reference.
Total Output Noise is Typically 14 μV_{RMS} .
Adjust the 10k pot for 10.000V.

(1) Absolute maximum ratings indicate limits beyond which damage to the component may occur. Electrical specifications do not apply when operating the device beyond its rated operating conditions.





Figure 65. Simple Low Quiescent Drain Voltage Regulator. Total Supply Current is approximately 320 μ A when $V_{IN} = 5V$, and output has no load.



$V_{OUT} = (R1/R2 + 1) V_{REF}$.
R1, R2 should be 1% metal film.
R3 should be low t.c. trim pot.

Figure 66. Slow Rise-Time Upon Power-Up, Adjustable Transducer Bridge Driver. Rise-time is approximately 0.5 ms.



Simplified Schematic Diagrams




Figure 69. Op Amp




Figure 70. Reference




Figure 71. Bias

REVISION HISTORY

Changes from Revision B (March 2013) to Revision C

Page

- Changed layout of National Data Sheet to TI format [21](#)

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish	MSL Peak Temp (3)	Op Temp (°C)	Top-Side Markings (4)	Samples
LM611CM	ACTIVE	SOIC	D	14	55	TBD	Call TI	Call TI	0 to 70	LM611CM	Samples
LM611CM/NOPB	ACTIVE	SOIC	D	14	55	Green (RoHS & no Sb/Br)	CU SN	Level-1-260C-UNLIM	0 to 70	LM611CM	Samples
LM611CMX	ACTIVE	SOIC	D	14	2500	TBD	Call TI	Call TI	0 to 70	LM611CM	Samples
LM611CMX/NOPB	ACTIVE	SOIC	D	14	2500	Green (RoHS & no Sb/Br)	CU SN	Level-1-260C-UNLIM	0 to 70	LM611CM	Samples
LM611IM	ACTIVE	SOIC	D	14	55	TBD	Call TI	Call TI	-40 to 85	LM611IM	Samples
LM611IM/NOPB	ACTIVE	SOIC	D	14	55	Green (RoHS & no Sb/Br)	CU SN	Level-1-260C-UNLIM	-40 to 85	LM611IM	Samples
LM611IMX	ACTIVE	SOIC	D	14	2500	TBD	Call TI	Call TI	-40 to 85	LM611IM	Samples
LM611IMX/NOPB	ACTIVE	SOIC	D	14	2500	Green (RoHS & no Sb/Br)	CU SN	Level-1-260C-UNLIM	-40 to 85	LM611IM	Samples

(1) The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSELETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) Multiple Top-Side Markings will be inside parentheses. Only one Top-Side Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Top-Side Marking for that device.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION


*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
LM611CMX	SOIC	D	14	2500	330.0	16.4	6.5	9.35	2.3	8.0	16.0	Q1
LM611CMX/NOPB	SOIC	D	14	2500	330.0	16.4	6.5	9.35	2.3	8.0	16.0	Q1
LM611IMX	SOIC	D	14	2500	330.0	16.4	6.5	9.35	2.3	8.0	16.0	Q1
LM611IMX/NOPB	SOIC	D	14	2500	330.0	16.4	6.5	9.35	2.3	8.0	16.0	Q1

TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
LM611CMX	SOIC	D	14	2500	349.0	337.0	45.0
LM611CMX/NOPB	SOIC	D	14	2500	349.0	337.0	45.0
LM611IMX	SOIC	D	14	2500	349.0	337.0	45.0
LM611IMX/NOPB	SOIC	D	14	2500	349.0	337.0	45.0

D (R-PDSO-G14)

PLASTIC SMALL OUTLINE



4040047-5/M 06/11

NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
- D. Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
- E. Reference JEDEC MS-012 variation AB.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.