

# 100 MHz to 1000 MHz Integrated Broadband Receiver ADRF6850

#### FEATURES

IQ quadrature demodulator Integrated fractional-N PLL and VCO Gain control range: 60 dB Input frequency range: 100 MHz to 1000 MHz Input P1dB: +12 dBm at 0 dB gain Input IP3: +22.5 dBm at 0 dB gain Noise figure: 11 dB at >39 dB gain, 49 dB at 0 dB gain Baseband 1 dB bandwidth: 250 MHz in wideband mode,

50 MHz in narrow-band mode SPI/I<sup>2</sup>C serial interface Power supply: +3.3 V/350 mA

#### **APPLICATIONS**

Broadband communications Cellular communications Satellite communications

### **GENERAL DESCRIPTION**

The ADRF6850 is a highly integrated broadband quadrature demodulator, frequency synthesizer, and variable gain amplifier (VGA). The device covers an operating frequency range from 100 MHz to 1000 MHz for use in both narrow-band and wideband communications applications, performing quadrature demodulation from IF directly to baseband frequencies.

The ADRF6850 demodulator includes a high modulus fractional-N frequency synthesizer with integrated VCO, providing better than 1 Hz frequency resolution, and a 60 dB gain control range provided by a front-end VGA.

Control of all the on-chip registers is through a user-selected SPI interface or  $I^2C$  interface. The device operates from a single power supply ranging from 3.15 V to 3.45 V.



#### FUNCTIONAL BLOCK DIAGRAM

#### Rev. 0

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

 One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.

 Tel: 781.329.4700
 www.analog.com

 Fax: 781.461.3113
 ©2010 Analog Devices, Inc. All rights reserved.

# TABLE OF CONTENTS

Features	1
Applications	1
General Description	1
Functional Block Diagram	1
Revision History	2
Specifications	3
Timing Characteristics	5
Absolute Maximum Ratings	7
ESD Caution	7
Pin Configuration and Function Descriptions	8
Typical Performance Characteristics10	0
Theory of Operation1	8
Overview1	8
PLL Synthesizer and VCO1	8
Quadrature Demodulator20	0
Variable Gain Amplifier (VGA)20	0

I <sup>2</sup> C Interface	. 20
SPI Interface	. 22
Program Modes	. 24
Register Map	. 26
Register Map Summary	. 26
Register Bit Descriptions	. 27
Suggested Power-Up Sequence	. 30
Initial Register Write Sequence	. 30
Evaluation Board	. 31
General Description	. 31
Hardware Description	. 31
PCB Schematic	. 33
PCB Artwork	. 34
Bill of Materials	. 35
Outline Dimensions	. 36
Ordering Guide	. 36

### **REVISION HISTORY**

10/10—Revision 0: Initial Version

# **SPECIFICATIONS**

 $V_{CC}$  = 3.3 V; ambient temperature (T<sub>A</sub>) = 25°C; Z<sub>S</sub> = 50  $\Omega$ ; Z<sub>L</sub> = 100  $\Omega$  differential; PLL loop bandwidth = 50 kHz; REFIN = 13.5 MHz; PFD = 27 MHz; baseband frequency = 20 MHz, narrow-band mode, unless otherwise noted.

Table 1.					
Parameter	Test Conditions/Comments	Min	Тур	Max	Unit
RF INPUT	RFI, RFI, VGAIN pins				
Operating Frequency Range		100		1000	MHz
Input P1dB	0 dB gain		+12		dBm
	60 dB gain		-48		dBm
Input IP3	0 dB gain		+22.5		dBm
	60 dB gain		-38		dBm
Input IP2	0 dB gain, single-ended input		+40		dBm
	60 dB gain, single-ended input		-20		dBm
Noise Figure (NF)	0 dB gain		49		dB
	<39 dB gain NF rises 1:1 as gain in dB falls				
	>39 dB gain		11		dB
Maximum Gain	$Z_s = 50 \Omega$ single-ended, $Z_L = 100 \Omega$ differential		60		dB
Minimum Gain	$Z_s = 50 \Omega$ single-ended, $Z_L = 100 \Omega$ differential		0		dB
Gain Conformance Error <sup>1</sup>	V <sub>GAIN</sub> from 200 mV to 1.3 V		0.5		dB
Gain Slope			25		mV/dB
VGAIN Input Impedance			20		kΩ
Return Loss	Relative to $Z_s = 50 \Omega$ , 100 MHz to 1 GHz		15		dB
REFERENCE CHARACTERISTICS	REFIN pin				
Input Frequency	With R divide-by-2 divider enabled	10		300	MHz
	With R divide-by-2 divider disabled	10		165	MHz
<b>REFIN Input Sensitivity</b>		0.4		V <sub>cc</sub>	V р-р
REFIN Input Capacitance				10	pF
REFIN Input Current				±100	μΑ
CHARGE PUMP	CP and RSET pins				
I <sub>CP</sub> Sink/Source	Programmable				
High Value	With $R_{SET} = 4.7 \text{ k}\Omega$		5		mA
Low Value			312.5		μA
Absolute Accuracy	With $R_{SET} = 4.7 \text{ k}\Omega$		2.5		%
VCO					
Gain	K <sub>vco</sub>		15		MHz/V
SYNTHESIZER SPECIFICATIONS	Loop bandwidth = 50 kHz				
Frequency Increment			1		Hz
Phase Frequency Detector		10		30	MHz
Spurs					
	Integer boundary < loop bandwidth		-55		dBc
	>10 MHz offset from carrier		-70		dBc
Phase Noise	LO frequency = 1000 MHz				
	@ 10 Hz offset		-75		dBc/Hz
	@ 100 Hz offset		-80		dBc/Hz
	@ 1 kHz offset		-90		dBc/Hz
	@ 10 kHz offset		-98		dBc/Hz
	@ 100 kHz offset		-110		dBc/Hz
	@ 1 MHz offset		-136		dBc/Hz
	>10 MHz offset		-149		dBc/Hz
Integrated Phase Noise	1 kHz to 8 MHz integration bandwidth		0.26		°rms

Parameter	Test Conditions/Comments	Min	Тур	Мах	Unit
Frequency Settling	Any step size, maximum frequency error = 1 kHz		260	-	μs
Maximum Frequency Step for No	Frequency step with no autocalibration routine; 100		100	kHz	
	Register CR24, Bit $0 = 1$				
BASEBAND OUTPUTS	IBB, IBB, QBB, QBB, VOCM pins				
Maximum Swing	Driving $Z_L = 100 \Omega$ differential		2.5		V р-р
Common-Mode Range		1.2		1.6	V
Output Impedance	Differential		28		Ω
Output DC Offset	RFI terminated in $Z_s = 50 \Omega$		±20		mV
1 dB Bandwidth					
Wideband Mode			250		MHz
Narrow-Band Mode			50		MHz
IQ Balance					
Amplitude					
Wideband Mode	Baseband frequency $\leq$ 250 MHz		±0.1		dB
Narrow-Band Mode	Baseband frequency $\leq$ 33.2 MHz		±0.1		dB
Phase					
Wideband Mode	Baseband frequency ≤ 250 MHz		±0.5		Degrees
Narrow-Band Mode	Baseband frequency ≤ 33.2 MHz		±0.25		Degrees
IQ Output Impedance Mismatch	Baseband frequency = 10 MHz		±0.3		%
Group Delay Variation					
Wideband Mode	Baseband frequency ≤ 210 MHz		0.25		ns
	Baseband frequency $\leq$ 250 MHz		0.35		ns
Narrow-Band Mode	Baseband frequency $\leq$ 33.2 MHz		0.2		ns
LO to IQ Leakage	1×LO		-40		dBm
5	2×LO		-60		dBm
	4×LO		-60		dBm
RF to IQ Leakage	Relative to IQ output level		-40		dBc
MONITOR OUTPUT	LOMON and LOMON pins				
Nominal Output Power			-24		dBm
LOGIC INPUTS	SDI/SDA, CLK/SCL, CS pins				
Input High Voltage, V <sub>INH</sub>	CS	1.4			V
Input Low Voltage, V <sub>INL</sub>	CS			0.6	V
Input High Voltage, V <sub>INH</sub>	SDI/SDA, CLK/SCL	2.1			V
Input Low Voltage, V <sub>INL</sub>	SDI/SDA, CLK/SCL			1.1	V
Input Current, I <sub>INH</sub> /I <sub>INL</sub>	CS, SDI/SDA, CLK/SCL	±1		μA	
Input Capacitance, C <sub>IN</sub>	CS, SDI/SDA, CLK/SCL			10	pF
LOGIC OUTPUTS					
Output High Voltage, V <sub>он</sub>	SDO, LDET pins; I <sub>OH</sub> = 500 μA	2.8			V
Output Low Voltage, V <sub>OL</sub>	SDO, LDET pins; $I_{OI} = 500 \mu\text{A}$			0.4	V
	SDA (SDI/SDA) pins; $I_{01} = 3 \text{ mA}$			0.4	V
POWER SUPPLIES	VCC1, VCC2, VCC3, VCC4, VCC5, VCC6, VCC7, VCC8, and VCC9 pins				
Voltage Range		3.15	3.3	3.45	V
Supply Current			350	440	mA
Operating Temperature		-40		+85	°C

<sup>1</sup> Difference between channel gain and linear fit to channel gain.

### TIMING CHARACTERISTICS

### l<sup>2</sup>C Interface Timing

#### Table 2.

Parameter <sup>1</sup>	Symbol	Limit	Unit	
SCL Clock Frequency	f <sub>scl</sub>	400	kHz max	
SCL Pulse Width High	t <sub>HIGH</sub>	600	ns min	
SCL Pulse Width Low	t <sub>LOW</sub>	1300	ns min	
Start Condition Hold Time	t <sub>HD;STA</sub>	600	ns min	
Start Condition Setup Time	t <sub>su;sta</sub>	600	ns min	
Data Setup Time	t <sub>su;DAT</sub>	100	ns min	
Data Hold Time	t <sub>HD;DAT</sub>	300	ns min	
Stop Condition Setup Time	t <sub>su;sto</sub>	600	ns min	
Data Valid Time	t <sub>vD;DAT</sub>	900	ns max	
Data Valid Acknowledge Time	t <sub>vD;ACK</sub>	900	ns max	
Bus Free Time	t <sub>BUF</sub>	1300	ns min	

<sup>1</sup> See Figure 2.



Figure 2. I<sup>2</sup>C Port Timing Diagram

### SPI Interface Timing

#### Table 3.

Parameter <sup>1</sup>	Symbol	Limit	Unit
CLK Frequency	f <sub>clK</sub>	20	MHz max
CLK Pulse Width High	t <sub>1</sub>	15	ns min
CLK Pulse Width Low	t <sub>2</sub>	15	ns min
Start Condition Hold Time	t <sub>3</sub>	5	ns min
Data Setup Time	t <sub>4</sub>	10	ns min
Data Hold Time	t <sub>5</sub>	5	ns min
Stop Condition Setup Time	t <sub>6</sub>	5	ns min
SDO Access Time	t <sub>7</sub>	15	ns min
CS to SDO High Impedance	t <sub>8</sub>	25	ns max

<sup>1</sup> See Figure 3.



Figure 3. SPI Port Timing Diagram

# **ABSOLUTE MAXIMUM RATINGS**

#### Table 4. Absolute Maximum Ratings

Parameter	Rating
Supply Voltage Pins (VCC1, VCC2, VCC3, VCC4, VCC5, VCC6, VCC7, VCC8, VCC9)	–0.3 V to +4.0 V
Analog Input/Output	–0.3 V to +4.0 V
Digital Input/Output	–0.3 V to +4.0 V
RFI, RFI, RFCM	0 V to 3.0 V
$\theta_{JA}$ (Exposed Paddle Soldered Down)	26°C/W
Maximum Junction Temperature	125°C
Storage Temperature Range	–65°C to +150°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

### **ESD CAUTION**



**ESD** (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

# **PIN CONFIGURATION AND FUNCTION DESCRIPTIONS**



#### **Table 5. Pin Function Descriptions**

Pin No.	Mnemonic	Description
1, 13, 14, 15, 16, 31, 36, 42, 49	VCC1 to VCC9	Positive Power Supplies. Apply a 3.3 V power supply to all VCCx pins. Decouple each pin with a power supply decoupling capacitor.
6, 8, 19, 20, 21, 24, 32, 37, 41, 44, 45, 46, 47, 48, 50, 52, 54, 56	GND	Analog Ground. Connect to a low impedance ground plane.
2, 3, 4, 5	IBB, IBB, QBB, QBB	Differential In-Phase and Quadrature Baseband Outputs. These low impedance outputs can drive 2.5 V p-p into 100 $\Omega$ differential loads.
7	VOCM	Baseband Common-Mode Voltage Input. When ac coupling the baseband output pins, ground VOCM. There is an option to apply an external voltage, which may be relevant when dc coupling the baseband output pins. Note that Register CR29, Bit 6 must be set accordingly.
33	CCOMP1	Internal Compensation Node. This pin must be decoupled to ground with a 100 nF capacitor.
34	CCOMP2	Internal Compensation Node. This pin must be decoupled to ground with a 100 nF capacitor.
35	CCOMP3	Internal Compensation Node. This pin must be decoupled to ground with a 100 nF capacitor.
38	VTUNE	Control Input to the VCO. This voltage determines the output frequency and is derived from filtering the CP output voltage.
9	RSET	Charge Pump Current Set. Connecting a resistor between this pin and ground sets the maximum charge pump output current. The relationship between I <sub>CP</sub> and R <sub>SET</sub> is $I_{CPmax} = \frac{23.5}{R_{SET}}$
		where $R_{SET} = 4.7 \text{ k}\Omega$ and $I_{CP max} = 5 \text{ mA}$ .
11	СР	Charge Pump Output. When enabled, this provides $\pm I_{CP}$ to the external loop filter, which in turn, drives the internal VCO.
27	CS	Chip Select. CMOS input. When CS is high, the data stored in the shift registers is loaded into one of the 31 registers. In I <sup>2</sup> C mode, when CS is high, the slave address of the device is 0x78, and when CS is low, the slave address is 0x58.
29	SDI/SDA	Serial Data Input for SPI Port, Serial Data Input/Output for I <sup>2</sup> C Port. In SPI mode. This input is a high impedance CMOS data input, and data is loaded in an 8-bit word. In I <sup>2</sup> C mode, this pin is a bidirectional port.
30	CLK/SCL	Serial Clock Input for SPI/I <sup>2</sup> C Port. This serial clock is used to clock in the serial data to the registers. This input is a high impedance CMOS input.
28	SDO	Serial Data Output for SPI Port. Register states can be read back on the SDO data output line in an 8-bit word.
17	REFIN	Reference Input. AC couple this high impedance CMOS input.
18	REFIN	Reference Input Bar. Ground this pin.

Rev. 0 | Page 8 of 36

Pin No.	Mnemonic	Description
51, 55	RFI, RFI	RF Inputs. 50 $\Omega$ internally biased RF inputs. For single-ended operation, RFI must be ac-coupled to the source, and RFI must be ac-coupled to the ground plane.
53	RFCM	RF Input Common Mode. Connect to RFI when driving the input in single-ended mode. When driving the input differentially using a balun, connect this pin to the common terminal of the output coil of the balun. Decouple RFCM to the ground plane.
25, 26	LOMON, LOMON	Differential Monitor Outputs. These pins provide a replica of the internal local oscillator frequency (1×LO) at four different power levels: -6 dBm, -12 dBm, -18 dBm, and -24 dBm, approximately. These open-collector outputs must be terminated with external resistors to VCCx. These outputs can be disabled through serial port programming and should be connected to VCCx if not used.
10, 12	LF3/LF2	Extra Loop Filter Pins for Fastlock. Use these pins to reduce lock time.
40	LDET	Lock Detect. This pin provides an active high output when the PLL frequency is locked. The lock detect timing is controlled by Register CR14 (Bit 7) and Register CR23 (Bit 3).
39	MUXOUT	Muxout. This output is a test output for diagnostic use only. Allow this pin to remain open circuit.
22, 23	TESTLO, TESTLO	Differential Test Inputs. For internal use only. These pins should be grounded.
43	VGAIN	VGA Gain Input. Drive this pin by a voltage in the range from 0 V to 1.5 V. This voltage controls the gain of the VGA. A 0 V input sets the VGA gain to 0 dB, whereas a 1.5 V input sets the VGA gain to +60 dB if the VGA Gain Mode Polarity Bit CR30, Bit 2, is set to 0. If the VGA gain mode polarity bit is set to 1, a 0 V input sets the VGA gain to +60 dB, whereas a 1.5 V input sets the VGA gain to 0 dB.
	EP	Exposed Paddle. Connect the exposed pad to the ground plane via a low impedance path.

# **TYPICAL PERFORMANCE CHARACTERISTICS**

A nominal condition is defined as 25°C, 3.30 V, and worst-case frequency. A worst-case condition is defined as having the worst-case temperature, supply voltage, and frequency.



Figure 5. Input 1dB Compression Point (IP1dB) vs. Channel Gain, and RF Input Frequency, Nominal Conditions, Narrow-Band Mode



Figure 6. Input 1dB Compression Point (IP1dB) vs. Channel Gain, Supply, and Temperature, RF Input Frequency = 100 MHz, Narrow-Band Mode



Figure 7. Input 1dB Compression Point (IP1dB) vs. Channel Gain, Supply, and Temperature, RF Input Frequency = 1000 MHz, Narrow-Band Mode



Figure 8. Input 1dB Compression Point (IP1dB) Distribution with Channel Gain = 0 dB at Nominal and Worst-Case Conditions



Figure 9. Input 1dB Compression Point (IP1dB) Distribution with Channel Gain = 60 dB at Nominal and Worst-Case Conditions



Figure 10. Input 1dB Compression Point (IP1dB) vs. Channel Gain, and RF Input Frequency,  $V_{oCM} = 1.2$  V, Nominal Conditions, Narrow-Band Mode



Figure 11. Input 1dB Compression Point (IP1dB) vs. Channel Gain, and RF Input Frequency,  $V_{OCM} = 1.6$  V, Nominal Conditions, Narrow-Band Mode



Figure 12. Input 1dB Compression Point (IP1dB) vs. Channel Gain, and IQ Output Frequency, LO = 1000 MHz, Nominal Conditions, Wideband Mode



Figure 13. Input IP3 vs. Channel Gain, and RF Input Frequency, Nominal Conditions



Figure 14. Input IP3 vs. Channel Gain, and RF Input Frequency, Worst-Case Conditions



Figure 15. Input IP3 Distribution with Channel Gain = 0 dB at Nominal and Worst-Case Conditions



Figure 16. Input IP3 Distribution with Channel Gain = 60 dB at Nominal and Worst-Case Conditions



Figure 17. Input IP3 vs. Channel Gain, and IQ Output Frequency, Wideband Mode, Nominal Conditions



Figure 18. Input IP3 vs. Channel Gain, and IQ Output Frequency, Wideband Mode, Worst-Case Conditions



Figure 19. Input IP2 vs. Channel Gain, Wideband Mode, Nominal Conditions



Figure 20. Input IP2 vs. Channel Gain, Wideband Mode, Worst-Case Conditions



Figure 21. Noise Figure vs. Channel Gain, and RF Input Frequency, Narrow-Band Mode, Nominal Conditions



Figure 22. Noise Figure vs. Channel Gain, and RF Input Frequency, Narrow-Band Mode, Worst-Case Conditions



Figure 23. Noise Figure Distribution vs. Channel Gain, Narrow-Band Mode, Nominal Conditions



Figure 24. Noise Figure Distribution vs. Channel Gain, Narrow-Band Mode, Worst-Case Conditions



Figure 25. Noise Figure vs. Channel Gain, and RF Input Frequency, Wideband Mode, Nominal Conditions



Figure 26. Channel Gain vs. V<sub>GAIN</sub> and RF Input Frequency, Nominal Conditions



Figure 27. Channel Gain Range Distribution at Nominal and Worst-Case Conditions



gure 28. Minimum Channel Gain vs. RF Input Frequenc Supply, and Temperature







Figure 30. Maximum Channel Gain vs. RF Input Frequency, Supply, and Temperature



Figure 31. Maximum Channel Gain Distribution at Nominal and Worst-Case Conditions



Figure 32. Channel Gain Conformance Error vs. V<sub>GAIN</sub> and RF Input Frequency, Nominal Conditions



Figure 33. Input Return Loss vs. RF Input Frequency and Channel Gain, Nominal Conditions



Figure 34. Integer Boundary Spurs vs. LO Frequency, Channel Gain, Supply, and Temperature



Figure 35. Reference Spurs at 13.5 MHz from Carrier vs. LO Frequency, Channel Gain, Supply, and Temperature



Figure 36. PFD Spurs at 27 MHz from Carrier vs. LO Frequency, Channel Gain, Supply, and Temperature



Figure 37. Phase Noise Performance Including Distribution Table at LO Frequency = 100 MHz at Nominal and Worst-Case Conditions



Figure 38. Phase Noise Performance Including Distribution Table at LO Frequency = 1000 MHz at Nominal and Worst-Case Conditions



Figure 39. Integrated Phase Noise vs. LO Frequency, Supply, and Temperature



Figure 40. Integrated Phase Noise Distribution with LO Frequency = 1000 MHz at Nominal and Worst-Case Conditions







Figure 42. Output DC Offset Distribution for I and Q Outputs, Nominal Conditions



Figure 43. Normalized IQ Output Bandwidth, Narrow-Band, and Wideband Modes, Nominal Conditions



Figure 44. Absolute IQ Amplitude Balance, Narrow-Band Mode, Nominal Conditions



Figure 45. IQ Phase Balance, Narrow-Band Mode, Nominal Conditions



Figure 46. 1×LO Feedthrough vs. LO Frequency, V<sub>GAIN</sub> Supply, and Temperature (Narrow-Band Mode)



Figure 47. 2× LO Feedthrough vs. LO Frequency, V<sub>GAIN</sub>, Supply, and Temperature (Narrow-Band Mode)



Figure 48. 4× LO Feedthrough vs. LO Frequency, V<sub>GAIN</sub> Supply, and Temperature (Narrow-Band Mode)



Figure 49. 1× LO Feedthrough Distribution at Nominal and Worst-Case Conditions with LO Frequency > 300 MHz, Narrow-Band Mode



Figure 50. 1×LO Feedthrough vs. LO Frequency, V<sub>GAIN</sub>, Supply, and Temperature, Fourth-Order Filter at 300 MHz Applied, Wideband Mode



Figure 51. 1× RF Feedthrough vs. RF Input Frequency, V<sub>GAIN</sub>, Supply, and Temperature, Narrow-Band Mode



Figure 52. 1× RF Feedthrough vs. RF Input Frequency, V<sub>GAIN</sub>, Supply, and Temperature, Fourth-Order Filter at 300 MHz Applied, Wideband Mode

### THEORY OF OPERATION overview

The ADRF6850 device can be separated into the following basic building blocks:

- PLL synthesizer and VCO
- Quadrature demodulator
- Variable gain amplifier (VGA)
- I<sup>2</sup>C/SPI interface

Each of these building blocks is described in detail in the sections that follow.

### PLL SYNTHESIZER AND VCO

#### Overview

The phase-locked loop (PLL) consists of a fractional-N frequency synthesizer with a 25-bit fixed modulus, allowing a frequency resolution of less than 1 Hz over the entire frequency range. It also has an integrated voltage controlled oscillator (VCO) with a fundamental output frequency ranging from 2000 MHz to 4000 MHz. An RF divider, controlled by Register CR28, Bits[2:0], extends the lower limit of the frequency range to less than 400 MHz. This 400 MHz to 4000 MHz frequency output is then applied to a divide-by-4 quadrature circuit to provide a local oscillator (LO) ranging from 100 MHz to 1000 MHz to the quadrature demodulator.

#### **Reference Input Section**

The reference input stage is shown in Figure 53. SW1 and SW2 are normally closed switches. SW3 is normally open. When power-down is initiated, SW3 is closed, and SW1 and SW2 are open. This ensures that there is no loading of the REFIN pin at power-down.



#### **Reference Input Path**

The on-chip reference frequency doubler allows the input frequency of the reference signal to be doubled. This is useful for increasing the PFD comparison frequency. Making the PFD frequency higher improves the noise performance of the system. Doubling the PFD frequency usually improves the in-band phase noise performance by 3 dBc/Hz.

The 5-bit R-divider allows the input reference frequency  $(REF_{IN})$  to be divided down to produce the reference clock to the PFD. Division ratios from 1 to 32 are allowed.

An additional divide-by-2  $(\div 2)$  function in the reference input path allows for a greater division range.



The PFD frequency equation is

 $f_{PFD} = f_{REFIN} \times \left[ (1+D)/(R \times (1+T)) \right]$ (1) where:

ilere:

 $f_{REFIN}$  is the reference input frequency.

*D* is the doubler bit.

*R* is the programmed divide ratio of the binary 5-bit programmable reference divider (1 to 32). *T* is the  $\div$ 2 bit (0 or 1).

#### **RF Fractional-N Divider**

The RF fractional-N divider allows a division ratio in the PLL feedback path that can range from 23 to 4095. The relationship between the fractional-N divider and the LO frequency is described in the following section.

#### INT and FRAC Relationship

The integer (INT) and fractional (FRAC) values make it possible to generate output frequencies that are spaced by fractions of the phase frequency detector (PFD) frequency. See the Programming the Correct LO Frequency section for more information.

The LO frequency equation is

$$LO = f_{PFD} \times (INT + (FRAC/2^{25}))/2 \times 2^{RFDIV}$$
(2)

where:

LO is the local oscillator frequency.

 $f_{PFD}$  is the PFD frequency.

*INT* is the integer component of the required division factor and is controlled by the CR6 and CR7 registers. *FRAC* is the fractional component of the required division factor and is controlled by the CR0 to CR3 registers. *RFDIV* is the setting in Register CR28, Bits[2:0], and controls the setting of a divider at the output of the PLL.



### Phase Frequency Detector (PFD) and Charge Pump

The PFD takes inputs from the R-divider and the N-counter and produces an output proportional to the phase and frequency difference between them (see Figure 56 for a simplified schematic). The PFD includes a fixed delay element that sets the width of the antibacklash pulse, ensuring that there is no dead zone in the PFD transfer function.

(3)



#### Lock Detect (LDET)

LDET (Pin 40) signals when the PLL has achieved lock to an error frequency of less than 1 kHz. On a write to Register CR0, a new PLL acquisition cycle starts, and the LDET signal goes low. When lock has been achieved, this signal returns high.

#### Voltage Controlled Oscillator (VCO)

The VCO core in the ADRF6850 consists of three separate VCOs, each with 16 overlapping bands. This configuration of 48 bands allows the VCO frequency range to extend from 2000 MHz to 4000 MHz. The three VCOs are divided externally by a programmable divider (RFDIV controlled by Register CR28, Bits[2:0]). This divider provides divisions of 1, 2, 4, and 8 to ensure that the frequency range is extended from 250 MHz (2000 MHz/8) to 4000 MHz (4000 MHz/1). A lower limit of only 400 MHz is required. A divide-by-4 quadrature circuit provides the full LO frequency range from 100 MHz to 1000 MHz. Figure 57 shows a sweep of V<sub>TUNE</sub> vs. LO frequency demonstrating the three VCOs overlapping and the multiple overlapping bands within each VCO at the LO frequency range of 100 MHz to 1000 MHz. Note that this plot includes the RFDIV divider being incorporated to provide further divisions of the fundamental VCO frequency; thus, each VCO is used on four different occasions throughout the full LO frequency range. The choice of three 16-band VCOs and an RFDIV divider allows the wide frequency range to be covered without large VCO sensitivity (K<sub>VCO</sub>) or resultant poor phase noise and spurious performance.



The correct VCO and band are chosen automatically by the VCO and band select circuitry when Register CR0 is updated. This is referred to as autocalibration. The autocalibration time is set by Register CR25.

Autocalibration Time = 
$$(BSCDIV \times 24)/PFD$$

where:

*BSCDIV* = Register CR25, Bits[7:0]. *PFD* = PFD frequency.

For a PFD frequency of 27 MHz, BSCDIV = 112 to set an autocalibration time of 100  $\mu$ s.

Note that BSCDIV must be recalculated if the PFD frequency is changed. The recommended autocalibration setting is 100  $\mu$ s. During this time, the VCO V<sub>TUNE</sub> is disconnected from the output of the loop filter and is connected to an internal reference voltage. A typical frequency acquisition is shown in Figure 58.



After autocalibration, normal PLL action resumes, and the correct frequency is acquired to within a frequency error of 1 kHz in 260 µs typically. For a maximum cumulative step of 100 kHz, autocalibration can be turned off by Register CR24, Bit 0. This enables cumulative PLL acquisitions of 100 kHz or less to occur without the autocalibration procedure, which improves acquisition times significantly (see Figure 59).



Figure 59. PLL Acquisition Without Autocalibration for a 100 kHz Step

The VCO displays a variation of  $K_{VCO}$  as  $V_{TUNE}$  varies within the band and from band to band. Figure 60 shows how the  $K_{VCO}$  varies across the fundamental LO frequency range from 500 MHz to 1000 MHz. Note that  $K_{VCO}$  is shown at the LO frequency rather than at the VCO frequency. Figure 60 is useful when calculating the loop filter bandwidth and individual loop filter components using ADISimPLL<sup>\*\*</sup>. ADISimPLL is an Analog Devices, Inc., simulator that aids in PLL design, particularly with respect to the loop filter. It reports parameters such as phase noise, integrated phase noise, acquisition time, and so forth for a particular set of input conditions. ADISimPLL can be downloaded from www.analog.com.



#### Programming the Correct LO Frequency

There are two steps to programming the correct LO frequency. The user can calculate the N-divider ratio that is required in the PLL and the RFDIV value based on the required LO frequency and PFD frequency.

1. Calculate the value of RFDIV, which is used to program Register CR28, Bits[2:0], from the following lookup table (Table 6). See also Table 24.

#### Table 6. RFDIV Lookup Table

LO Frequency (MHz)	RFDIV = Register CR28[2:0]
500 to 1000	000 = divide-by-1
250 to 500	001 = divide-by-2
125 to 250	010 = divide-by-4
100 to 125	011 = divide-by-8

2. Using the following equation, calculate the value of the N-divider:

$$N = (2^{RFDIV} \times 2 \times LO) / (f_{PFD})$$
(4)

where: *N* is the N-divider value. *RFDIV* is the setting in Register CR28, Bits[2:0]. *LO* is the local oscillator frequency.  $f_{PFD}$  is the PFD frequency.

This equation is a different representation of Equation 2.

#### Example to Program the Correct LO Frequency

Assume that the PFD frequency is 27 MHz and the required LO frequency is 330 MHz.

Step 1. From Table 6, 
$$2^{\text{RFDIV}} = 2$$
.

Step 2. *N* = (2 × 2 × 330E+6)/(27E+6) = 48.888888889.

The N-divider value is composed of integer (INT) and fractional (FRAC) components according to the following equation:

$$N = INT + FRAC/2^{25}$$
<sup>(5)</sup>

INT = 48 and FRAC = 29,826,162.

The appropriate registers must then be programmed according to the register map, ensuring that Register CR0 is the last register to be programmed because this write starts a new PLL acquisition cycle.

### QUADRATURE DEMODULATOR

The quadrature demodulator can be powered up by Register CR29, Bit 0. It has an output filter with narrow-band and wideband modes, which are selected by Register CR29, Bit 3. Wideband mode has a 1 dB filter cutoff of 250 MHz. Narrow-band mode has selectable cutoff filters of 30 MHz through 50 MHz by programming Register CR29, Bits[5:4]. A dc bias voltage of 1.4 V ( $V_{OCM}$ ) can be set internally by setting Register CR29, Bit 6 = 1. To select an external dc bias voltage, set Register CR29, Bit 6 = 0, and drive Pin 7, VOCM, with the requisite external bias voltage.

### VARIABLE GAIN AMPLIFIER (VGA)

The variable gain amplifier (VGA) at the input to the demodulator can be driven either single-ended or differentially.

To drive single-ended, connect Pin 53, RFCM, to Pin 51,  $\overline{\text{RFI}}$ , and decouple both pins to ground with a 10 nF capacitor. Drive the input signal through Pin 55, RFI.

To drive differentially, use a balun with the RFI and  $\overline{\text{RFI}}$  pins driven by the balanced outputs of the balun, and connect the RFCM pin to the common balun output terminal. Decouple RFCM to ground.

The VGA gain range is approximately 60 dB and is achieved by varying the VGAIN voltage from 0 V to 1.5 V. The Typical Performance Characteristics section has more information on the VGA gain performance. A 0 V input on VGAIN sets the VGA gain to 0 dB, whereas a 1.5 V input sets the VGA gain to +60 dB if the VGA Gain Mode Polarity Bit CR30, Bit 2, is set to 0. If the VGA gain mode polarity bit is set to 1, a 0 V input voltage on VGAIN sets the VGA gain to +60 dB, whereas a 1.5 V input sets the VGA gain to 0 dB.

The VGA can be powered down by setting Register CR30, Bit 0, to 0 and can be powered up by setting this same bit to 1.

### I<sup>2</sup>C INTERFACE

The ADRF6850 supports a 2-wire, I<sup>2</sup>C-compatible serial bus that drives multiple peripherals. The part powers up in I<sup>2</sup>C mode but is not locked in this mode. To remain in I<sup>2</sup>C mode, it is

recommended that the user tie the CS line to either 3.3 V or GND, thus disabling SPI mode.

The serial data (SDA) and serial clock (SCL) inputs carry information between any devices that are connected to the bus. Each slave device is recognized by a unique address. The ADRF6850 has two possible 7-bit slave addresses for both read and write operations, 0x78 and 0x58. The MSB of the 7-bit slave address is set to 1. Bit 5 of the slave address is set by the CS pin (Pin 27). Bits[4:0] of the slave address are set to 11000. The slave address consists of the seven MSBs of an 8-bit word. The LSB of the word sets either a read or a write operation (see Figure 61). Logic 1 corresponds to a read operation, whereas Logic 0 corresponds to a write operation.

To control the device on the bus, the following protocol must be followed:

- 1. The master initiates a data transfer by establishing a start condition, defined by a high-to-low transition on SDA while SCL remains high. This indicates that an address/ data stream follows.
- 2. All peripherals respond to the start condition and shift the next eight bits (the 7-bit address and the R/W bit). The bits are transferred from MSB to LSB.
- 3. The peripheral that recognizes the transmitted address responds by pulling the data line low during the ninth clock pulse. This is known as an acknowledge bit.
- 4. All other devices then withdraw from the bus and maintain an idle condition. During the idle condition, the device

monitors the SDA and SCL lines waiting for the start condition and the correct transmitted address.

5. The R/W bit determines the direction of the data. Logic 0 on the LSB of the first byte indicates that the master writes information to the peripheral. Logic 1 on the LSB of the first byte indicates that the master reads information from the peripheral.

The ADRF6850 acts as a standard slave device on the bus. The data on the SDA pin is eight bits long, supporting the 7-bit addresses plus the R/W bit. The ADRF6850 has 34 subaddresses to enable the user-accessible internal registers; therefore, it interprets the first byte as the device address and the second byte as the starting subaddress.

Auto-increment mode is supported, which allows data to be read from or written to the starting subaddress, and each subsequent address, without manually addressing the subsequent subaddress. A data transfer is always terminated by a stop condition. The user can also access any unique subaddress register on a one-by-one basis without updating all registers.

Stop and start conditions can be detected at any stage of the data transfer. If these conditions are asserted out of sequence with normal read and write operations, they cause an immediate jump to the idle condition. If an invalid subaddress is issued by the user, the ADRF6850 does not issue an acknowledge and returns to the idle condition. In a no acknowledge condition, the SDA line is not pulled low on the ninth pulse. See Figure 62 and Figure 63 for sample write and read data transfers, Figure 64 for the timing protocol, and Figure 2 for a more detailed timing diagram.



Figure 64. I<sup>2</sup>C Data Transfer Timing

### **SPI INTERFACE**

The ADRF6850 supports the SPI protocol; however, the part powers up in I<sup>2</sup>C mode. To select and lock the SPI mode, three pulses must be sent to the CS pin, as shown in Figure 65. When the SPI protocol is locked in, it cannot be unlocked while the device remains powered up. To reset the serial interface, the part must be powered down and powered up again.

#### Serial Interface Selection

The CS pin controls selection of the I<sup>2</sup>C or SPI interface. Figure 65 shows the selection process that is required to lock in the SPI mode. To communicate with the part using the SPI protocol, three pulses must be sent to the CS pin. On the third rising edge, the part selects and locks the SPI protocol. Consistent with most SPI standards, the CS pin must be held low during all SPI communication to the part and held high at all other times.

#### SPI Serial Interface Functionality

The SPI serial interface of the ADRF6850 consists of the CS, SDI (SDI/SDA), CLK (CLK/SCL), and SDO pins. CS is used to select the device when more than one device is connected to the serial clock and data lines. CLK is used to clock data in and out of the part. The SDI line is used to write to the registers. The SDO pin is a dedicated output for the read mode. The part operates in slave mode and requires an externally applied serial clock to the CLK pin. The serial interface is designed to allow the part to be interfaced to systems that provide a serial clock that is synchronized to the serial data.

Figure 66 shows an example of a write operation to the ADRF6850. Data is clocked into the registers on the rising edge of CLK using a 24-bit write command. The first eight bits represent the write command (0xD4), the next eight bits are the register address, and the final eight bits are the data to be written to the specific register. Figure 67 shows an example of a read operation. In this example, a shortened 16-bit write command is first used to select the appropriate register for a read operation, the first eight bits representing the write command (0xD4) and the final eight bits representing the specific register. Then the CS line is pulsed low for a second time to retrieve data from the selected register using a 16-bit read command, the first eight bits representing the contents of the register being read. Figure 3 shows the timing for both SPI read and SPI write operations.





### **PROGRAM MODES**

The ADRF6850 has 34 8-bit registers to allow program control of a number of functions. Only 31 of these registers are writeable. Either an SPI or an  $I^2C$  interface can be used to program the register set. For details about the interfaces and timing, see Figure 61 to Figure 67. The registers are documented in Table 8 to Table 27.

Several settings in the ADRF6850 are double buffered. These settings include the FRAC value, the INT value, the RFDIV value, the 5-bit R-divider value, the reference doubler, the R  $\div$ 2 divider, and the charge pump current setting. This means that two events must occur before the part uses a new value for any of the double buffered settings. First, the new value is latched into the device by writing to the appropriate register. Next, a new write must be performed on Register CR0. When Register CR0 is written, a new PLL acquisition occurs.

For example, updating the fractional value involves a write to Register CR3, Register CR2, Register CR1, and Register CR0. Register CR3 should be written to first, followed by Register CR2 and Register CR1 and, finally, Register CR0. The new acquisition begins after the write to Register CR0. Double buffering ensures that the bits written to do not take effect until after the write to Register CR0.

#### 12-Bit Integer Value

Register CR7 and Register CR6 program the integer value (INT) of the feedback division factor (N); see Equation 5 for details. The INT value is a 12-bit number whose MSBs are programmed through Register CR7, Bits[3:0]. The LSBs are programmed through Register CR6, Bits[7:0]. The LO frequency setting is described by Equation 2. An alternative to this equation is provided by Equation 4, which details how to set the N-divider value. Note that these registers are double buffered.

#### 25-Bit Fractional Value

Register CR3 to Register CR0 program the fractional value (FRAC) of the feedback division factor (N); see Equation 5 for details. The FRAC value is a 25-bit number whose MSB is programmed through Register CR3, Bit 0. The LSB is programmed through Register CR0, Bit 0. The LO frequency setting is described by Equation 2. Again, an alternative to this equation is described by Equation 4, which details how to set the N-divider value. Note that these registers are double buffered.

#### **RFDIV Value**

The RFDIV value is dependent on the value of the LO frequency. The RFDIV value can be selected from the list in Table 6. Apply the selected RFDIV value to Equation 4, together with the LO frequency and PFD frequency values, to calculate the correct Ndivider value.

#### **Reference Input Path**

The reference input path consists of a reference doubler, a 5-bit frequency divider, and a divide-by-2 function (see Figure 54). The doubler is programmed through Register CR10, Bit 5. The

5-bit divider is enabled by programming Register CR5, Bit 4; and the division ratio is programmed through Register CR10, Bits[4:0]. The R  $\div$ 2 divider is programmed through Register CR10, Bit 6. Note that these registers are double buffered.

#### **Charge Pump Current**

Register CR9, Bits[7:4], set the charge pump current setting. With an  $R_{SET}$  value of 4.7 k $\Omega$ , the maximum charge pump current is 5 mA. The following equation applies:

$$I_{CP\,max} = 23.5/R_{SET} \tag{6}$$

The charge pump current has 16 settings from 325  $\mu A$  to 5 mA.

#### Power-Down/Power-Up Control Bits

The four programmable power-up and power-down control bits are as follows:

- Register CR12, Bit 2. Master power control bit for the PLL, including the VCO. This bit is normally set to a default value of 0 to power up the PLL.
- Register CR27, Bit 2. Controls the LO monitor outputs, LOMON and LOMON. The default is 0 when the monitor outputs are powered down. Setting this bit to 1 powers up the monitor outputs to one of -6 dBm, -12 dBm, -18 dBm, or -24 dBm, as controlled by Register CR27, Bits[1:0].
- Register CR29, Bit 0. Controls the quadrature demodulator power. The default is 0, which powers down the demodulator. Write a 1 to this bit to power up the demodulator.
- Register CR30, Bit 0. This bit controls the VGA power and must be set to a 1 to power up the VGA.

#### Lock Detect (LDET)

Lock detect is enabled by setting Register CR23, Bit 4, to 1. Register CR23, Bit 3, in conjunction with Register CR14, Bit 7, sets the number of up/down pulses generated by the PFD before lock detect is declared by the LDET pin returning high. The options are 2048 pulses, 3072 pulses, and 4096 pulses.

The default setting is 3072 pulses, which is selected by programming Register CR23, Bit 3, to 0, and Register CR14, Bit 7, to 0. A more aggressive setting of 2048 is selected when Register CR23, Bit 3, is set to 1 and Register CR14, Bit 7, is set to 0. This improves the lock detect time by 50  $\mu$ s (for a PFD frequency of 27 MHz). Note, however, that it does not affect the acquisition time to an error frequency of 1 kHz. A setting of 4096 pulses is selected when Register CR14, Bit 7, is set to 1. For best operation, set Register CR23, Bit 2 to 0. This bit sets up the PFD up/down pulses to a coarse or low precision setting.

#### **Baseband VOCM Reference**

Register CR29, Bit 6, selects whether the common-mode reference for the baseband outputs is internal or external. When the baseband outputs are ac-coupled, then the internal reference must be selected by setting Register CR29, Bit 6, to 1, and by grounding Pin 7, VOCM.

When the baseband outputs are dc-coupled, it is likely that an external bias is needed unless the internal dc bias provided is

within a suitable range to match the specification of the followon device. This is accomplished by setting Register CR29, Bit 6, to 0, and driving Pin 7, VOCM, with the requisite external bias voltage.

#### Narrow-Band and Wideband Filter Mode

By default, the second-order low-pass filter in the output buffers of the baseband output signal paths is selected, and the baseband outputs are in narrow-band mode. By setting Register CR29, Bits[5:4], this filter can be set to a cutoff frequency of 50 MHz, 43 MHz, 37 MHz, or 30 MHz. By setting Register CR29, Bit 3, to 1, this filter is bypassed and wideband mode is selected.

CR29[5:4]	Filter Cutoff Frequency (MHz)
00	50
01	43
10	37
11	30

#### VGA Gain Mode Polarity

The polarity of the VGA gain is set by programming Bit 2 of Register CR30. By setting Register CR30, Bit 2, to 0, a positive gain slope is selected where  $V_{GAIN} = 0$  V sets the VGA gain to be 0 dB, and  $V_{GAIN} = 1.5$  V sets the VGA gain to be 60 dB. By setting Register CR30, Bit 2, to 1, a negative gain slope is selected.

### **REGISTER MAP** REGISTER MAP SUMMARY

Table 8. Register Map Summary

Register Address (Hex)	Register Name	Туре	Description
0x00	CR0	Read/write	Fractional Word 4
0x01	CR1	Read/write	Fractional Word 3
0x02	CR2	Read/write	Fractional Word 2
0x03	CR3	Read/write	Fractional Word 1
0x04	CR4	Read/write	Reserved
0x05	CR5	Read/write	Reference 5-bit, R-divider enable
0x06	CR6	Read/write	Integer Word 2
0x07	CR7	Read/write	Integer Word 1
0x08	CR8	Read/write	Reserved
0x09	CR9	Read/write	Charge pump current setting
0x0A	CR10	Read/write	Reference frequency control
0x0B	CR11	Read/write	Reserved
0x0C	CR12	Read/write	PLL power-up
0x0D	CR13	Read/write	Reserved
0x0E	CR14	Read/write	Lock Detector Control 2
0x0F	CR15	Read/write	Reserved
0x10	CR16	Read/write	Reserved
0x11	CR17	Read/write	Reserved
0x12	CR18	Read/write	Reserved
0x13	CR19	Read/write	Reserved
0x14	CR20	Read/write	Reserved
0x15	CR21	Read/write	Reserved
0x16	CR22	Read/write	Reserved
0x17	CR23	Read/write	Lock Detector Control 1
0x18	CR24	Read/write	Autocalibration
0x19	CR25	Read/write	Autocalibration timer
0x1A	CR26	Read/write	Reserved
0x1B	CR27	Read/write	LO monitor output
0x1C	CR28	Read/write	LO selection
0x1D	CR29	Read/write	Demodulator power and filter selection
0x1E	CR30	Read/write	VGA
0x1F	CR31	Read only	Reserved
0x20	CR32	Read only	Reserved
0x21	CR33	Read only	Revision code

### **REGISTER BIT DESCRIPTIONS**

#### Table 9. Register CR0 (Address 0x00), Fractional Word 4

Bit	Description
7	Fractional Word F7 <sup>1</sup>
6	Fractional Word F6 <sup>1</sup>
5	Fractional Word F5 <sup>1</sup>
4	Fractional Word F4 <sup>1</sup>
3	Fractional Word F3 <sup>1</sup>
2	Fractional Word F2 <sup>1</sup>
1	Fractional Word F1 <sup>1</sup>
0	Fractional Word F0 (LSB) <sup>1</sup>
1 0	Fractional Word F1 <sup>1</sup> Fractional Word F0 (LSB) <sup>1</sup>

<sup>1</sup> Double buffered. Load on the write to Register CR0.

#### Table 10. Register CR1 (Address 0x01), Fractional Word 3

Bit	Description
7	Fractional Word F15 <sup>1</sup>
6	Fractional Word F14 <sup>1</sup>
5	Fractional Word F13 <sup>1</sup>
4	Fractional Word F12 <sup>1</sup>
3	Fractional Word F11 <sup>1</sup>
2	Fractional Word F10 <sup>1</sup>
1	Fractional Word F9 <sup>1</sup>
0	Fractional Word F8 <sup>1</sup>

<sup>1</sup> Double buffered. Load on the write to Register CR0.

### Table 11. Register CR2 (Address 0x02), Fractional Word 2

Bit	Description
7	Fractional Word F23 <sup>1</sup>
6	Fractional Word F22 <sup>1</sup>
5	Fractional Word F21 <sup>1</sup>
4	Fractional Word F20 <sup>1</sup>
3	Fractional Word F19 <sup>1</sup>
2	Fractional Word F18 <sup>1</sup>
1	Fractional Word F17 <sup>1</sup>
0	Fractional Word F16 <sup>1</sup>

<sup>1</sup> Double buffered. Load on the write to Register CR0.

#### Table 12. Register CR3 (Address 0x03), Fractional Word 1

Bit	Description
7	Reserved
6	Reserved
5	Reserved
4	Reserved
3	Reserved
2	Reserved
1	Reserved
0	Fractional Word F24 (MSB) <sup>1</sup>

<sup>1</sup> Double buffered. Load on the write to Register CR0.

# Table 13. Register CR5 (Address 0x05), Reference 5-Bit, R-Divider Enable

Bit	Description	
7	Reserved	
6	Reserved	
5	Reserved	
4	5-bit R-divider enable <sup>1</sup>	
	0 = disable 5-bit R-divider (default)	
	1 = enable 5-bit R-divider	
3	Reserved	
2	Reserved	
1	Reserved	
0	Reserved	

<sup>1</sup> Double buffered. Load on the write to Register CR0.

#### Table 14. Register CR6 (Address 0x06), Integer Word 2

Bit	Description
7	Integer Word N7 <sup>1</sup>
6	Integer Word N6 <sup>1</sup>
5	Integer Word N5 <sup>1</sup>
4	Integer Word N4 <sup>1</sup>
3	Integer Word N3 <sup>1</sup>
2	Integer Word N2 <sup>1</sup>
1	Integer Word N1 <sup>1</sup>
0	Integer Word N0 <sup>1</sup>
	•

<sup>1</sup> Double buffered. Load on the write to Register CR0.

#### Table 15. Register CR7 (Address 0x07), Integer Word 1

Bit	Description
[7:4]	MUXOUT control
	0000 = tristate
	0001 = logic high
	0010 = logic low
	1101 = RCLK/2
	1110 = NCLK/2
3	Integer Word N11 <sup>1</sup>
2	Integer Word N10 <sup>1</sup>
1	Integer Word N9 <sup>1</sup>
0	Integer Word N8 <sup>1</sup>

<sup>1</sup> Double buffered. Load on the write to Register CR0.

Bit	Description
[7:4]	Charge pump current <sup>1</sup>
	0000 = 0.31 mA (default)
	0001 = 0.63 mA
	0010 = 0.94 mA
	0011 = 1.25 mA
	0100 = 1.57 mA
	0101 = 1.88 mA
	0110 = 2.19 mA
	0111 = 2.50 mA
	1000 = 2.81 mA
	1001 = 3.13 mA
	1010 = 3.44 mA
	1011 = 3.75 mA
	1100 = 4.06 mA
	1101 = 4.38 mA
	1110 = 4.69 mA
	1111 = 5.00 mA
3	Reserved
2	Reserved
1	Reserved
0	Reserved

#### Table 16. Register CR9 (Address 0x09), Charge Pump **Current Setting**

### Table 18. Register CR12 (Address 0x0C), PLL Power-Up

Bit	Description
7	Reserved
6	Reserved
5	Reserved
4	Reserved
3	Reserved
2	PLL power-down
	0 = power up PLL (default)
	1 = power down PLL
1	Reserved
0	Reserved

#### Table 19. Register CR14 (Address 0x0E), Lock Detector Control 2

Bit	Description	
7	Lock Detector Up/Down Count 2	
	0 = 2048/3072 up/down pulses	
	1 = 4096 up/down pulses	
6	Reserved	
5	Reserved	
4	Reserved	
3	Reserved	
2	Reserved	
1	Reserved	
0	Reserved	

### <sup>1</sup> Double buffered. Load on the write to Register CR0.

# Table 17. Register CR10 (Address 0x0A), Reference Frequency Control

Frequency Control		Table 20. Register CR23 (Address 0x17), Lock Detector	
Bit	Description	Control 1	
7	Reserved <sup>1</sup>	Bit	Description
6	R divide-by-2 divider enable <sup>1</sup>	7	Reserved
0       = bypass         1       = enable         5       R-doubler e         0       = disable         1       = enable         1       = enable         2       5-bit R-divid         00000       = div         00001       = div          11110	0 = bypass R divide-by-2 divider 1 = enable R divide-by-2 divider R-doubler enable <sup>1</sup> 0 = disable doubler (default) 1 = enable doubler 5-bit R-divider setting <sup>1</sup> 00000 = divide by 32 (default) 00001 = divide by 1	6	Reserved
		5	Reserved
		4	Lock detector enable
			0 = lock detector disabled (default)
			1 = lock detector enabled
		3	Lock detector up/down count
			With Register $CR14[7] = 0$ :
			0 = 3072 up/down pulses
	00010 = divide by  2		1 = 2048 up/down pulses
		2	Lock detector precision
	 11110 = divide by 30		0 = low, coarse (16 ns)
	11111 = divide by  31		1 = high, fine (6 ns)
<sup>1</sup> Double buffered. Load on the write to Register CR0.		1	Reserved
		0	Reserved

Bit	Description
7	Reserved
6	Reserved
5	Reserved
4	Reserved
3	Reserved
2	Reserved
1	Reserved
0	Disable autocalibration
	0 = enable autocalibration (default)
	1 = disable autocalibration

#### Table 21. Register CR24 (Address 0x18), Autocalibration

### Table 22. Register CR25 (Address 0x19), Autocalibration

Timer	
Bit	Description
[7:0]	Autocalibration timer

#### Table 23. Register CR27 (Address 0x1B), LO Monitor Output

Bit	Description
7	Reserved
6	Reserved
5	Reserved
4	Reserved
3	Reserved
2 Power-up monitor output	
	0 = power down (default)
	1 = power up
[1:0]	Monitor output power into 50 $\Omega$
	00 = -24  dBm (default)
	01 = -18  dBm
	10 = -12  dBm
	11 = –6 dBm

#### Table 24. Register CR28 (Address 0x1C), LO Selection

Bit	Description
7	Reserved
6	Reserved
5	Reserved
4	Reserved
3	Reserved; set to 1
[2:0]	RFDIV
	000 = divide by 1; LO = 500 MHz to 1000 MHz
	001 = divide by 2; LO = 250 MHz to 500 MHz
	010 = divide by 4; LO = 125 MHz to 250 MHz
	011 = divide by 8; LO = 100 MHz to 125 MHz

# Table 25. Register CR29 (Address 0x1D), Demodulator Power and Filter Selection

Bit	Description	
7	Reserved	
6	Internal baseband (V <sub>OCM</sub> ) select	
	0 = select external baseband (V <sub>OCM</sub> ) reference	
	1 = select internal baseband (V <sub>OCM</sub> ) reference	
[5:4]	Narrow-band filter cut off	
	00 = 50 MHz	
	01 = 43 MHz	
	10 = 37 MHz	
	11 = 30 MHz	
3	Baseband wideband/narrow-band modes	
	0 = narrow-band mode	
	1 = wideband mode	
2	Reserved; set to 0	
1	Reserved; set to 0	
0	Power-up demodulator	
	0 = power down (default)	
	1 = power up	

#### Table 26. Register CR30 (Address 0x1E), VGA

Bit	Description		
7	Reserved		
6	Reserved		
5	Reserved		
4	Reserved		
3	Reserved		
2	VGA gain mode polarity		
	0 = positive gain slope		
	1 = negative gain slope		
1	Reserved		
0	Power-up VGA		
	0 = power down		
	1 = power up		

#### Table 27. Register CR33 (Address 0x21), Revision Code<sup>1</sup>

Bit	Description
7	Revision code
6	Revision code
5	Revision code
4	Revision code
3	Revision code
2	Revision code
1	Revision code
0	Revision code

<sup>1</sup> Read-only register.

# SUGGESTED POWER-UP SEQUENCE

After applying power to the device, adhere to the following write sequence, particularly with respect to the reserved register settings. Note that Register CR33, Register CR32, and Register CR31 are read-only registers. Also note that all writeable registers should be written to on power-up. Refer to the Register Map section for more details on all registers.

- 1. Write the following to Register CR30 = 0x00. Set VGA power to off and the VGA gain slope to be positive.
- 2. Write the following to Register CR29: 0x41. The demodulator is powered up. The baseband narrow-band mode is selected and set to a cutoff frequency of 50 MHz. The internal baseband  $V_{OCM}$  reference is selected.
- 3. Write the following to Register CR28: 0x0X RFDIV depends on the value of the LO frequency to be used and is set according to Table 6. Note that Register CR28, Bit 3, is set to 1.
- 4. Write the following to Register CR27: 0x00. Power the LO monitor in a power-down state.
- 5. Write the following to Register CR26: 0x00. Reserved register.
- Write the following to Register CR25: 0x70. Set the autocalibration time to 100 μs with a PFD frequency setting of 27 MHz. If the PFD frequency is different, set CR25 according to Equation 3.
- 7. Write the following to Register CR24: 0x38. Enable autocalibration.
- Write the following to Register CR23: 0x70. Enable lock detector and set lock detector counter = 3072 up/down pulses.
- 9. Write the following to Register CR22: 0x00. Reserved register.
- 10. Write the following to Register CR21: 0x00. Reserved register.
- 11. Write the following to Register CR20: 0x00. Reserved register.
- 12. Write the following to Register CR19: 0x00. Reserved register.
- 13. Write the following to Register CR18: 0x60. Reserved register.
- 14. Write the following to Register CR17: 0x00. Reserved register.
- 15. Write the following to Register CR16: 0x00. Reserved register.

- 16. Write the following to Register CR15: 0x00. Reserved register.
- 17. Write Register CR14: 0x00. Lock Detector Control 2.
- 18. Write Register CR13: 0x08. Reserved register.
- 19. Write the following to Register CR12: 0x18. PLL powered up.
- 20. Write the following to Register CR11: 0x00. Reserved register.
- 21. Write the following to Register CR10: 0x21. The reference path doubler is enabled and the 5-bit divider and R divideby-2 divider are bypassed.
- 22. Write the following to Register CR9: 0x70. With the recommended loop filter component values and  $R_{SET} = 4.7 \text{ k}\Omega$ , the charge pump current is set to 2.5 mA for a loop bandwidth of 50 kHz.
- 23. Write the following to Register CR8: 0x00. Reserved register.
- 24. Write the following to Register CR7: 0x0X. Set according to Equation 4 and Equation 5 in the Theory of Operation section.
- 25. Write the following to Register CR6: 0xXX. Set according to Equation 4 and Equation 5 in the Theory of Operation section.
- 26. Write Register CR5: 0x00. Disable the 5-bit reference divider.
- 27. Write the following to Register CR4: 0x01. Reserved register.
- 28. Write the following to Register CR3: 0x0X. Set according to Equation 4 and Equation 5 in the Theory of Operation section.
- 29. Write the following to Register CR2: 0xXX. Set according to Equation 4 and Equation 5 in the Theory of Operation section.
- 30. Write the following to Register CR1: 0xXX. Set according to Equation 4 and Equation 5 in the Theory of Operation section.
- 31. Write the following to Register CR0: 0xXX. Set according to Equation 4 and Equation 5 in the Theory of Operation section. Register CR0 must be the last register written for all the double buffered bit writes to take effect.
- 32. Monitor the LDET output or wait 260 μs to ensure that the PLL is locked.
- 33. Write the following to Register CR30: 0x01. Set the VGA to power on.

### **EVALUATION BOARD GENERAL DESCRIPTION**

The evaluation board is designed to allow the user to evaluate the performance of the ADRF6850. It contains the following:

- The ADRF6850 DUT. This is an I/Q demodulator with an integrated fractional-N PLL and VCO.
- SPI and I<sup>2</sup>C interface connectors.
- Baseband output connectors.
- Fourth-order low-pass loop filter circuitry.
- 13.5 MHz reference clock, and the ability to drive the reference input external to the board.
- Circuitry to support differential signaling to the TESTLO inputs, including dc biasing circuitry.
- Circuitry to monitor the LOMON outputs.
- SMA connectors for power supplies, the VGAIN input and a single-ended RF input.

The evaluation board comes with associated software to allow easy programming of the ADRF6850.

#### HARDWARE DESCRIPTION

For more information, refer to the circuit diagram in Figure 69.

#### **Power Supplies**

An external +3.3 V supply (DUT + 3.3 V) powers each of the nine VCCx supplies on the ADRF6850 as well as the 13.5 MHz clock reference.

#### **Recommended Decoupling for Supplies**

Initially, the external +3.3 V supply is decoupled by a 10  $\mu$ F capacitor and then further by a parallel combination of 100 nF and 56 pF capacitors that are placed as close to the DUT as possible for good local decoupling. The impedance of all these capacitors should be low and constant across a broad frequency range. Surface-mount multilayered ceramic chip (MLCC) Class II capacitors provide very low ESL and ESR, which assist in decoupling supply noise effectively. They also provide good temperature stability and good aging characteristics. Capacitance changes per the bias voltage that is applied. Larger case sizes have less capacitance change vs. applied bias voltage, and also lower ESR but higher ESL. A combination of 0402 size cases for the 56 pF capacitors and 0603 size cases for the 100 nF capacitors give a good compromise allowing the 56 pF capacitors to be placed as close as possible to the supply pins on the top side of the PCB with the 100 nF capacitors placed on the bottom side of the PCB quite close to the supply pins. X5R and X7R capacitors are examples of these types of capacitors and are recommended for decoupling.

#### SPI and I<sup>2</sup>C Interface

The SPI interface connector is a nine-way, D-type connector that can be connected to the printer port of a PC. Figure 68 shows the PC cable diagram that must be used with the provided software.

There is also an option to use the I<sup>2</sup>C interface by using the I<sup>2</sup>C receptacle connector. This is a standard I<sup>2</sup>C connector. A supply voltage of +3.3 V is provided by the I<sup>2</sup>C bus master. Pull-up resistors are required on the signal lines. The CS pin can be used to set the slave address of the ADRF6850. CS high sets the slave address to 0x78, and CS low sets the slave address to 0x58.



Figure 68. SPI PC Cable Diagram

### **Baseband Outputs and VOCM**

The pair of I and Q baseband outputs are connected to the board by SMA connectors. They are ac-coupled to the output connectors. VOCM, which sets the common-mode output voltage, is grounded and the internal baseband ( $V_{OCM}$ ) reference is selected by Register CR29, Bit 6. If the external baseband ( $V_{OCM}$ ) reference is selected by setting this bit to a 0, then a voltage needs to be applied through J6 and R20 needs to be removed.

### Loop Filter

A fourth-order loop filter is provided at the output of the charge pump and is required to adequately filter noise from the  $\Sigma$ - $\Delta$ modulator used in the N-divider. With the charge pump current set to a midscale value of 2.5 mA and using the on-chip VCO, the loop bandwidth is approximately 50 kHz, and the phase margin is 55°. COG capacitors are recommended for use in the loop filter because they have low dielectric absorption, which is required for fast and accurate settling time. The use of non COG capacitors may result in a long tail being introduced into the PLL settling time transient.

### **Reference Input**

The reference input can be supplied by a 13.5 MHz Jauch clock generator or by an external clock through the use of Connector J7. The frequency range of the reference input is from 10 MHz to 300 MHz with the PFD frequency limited to a maximum of 30 MHz. Double the 13.5 MHz clock to 27 MHz by using the onchip reference frequency doubler to optimize phase noise performance.

### **TESTLO** Inputs

These pins are differential test inputs that allow a variety of debug options. On this board, the capability is provided to drive these pins with an external  $4 \times \text{LO}$  signal that is then applied to an Anaren balun to provide a differential input signal.

When driving the TESTLO pins, the PLL can be bypassed, and the demodulator can be driven directly by this external LO signal. The frequency of the LO signal needs to be 4 times the operating frequency. These inputs also require a dc bias. A dc bias of 3.3 V is the default option used on the board.

### **LOMON** Outputs

These pins are differential LO monitor outputs that provide a replica of the internal LO frequency at  $1 \times \text{LO}$ . The single-ended power in a 50  $\Omega$  load can be programmed to -24 dBm, -18dBm, -12 dBm, or -6 dBm. These open-collector outputs must be terminated to 3.3 V. Because both outputs must be terminated to 50  $\Omega$ , options are provided to terminate to 3.3 V using onboard 50  $\Omega$  resistors or by series inductors (or a ferrite bead), in which case the 50  $\Omega$  termination is provided by the measuring instrument.

### **CCOMPx** Pins

The CCOMPx pins are internal compensation nodes that must be decoupled to ground with a 100 nF capacitor.

### михоит

MUXOUT is a test output that allows different internal nodes to be monitored. It is a CMOS output stage that requires no termination.

### Lock Detect (LDET)

Lock detect is a CMOS output that indicates the state of the PLL. A high level indicates a locked condition, and a low level indicates a loss of lock condition.

### RF Inputs (RFI, RFCM, and RFI)

RFI and  $\overline{\text{RFI}}$  are 50  $\Omega$  internally biased RF inputs. For singleended operation as demonstrated on the evaluation board, RFI must be ac-coupled to the source and  $\overline{\text{RFI}}$  must be ac-coupled to the ground plane. RFCM is the RF input common-mode pin. It should be connected to  $\overline{\text{RFI}}$  when driving the input in singleended mode. When driving the input differentially using a balun, connect this pin to the common terminal of the output coil of the balun.

### VGAIN

The VGAIN pin sets the gain of the VGA. The V<sub>GAIN</sub> voltage range is from 0 V to 1.5 V. This allows the gain of the VGA to vary from 0 dB to +60 dB.



#### Figure 69. Applications Circuit

### **PCB ARTWORK**

**Component Placement** 



Figure 70. Evaluation Board, Top Side Component



Figure 71. Evaluation Board, Top Side—Layer 1



Figure 72. Evaluation Board, Ground—Layer 2



Figure 74. Evaluation Board Power—Layer 3



Figure 75. Evaluation Board, Bottom Side—Layer 4

### **BILL OF MATERIALS**

#### Table 28. Bill of Materials

Qty.	Reference Designator	Description	Manufacturer	Part Number
1	DUT	ADRF6850 LFCSP, 56-lead 8 mm × 8 mm	Analog Devices	ADRF6850BCPZ
1	Y2	VCO, 13.5 MHz	Jauch	0 13.50-VX7-G-3.3-1- T1-LF
1	SPI	Connector, 9-pin, D-sub plug, D-SUB9MR	ITW McMurdo	FEC 1071806
1	l <sup>2</sup> C	Connector, I <sup>2</sup> C, SEMCONN receptacle	Digikey	5-1761185-1-ND
2	C1, C34	Capacitor, 10 μF, 25 V, tantalum, TAJ-C	AVX	FEC 197518
10	C4, C6, C10, C12, C14, C16, C40, C48, C53, C55	Capacitor, 56 pF, 50 V, ceramic, C0G, 0402	AVX	FEC 1658861
14	C5, C7, C11, C13, C15, C17, C22, C27, C47, C49 to C52, C54	Capacitor, 100 nF, 25 V, X7R, ceramic, 0603	AVX	FEC 317287
1	C3	Capacitor, 1.8 nF, 50 V, C0G, ceramic, 0603	Murata	FEC 1402814
1	C35	Capacitor, 68 nF, 50 V, NPO, ceramic, 1206	Kemet	FEC 1535582
4	C2, C21, C38, C39	Capacitor, 1 nF, 50 V, C0G, ceramic, 0603	Murata	FEC 8819920
2	C44, C46	Capacitor, 100 pF, 50 V, C0G, ceramic, 0402	Murata	FEC 8819572
2	C43, C56	Capacitor, 10 nF, 50 V, X7R, ceramic, 0402	Murata	FEC 1414575
1	C18	Capacitor, 10 pF, 50 V, C0G, ceramic, 0402	Murata	FEC 8819564
4	C30 to C33	Capacitor, 10 μF, 6.3 V, X5R, ceramic, 0603	Phycomp	FEC 1458902
12	J2 to J12, J14	SMA end launch connector	Johnson/Emerson	142-0701-851
2	J20, J21	Jumper, 3-pin plus shunt	Harwin	FEC 148533 + FEC 150411
2	L1, L2	Inductor, 20 nH, 0402, LQW series	Murata	LQW15AN20N
2	L3, L4	Inductor, 10 μH, 0805, LQM series	Murata	LQM21FN1N100M
2	R20, R36	Resistor, 0 Ω, 1/16 W, 1%, 0402	Vishay Draloric	FEC 1158241
1	R13	Resistor, 4.7 kΩ, 1/10 W, 1%, 0603	Multicomp	FEC 1576293
2	R14, R39	Resistor, 1.2 kΩ, 1/10 W, 5%, 0603	Phycomp	FEC 9233393
1	R1	Resistor, 220 Ω, 1/16 W, 1%, 0603	Multicomp	FEC 9330801
2	R3, R4	Resistor, 200 Ω, 1/16 W, 5%, 0402	Vishay Dale	FEC 1514682
2	R17, R18	Resistor, 0603, spacing (do not install)		
3	R35, R44, R45	Resistor, 51 Ω, 1/16 W, 1%, 0402	Multicomp	FEC 1358008
4	R48 to R51	Resistor, 330 Ω, 1/10 W, 5%, 0805	Vishay Draloric	FEC 1739223
2	R60, R61	Resistor, 100 Ω, 1/10 W, 5%, 0805	Bourns	Digi Key RR12P100DTR-ND
2	R46, R47	Resistor, 10 kΩ, 1/16 W, 1%, 0402	Phycomp	FEC 9239359
7	CS, LDET, MUXOUT, VTUNE, SCLK, SDA, SDO	Test point, 1-pin, 0.035 inch diameter	Not inserted	
1	BAL1	Balun, 0805, 50 $\Omega$ to 100 $\Omega$ balanced (1.3 GHz to 3.1 GHz)	Anaren	BD1631J50100A00

# **OUTLINE DIMENSIONS**



#### **ORDERING GUIDE**

Model <sup>1</sup>	Temperature Range	Package Description	Package Option
ADRF6850BCPZ	-40°C to +85°C	56-Lead Lead Frame Chip Scale Package [LFCSP_VQ], Tray	CP-56-5
ADRF6850BCPZ-R7	-40°C to +85°C	56-Lead Lead Frame Chip Scale Package [LFCSP_VQ], 7" Tape and Reel	CP-56-5
EVAL-ADRF6850EB1Z		Evaluation Board	

<sup>1</sup> Z = RoHS Compliant Part.

I<sup>2</sup>C refers to a communications protocol originally developed by Philips Semiconductors (now NXP Semiconductors).

©2010 Analog Devices, Inc. All rights reserved. Trademarks and registered trademarks are the property of their respective owners. D09316-0-10/10(0)



www.analog.com

Rev. 0 | Page 36 of 36



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный) Факс: 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.