HA13150A

21 W × 4-Channel BTL Power IC

HITACHI

ADE-207-107
1st. Edition

Description

HA13150A is a four-channel BTL amplifier IC designed for car audio, featuring high output and low distortion, and applicable to digital audio equipment. It provides 21 W output per channel, with a 14.4 V power supply and at 10% distortion.

Functions


- Built-in standby circuit
- Built-in muting circuit
- Built-in protection circuits (surge, TSD, and ASO)

Features

- Requires few external parts
- Low distortion (total harmonic distortion = 0.01% at 3 W)
- Low noise (at Rg = 620 Ω, noise is 0.15 mV (muting off) or 0.1 mV (muting on))
- Popping noise minimized
- Highly reliable current-limiting ASO protector keeps speakers safe from all kinds of trouble. Reliability is further enhanced by a fast-acting thermal shutdown protection circuit with on/off hysteresis.


Hitachi semiconductor

Block Diagram




' C1 to C8 should be polyester film capacitors with no secondary resonance (non-inductive), to assure stable operation.

Notes: 1. Standby
Power is turned on when a signal of 3.5 V or 0.05 mA is impressed at pin 2. When pin 2 is open or connected to GND, standby is turned on (output off).



2. Muting
Muting is turned off (output on) when a signal of 3.5 V or 0.1 mA is impressed at pin 10.
When pin 10 is open or connected to GND, muting is turned on (output off).




Absolute Maximum Ratings (Ta = 25°C)

Item	Symbol	Rating	Unit	Remarks

Operating supply voltage	V_{CC}	18	V
Supply voltage when no signal *1	V_{CC} (DC)	26	V
Peak supply voltage *2	V_{CC} (PEAK)	50	V
Output current *3	I_O (PEAK)	4	A
Power dissipation *4	P_T	83	W
Junction temperature	Tj	150	°C
Operating temperature	Topr	–30 to +85	°C
Storage temperature	Tstg	–55 to +125	°C





Notes: 1. Tolerance within 30 seconds
2. Tolerance in surge pulse waveform
3. Value per 1 channel
4. Value when attached on the infinite heat sink plate at Ta = 25°C.
The derating carve is as shown in the graph below.




Electrical Characteristics (V_{CC} = 13.2 V, f = 1 kHz, R_L = 4 Ω, Rg = 620 Ω, Ta = 25°C)

Item	Symbol	Min	Typ	Max	Unit	Test Conditions
Current when no signal	Iq1	—	240	—	mA	Vin = 0
Output offset voltage	ΔVq	–250	0	+250	mV	
Gain	Gv	30.5	32	33.5	dB	
Gain difference between channels	ΔGv	–1.5	0	+1.5	dB	
Rated output power	Po	—	18	—	W	V_{CC} = 13.2 V R_L = 4 Ω, THD = 10%
Max output power	Pomax	—	30	—		V_{CC} = 13.7 V R_L = 4 Ω, THD = Max
Total harmonic distortion	T.H.D	—	0.01	—	%	Po = 3 W
Output noise voltage	WBN	—	0.15	0.5	mVrms	Rg = 0 Ω BW = 20 to 20 kHz
Ripple rejection	SVR	—	55	—	dB	Rg = 600 Ω f = 120 Hz
Channel crosstalk	C.T	—	70	—	dB	Rg = 600 Ω Vout = 0 dBm
Input impedance	Rin	—	25	—	kΩ	
Standby current	Iq2	—	—	200	μA	
Standby control voltage (high)	V_{STH}	3.5	—	V_{CC}	V	
Standby control voltage (low)	V_{STL}	0	—	1.5	V	
Muting control voltage (high)	V_{MH}	3.5	—	V_{CC}	V	
Muting control voltage (low)	V_{ML}	0	—	1.5	V	
Muting attenuation	A_{TTM}	—	70	—	dB	Vout = 0 dBm

Pin Explanation

Pin No.	Symbol	Functions	Input Impedance	DC Voltage	Equivalence Circuit
1	IN1	CH1 INPUT	25 kΩ (Typ)	0 V	
11	IN2	CH2 INPUT			
13	IN3	CH3 INPUT			
23	IN4	CH4 INPUT			
2	STBY	Standby control	90 kΩ (at Trs. cutoff)	—	
3	OUT1 (+)	CH1 OUTPUT	—	$V_{CC}/2$	
5	OUT1 (–)				
7	OUT2 (+)	CH2 OUTPUT			
9	OUT2 (–)				
15	OUT3 (+)	CH3 OUTPUT			
17	OUT3 (–)				
19	OUT4 (+)	CH4 OUTPUT			
21	OUT4 (–)				
10	MUTE	Muting control	25 kΩ (Typ)	—	

Pin Explanation (cont)

Pin No.	Symbol	Functions	Input Impedance	DC Voltage	Equivalence Circuit
22	RIPPLE	Bias stability	—	$V_{CC}/2$	
6	$PV_{CC}1$	Power of output stage	—	V_{CC}	—
18	$PV_{CC}2$				
14	INV_{CC}	Power of input stage	—	V_{CC}	—
4	CH1 GND	CH1 power GND	—	—	—
8	CH2 GND	CH2 power GND			
16	CH3 GND	CH3 power GND			
20	CH4 GND	CH4 power GND			
12	IN GND	Input signal GND	—	—	—

Point of Application Board Design

1. Notes on Application board's pattern design

· For increasing stability, the connected line of V_{CC} and OUTGND is better to be made wider and lower impedance.

· For increasing stability, it is better to place the capacitor between V_{CC} and GND (0.1 µF) close to IC.

· For increasing stability, it is better to place C1 to C8 and R1 to R8, which are for stopping oscillation, close to IC.

· It is better to place the grounding of resistor (Rg), between input line and ground, close to INGND (Pin 12) because if OUTGND is connected to the line between Rg and INGND, THD will become worse due to current from OUTGND.




Figure 1 Notes on Application Board's Pattern Design

2. How to reduce the popping noise by Muting circuit

   At normal operating circuit, Muting circuit operates at high speed under 1 µs.

   In case popping noise becomes a problem, it is possible to reduce the popping noise by connecting capacitor, which determines the switching time constant, between pin 10 and GND. (Following figure 2)

   We recommend value of capacitor greater then 1 µF.

   Also transitional popping noise can be reduced sharply by muting before V_{CC} and Standby are ON/OFF.







Figure 2 How to use Muting Circuit


Table 1 Muting ON/OFF Time


C (µF)	ON Time	OFF Time
nothing	under 1 µs	under 1 µs
0.47	2 ms	2 ms
4.7	19 ms	19 ms



Quiescent Current vs. Supply Voltage
Quiescent Current IQ (mA)
300
200
100
0
8
10
12
14
16
18
20
Supply Voltage Vcc (V)


Output Power vs. Supply Voltage
RL = 4 Ω
f = 1 kHz
1 ch operation
THD = 10%
THD = 1%
Output Power Po (W)
40
30
20
10
0
8
10
12
14
16
18
Supply Voltage Vcc (V)



Output Power (Po max)
vs. Supply Voltage
RL = 4 Ω
f = 1 kHz
1 ch operation
Output Power Po max (W)
50
40
30
20
10
0
8
10
12
14
16
18
Supply Voltage Vcc (V)


Total Harmonic Distortion vs. Frequency
Vcc = 13.2 V
RL = 4 Ω
80 kHz L.P.F.
Po = 1.5 W (ch 1 to ch 4)
Po = 8 W (ch 1 to ch 4)
Total Harmonic Distortion T.H.D. (%)
1
0.5
0.2
0.1
0.05
0.02
0.01
20
50
100
200
500
1 k
2 k
5 k
10 k
20 k
Frequency f (Hz)



Total Harmonic Distortion vs. Output Power
Vcc = 13.2 V 80 kHz L.P.F.
RL = 4 Ω
f = 100 Hz (ch 1 to ch 4)
1 kHz (ch 1 to ch 4)
10 kHz (ch 1 to ch 4)
Total Harmonic Distortion T.H.D. (%)
10
5.0
2.0
1.0
0.5
0.2
0.1
0.05
0.02
0.01
0.02
0.05
0.1
0.2
0.5
1
2
5
10
20
Output Power Po (W)



Supply Voltage Rejection Ratio vs. Frequency
Supply Voltage Rejection Ratio S.V.R. (dB)
70
60
50
40
30
20
10
0
20
50
100
200
500
1 k
2 k
5 k
10 k
20 k
50 k
Frequency f (Hz)
Vcc = 13.2 V
RL = 4 Ω
Vrip = 0 dBm
ch 1
ch 2
ch 3
ch 4
Cross-Talk vs. Frequency (1)
Cross-Talk CT (dB)
-20
-30
-40
-50
-60
-70
-80
20
50
100
200
500
1 k
2 k
5 k
10 k
20 k
Frequency f (Hz)
Input ch 1
Vcc = 13.2 V, RL = 4 Ω, Vout = 0 dBm
ch 2
ch 3
ch 4

Cross-Talk vs. Frequency (2)




Cross-Talk vs. Frequency (3)





Cross-Talk vs. Frequency (4)
Input ch 4
V_{CC} = 13.2 V, R_L = 4 Ω, Vout = 0 dBm
ch 1
ch 2
ch 3
Cross-Talk CT (dB)
-20
-30
-40
-50
-60
-70
-80
20
50
100
200
500
1 k
2 k
5 k
10 k
20 k
Frequency f (Hz)
Wide Band Noise vs. Signal Source Resistance
V_{CC} = 13.2 V
R_L = 4 Ω
30 kHz L.P.F.
400 Hz H.P.F.
ch 1 to ch 4
MUTE OFF
MUTE ON
ch 1 to ch 4
Wide Band Noise W.B.N. (mVrms)
1.0
0.5
0.2
0.1
0.05
0.02
20
50
100
200
500
1 k
2 k
5 k
10 k
20 k
50 k
Signal Source Resistance Rg (Ω)

Power Dissipation vs. Output Power



Gain vs. Frequency



When using this document, keep the following in mind:

1. This document may, wholly or partially, be subject to change without notice.
2. All rights are reserved: No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without Hitachi's permission.
3. Hitachi will not be held responsible for any damage to the user that may result from accidents or any other reasons during operation of the user's unit according to this document.
4. Circuitry and other examples described herein are meant merely to indicate the characteristics and performance of Hitachi's semiconductor products. Hitachi assumes no responsibility for any intellectual property claims or other problems that may result from applications based on the examples described herein.
5. No license is granted by implication or otherwise under any patents or other rights of any third party or Hitachi, Ltd.
6. MEDICAL APPLICATIONS: Hitachi's products are not authorized for use in MEDICAL APPLICATIONS without the written consent of the appropriate officer of Hitachi's sales company. Such use includes, but is not limited to, use in life support systems. Buyers of Hitachi's products are requested to notify the relevant Hitachi sales offices when planning to use the products in MEDICAL APPLICATIONS.

HITACHI

Hitachi, Ltd.
Semiconductor & IC Div.
Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100, Japan
Tel: Tokyo (03) 3270-2111
Fax: (03) 3270-5109

For further information write to:

Hitachi America, Ltd.
Semiconductor & IC Div.
2000 Sierra Point Parkway
Brisbane, CA. 94005-1835
U.S.A.
Tel: 415-589-8300
Fax: 415-583-4207

Hitachi Europe GmbH
Electronic Components Group
Continental Europe
Dornacher Straße 3
D-85622 Feldkirchen
München
Tel: 089-9 91 80-0
Fax: 089-9 29 30 00

Hitachi Europe Ltd.
Electronic Components Div.
Northern Europe Headquarters
Whitebrook Park
Lower Cookham Road
Maidenhead
Berkshire SL6 8YA
United Kingdom
Tel: 0628-585000
Fax: 0628-778322

Hitachi Asia Pte. Ltd.
16 Collyer Quay #20-00
Hitachi Tower
Singapore 0104
Tel: 535-2100
Fax: 535-1533

Hitachi Asia (Hong Kong) Ltd.
Unit 706, North Tower,
World Finance Centre,
Harbour City, Canton Road
Tsim Sha Tsui, Kowloon
Hong Kong
Tel: 27359218
Fax: 27306071


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.