

1SP0335x2xx-5SNA0500J650300

Preliminary Data Sheet

Compact, high-performance, plug-and-play single-channel IGBT driver based on SCALE-2 technology for individual and parallel-connected modules in 2-level, 3-level and multilevel converter topologies

Abstract

The SCALE-2 plug-and-play driver 1SP0335x2xx-5SNA0500J650300 is a compact single-channel intelligent gate driver designed for ABB's IGBTs 5SNA0500J650300. The master driver 1SP0335x2Mx-5SNA0500J650300 features a fiber-optic interface. It can be used as stand-alone driver or in conjunction with up to three 1SP0335D2Sx-5SNA0500J650300 slaves to drive up to four parallel-connected IGBT modules of type 5SNA0500J650300.

The DC/DC power supply must be purchased as a separate unit (one per master driver).

For drivers adapted to other types of high-power and high-voltage IGBT modules, refer to:

www.IGBT-Driver.com/go/plug-and-play

Features

- ✓ Plug-and-play solution
- ✓ Allows parallel connection of IGBT modules
- ✓ For 2-level, 3-level and multilevel topologies
- ✓ Fiber-optic links (master)
- ✓ Built-in interface to 1SP0335D2Sx (slave)
- ✓ Duty cycle 0...100%
- ✓ Dynamic Advanced Active Clamping DA²C
- ✓ Dynamic IGBT short-circuit protection
- ✓ Monitoring of supply voltage
- ✓ Monitoring of gate voltage
- ✓ Extremely reliable; long service life
- ✓ Shortens application development time
- ✓ Suitable for 5SNA0500J650300

Applications

- ✓ Traction
- ✓ Railroad power supplies
- ✓ Light rail vehicles
- ✓ HVDC
- ✓ Flexible AC transmission systems (FACTS)
- ✓ Medium-voltage converters
- ✓ Industrial drives
- ✓ Wind-power converters
- ✓ Medical applications
- ✓ Research
- ✓ And many others

Preliminary Data Sheet

Safety Notice!

The data contained in this data sheet is intended exclusively for technically trained staff. Handling all high-voltage equipment involves risk to life. Strict compliance with the respective safety regulations is mandatory!

Any handling of electronic devices is subject to the general specifications for protecting electrostatic-sensitive devices according to international standard IEC 60747-1, Chapter IX or European standard EN 100015 (i.e. the workplace, tools, etc. must comply with these standards). Otherwise, this product may be damaged.

Important Product Documentation

This data sheet contains only product-specific data. For a detailed description, must-read application notes and common data that apply to the whole series, please refer to the "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers" on www.IGBT-Driver.com/go/1SP0335.

When applying SCALE-2 plug-and-play drivers, please note that these drivers are specifically adapted to a particular type of IGBT module. Therefore, the type designation of SCALE-2 plug-and-play drivers also includes the type designation of the corresponding IGBT module. These drivers are not valid for IGBT modules other than those specified. Incorrect use may result in failure.

Mechanical Dimensions

Dimensions: See the relevant "Description and Application Manual"

Mounting principle: Connected to IGBT module with screws

Fiber-Optic Interfaces (1SP0335x2Mx)

| Interface | Remarks | Part type # |
|--------------------|--|-------------|
| Drive signal input | 1SP0335V, fiber-optic receiver (Notes 1, 2) | HFBR-2522Z |
| Drive signal input | 1SP0335S, fiber-optic receiver (Notes 1, 2) | HFBR-2412Z |
| Status output | 1SP0335V, fiber-optic transmitter (Notes 1, 3) | HFBR-1522Z |
| Status output | 1SP0335S, fiber-optic transmitter (Notes 1, 3) | HFBR-1412Z |

Electrical Connectors

| Interface | Remarks | Part type # |
|---------------------------|------------------------------|-------------|
| Power supply connector X1 | On-board connector (Note 4) | 214012 |
| Bus connectors X2 and X3 | On-board connectors (Note 5) | 214013 |

Preliminary Data Sheet

Absolute Maximum Ratings

| Parameter | Remarks | Min | Max | Unit |
|---------------------------------|--|-----|------|-------------------|
| Supply voltage V_{DC} | VDC to COM | 0 | 30 | V |
| Average supply current I_{DC} | 1SP0335x2Mx only (Note 6) | | 215 | mA |
| Average supply current I_{DC} | 1SP0335x2Mx with three 1SP0335D2Sx (Note 6) | | 740 | mA |
| Gate output power | 1SP0335x2Mx, $T_a < 70^\circ\text{C}$ (Note 7) | | 3.5 | W |
| | 1SP0335x2Mx, $T_a = 85^\circ\text{C}$ (Note 7) | | 2.5 | W |
| Gate output power | 1SP0335D2Sx, $T_a < 70^\circ\text{C}$ (Note 8) | | 3.3 | W |
| | 1SP0335D2Sx, $T_a = 85^\circ\text{C}$ (Note 8) | | 2.3 | W |
| Switching frequency F | 1SP0335x2Mx, $T_a < 70^\circ\text{C}$ | | 17 | kHz |
| | 1SP0335x2Mx, $T_a = 85^\circ\text{C}$ | | 12 | kHz |
| Switching frequency F | 1SP0335D2Sx, $T_a < 70^\circ\text{C}$ | | 16 | kHz |
| | 1SP0335D2Sx, $T_a = 85^\circ\text{C}$ | | 11 | kHz |
| Gate peak current I_{out} | Note 9 | -35 | +35 | A |
| DC-link voltage | Switching operation (Note 10) | | 4400 | V |
| | Off state (Note 11) | | 5200 | V |
| Operating voltage | Collector-emitter voltage | | 6500 | V_{peak} |
| Max. emitter-emitter voltage | Between parallel connected drivers (Note 12) | | 200 | V_{peak} |
| dV/dt | Between parallel connected drivers (Note 13) | | 50 | kV/ μs |
| Max. interface current | X2 and X3, total RMS value (Note 14) | | 4 | A_{rms} |
| | X2 and X3, total peak value (Note 14) | | 20 | A_{peak} |
| Operating temperature | | -40 | +85 | $^\circ\text{C}$ |
| Storage temperature | | -40 | +90 | $^\circ\text{C}$ |

Recommended Operating Conditions

| Power Supply | Remarks | Min | Typ | Max | Unit |
|-------------------------|---------|------|-----|------|------|
| Supply voltage V_{DC} | To COM | 23.5 | 25 | 26.5 | V |

Preliminary Data Sheet

| |
|-----------------------------------|
| Electrical Characteristics |
|-----------------------------------|

All data refer to +25°C and $V_{DC} = 25V$ unless otherwise specified

| Power Supply | Remarks | Min | Typ | Max | Unit |
|-------------------------------------|--|------|------|------|------|
| Supply current I_{DC} | Without load, only 1SP0335x2Mx | | 45 | | mA |
| | Without load, per additional 1SP0335D2Sx | | 20 | | mA |
| Power Supply Monitoring | Remarks | Min | Typ | Max | Unit |
| Supply threshold $V_{iso}-V_{ee}$ | Clear fault | 12.1 | 12.6 | 13.1 | V |
| | Set fault (Note 15) | 11.5 | 12.0 | 12.5 | V |
| Monitoring hysteresis | Set/clear fault | 0.35 | | | V |
| Supply threshold $V_{ee}-V_{COM}$ | Clear fault | 5 | 5.15 | 5.3 | V |
| | Set fault (Note 15) | 4.7 | 4.85 | 5 | V |
| Monitoring hysteresis | Set/clear fault | 0.15 | | | V |
| Bus to 1SP0335D2Sx | Remarks | Min | Typ | Max | Unit |
| Supply voltage | | | VDC | | V |
| Turn-off command | To COM | | 0 | | V |
| Turn-on command | To COM | | 15 | | V |
| Gate Monitoring | Remarks | Min | Typ | Max | Unit |
| Turn-on threshold $V_{GE,on,min}$ | G_{mean} to E, set fault (Note 16) | | 12.9 | | V |
| Turn-off threshold $V_{GE,off,max}$ | G_{mean} to E, set fault (Note 16) | | -7.6 | | V |
| Filter delay | Turn-on (Note 16) | | 28 | | µs |
| | Turn-off (Note 16) | | 42 | | µs |
| Short-circuit Protection | Remarks | Min | Typ | Max | Unit |
| Static Vce-monitoring threshold | Between auxiliary terminals (Note 17) | | 247 | | V |
| Response time | DC-link voltage = 4400V (Note 18) | | 5.9 | | µs |
| | DC-link voltage = 3000V (Note 18) | | 6 | | µs |
| | DC-link voltage = 2200V (Note 18) | | 6.4 | | µs |
| | DC-link voltage = 1500V (Note 18) | | 10.2 | | µs |
| | DC-link voltage = 1500V (Note 18) | | 10.2 | | µs |
| Delay to IGBT turn-off | After the response time (Note 19) | | 0.3 | | µs |
| Timing Characteristics | Remarks | Min | Typ | Max | Unit |
| Turn-on delay $t_{d(on)}$ | Note 20 | | 190 | | ns |
| Turn-off delay $t_{d(off)}$ | Note 20 | | 185 | | ns |
| Timing Characteristics | Remarks | Min | Typ | Max | Unit |
| Output rise time $t_{r(out)}$ | G to E (Note 21) | | 9 | | ns |
| Output fall time $t_{f(out)}$ | G to E (Note 21) | | 30 | | ns |

Preliminary Data Sheet

| Timing Characteristics | Remarks | Min | Typ | Max | Unit |
|-----------------------------------|--|-----|-----|------|------|
| Transmission delay of fault state | Note 22 | | 90 | | ns |
| Delay to clear fault state | After IGBT short circuit (Note 23) | | 9 | | μs |
| | After gate-monitoring fault (Notes 23, 27) | | 1 | | μs |
| Acknowledge delay time | Note 24 | | 250 | | ns |
| Acknowledge pulse width | On host side | 400 | 700 | 1050 | ns |

| Gate Output | Remarks | Min | Typ | Max | Unit |
|-------------------------------------|---------|-----|-----|-----|------|
| Turn-on gate resistor $R_{g(on)}$ | Note 25 | | 4.1 | | Ω |
| Turn-off gate resistor $R_{g(off)}$ | Note 25 | | 23 | | Ω |
| Auxiliary gate capacitor C_{ge} | | | 150 | | nF |
| Gate voltage at turn-on | Note 26 | | 15 | | V |
| Gate-voltage at turn-off | Note 26 | | -10 | | V |

Footnotes to the Key Data

- 1) The transceivers required on the host controller side are not supplied with the gate driver. It is recommended to use the same types as used in the gate driver. For product information refer to www.IGBT-Driver.com/go/fiberoptics
- 2) The recommended transmitter current at the host controller is 20mA. A higher current may increase jitter or delay at turn-off.
- 3) The typical transmitter current at the gate driver is 18mA. In case of supply undervoltage, the minimum transmitter current at the gate driver is 12mA: this is suitable for adequate plastic optical fibers with a length of more than 10 meters.
- 4) This refers to the manufacturer ordering number, see www.igbt-driver.com/go/ext_erni. The customer-side connector as well as cables with different lengths can be supplied by CONCEPT. Refer to the "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers" for more information.
- 5) This refers to the manufacturer ordering number, see www.igbt-driver.com/go/ext_erni. These connectors are to be used to connect 1SP0335x2Mx (master) or 1SP0335D2Sx (slave) to 1SP0335D2Sx (slave) if parallel connection of IGBT modules is required. Cables with different lengths can be supplied by CONCEPT. Refer to the "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers" for more information.
- 6) If the specified value is exceeded, this indicates a driver overload. It should be noted that the driver is not protected against overload.
- 7) The given power can only be fully exploited without slaves 1SP0335D2Sx (no parallel connection of IGBT modules). If the specified value is exceeded, this indicates a driver overload. It should be noted that the driver is not protected against overload. From 70°C to 85°C, the maximum permissible output power can be linearly interpolated from the given data.
- 8) The given power can be fully exploited with slaves 1SP0335D2Sx (parallel connection of IGBT modules). If the specified value is exceeded, this indicates a driver overload. It should be noted that the driver is not protected against overload. From 70°C to 85°C, the maximum permissible output power can be linearly interpolated from the given data.
- 9) The gate current is limited by the gate resistors located on the driver.
- 10) This limit is due to active clamping under switching conditions. Refer to the "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers".
- 11) Due to the Dynamic Active Advanced Clamping Function (DA²C) implemented on the driver, the DC-link voltage can be increased in the off-state condition (e.g. after emergency shut-down). This value is only valid when the IGBTs are in the off state (not switching). The time during which the voltage can be applied should be limited to short periods (< 60 seconds). Refer to the "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers".

Preliminary Data Sheet

- 12) The maximum dynamic voltage between auxiliary emitters of parallel-connected drivers due to asymmetrical operation at turn-on and turn-off must be limited to the given value.
- 13) Maximum allowed rate of change of auxiliary emitter voltage of parallel connected drivers. This specification guarantees that the drive information will be transferred reliably even with high rate of change of auxiliary emitter voltages (asymmetrical operation).
- 14) Dynamic voltages between auxiliary emitters of parallel connected drivers at turn-on and turn-off lead to equalizing currents over the X2 or X3 bus. The peak and RMS values of the resulting current must be limited to the given value.
- 15) Undervoltage monitoring of the secondary-side supply voltage (Viso to Vee and Vee to COM which correspond with the approximate turn-on and turn-off gate-emitter voltages). If the corresponding voltage drops below this limit on 1SP0335x2Mx (masters), all paralleled IGBTs (master and slaves) are switched off and a fault is transmitted to the status output. If the corresponding voltage drops below this limit on 1SP0335D2Sx (slaves), the corresponding IGBT is switched off. If the IGBT was turned on, a fault will be generated by the gate-monitoring function on the master which will turn off all paralleled IGBT after the corresponding delay.
- 16) The mean value $V_{GE,mean}$ of all gate voltages (master and all slaves) is filtered and compared to the given values at turn-on and turn-off. If the specified values are exceeded ($V_{GE,mean} < V_{GE,on,min}$ at turn-on resp. $V_{GE,mean} > V_{GE,off,max}$ at turn-off) after the given filter delay, the driver turns off all parallel-connected IGBTs and a fault is transmitted to the status output.
- 17) A dynamic Vce protection is implemented on the driver. The maximum allowed Vce voltage at turn-on is dynamically adjusted in order to better fit to the IGBT characteristics at turn-on. At the end of the turn-on process the given static value applies.
- 18) The resulting pulse width of the direct output of the gate drive unit for short-circuit type I (excluding the delay of the gate resistors) is the sum of the response time plus the delay to IGBT turn-off.
- 19) The turn-off event of the IGBT is delayed by the specified time after the response time.
- 20) Including the delay of the external fiber-optic links (cable length: 1m). Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the direct output of the gate drive unit (excluding the delay of the gate resistors).
- 21) Output rise and fall times are measured between 10% and 90% of the nominal output swing. The values are given for the driver side of the gate resistors with $2\Omega/1\mu F$ load. The time constant of the output load in conjunction with the present gate resistors leads to an additional delay at their load side.
- 22) Delay of external fiber-optic links. Measured from the driver secondary side (ASIC output) to the optical receiver on the host controller.
- 23) Measured on the host side. The fault status on the secondary side is automatically reset after the specified time.
- 24) Including the delay of the external fiber-optic links. Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the transition of the acknowledge signal at the optical receiver on the host controller side.
- 25) The gate resistors can be leaded or surface mounted. CONCEPT reserves the right to determine which type will be used. Typically, higher quantities will be produced with SMD resistors and small quantities with leaded resistors.
- 26) The driver supply voltage VDC is split into two distinct voltages on the driver. The first one is the turn-on voltage which is regulated at about 15V. The difference between VDC and the turn-on voltage is the turn-off voltage which is not regulated and mainly dependent on the driver input voltage VDC.
- 27) The fault status is set as long as the gate monitoring fault is present. The given value applies if the driver goes from the "off state" to the "on state" and the gate-emitter voltage of one or more parallel connected drivers does not turn on. If the driver goes from the "on state" to the "off state" and the gate-emitter voltage of one or more parallel connected drivers does not turn off, the fault status is applied as long as the gate monitoring fault is present.

Legal Disclaimer

This data sheet specifies devices but cannot promise to deliver any specific characteristics. No warranty or guarantee is given – either expressly or implicitly – regarding delivery, performance or suitability.

CT-Concept Technologie AG reserves the right to make modifications to its technical data and product specifications at any time without prior notice. The general terms and conditions of delivery of CT-Concept Technologie AG apply.

Preliminary Data Sheet

Ordering Information

The general terms and conditions of delivery of CT-Concept Technologie AG apply.

| Interface | CONCEPT Driver Type # | Related IGBT |
|---|-----------------------------|-----------------|
| Master, Fiber-Optic Interface ¹⁾ | 1SP0335V2M1-5SNA0500J650300 | 5SNA0500J650300 |
| Master, Fiber-Optic Interface ²⁾ | 1SP0335S2M1-5SNA0500J650300 | 5SNA0500J650300 |
| Slave, Electrical Interface | 1SP0335D2S1-5SNA0500J650300 | 5SNA0500J650300 |

1) Fiber-optic interface with versatile link (HFBR-2522Z and HFBR-1522Z)

2) Fiber-optic interface with ST (HFBR-2412Z and HFBR-1412Z)

See "Description & Application Manual for 1SP0335 SCALE-2 IGBT Drivers"

Product home page: www.IGBT-Driver.com/go/1SP0335

Refer to www.IGBT-Driver.com/go/nomenclature for information on driver nomenclature

Information about Other Products

For other drivers, evaluation systems, product documentation and application support

Please click onto: www.IGBT-Driver.com

Manufacturer

CT-Concept Technologie AG
Intelligent Power Electronics
Renferstrasse 15
CH-2504 Biel-Bienne
Switzerland

Tel. +41 - 32 - 344 47 47

Fax +41 - 32 - 344 47 40

E-mail Info@IGBT-Driver.com

Internet www.IGBT-Driver.com

© 2010...2012 CT-Concept Technologie AG - Switzerland.

We reserve the right to make any technical modifications without prior notice.

All rights reserved.

Version from 2012-02-29

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Power Integrations:](#)

[1SP0335V2M1-5SNA0500J650300](#)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.