

High-performance Regulator IC Series for PCs

300mA Linear Regulators for Desktop PC



BD35613HFV/EFJ/HFN, BD35615HFV/EFJ/HFN, BD35618HFV/EFJ/HFN

●Description

BD3561□ series is a LDO regulator with output current 300mA. The output accuracy is $\pm 1\%$ of output voltage. BD3561□ series has some kinds of output voltage line-up and package line-up. Thus, it is used for the wide applications of digital appliances. Over current protection (for protecting the IC destruction by output short circuit), shutdown ON/OFF switch (for setting the circuit current $0\mu\text{A}$ at shutdown mode), and thermal shutdown circuit (for protecting ICs from heat destruction by over load condition) are all built in.

●Features

- 1) Output current 300mA
- 2) Output voltage accuracy : $\pm 1\%$
- 3) Built-in Over Current Protection circuit (OCP)
- 4) Built-in Thermal Shut Down circuit (TSD)
- 5) With shut down switch
- 6) Rich package line-up : HSON8, HTSOP-J8, HVSO6

●Line-up

| Product name | 8.0V | 5.0V | 3.3V | Package |
|--------------|------|------|------|----------|
| BD3561□HFN | ○ | ○ | ○ | HSON8 |
| BD3561□EFJ | ○ | ○ | ○ | HTSOP-J8 |
| BD3561□HFV | ○ | ○ | ○ | HVSO6 |

Product name : BD3561□ □□□
↑ ↑
a b

| Symbol | | | |
|--------|--------------------|-----|----------|
| a | | b | |
| 1□ | Output Voltage (V) | □□□ | Package |
| 18 | 8.0V typ. | HFN | HSON8 |
| 15 | 5.0V typ. | EFJ | HTSOP-J8 |
| 13 | 3.3V typ. | HFV | HVSO6 |

● Absolute maximum ratings (Ta=25°C)

| Parameter | Symbol | Limits | Unit |
|-----------------------------|----------|----------------------|------|
| Power Supply Voltage | Vcc | 15.0 * ¹ | V |
| EN Voltage | VEN | 15.0 | V |
| Power Dissipation | HSO8 | 1350 * ² | mW |
| | HTSOP-J8 | 2110 * ³ | |
| | HVSOF6 | 850.0 * ⁴ | |
| Operating Temperature Range | Topr | -10~+100 | °C |
| Storage Temperature Range | Tstg | -55~+150 | °C |
| Junction Temperature | Tjmax | +150 | °C |

*1 Not to exceed Pd

*2 Reduced by 10.8mW for each increase in Ta of 1°C over 25°C.

(when mounted on a board 70.0mm × 70mm × 1.6mm Glass-epoxy PCB. (copper foil area:100mm²))

*3 Reduced by 16.9mW for each increase in Ta of 1°C over 25°C.

(when mounted on a board 70.0mm × 70mm × 1.6mm Glass-epoxy PCB, 2 layer)

*4 Reduced by 6.8mW for each increase in Ta of 1°C over 25°C.

(when mounted on a board 70.0mm × 70mm × 1.6mm Glass-epoxy PCB. (copper foil area:100mm²))

● Operating Conditions (Ta=25°C)

| Parameter | Symbol | Min. | Max. | Unit |
|----------------------------|--------|--------|------|------|
| Input Power Supply Voltage | VCC | Vo+1.8 | 14.0 | V |
| EN Voltage | VEN | - | 14.0 | V |
| Output Current | Io | - | 300 | mA |

★ This product should not be used in a radioactive environment.

● ELECTRICAL CHARACTERISTICS

BD3561 □ HFN/EFJ/HFV (Unless otherwise noted, Ta=25°C, EN=3V, Vcc=12V)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions |
|----------------------------------|------------|---------------|-------|---------------|------|----------------------------------|
| Output Voltage 1 | Vo1 | Vo(T) × 0.99 | Vo(T) | Vo(T) × 1.01 | V | Io=0mA |
| Output Voltage 2 | Vo2 | Vo(T) × 0.985 | Vo(T) | Vo(T) × 1.015 | V | Tj=0 to 100°C Io=0mA→300mA |
| Circuit Current at shutdown mode | Isd | - | 0 | 5 | μA | EN=0V, @OFF mode |
| Bias Current | Icc | - | 200 | 300 | μA | |
| Output Current Ability | Io | 300 | - | - | mA | |
| Line Regulation | Reg.I | - | 25 | 50 | MV | Vcc=(Vo+1.8V)→14.0V, Io=300mA |
| EN Low Voltage | VEN (Low) | 0 | - | 0.8 | V | |
| EN High Voltage | VEN (High) | 2.4 | - | 14.0 | V | |
| EN Bias Current | IEN | 0.5 | 1.0 | 5.0 | μA | |

● Reference Data

BD35618HFV (Unless otherwise specified, $T_a=25^\circ\text{C}$, $V_{EN}=3\text{V}$, $V_{CC}=12\text{V}$)




Fig.1 Transient Response
(50→0mA)
 $C_o=1\ \mu\text{F}$




Fig.2 Transient Response
(0→50mA)
 $C_o=1\ \mu\text{F}$




Fig.3 Waveform at output start
 $C_o=1\ \mu\text{F}$




Fig.4 Waveform at output OFF
 $C_o=1\ \mu\text{F}$




Fig.5 Input sequence 1
 $C_o=1\ \mu\text{F}$




Fig.6 Input sequence 2
 $C_o=1\ \mu\text{F}$




Fig.7 T_a - V_o ($I_o=0\text{mA}$)




Fig.8 T_a - I_{CC}
($V_{EN}=12\text{V}$)




Fig.9 T_a - I_{CC}
($V_{CC}=12\text{V}$, $V_{EN}=0\text{V}$)




Fig.10 T_a - I_{EN}
($V_{CC}=12\text{V}$, $V_{EN}=3\text{V}$)




Fig.11 I_o - V_o




Fig.12 V_{CC} - I_{STB}
($V_{CC}=12\text{V}$, $V_{EN}=3\text{V}$)

●Reference Data

BD35618HFV (Unless otherwise specified, Ta=25°C, EN=3V, Vcc=12V)






Fig.13 Vcc-Vo

●Heat Dissipation Characteristics


◎HSON8



◎HTSOP-J8




◎HVSOF6




●Block Diagram

(HSON8, HTSOP-J8)



(HVSOF6)




● Pin Function Table (HSON8, HTSOP-J8)

| Pin No. | Pin name | Pin Function |
|---------|----------|--------------------|
| 1 | Vcc | Input Voltage Pin |
| 2 | N.C. | Open |
| 3 | Vo | Output Voltage Pin |
| 4 | N.C. | Open |
| 5 | GND | GND Pin |
| 6 | GND_S | GND Sense Pin |
| 7 | N.C. | Open |
| 8 | EN | Enable Pin |


(HVSOF6)

| Pin No. | Pin name | Pin Function |
|---------|----------|--------------------|
| 1 | Vo | Output Voltage Pin |
| 2 | GND | GND Pin |
| 3 | GND_S | GND Sense Pin |
| 4 | EN | Enable Pin |
| 5 | N.C | Open |
| 6 | Vcc | Input Voltage Pin |


● Pin Layout (HSON8, HTSOP-J8)



(HVSOF6)




●Evaluation Board Circuit (Vo=8.0V)



●Evaluation Board Parts List

| Designation | Value | Part No. | Company |
|-------------|-------|---------------|---------|
| R1 | - | - | - |
| R2 | - | - | - |
| R3 | - | - | - |
| R4 | - | - | - |
| C1 | - | - | - |
| C2 | 1uF | CM105B105K10A | KYOCERA |
| C3 | - | - | - |
| C4 | - | - | - |
| C5 | - | - | - |
| C6 | 1uF | CM105B105K16A | KYOCERA |
| C7 | - | - | - |
| C8 | - | - | - |
| U1 | - | BD3561XHFV | ROHM |
| U2 | - | - | - |


●Reference landing pattern
 ©HSON8



| | | | |
|--------------------------|-------------------------|-----------------------|---------------------|
| Lead pitch e | landing pitch MIE | landing length ≥l2 | landing pitch b2 |
| 0.65 | 2.50 | 0.40 | 0.35 |
| central pad length D3 | central pad pitch E3 | | |
| 2.90 | 1.90 | | |

*It is recommended to design suitable for the actual application.

©HVSOF6



| | | | |
|-----------------|----------------------|----------------------|---------------------|
| Lead pitch e | landing pitch MIE | landing length l2 | landing pitch b2 |
| 0.50 | 3.00 | 0.55 | 0.25 |

| | |
|--------------------------|-------------------------|
| central pad length D3 | central pad pitch E3 |
| 1.60 | 2.60 |

*It is recommended to design suitable for the actual application.

● Operation Notes

1. Absolute maximum ratings

An excess in the absolute maximum ratings, such as supply voltage, temperature range of operating conditions, etc., can break down the devices, thus making impossible to identify breaking mode, such as a short circuit or an open circuit. If any over rated values will expect to exceed the absolute maximum ratings, consider adding circuit protection devices, such as fuses.

2. Connecting the power supply connector backward

Connecting of the power supply in reverse polarity can damage IC. Take precautions when connecting the power supply lines. An external direction diode can be added.

3. Power supply lines

Design PCB layout pattern to provide low impedance GND and supply lines. To obtain a low noise ground and supply line, separate the ground section and supply lines of the digital and analog blocks. Furthermore, for all power supply terminals to ICs, connect a capacitor between the power supply and the GND terminal. When applying electrolytic capacitors in the circuit, not that capacitance characteristic values are reduced at low temperatures.

4. GND voltage

The potential of GND pin must be minimum potential in all operating conditions.

5. Thermal design

Use a thermal design that allows for a sufficient margin in light of the power dissipation (Pd) in actual operating conditions.

6. Inter-pin shorts and mounting errors

Use caution when positioning the IC for mounting on printed circuit boards. The IC may be damaged if there is any connection error or if pins are shorted together.

7. Actions in strong electromagnetic field

Use caution when using the IC in the presence of a strong electromagnetic field as doing so may cause the IC to malfunction.

8. ASO

When using the IC, set the output transistor so that it does not exceed absolute maximum ratings or ASO.

9. Thermal shutdown circuit

The IC incorporates a built-in thermal shutdown circuit (TSD circuit). The thermal shutdown circuit (TSD circuit) is designed only to shut the IC off to prevent thermal runaway. It is not designed to protect the IC or guarantee its operation. Do not continue to use the IC after operating this circuit or use the IC in an environment where the operation of this circuit is assumed.

| | TSD on temperature [°C] (typ.) | Hysteresis temperature [°C] (typ.) |
|--------------------|--------------------------------|------------------------------------|
| BD3561XHFN/EFJ/HFV | 175 | 15 |

10. Testing on application boards

When testing the IC on an application board, connecting a capacitor to a pin with low impedance subjects the IC to stress. Always discharge capacitors after each process or step. Always turn the IC's power supply off before connecting it to or removing it from a jig or fixture during the inspection process. Ground the IC during assembly steps as an antistatic measure. Use similar precaution when transporting or storing the IC.


11. Regarding input pin of the IC

This monolithic IC contains P+ isolation and P substrate layers between adjacent elements in order to keep them isolated. P-N junctions are formed at the intersection of these P layers with the N layers of other elements, creating a parasitic diode or transistor. For example, the relation between each potential is as follows:

When $GND > Pin A$ and $GND > Pin B$, the P-N junction operates as a parasitic diode.

When $GND > Pin B$, the P-N junction operates as a parasitic transistor.


Parasitic diodes can occur inevitable in the structure of the IC. The operation of parasitic diodes can result in mutual interference among circuits, operational faults, or physical damage. Accordingly, methods by which parasitic diodes operate, such as applying a voltage that is lower than the GND (P substrate) voltage to an input pin, should not be used.



12. Ground Wiring Pattern.

When using both small signal and large current GND patterns, it is recommended to isolate the two ground patterns, placing a single ground point at the ground potential of application so that the pattern wiring resistance and voltage variations caused by large currents do not cause variations in the small signal ground voltage. Be careful not to change the GND wiring pattern of any external components, either.

●Type Designations (Ordering Information)



Product Name



- BD35618
- BD35615
- BD35613

Package Type



- HFN : HSON8
- EFJ : HTSOP-J8
- HFV : HVSO6

E2 Emboss tape reel opposite draw-out side: 1 pin
TR Emboss tape reel opposite draw-out side: 1 pin



HSON8



HVSO6



HTSOP-J8



- The contents described herein are correct as of October, 2008
- The contents described herein are subject to change without notice. For updates of the latest information, please contact and confirm with ROHM CO.,LTD.
- Any part of this application note must not be duplicated or copied without our permission.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams and information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by ROHM CO., LTD. is granted to any such buyer.
- The products described herein utilize silicon as the main material.
- The products described herein are not designed to be X ray proof.

The products listed in this catalog are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys). Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

Contact us for further information about the products.

| | | | | | |
|-----------------------|------------------------|------------------------|---------------------|------------------------|------------------------|
| San Diego | TEL: +1-858-625-3630 | FAX: +1-858-625-3670 | Tianjin | TEL: +86-22-23029181 | FAX: +86-22-23029183 |
| Atlanta | TEL: +1-770-754-5972 | FAX: +1-770-754-0691 | Shanghai | TEL: +86-21-6279-2727 | FAX: +86-21-6247-2066 |
| Boston | TEL: +1-978-371-0382 | FAX: +1-928-438-7164 | Hangzhou | TEL: +86-571-87658072 | FAX: +86-571-87658071 |
| Chicago | TEL: +1-847-368-1006 | FAX: +1-847-368-1008 | Nanjing | TEL: +86-25-8689-0015 | FAX: +86-25-8689-0393 |
| Dallas | TEL: +1-469-287-5366 | FAX: +1-469-362-7973 | Ningbo | TEL: +86-574-87654201 | FAX: +86-574-87654208 |
| Denver | TEL: +1-303-708-0908 | FAX: +1-303-708-0858 | Qingdao | TEL: +86-532-5779-312 | FAX: +86-532-5779-653 |
| Detroit | TEL: +1-248-348-9920 | FAX: +1-248-348-9942 | Suzhou | TEL: +86-510-82702693 | FAX: +86-510-82702992 |
| Nashville | TEL: +1-615-620-6700 | FAX: +1-615-620-6702 | Wuxi | TEL: +86-510-82702693 | FAX: +86-510-82702992 |
| Mexico | TEL: +52-33-3123-2001 | FAX: +52-33-3123-2002 | Shenzhen | TEL: +86-755-8307-3008 | FAX: +86-755-8307-3003 |
| Düsseldorf | TEL: +49-2154-9210 | FAX: +49-2154-921400 | Dongguan | TEL: +86-769-8393-3320 | FAX: +86-769-8398-4140 |
| Munich | TEL: +49-8999-216168 | FAX: +49-8999-216176 | Fuzhou | TEL: +86-591-8801-8698 | FAX: +86-591-8801-8690 |
| Stuttgart | TEL: +49-711-7272-370 | FAX: +49-711-7272-3720 | Guangzhou | TEL: +86-20-3878-8100 | FAX: +86-20-3825-5965 |
| France | TEL: +33-1-5697-3060 | FAX: +33-1-5697-3080 | Huizhou | TEL: +86-752-205-1054 | FAX: +86-752-205-1059 |
| United Kingdom | TEL: +44-1-908-306700 | FAX: +44-1-908-235788 | Xiamen | TEL: +86-592-238-5705 | FAX: +86-592-239-8380 |
| Denmark | TEL: +45-3694-4739 | FAX: +45-3694-4789 | Zhuhai | TEL: +86-756-3232-480 | FAX: +86-756-3232-460 |
| Espoo | TEL: +358-9725-54491 | FAX: +358-9-7255-4499 | Hong Kong | TEL: +852-2-740-6262 | FAX: +852-2-375-8971 |
| Salo | TEL: +358-2-7332234 | FAX: +358-2-7332237 | Taipei | TEL: +886-2-2500-6956 | FAX: +886-2-2503-2869 |
| Oulu | TEL: +358-8-5372930 | FAX: +358-8-5372931 | Kaohsiung | TEL: +886-7-237-0881 | FAX: +886-7-238-7332 |
| Barcelona | TEL: +34-9375-24320 | FAX: +34-9375-24410 | Singapore | TEL: +65-6332-2322 | FAX: +65-6332-5662 |
| Hungary | TEL: +36-1-4719338 | FAX: +36-1-4719339 | Philippines | TEL: +63-2-807-6872 | FAX: +63-2-809-1422 |
| Poland | TEL: +48-22-5757213 | FAX: +48-22-5757001 | Thailand | TEL: +66-2-254-4890 | FAX: +66-2-256-6334 |
| Russia | TEL: +7-495-739-41-74 | FAX: +7-495-739-41-74 | Kuala Lumpur | TEL: +60-3-7958-8355 | FAX: +60-3-7958-8377 |
| Seoul | TEL: +82-2-8182-700 | FAX: +82-2-8182-715 | Penang | TEL: +60-4-2286453 | FAX: +60-4-2286452 |
| Masan | TEL: +82-55-240-6234 | FAX: +82-55-240-6236 | Kyoto | TEL: +81-75-365-1218 | FAX: +81-75-365-1228 |
| Dalian | TEL: +86-411-8230-8549 | FAX: +86-411-8230-8537 | Yokohama | TEL: +81-45-476-2290 | FAX: +81-45-476-2295 |
| Beijing | TEL: +86-10-8525-2483 | FAX: +86-10-8525-2489 | | | |

Excellence in Electronics

ROHM

ROHM CO., LTD.

21 Saiin Mizosaki-cho, Ukyo-ku, Kyoto
615-8585, Japan
TEL: +81-75-311-2121 FAX: +81-75-315-0172
URL: <http://www.rohm.com>

Published by
KTC LSI Development Headquarters
LSI Business Promotion Group



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.