





Acc. To IEC 61076-4-101

2.0 mm ERmet Hard Metric Connector System **Table of Contents**



Application Notes	2.0 mm ERmet Hard Metric Connector System Introduction
10 mm Elmeit Hard Metric Connectors System 146 Jomparsion of 2.0 mm Connectors 146 Optication Netces 148 Voluct Features 149 Splication Netces 149 Voluct Features 149 Voluct Features 149 Suppression Requirements For Printed Circuit Boards 151 Viginer and Stacking Applications 152 Stroudt Selection Information 153 Drading Information Shroud Selection Chart 154 Achanical Specifications and Performance 156 How Electrical Performance 156 How Electrical Performance 160 Vaporoval Certificates, Parformance Lawels And Ordering Information 162 Vigit Angle Female Connectors Type A for Daughter Cards 163 Vigit Angle Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 183 Vigit Angle Female Connectors Type B for Daughter Cards 183 Vigit Angle Female Connectors Type B for Daughter Cards 183 Vigit Angle Female Connectors Type A for Daughter Cards 183 Vigit Angle Female Connectors Type B for Daughter Cards 183 Vigit Angle Female Connectors Type B for Daughter Cards 184 Vigit Angle Female Connectors Type C 198	
Comparison of 2.0 mm Connectors 146 Application Notes 148 Opplication Notes 149 Design Requirements For Printed Circuit Boards 151 Wighment Tolerance 152 Midplane and Stacking Applications 152 Stroud Selection Information 153 Drivering Information Shroud Selection Chart 154 Achanical Specifications and Performance 156 Flow Electrical Performance 156 OF Row Electrical Performance 156 OF Row Electrical Performance 160 Naporval Certificates, Performance Levels And Ordering Information 162 Night Angle Female Connectors Type A for Daughter Cards 163 Vertical Female Connectors Type A for Daughter Cards 174 Vertical Mela Connectors Type A for Daughter Cards 174 Vertical Mela Connectors Type A for Daughter Cards 174 Vertical Mela Connectors Type B for Backplanes 174 Vertical Mela Connectors Type B for Backplanes 174 Vertical Mela Connectors Type B for Backplanes 174 Vertical Mela Connectors Type B for Daughter Cards 188 Vertical Mela Connectors Type C for Daughter Cards	
Application Notes	2.0 mm ERmet Hard Metric Connector System
Induct Features 149 Design Requirements For Printed Circuit Boards 151 Uliginement Discretance 152 Victoria Selection Information 153 Dirude Selection Information 153 Driver Selection Information 153 Dirude Selection Information 153 Driver Selectina Performance 156 Prove Electrical Performance 158 Pioproval Certificates, Performance 150 O Pow Electrical Performance 160 O Pow Electrical Performance 160 O Pow Electricates, Performance Levels And Ordering Information 162 Vight Angle Female Connectors Type A for Daughter Cards 163 Firtical Male Connectors Type A for Daughter Cards 163 Firtical Male Connectors Type A for Daughter Cards 174 Vietchad Heine Connectors Type A for Daughter Cards 174 Vietchad Male Connectors Type B for Backplanes 174 Vietchad Male Connectors Type B for Daughter Cards 188 Vight Angle Female Connectors Type AB for Daughter Cards 188 Vight Angle Female Connectors Type C for Daughter Cards 193 Vight Angle Female Connectors Type C for Daughter Cards 193 Vight Angle Female Connectors Type D for Daughter Cards 194 Vight Angle Female Connectors Type D for	Comparsion of 2.0 mm Connectors
Jesign Requirements For Printed Circuit Boards 151 Wigment Tolerance 152 Vigune and Stacking Applications 152 Stroud Selection Information 153 Urdering Information Shroud Selection Chart 154 Verdering Informance 156 Information Shroud Selection Chart 156 Verdering Informance 156 UP Row Electrical Performance 158 UP Row Electrical Performance 160 Approval Centrificates. Performance Levels And Ordering Information 162 Naproval Centrificates. Performance Levels And Ordering Information 162 Vight Angle Female Connectors Type A for Daughter Cards 163 Vight Angle Female Connectors Type B for Backplanes 170 Vight Angle Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type A for Daughter Cards 188 Vight Angle Female Connectors Type A for Daughter Cards 188 Vight Angle Female Connectors Type C for Backplanes 177 Vertical Female Connectors Type C for Backplanes 193 Vight Angle Female Connectors Type D for Daughter Cards 194	
Nightane and Stacking Applications 152 Michoud Selection Information 153 Ordering Information Stroud Selection Chart 154 Acchanical Specifications and Performance 156 'Row Electrical Performance 158 (Jo Prequency Characteristics 158 (Jo Prequency Characteristics 160 Proval Cartificates, Performance 160 Night Angle Female Connectors Type A for Daughter Cards 163 Vight Angle Female Connectors Type A for Backplanes 164 Vight Angle Female Connectors Type A for Backplanes 170 Vight Angle Female Connectors Type B for Daughter Cards 163 Vight Angle Female Connectors Type B for Daughter Cards 164 Vight Angle Female Connectors Type B for Daughter Cards 170 Vight Angle Female Connectors Type B for Daughter Cards 174 Vight Angle Female Connectors Type B for Daughter Cards 183 Vight Angle Female Connectors Type B for Daughter Cards 184 Vight Angle Female Connectors Type B for Daughter Cards 183 Vight Angle Female Connectors Type D for Daughter Cards 184 Vight Angle Female Connectors Type D for Daughter Cards 204 Vietical Male Conne	
Micplane and Stacking Applications 152 Shroud Selection Information 153 Shroud Selection Stroud Selection Chart 154 Jederan Information Stroud Selection Chart 154 Adechanical Specifications and Performance 156 Igh Frequency Characteristics 158 0-Row Electrical Performance 160 Approval Certificates, Performance Levels And Ordering Information 162 Approval Certificates 163 Approval Certificates 164 Apple Female Connectors Type A for Daughter Cards 174 Aprical Male Connectors Type B In Backplanes 177 Arrical Male Connectors Type A for Daughter Cards 188 Apple Female Connectors Type C for Daughter Cards 193 Aprificat Male Connectors Type D for Daughter Cards	Design Requirements For Printed Circuit Boards151
Shroud Selection Information 153 Ordering Information Stroud Selection Chart 154 Acchanical Specifications and Performance 156 - Row Electrical Performance 158 Igh Frequency Characteristics 158 OR-Ow Electrical Performance 160 Hop Tequency Characteristics 158 Opticates, Performance Levels And Ordering Information 162 Hight Angle Female Connectors Type A for Daughter Cards 163 Fertical Male Connectors Type B 170 Alght Angle Female Connectors Type B for Daughter Cards 174 Artical Mele Connectors Type B for Daughter Cards 174 Artical Mele Connectors Type B for Daughter Cards 174 Artical Mele Connectors Type A 170 Alght Angle Female Connectors Type A for Daughter Cards 174 Artical Mele Connectors Type A for Daughter Cards 183 Alght Angle Female Connectors Type C for Daughter Cards 184 Angle Female Connectors Type C for Daughter Cards 198 Areital Male Connectors Type D for Daughter Cards 202 Areital Male Connectors Type D for Daughter Cards 202 Areital Male Connectors Type D for Daughter Cards 202 <td></td>	
Drdering Information Shroud Selection Chart 154 Mechanical Specifications and Performance 156 How Electrical Performance 158 Uigh Frequency Characteristics 168 D'Row Electrical Performance Levels And Ordering Information 160 Vight Angle Female Connectors Type A for Daughter Cards 163 Vight Angle Female Connectors Type A for Daughter Cards 163 Vight Angle Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 174 Vertical Female Connectors Type B for Daughter Cards 178 Vight Angle Female Connectors Type C for Daughter Cards 188 Vertical Male Connectors Type C for Daughter Cards 183 Vight Angle Female Connectors Type C for Daughter Cards 193 Vight Angle Female Connectors Type C for Daughter Cards 193 Vight Angle Female Connectors Type C for Daughter Cards 193 Vight Angle Female Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daugh	
4echanical Specifications and Performance 156 '-Row Electrical Performance 158 10-Row Electrical Performance 160 ligh Frequency Characteristics 160 ligh Frequency Characteristics 160 poprval Cartificates, Performance Levels And Ordering Information 162 light Angle Female Connectors Type A for Daughter Cards 163 refrical Female Connectors Type A 170 Night Angle Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type A 177 Vertical Male Connectors Type A for Daughter Cards 183 light Angle Female Connectors Type A for Daughter Cards 184 light Angle Female Connectors Type A for Daughter Cards 184 light Angle Female Connectors Type C for Daughter Cards 191 light Angle Female Connectors Type C for Daughter Cards 202 vertical Female Connectors Type D for Daughter Cards 202 light Angle Female Connectors Type D for Daughter Cards 202 vertical Male Connectors Type D for Daughter Cards 202 light Angle	
-Flow Electrical Performance 158 ilgh -Requency Characteristics 150 O-Row Electrical Performance 160 igh Trequency Characteristics 160 Apport Certificates, Performance Levels And Ordering Information 162 Applet Trequency Characteristics 163 Africal Finale Connectors Type A for Daughter Cards 170 Right Angle Female Connectors Type B for Daughter Cards 174 Africal Finale Connectors Type AB for Daughter Cards 183 Right Angle Female Connectors Type AB for Daughter Cards 183 Africal Finale Connectors Type C To Daughter Cards 193 Africal Finale Connectors Type C To Daughter Cards 193 Africal Finale Connectors Type D To Daughter Cards 202 Africal Finale Connectors Type D To Daughter Cards 202 Africal Finale Connectors Type D To Daughter Cards 202 Africal Male Connectors Type D To Daughter Cards 208 <t< td=""><td></td></t<>	
High Frequency Characteristics 158 0-Row Electrical Performance 160 High Frequency Characteristics 160 Approval Certificates, Performance Levels And Ordering Information 162 Approval Certificates, Performance Levels And Ordering Information 170 Approval Certificates, Performance Levels And Ordering Information 170 Approval Certificates, Performance Connectors Type B for Daughter Cards 183 Apple Female Connectors Type D for Daughter Cards 202 Apricial Male Connectors Type D for Daughter Cards 204	
0-Row Electrical Performance 160 tigh Frequency Characteristics 160 Approval Certificates, Performance Levels And Ordering Information 162 Right Angle Female Connectors Type A for Daughter Cards 163 Fertical Male Connectors Type A for Daughter Cards 163 Right Angle Female Connectors Type B for Daughter Cards 170 Right Angle Female Connectors Type B for Daughter Cards 174 Fertical Female Connectors Type B for Daughter Cards 183 Right Angle Female Connectors Type B for Daughter Cards 183 Right Angle Female Connectors Type AB for Daughter Cards 188 Fertical Male Connectors Type A for Daughter Cards 188 Fertical Male Connectors Type C for Daughter Cards 193 Right Angle Female Connectors Type C for Daughter Cards 193 Right Angle Female Connectors Type D for Daughter Cards 202 Fertical Male Connectors Type D for Daughter Cards 202 Right Angle Female Connectors Type D for Daughter Cards 202 Right Angle Female Connectors Type D for Daughter Cards 202 Right Angle Female Connectors Type D for Daughter Cards 208 Right Angle Female Connectors Type E for Daughter Cards 208 Right A	
High Frequency Characteristics 160 Approval Certificates, Performance Levels And Ordering Information 162 Sight Angle Franela Connectors Type A for Daughter Cards 163 Vertical Male Connectors Type A 170 Sight Angle Franela Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B 174 Vertical Male Connectors Type A for Daughter Cards 174 Vertical Male Connectors Type A for Daughter Cards 183 Vertical Male Connectors Type A for Daughter Cards 188 Vertical Male Connectors Type C for Daughter Cards 188 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 204 Vertical Male Connectors Type D for Daughter Cards 204 Vertical Famale Connectors Type D for Daughter Cards 204 Vertical Famale Connectors Type D for Daughter Cards <td< td=""><td></td></td<>	
Approval Certificates, Performance Levels And Ordering Information 162 Right Angle Female Connectors Type A for Daughter Cards 163 Vertical Male Connectors Type B for Daughter Cards 170 Right Angle Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Backplanes 177 Vertical Female Connectors Type B for Daughter Cards 178 Right Angle Female Connectors Type AB for Daughter Cards 188 Vertical Male Connectors Type C for Daughter Cards 188 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type E for Daughter Cards 202 Vertical Male Connectors Type E for Daughter Cards 204 Vertical Male Connectors Type E for Daughter Card	
Right Angle Female Connectors Type A for Daughter Cards 163 Vertical Male Connectors Type A for Backplanes 165 Right Angle Female Connectors Type B for Daughter Cards 170 Right Angle Female Connectors Type B for Daughter Cards 177 Vertical Female Connectors Type B for Daughter Cards 177 Vertical Male Connectors Type B for Daughter Cards 188 Vertical Male Connectors Type A for Daughter Cards 188 Vertical Male Connectors Type A for Daughter Cards 188 Vertical Male Connectors Type A for Daughter Cards 191 Right Angle Female Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Male Connectors Type D for Backplanes 195 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type E for Daughter Cards 204 Vertical Male Connectors Type E for Daughter Cards 208 Vertical Male Connectors Type E for Daughter Cards 208 Verticale Male Connectors Type E for Daughter Cards 204 Verticale Male Connectors Type D for Daughter Cards 208 Verticale Male Connectors Type D for Daughter Cards 212 Right Angle Female	
Vertical Male Connectors Type A for Backplanes 165 Vertical Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B for Daughter Cards 183 Vertical Male Connectors Type B 188 Vertical Male Connectors Type AB for Daughter Cards 183 Vertical Male Connectors Type AB for Backplanes 191 Vight Angle Female Connectors Type C for Backplanes 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type E for Daughter Cards 204 Vertical Female Connectors Type E for Daughter Cards 204 Vertical Female Connectors Type D for Daughter Cards 208 Vertical Female Connectors Type E for Daughter Cards 204 Verticale Male Connectors Type E for Daughter Cards 208 Verticale Male Connectors Type E for Daughter Cards 212 Right Angle Female Connectors Type E for Daug	Approval Certificates, Performance Levels And Ordering Information
Vertical Female Connectors Type A 170 Night Angle Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B 177 Vertical Female Connectors Type AB for Daughter Cards 183 Night Angle Female Connectors Type AB for Daughter Cards 188 Vertical Female Connectors Type C for Daughter Cards 191 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 193 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 204 Vertical Female Connectors Type D for Daughter Cards 204 Vertical Female Connectors Type D for Daughter Cards 204 Verticale Female Connectors Type D for Daughter Cards 204 Verticale Female Connectors Type D for Daughter Cards 204 Verticale Female Connectors Type D for Daughter Cards 210 Verticale Male Connectors Type D for Daughter Cards 212 Night Angle Female Connectors Type D for Daughter Cards 214 Verticale Male Connectors Type D for D	Right Angle Female Connectors Type A for Daughter Cards 163
Right Angle Female Connectors Type B for Daughter Cards 174 Vertical Male Connectors Type B 177 Vertical Female Connectors Type AB for Daughter Cards 183 Xight Angle Female Connectors Type AB for Daughter Cards 184 Vertical Male Connectors Type AB for Daughter Cards 191 Xight Angle Female Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type C for Daughter Cards 193 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 202 Vertical Female Connectors Type D for Daughter Cards 204 Vertical Female Connectors Type D for Daughter Cards 208 Verticale Female Connectors Type E 208 Verticale Female Connectors Type E 208 Verticale Female Connectors Type E for Daughter Cards 208 Verticale Female Connectors Type E for Daughter Cards 210 Verticale Female Connectors Type E for Daughter Cards 212 Vight Angle Female Connectors Type F for Daughter Cards 214 Verticale Male Connectors Type F for Daughte	
/ertical Male Connectors Type B for Backplanes .177 /ertical Female Connectors Type AB for Daughter Cards .183 Right Angle Female Connectors Type AB for Daughter Cards .181 Right Angle Female Connectors Type AB for Daughter Cards .191 Right Angle Female Connectors Type C for Daughter Cards .193 Identical Male Connectors Type C for Daughter Cards .193 Pertical Female Connectors Type D for Daughter Cards .193 Right Angle Female Connectors Type D for Daughter Cards .202 Vertical Female Connectors Type D for Daughter Cards .202 Vertical Female Connectors Type D for Daughter Cards .202 Vertical Female Connectors Type E for Daughter Cards .208 Verticale Female Connectors Type E for Daughter Cards .208 Verticale Female Connectors Type E for Daughter Cards .208 Verticale Male Connectors Type D E for Daughter Cards .212 Right Angle Female Connectors Type D F or Daughter Cards .212 Verticale Female Connectors Type F for Daughter Cards .212 Right Angle Female Connectors Type F for Daughter Cards .212 Right Angle Female Connectors Type F for Daughter Cards .220 Verticale Male Connectors Type F for Daughter Cards	
/ertical Female Connectors Type B 183 Right Angle Female Connectors Type AB for Daughter Cards 188 /ertical Male Connectors Type C for Daughter Cards 191 /ight Angle Female Connectors Type C for Backplanes 193 /ertical Male Connectors Type C for Backplanes 193 /ertical Female Connectors Type D for Daughter Cards 198 Right Angle Female Connectors Type D for Daughter Cards 204 /ertical Hale Connectors Type D for Backplanes 204 /ertical Female Connectors Type D for Backplanes 204 /ertical Female Connectors Type D for Backplanes 204 /ertical Female Connectors Type E for Daughter Cards 208 /erticale Female Connectors Type E for Daughter Cards 208 /erticale Male Connectors Type D for Daughter Cards 212 Right Angle Female Connectors Type D for Daughter Cards 214 /erticale Male Connectors Type D for Daughter Cards 214 /erticale Male Connectors Type D for Daughter Cards 214 /erticale Male Connectors Type F for Backplanes 216 Right Angle Female Connectors Type F for Backplanes 220 /erticale Male Connectors Type F for Backplanes 220 /erticale Male Connectors Type I for Daughter	
Right Angle Female Connectors Type AB for Daughter Cards 188 Vertical Male Connectors Type AB for Backplanes 191 Right Angle Female Connectors Type C for Daughter Cards 193 Vertical Male Connectors Type C for Daughter Cards 195 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Daughter Cards 202 Vertical Male Connectors Type D for Backplanes 204 Vertical Male Connectors Type D for Backplanes 204 Vertical Pemale Connectors Type D for Backplanes 204 Vertical Pemale Connectors Type D for Daughter Cards 208 Verticale Female Connectors Type E for Daughter Cards 208 Verticale Female Connectors Type E for Daughter Cards 210 Verticale Female Connectors Type E for Daughter Cards 214 Verticale Female Connectors Type F for Daughter Cards 214 Verticale Male Connectors Type F for Daughter Cards 214 Verticale Male Connectors Type F for Daughter Cards 214 Verticale Female Connectors Type F for Daughter Cards 220 Verticale Male Connectors Type F for Daughter Cards 220 Verticale Female Connectors Type F for Daughter Cards 220 Verticale Female C	Vertical Male Connectors Type B for Backplanes
Vertical Male Connectors Type AB for Backplanes	Vertical Female Connectors Type B
Right Angle Female Connectors Type C for Daughter Cards	Right Angle Female Connectors Type AB for Daughter Cards 186
Vertical Male Connectors Type C for Backplanes .195 Vertical Female Connectors Type D for Daughter Cards .202 Vertical Male Connectors Type D for Backplanes .204 Vertical Male Connectors Type D .206 Right Angle Female Connectors Type D .208 Verticale Male Connectors Type E for Daughter Cards .208 Verticale Female Connectors Type D E for Backplanes .210 Verticale Male Connectors Type DE for Daughter Cards .212 Right Angle Female Connectors Type DE for Daughter Cards .214 Verticale Male Connectors Type F for Daughter Cards .214 Verticale Male Connectors Type F for Daughter Cards .218 Verticale Female Connectors Type F for Daughter Cards .222 Right Angle Female Connectors Type I for Daughter Cards .222 Right Angle Female Connectors Type I for Daughter Cards .222 Verticale Male Connectors Type I for Daughter Cards .222 Right Angle Female Connectors Type I for Daughter Cards .224 Verticale Male Connectors Type M for Daughter Cards .22	Vertical Male Connectors Type AB for Backplanes
/ertical Female Connectors Type C .198 Right Angle Female Connectors Type D for Daughter Cards .202 /ertical Male Connectors Type D .204 /ertical Female Connectors Type D .206 Right Angle Female Connectors Type D .206 Right Angle Female Connectors Type E .208 /erticale Male Connectors Type E for Daughter Cards .208 /erticale Male Connectors Type E .210 /erticale Male Connectors Type DE for Daughter Cards .211 Right Angle Female Connectors Type DE for Daughter Cards .212 Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type F for Daughter Cards .214 /erticale Male Connectors Type F for Daughter Cards .212 Right Angle Female Connectors Type F for Daughter Cards .220 /erticale Male Connectors Type F .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .224 /erticale Male Connectors Type L for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228	Right Angle Female Connectors Type C for Daughter Cards
Right Angle Female Connectors Type D for Daughter Cards .202 /ertical Male Connectors Type D for Backplanes .204 /ertical Female Connectors Type D .206 Right Angle Female Connectors Type E for Daughter Cards .208 /erticale Male Connectors Type E for Daughter Cards .210 /erticale Male Connectors Type E .212 Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Backplanes .216 Right Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .216 /erticale Female Connectors Type F for Backplanes .218 /erticale Female Connectors Type F for Daughter Cards .228 /erticale Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type L for Backplanes .226 Right Angle Female Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .228 /erticale Male Connectors	Vertical Male Connectors Type C for Backplanes
Vertical Male Connectors Type D for Backplanes .204 Vertical Female Connectors Type E .206 Right Angle Female Connectors Type E for Daughter Cards .208 Verticale Female Connectors Type E for Backplanes .210 Verticale Female Connectors Type DE .212 Right Angle Female Connectors Type DE for Daughter Cards .214 Verticale Female Connectors Type DE for Daughter Cards .214 Verticale Male Connectors Type DE for Backplanes .216 Right Angle Female Connectors Type F for Daughter Cards .218 Verticale Female Connectors Type F for Backplanes .220 Verticale Female Connectors Type F for Daughter Cards .218 Verticale Female Connectors Type F for Daughter Cards .2214 Verticale Female Connectors Type L for Daughter Cards .2224 Verticale Male Connectors Type L for Daughter Cards .2224 Verticale Male Connectors Type M for Daughter Cards .224 Verticale Male Connectors Type M for Daughter Cards .224 Verticale Male Connectors Type M for Daughter Cards .228 Right Angle Female Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type N for Daughter Cards .228 Verticale Male Con	Vertical Female Connectors Type C
/ertical Female Connectors Type D .206 Right Angle Female Connectors Type E for Daughter Cards .208 /erticale Male Connectors Type E .210 /erticale Female Connectors Type D .210 /erticale Female Connectors Type D .212 Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type F for Daughter Cards .216 /ight Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .220 /erticale Female Connectors Type F .222 Right Angle Female Connectors Type F .222 Right Angle Female Connectors Type I for Daughter Cards .222 /erticale Male Connectors Type I for Daughter Cards .222 /erticale Male Connectors Type I for Daughter Cards .226 /erticale Male Connectors Type M for Daughter Cards .226 /erticale Male Connectors Type N for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .230 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232	Right Angle Female Connectors Type D for Daughter Cards 202
Right Angle Female Connectors Type E for Daughter Cards .208 /erticale Male Connectors Type E .210 /erticale Female Connectors Type DE for Backplanes .212 Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Daughter Cards .216 Right Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .220 /erticale Female Connectors Type F for Backplanes .222 Right Angle Female Connectors Type I for Daughter Cards .222 /erticale Male Connectors Type I for Daughter Cards .222 /erticale Male Connectors Type I for Daughter Cards .222 /erticale Male Connectors Type M for Daughter Cards .224 /erticale Male Connectors Type M for Daughter Cards .226 Right Angle Female Connectors Type M for Daughter Cards .230 /erticale Male Connectors Type M for Daughter Cards .230 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .230 /igh	Vertical Male Connectors Type D for Backplanes
Verticale Male Connectors Type E for Backplanes .210 Verticale Female Connectors Type DE for Daughter Cards .212 Right Angle Female Connectors Type DE for Daughter Cards .214 Verticale Male Connectors Type DE for Daughter Cards .214 Verticale Male Connectors Type DE for Daughter Cards .216 Right Angle Female Connectors Type F for Daughter Cards .218 Verticale Male Connectors Type F .220 Verticale Female Connectors Type F .220 Verticale Male Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .232 Verticale Male Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Daughter Cards .232 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .245	Vertical Female Connectors Type D
/erticale Female Connectors Type E .212 Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Dackplanes .216 Right Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .220 /erticale Female Connectors Type F .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .2224 /erticale Male Connectors Type L for Backplanes .226 Right Angle Female Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .243 Shrouds Type A for Backplanes .245 Shrouds Ty	Right Angle Female Connectors Type E for Daughter Cards
Right Angle Female Connectors Type DE for Daughter Cards .214 /erticale Male Connectors Type DE for Backplanes .216 Right Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .220 /erticale Female Connectors Type F .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .224 /erticale Male Connectors Type M for Daughter Cards .224 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .233 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .234 Shrouds Type A for Backplanes .243 Shrouds Type A for Backplanes .243	Verticale Male Conneactors Type E for Backplanes
Verticale Male Connectors Type DE for Backplanes .216 Right Angle Female Connectors Type F for Daughter Cards .218 Verticale Male Connectors Type F for Backplanes .220 Verticale Female Connectors Type F .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .226 Right Angle Female Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type N for Daughter Cards .230 Right Angle Female Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Backplanes .230 Shrouds Type A for Backplanes .232 Shrouds Type B for Backplanes .233 Shrouds Type A for Backplanes .245 Shrouds Type A for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes </td <td>Verticale Female Connectors Type E</td>	Verticale Female Connectors Type E
Right Angle Female Connectors Type F for Daughter Cards .218 /erticale Male Connectors Type F for Backplanes .220 /erticale Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .224 /erticale Male Connectors Type L for Backplanes .224 /erticale Male Connectors Type L for Backplanes .224 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type N for Daughter Cards .230 Right Angle Female Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .230 Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .238 Shrouds Type C for Backplanes .245 Shrouds Type C for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .245 Shrouds Type E for Backplanes	Right Angle Female Connectors Type DE for Daughter Cards .214
Verticale Male Connectors Type F for Backplanes .220 Verticale Female Connectors Type L for Daughter Cards .222 Right Angle Female Connectors Type L for Daughter Cards .224 Verticale Male Connectors Type L for Backplanes .226 Right Angle Female Connectors Type M for Daughter Cards .226 Verticale Male Connectors Type M for Daughter Cards .226 Verticale Male Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .230 Right Angle Female Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Backplanes .233 Shrouds Type A for Backplanes .234 Shrouds Type B for Backplanes .233 Shrouds Type B for Backplanes .245 Shrouds Type AB for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .245	Verticale Male Connectors Type DE for Backplanes
/erticale Female Connectors Type F .222 Right Angle Female Connectors Type L for Daughter Cards .224 /erticale Male Connectors Type L for Backplanes .226 Right Angle Female Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .234 Shrouds Type B for Backplanes .239 Shrouds Type A for Backplanes .243 Shrouds Type A for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .245	Right Angle Female Connectors Type F for Daughter Cards
Right Angle Female Connectors Type L for Daughter Cards .224 Verticale Male Connectors Type L for Backplanes .226 Right Angle Female Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Daughter Cards .228 Verticale Male Connectors Type M for Backplanes .230 Right Angle Female Connectors Type N for Daughter Cards .232 Verticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .239 Shrouds Type A for Backplanes .245 Shrouds Type A for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .245 Shrouds Type E for Backplanes .245	Verticale Male Connectors Type F for Backplanes
/erticale Male Connectors Type L for Backplanes	Verticale Female Connectors Type F
Right Angle Female Connectors Type M for Daughter Cards .228 /erticale Male Connectors Type M for Backplanes .230 Right Angle Female Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .232 /erticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .239 Shrouds Type A for Backplanes .239 Shrouds Type A for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .245 Shrouds Type E for Backplanes .245	Right Angle Female Connectors Type L for Daughter Cards
Verticale Male Connectors Type M for Backplanes	Verticale Male Connectors Type L for Backplanes
Right Angle Female Connectors Type N for Daughter Cards .232 /erticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .239 Shrouds Type C for Backplanes .239 Shrouds Type C for Backplanes .245 Shrouds Type D for Backplanes .245 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .245	Right Angle Female Connectors Type M for Daughter Cards
/erticale Male Connectors Type N for Backplanes .234 Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .239 Shrouds Type C for Backplanes .243 Shrouds Type D for Backplanes .243 Shrouds Type D for Backplanes .243 Shrouds Type D for Backplanes .245 Shrouds Type D for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .249	Verticale Male Connectors Type M for Backplanes
Shrouds Type A for Backplanes .236 Shrouds Type B for Backplanes .239 Shrouds Type C for Backplanes .243 Shrouds Type AB for Backplanes .243 Shrouds Type D for Backplanes .249 Shrouds Type E for Backplanes .249	Right Angle Female Connectors Type N for Daughter Cards
Shrouds Type B for Backplanes .239 Shrouds Type C for Backplanes .243 Shrouds Type AB for Backplanes .245 Shrouds Type D for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .241 Shrouds Type E for Backplanes .242	Verticale Male Connectors Type N for Backplanes
Shrouds Type B for Backplanes .239 Shrouds Type C for Backplanes .243 Shrouds Type AB for Backplanes .245 Shrouds Type D for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .241 Shrouds Type E for Backplanes .242	Shrouds Type A for Backplanes
Shrouds Type C for Backplanes .243 Shrouds Type AB for Backplanes .245 Shrouds Type D for Backplanes .249 Shrouds Type E for Backplanes .249 Shrouds Type E for Backplanes .251	Shrouds Type B for Backplanes
Shrouds Type AB for Backplanes	Shrouds Type C for Backplanes
Shrouds Type D for Backplanes	Shrouds Type AB for Backplanes
Shrouds Type E for Backplanes	Shrouds Type D for Backplanes
	Shrouds Type E for Backplanes
Shrouds type Flor Backplanes	Shrouds Type F for Backplanes

2.0 mm ERmet Hard Metric Connector System **Table of Contents**



N
5
3
2
9
Ĵ.
ē.

Right Angle Female Monoblock Modules	055
Vertical Male Monoblock Modules	
Dust Covers For Type A, B, AB, D, E and DE	
Coding Keys	
Guide Pin for ERmet 10 Row Type D	
Special Contacts for Type L, M and N	
Modular press-fit tools for male and female connectors	
Press-In-Tools For The Female Connectors	
Press-In-Tools For The Male Connectors	
Toolholder	
3U CompactPCI® Daughter Card Layout	
3U CompactPCI® Backplane Layout	
6U CompactPCI® Daughter Card Layout	
6U CompactPCI® Backplane Layout	
9U 10-Row 2mm Daughter Card Layout	
9U 10-Row 2mm Backplane Layout	
IEEE 1301 Daughter Cards for IEC 61076-4-101 2mm HM Connectors	
IEEE 1301 Backplane Layouts For IEC 61076-4-101 2mm HM Connectors	
VME64 Extensions Daughter Card	275
VME64 Extensions Backplane	276
64 Bit CompactPCI® System Slot Pin Assignments	
32 Bit CompactPCI® System Slot Pin Assignments	279
32 Bit CompactPCI® Peripheral Slot Pin Assignments	280
cPCI Computer Telephony P4 Pin Assignments	281
cPCI Computer Telephony Safety Classifications for J4/P4	282
cPCI Computer Telephony P5 Pin Assignments	283
cPCI Computer Telephony Safety Classifications for J5/P5	284
PXI Generic Peripheral Slot Pinout	285
PXI System Slot Pinout	286
PXI Star Trigger Slot Pinout	287
VME64x on CompactPCI® J4/P4 and J5/P5 Pin Assignments	288
Single PMC's I/O Signal Mapping to CompactPCI® 3U J2 Connector	289
PMC Mezzanine Card I/O Pin Assignments	289
IP Mezzanine Module I/O Pin Assignments	
Bellcore Lubrication	
Glossary Of Terminology	
2ERNI Customer Request Form	
Applications	
Right Angle Male Connectors Type A for Daughter Cards	
Right Angle Male Connectors Type B for Daughter Cards	
Right Angle Male Connectors Type C for Daughter Cards	
ERmet Thru Hole Reflow (THR) Female Connectors	
CompactPCI Connectors acc. to PIGMG 2.0 Rev. 3.0	
ERmet® Power Modules	
Electrical and Mechanical Characteristics	
Derating Curve and PTH Drawing	
Right Angle Male	
Right Angle Male	
Verucai remaie	320





Introduction

The ERmet 2mm H.M. connector line from ERNI offers unparalleled performance and flexibility for today's high performance circuit designs. Since its introduction in 1993, this product line has expanded and now offers almost every module configuration possible in a board to backplane interconnect system. Standard and reverse configurations are available including shielded vertical females, stacking designs, stamped power connectors. This connector system has now become the standard for board to backplane applications.

The ERmet 2mm H.M. connector system has achieved widespread acceptance and popularity as the interconnect system chosen for CompactPCI. It is also widely used by OEMs serving the telecommunications and networking industry segments. It has achieved this unparalleled acceptance due to its high frequency per-formance, its wide selection of modular components and its cost-benefit ratio. This connector is supported by one of the industry's most comprehensive international connector standards, IEC 61076-4-101.

Whether you are developing a new backplane, a high performance CPU or I/O card or integrating a sophisticated hybrid system, ERNI has anticipated your needs. The ERNI team stands ready to partner with you to develop the most efficient solution to your design challenge.

Features

- Modular connectors with 2.0 mm signal contact pitch for backplanes and daughter cards.
- · High density board to backplane connector system.
- Up to 8 signal rows plus two shield rows for optimum performance.
- Three levels of sequential mating for front or rear hot swap applications. 1.5 mm increments.
- 15 standard contacts available for any pin loading requirement.
- Complete line of complementary accessories to include stamped power connectors, color coded coding keys, latching shrouds, ground return shields, high frequency, and high power contacts.
- Superior female connector contact design provides a uniform signal path.
- Comply to the international standard IEC 61076-4-101.
- For networking, telecommunications, high performance computing and other demanding applications.

2.0 mm ERmet Hard Metric Connector System Product Overview



ERmet 2mm H.M. connectors are a versatile, cost-effective board-to-backplane solution for today's high performance, high density applications.

The ERmet 2mm H.M. line consists of 26 different module types including matching shrouds for midplane, stacking applications, power modules, upper and lower ground return shields, coding keys.

For circuit design versatility, the connectors are offered with a selection of contacts including signal, high power, high frequency and coaxial. They are available in 50mm, 44 mm, 38 mm, and 25mm modules for end-to-end stacking without contact loss. The dual beam female contact design provides equalized signal path lengths which results in virtually identical propagation times for each contact row.



Type A Connector

- 110 signal contacts.
- 44 shield contacts.
- 50 mm long including the multifunction area for coding keys.
- Integral pre-alignment guide and polarizing pins.
- Optional locating pegs for printed circuit board (PCB) mounting.
- 3 contact lengths for sequential mating.



Type B Connector

- 125, 110 and 95 signal contacts.
- 50 shield contacts.
- 50 mm, 44 mm and 38 mm long without the multifunction area.
- 3 contact lengths for sequential mating.



Type C Connector

- 55 signal contacts.
- 22 shield contacts.
- 25 mm long.
- For end positions only.
- Pre-alignment guide pins.
- Optional locating pegs for printed circuit board (PCB) mounting.
- 3 contact lengths for sequential mating.



Type D Connector

- 176 signal contacts.
- 44 shield contacts.
- 50 mm long including the multifunction area for coding keys.
- Integral pre-alignment guide and polarizing pins.
- Optional locating pegs for printed circuit board (PCB) mounting.
- Positions for optional early mate ground pin.
- 3 contact lengths for sequential mating.



Type E Connector

- 200 signal contacts.
- 50 shield contacts.
- 50 mm long without the multifunction area.
- 3 contact lengths for sequential mating.



Type F Connector

- 88 signal contacts.
- 22 shield contacts.
- 25 mm long.
- For end positions only
- Pre-alignment guide pins.
- Optional locating pegs for printed circuit board (PCB) mounting.
- 3 contact lengths for sequential mating.

2.0 mm ERmet Hard Metric Connector System Product Overview





Type A Ground Return Shield

- Upper and lower shields for Type A connectors.
- Upper shield available integrated with female connector or as separate component.



Type D Ground Return Shield

- Upper and lower shields for Type D connectors.
- Upper shield available integrated with female connector or as separate component.



Type B Ground Return Shield

- Upper and lower shields for the Type B female connectors.
- Upper shield available integrated with female connector or as separate component.



Type E Ground Return Shield

- Upper and lower shields for the Type E female connectors.
- Upper shield available integrated with female connector or as separate component.



Type C Ground Return Shield

- Upper and lower shields for Type C and M connectors.
- Upper shield available integrated with female connector or as separate component.



Type F Ground Return Shield

- Upper and lower shields for Type F connectors.
- Upper shield available integrated with female connector or as separate component.



Type L Connector

- 6 special contact cavities.
- 50 mm long.
- Multifunction area for coding keys.
- Integral pre-alignment guide and
- oplarizing pins.
 Optional locating pegs for printed circuit board (PCB) mounting.



Type M Connector

- 3 special contact cavities.
- 55 signal contacts.
- 50 mm long.
- Multifunction area for coding keys.
- Integral pre-alignment guide and polarizing pins.
- Optional locating pegs for printed circuit board (PCB) mounting.



Type N Connector

- 3 special contact cavities.
- 25 mm long.
- For end positions only
- Pre-alignment guide pins.
- Optional locating pegs for printed circuit board (PCB) mounting.

T

2.0 mm ERmet Hard Metric Connector System Product Overview





Type A Vertical Female Connector

- 110 signal contacts.
- 44 shield contacts.
- 50 mm long including the multifunction area for coding keys.
- Pre-alignment guide and integral polarizing pins.
- Optional shields.
- Extended terminals and spacers available.



Type B Vertical Female Connector

- 125, 110 and 95 signal contacts.
- 50, 44 and 38 shield contacts.
- 50 mm, 44 mm and 38 mm long without a multifunction area.
- Optional shields.
- Extended terminals and spacers available.



Type C Vertical Female Connector

- 55 signal contacts.
- 22 shield contacts.
- 25 mm long.
- For end positions only
- Pre-alignment guide pins.
- Optional locating pegs for printed circuit board (PCB) mounting.
- Optional shields.
- Extended terminals and spacers available.



Type AB25 Right Angle Female

- 125 signal contacts.
- 44 shield contacts.
- 50 mm long.
- Integral prealignment guide and polarizing pins.
- AB compatible males also available.



Type AB22 Right Angle Female

- 110 signal contacts.
- 40 shield contacts.
- 44 mm long.
- Integral prealignment guide and polarizing pins.
- AB compatible males also available.



Type AB19 Right Angle Female

- 95 signal contacts.
- 32 shield contacts.
- 38 mm long.
- Integral prealignment guide and polarizing pins.
- AB compatible males also available.



Type DE Right Angle Female

- 200 signal contacts.
- 50 shield contacts.
- 50 mm long.
- Integral prealignment guide and polarizing pins.
- · DE compatible males also available.



Connector Coding System

- Up to 70 unique male and female coding keys.
- For use in the multifunction center of the Type A, D, L and M male or female connectors.
- Low cost, industry standard design.
- Easy snap-in installation no epoxy adhesive required.
- Bright colors for quick visual identification conform to industry standard.
- Crush resistant construction, exceeds IEC requirements.

2.0 mm ERmet Hard Metric Connector System Product Overview





Type D Vertical Female Connector

- 176 signal contacts.
- 44 shield contacts.
- 50 mm long including the multifunction area for coding keys.
- Pre-alignment guide and integral polarizing pins.
- Optional shields.



Type E Vertical Female Connector

- 200 signal contacts.
- 50 shield contacts.
- 50 mm long without a multifunction area.
- Optional shields.



Type F Vertical Female Connector

- 88 signal contacts.
- 22 shield contacts.
- 25 mm long.
- For end positions only
- Pre-alignment guide pins.
- Optional shields.

2.0 mm ERmet Hard Metric Connector System

Complementary Components





Type A Shroud

- 4 heights for printed circuit boards (PCBs) 1.6 to 6.0 mm thick.
- 50 mm and 38 mm long.
- Multifunction area for coding keys.



Type B Shroud

- 4 heights for printed circuit boards (PCBs) 1.6 to 6.0 mm thick.
- 50 mm, 44 mm and 38 mm long.



Type C Shroud

- 4 heights for printed circuit boards (PCBs) 1.6 to 6.0 mm thick.
- 25 mm long.
- For end positions only.



Type AB 19 & AB 25 Shroud

- 38 mm and 50 mm respectively.
- Integral pre-alignment and guide pins.
- 4 heights for printed circuit boards (PCBs) 1.6 to 6.0 mm thick.



Type AB 22 Shroud

- 44 mm long.
- Integral pre-alignment and guide pins.
- 4 heights for printed circuit boards (PCBs) 1.6 to 6.0 mm thick.



Optional Latch Arm

- Can be added to standard ERmet shroud body.
- · Spring action latch.
- Easy installation, no tools required.



Monoblock Modules

- Male and Female monoblock modules.
- Optional integrated coding keys for 3.3V, 5.0V or Telecom applications.
- Multifunction area for coding keys.
- Available in a variety of configurations 94 or 100 mm long.



Male & Female Power Module

- Closed entry female connector for backplane.
- 3 pin levels for sequential mating.
- 8 ampere, per contact.
- Pressfit, flat rock assembly.

2.0 mm ERmet Hard Metric Connector System Comparsion of 2.0 mm Connectors

A 2.0 mm Connector For CompactPCI Needs To Be Different. Here's Why.

When you're choosing a 2.0 mm connector for your product, it pays to give your choice a little extra thought. Just knowing a connector is a 2.0 mm connector is not enough – there are really three distinctly separate and non-intermateable connector lines. They are the Futurebus style, the HDM style and the Hard Metric style, such as the ERmet 2mm H.M. from ERNI for CompactPCI architecture.

All three connector systems use a 2.0 mm grid and are offered in modular formats, but there the similarity ends. Each line has different printed circuit board hole sizes, contact sizes, shield configurations, keying methods and electrical characteristics. In short, there are very few similarities beyond the 2.0 mm grids they share.

All three 2.0 mm connector designs consist of multi-row pin headers on the backplane, right angle female connectors on the daughter card and a 2.0 mm grid spacing. One immediate difference is in terminal area design. The HDM style has exposed terminals on the right angle daughter card female connector, while the Futurebus and Hard Metric designs have encapsulated terminals. The 5+2 row Hard Metric backplane connector is 3.0 mm more narrow than the 5+2 row Futurebus connector. The 7 (5+2) row Hard Metric connector is more narrow even than the 6 row HDM connector. The Hard Metric design preserves more space on the backplane for components that must be placed between the connectors.

The mating distances also differ between the three product lines. Mating distance is measured from the rear edge of the daughter card to the front surface of the backplane when the daughter card is fully seated. The Futurebus mating distance is 10 mm, while the mating distance for both Hard Metric and HDM is 12.5 mm. The 12.5 mm measurement is important because it matches the mating distance of the established DIN 41612 connectors and the 2.5 mm IEC 61076-4-100 connector.

Matching mating distances allows industries that use Eurocard packaging (IEC 273 or IEEE 1101 or 1101.10) to build systems that combine the popular 96 pin DIN connectors and the newer Hard Metric and HDM connectors. This supports legacy architectures while allowing the addition of new features that require the greater signal density of 2.0 mm connectors. The VME64 Extensions committee chose the Hard Metric connector system for the P0/J0 connector because of this advantage.



*Trademark of Teradyne Corporation

ERmet 2mm H.M. Connectors

......

2.0 mm ERmet Hard Metric Connector System **Comparsion of 2.0 mm Connectors**

=	1	2	N	

		Connector Lines		
De	sign Criteria	HDM™	Futurebus	ERNI Hard Metric 5+2/8+2
Gene	ral Specification	Proprietary	IEC 1076-4-104	IEC 61076-4-101
Number of R	ows (Signal and Ground)	6*	5+2	5+2/8+2
Total Con	tacts Per Linear Inch	76	88	88/127
Number	of Standard Modules	3	7	6/15
Width	of Male Housing	15.8 mm	17.8 mm	15.4 mm – 21.4 mm
Distance from Da	aughter Card Edge to Row A	2.50 mm	7.00 mm	1.50 mm
Mated Distance fr	om Backplane Front to Row A	15.0 mm	17.0 mm	14.0 mm
Signal Mating	g Levels / Step Distance	3 levels, 0.50 mm each	5 levels, 0.75 mm each	3 levels 1.50 mm each
E	MI Shielding	Yes	Yes ⁺	Yes
Extended	d Guidance Features	See footnote +++	Add-On Module+	Integrated
Co	ding Locations	See footnote +++	Integrated	Integrated
Coding Corr	nbinations Per Location	8	3	70
	onnector Configuration /ertical Male	Yes	Yes	Yes
	onnector Configuration ertical Female	Yes	Yes+	Yes ⁺
Power	Contact Modules	Yes	Yes	Yes
Coaxia	I Contact Modules	Yes	Yes	Yes
Maximum Contact Resistance of Mated Pair		40 mΩ	50 mΩ	20 mΩ
Propaga	tion Delay (max.)++	235 ps	210 ps	135 ps/190 ps
РСВ	Plated Hole Size	0.70 mm	0.70 mm	0.60 mm
Press-Fit	Daughter Card	Yes	Yes	Yes
Termination	Backplane	Yes	Yes	Yes

* Shield Pins Implemented Through Signal Pins

- + Not Defined in (IEC) Specification
- ++ Published Industry Test Results
- +++ Integrated in Header and add-on module for female

2.0 mm ERmet Hard Metric Connector System Application Notes



The ERmet 2mm H.M. connector system now consists of two basic signal module configurations. The original 5+2 design and the newer 8+2 design for higher pin count requirements. Both connector systems consist of a daughter card mounted, right angle female connector featuring the high performance, low skew patented ERmet leaf contact design and a versatile vertical male header mounted on the backplane. Additionally, this arrangement is particularly effective for midplane application and makes sequential mating easy.

ERNI can provide 15 standard pins in any row or position required for your design. This allows for three levels of sequential mating in both the front and rear of the backplane, as well as two shorter terminal lengths for applications which don't require rear feed through pins. For midplane and rear I/O applications, ERNI offers complementary 2.0 mm shrouds, vertical female connectors and latch accessories which are used in con-junction with the long terminal lengths (R1, R2 and R3). Specific contact loading configurations have already been defined for standard applications and special needs like live insertion on CompactPCI. However, to specify a custom loading configuration, use the ERNI customer request forms located in the back of the catalog. A form is provided for the 5+2 configuration and another form is available for the 8+2 configuration.

Features

- 3 step lengths in 1.5 mm increments ensure dependable sequential mating.
- Both front and rear mating areas meet the same IEC performance level.
- 15 pin lengths defined by IEC 61076-4-101.
- Long terminal contacts (R1, R2 and R3) require the use of rear shrouds.



Backplane Connector

Daughter Card Connector

2.0 mm ERmet Hard Metric Connector System Product Features

AB Alignment Option (features)

The IEC 61076-4-101 connector standard only provides for connector Types A, B, C, D, E, F, L, M and N. Many customers require a connector with the density of a Type B (25 columns) and with the pre-alignment guide pins of the Type A. D. L and M connectors. This became a particular issue within the CompactPCI computer architecture for rear plug in applications where only B connectors were being used. The problem is that if a plug in card only utilizes Type B connectors, the cards will not have adequate vertical alignment even in the most carefully constructed subrack. The result can be pin stubbing and ultimately serious damage to both the backplane connectors and the female connectors on the daughter cards. For our customers who need a solution to this situation or who need the additional 15 pins that a Type B connector provides, but who also need the vertical alignment that the pre-alignment guide pins afford, ERNI has developed the Type AB connector. This new AB design, which does not allow for coding keys, is now required for rP3 and rP5 shrouds by the current draft PICMG Core specification (draft 3.0).



Coding Keys

CompactPCI® supports both conventional 5.0 V logic and 3.3 V logic. To prevent damage to the system resulting from incorrect insertion of cards with differing logic, coding keys are snapped into the multifunctional area of the male and female connector. This is done with the use of a plastic tool after the

connector has been pressed in. The unique, bright color of the coding pairs allows for quick and easy visual identification and differentiation. For the 5.0 V logic, CompactPCI® use brilliant blue coding keys, 3.3 V logic use cadmium yellow and Telecom applications use strawberry red. The IEC 61076-4-101 standard defines a unique configuration and color for 70 different coding keys.

The ERNI design has special integral supports that exceed the IEC requirements.



2.0 mm ERmet Hard Metric Connector System Product Features



Male Contact Range

The ERmet 2mm H.M. Connector System has one of the longest wipe areas of any connector system as defined in IEC 61076-4-101. This ensures reliable contact mating even under adverse mating conditions. Features include:

- 2.5 mm minimum wipe length for all three contact lengths.
- The required wipe length for rear applications may be achieved by selecting the proper rear shroud height for the backplane thickness.
- IEC standardization completely defines tip blade and contact geometry, thus ensuring intermatability.



Relation To IEEE 1101.10 And IEC 297.3

The ERmet 2mm H.M. Connector System has been chosen by the PICMG for the CompactPCI bus architecture and the VITA Standards Organization for the VME64 Extensions, PO/JO connector. Both of these applications require this connector to be used in 0.8" wide slots in accordance with IEC 297.3 and IEEE 1101.10 mechanical chassis requirements. This chassis system defines the daughter card location within the card slot, relative to the interboard separation planes. When the ERmet Connector System is used within such a chassis system, the dimensions shown in the drawing will be observed. ERNI has designed the lower shield to

Male Contact Selection Options

The ERmet 2mm H.M. Connector System offers 15 standard contact lengths that utilize the proven pressfit assembly technique. Within the 15 contact lengths are 3 mating levels, achievable on both the plug-in and rear I/O side. Note you always keep 1.5 mm spacing between levels, for enhanced sequential mating.

On the plug-in side, the 3 contact levels are: 8.2 mm, 9.7 mm and 11.2 mm. On the rear *I*/O side there are 5 pressfit terminal length options: P1, P2, R1, R2, and R3. The P1 and P2 terminal lengths are for standard backplane applications with terminal lengths of 3.7 mm and 4.5 mm respectively. The R1, R2 and R3 terminal lengths are for rear *I*/O applications with lengths of 13.0 mm, 14.5 mm and 16.0 mm respectively. The optimum terminal length is determined by the printed circuit board thickness, rear shroud height and the desired mating level.

For contact plating information, refer to the Mechanical Specifications. To specify custom loading configurations, use the ERNI Customer Request Form. avoid any interference with the interboard separation plane. This ensures that the daughter card and shield assembly will not snag or interfere with high components in the adjacent slot during installation or removal.





2.0 mm ERmet Hard Metric Connector System



The ERmet 2mm H.M. connector line utilizes the proven pressfit assembly method. This design was chosen because it is an efficient assembly method that offers a number of benefits over soldering including higher reliability, easier inspection and repairability, and easier installation. In addition, the pressfit method avoids exposing the high layer count printed circuit boards (PCBs) to the additional thermal stress of soldering.

Design Requirements For Printed Circuit Boards

Plated Through-hole For Pressfitting Signal Contacts, Power Contacts And Shielding Contacts

All ERmet 5+2 row and 8+2 row signal contacts are pressfit. In addition, the bladed ERmet power connectors are also pressfit and share the same board plated hole requirements as the male and female signal connectors. The ERmet 2mm H.M. Connectors have been used successfully with reflowed tin-lead, plated tin-lead, immersion tin, organic coatings over bare copper and immersion gold hole plating regimes. The hole recommendations and press in force information shown in this catalog are for reflowed tin-lead and plated tinlead. Additional test data for other hole plating regimes are available through customer service.

Plated Through-hole For Pressfitting High-current Contacts (Special Contacts For Modules L, M And N)

The ERmet Type L, M and N connectors have provisions for high frequency coaxial and high current circular contacts. These contacts have a variety of different plated through-hole requirements. For these, please consult ERNI Customer Service.

However, ERNI does offer both 20 Amp and 40 Amp high power pressfit contacts for the L, M, and N connectors, which have the specific plated through-hole requirements shown to the right.



3 traces between pads

T

Maximum Circuit Density

The dense ERmet 2.0 mm grid spacing utilizes a 0.6 mm plated through via. This via diameter, together with an appropriate plated annular ring, leaves a 1.0 mm imimum space between adjacent annular rings for trace routing. This space allows for either two equally spaced conductor traces of 0.2 mm (.008") wide or three equally spaced conductors 0.14 mm (.006") wide, as shown in the drawing to the right. This layout can be used to bus two or three rows of the connector on each layer respectively. Many designers bus each row on a separate layer with a ground or power layer between for best signal integrity.





2.0 mm ERmet Hard Metric Connector System



Alignment Tolerance

The pre-alignment pins ensure accurate alignment, eliminating the possibility of pin stubbing on the female insulator. When modules with the pre-alignment feature are used, the following mating tolerances can be accommodated:

- Up to 2.0 mm of vertical or horizontal misalignment.
- Up to 2 degrees of vertical or horizontal angular inclination.

Midplane and Stacking Applications

Midplane - inline

The most common configuration for mid plane application: is to have a rear shroud over long terminals. The rear shroud is oriented so that the shroud's "a" row lines up with the "a" row of the male connector on the front side of the backplane. In this configuration, the card guides in the front of the backplane line up exactly with those behind the backplane.

Midplane - out of line

This less common configuration has the "a" row of the shroud aligned with the "e" row of the male connector on the front side of the backplane. In this configuration, the card that plugs into the rear side has the same appearance as the board that plugs into the front side of the backplane. This usually requires a more complex card guide arrangement than the inline configuration.

Parallel stacking

This configuration has a vertical female connector on a mezzanine board mating into a rear shroud on the rear of a backplane. This is a very popular method often used to connect two or more slots with a PCB which is parallel to the backplane. This is a common solution for switched fabrics such as Raceway or for modular dedicated bused lines such as a special processor to board memory bus. The ERmet vertical female is also available with long tails to allow two levels of stacking. The ERNI vertical females has shields so all male pins can be contacted. Vertical females with long terminals are available for additional levels of stacking.

Allowed Misalignment

Allowed Angular Inclination









2.0 mm ERmet Hard Metric Connector System Shroud Selection Information



After the backplane has been designed and its final overall thickness is determined, it is often challenging to select the proper shroud. Furthermore, a design may specify sequential mating in the rear which requires several different terminal lengths.

To accommodate a wide range of backplane thicknesses and up to 3 rear mating levels, ERNI offers shrouds with 4 different base thicknesses. Which base thickness you select depends on both the backplane thickness and the number of terminal lengths you need. Note that due to the extremely long contact wipe length (2.5 mm), several different combinations of pin terminal lengths and shroud base thicknesses may be used to achieve the same functional result. The chart at right shows for each of the four shroud base thicknesses, which connector terminal lengths (R1, R2 or R3) may be used for any specific backplane thickness (1.5 mm to 8.0 mm).

Examples:

- For a backplane thickness of 2.5 mm and the need to accommodate all three rear mating lengths (terminals R1, R2 and R3), a shroud base thickness of 6.1 mm must be used.
- With a 5.0 mm thick backplane and a shroud with a 5.3 mm base thickness, only the R1 and R2 terminal length pins may be used. The R3 terminal would be too short to ensure the proper wipe length for reliable mating.
- With a 3.0 mm thick backplane and a shroud with a 5.3 mm base thickness any R1, R2 and R3 terminal length pin may be used.











Ordering Information Shroud Selection Chart

Description	Base Thickness (mm)	Length (A) (mm)	Shroud Part #	Tool for Press* Assembly
T 405.01	3.9	49.9	114436	914070
Type A25 Shroud	4.5	49.9	054795	914070
CompactPCI	5.3	49.9	054794	914070
rP1 and rP4 positions	6.1	49.9	054793	914070
	3.9	37.9	NA	914079
Tura A10 Chanud	4.5	37.9	923109	914079
Type A19 Shroud	5.3	37.9	923108	914079
	6.1	37.9	923107	914079
	3.9	49.9	114482	914690
	4.5	49.9	114483	914690
Type AB25 Shroud	5.3	49.9	114484	914690
	6.1	49.9	114485	914690
	3.9	43.9	114425	914691
Type AB22 Shroud	4.5	43.9	114426	914691
CompactPCI [®]	5.3	43.9	114427	914691
rP2 and rP5 positions	6.1	43.9	114428	914691
	3.9	37.9	114487	914692
Type AB19 Shroud	4.5	37.9	114488	914692
CompactPCI [®]	5.3	37.9	114489	914692
rP3 position	6.1	37.9	114490	914692
	3.9	49.9	114437	914069
Type B25 Shroud	4.5	49.9	054797	914069
	5.3	49.9	054798	914069
	6.1	49.9	054799	914069
	3.9	43.9	114619	914083
Type B22 Shroud	4.5	43.9	064692	914083
	5.3	43.9	064693	914083
	6.1	43.9	064694	914083
	3.9	37.9	114618	914084
T	4.5	37.9	064622	914084
Type B19 Shroud	5.3	37.9	064623	914084
	6.1	37.9	064624	914084
	3.9	24.55	114438	914068
	4.5	24.55	064172	914068
Type C11 Shroud	5.3	24.55	064171	914068
	6.1	24.55	064170	914068
Tool for Manual Assembly	-	-	064202	-
Latch Arm	-	-	064219	-
Replacement Locking Wafers	_	_	_	054521

Dimensions shown are for reference purposes only. All dimensions are in millimeters (mm) unless otherwise noted. *The tools are the same tools used to pressfit the equivalent male connectors. The tools listed will only accommodate pins extending no more than 8.7 mm from the inside floor of the shroud. Calculated as follows: [8.7 mm > 16.0 mm – (BP thickness (mm) + shroud base thickness (mm))]

2.0 mm ERmet Hard Metric Connector System



Connector System Modularity And Configuration

Modularity

The ERmet 2mm H.M. connector has been designed in accordance with IEC 61076-4-101, with eleven basic connector types: A, B, AB, C, D, E, DE, F, L, M and N. These connectors can be assembled end to end in a great variety of combinations but certain guidelines must be followed: You cannot mix 5+2 and 8+2 versions except under some very special situations.

Type B connectors cannot be used alone. A Type B connector must be used in conjunction with a module containing a pre-alignment guide such as connector types A, AB, C, L, M or N.

Type E connectors cannot be used alone. A Type E connector must be used in conjunction with a module containing a pre-alignment guide such as connector types D, DE or F. Type C, N and F connectors must be assembled at the lower end of a connector stack.

Each end of the connector is designed so that the modules "nest" together. This provides additional support for the side walls and makes for a very neat appearance.

When shrouds are used on the rear side of a backplane, care must be taken to align the shrouds properly. The correct orientation will depend upon the configuration of the rear plug in cards. For most applications following the "inline" configuration, the rear shrouds will have the convex end detail facing down which is opposite to the arrangement depicted in the detailed drawing on this page. The "a" row of the shroud will match the "a" row of the male connector.

Male Connector Stacking And Connector End Details

The ERmet 2mm H.M. Connector System is a modular system designed to be assembled on a 2.0 mm grid. The connectors are designed with a unique locking feature which ties the sidewalls together. This ensures that any stress is shared across an entire connector stack when assembled as a group. The connector's convex top end and concave bottom end fit together, maintaining the dense 2.0 mm grid. The bottom of the VME64 Extensions JO connector is the one exception. It is molded flat across as it is not designed for modular stacking and would otherwise interfere with the DIN 41612 connectors. It can be used in a modular stacking configuration but will not benefit from interlocking sidewalls.

Connector Bottom Nests With ____ Connector Tops.





Combined Stack Height in mm

2.0 mm ERmet Hard Metric Connector System Mechanical Specifications and Performance



General Connector Specifications

Connector Pitch		2.0 mm
		-55°C to +125°C
)1		≥ 50 mating cycles
4-101		≥ 250 mating cycles
4-101		≥ 500 mating cycles
	0.55 mm hole	36 Newtons (N) typical
	0.65 mm hole	25 Newtons (N) typical
		0.8 Newtons (N)/contact
+ 0.0	Contact	10 ⁴ MΩ min @ 100DC
l Ja	Shield	10 ⁴ MΩ min @ 100 DC
	Contact	n x 0.75 Newtons (N) maximum (n=number of contacts)
per IEC 512-7, Test 13a		n x 1 Newtons (N) maximum (n=number of contacts)
2-7,	Contact	0.15 Newtons (N) minimum
Test 16e		0.15 Newtons (N) minimum
Contact insertion force (per pin) IEC 352-5 paragraph 3.2.2.2		36.3 Newtons (N) average (male or female)
Flammability		UL 94 V-0
Hole requirements for daughter card and backplane		0.6 mm ± 0.05 mm after plating
Contact Resistance per IEC 512-2. Test 2a		20 mΩ maximum
	4-101 4-101 t 3a 2-7, 352-5 p	4-101 4-101 0.55 mm hole 0.65 mm hole t 3a Contact Ground pin to shield 2-7, Contact Ground pin to shield 352-5 paragraph 3.2.2.2 and backplane

Male Contact and Housings

Housing Material (8+2) and (5+2)		PBT 30% glass filled
CTI value per IEC 112		CTI 250 - 399
Contact Material		Phosphor bronze
Contact Plating/Performance Level P1, P2	Contact area	Gold plated
	Compliant area	Sn
	Rear terminal	Sn
	Contact area	Gold plated
Contact Plating/Performance Level		
R1, R2, R3	Rear terminal	Gold plated

Right Angle Female Contact and Housings		Type 1	Type 2
Housing Material (8+2)		LCP 30% glass filled	n/a
Housing Material (5+2)		LCP 30% glass filled	PBT 30% glass filled
Wafer (8+2) and (5+2)		PBT 30% glass filled	PBT 30% glass filled
CTI value per IEC 112		CTI 175	CTI 250 - 399
Contact Material		Phosphor bronze	
Contact Plating/Performance Level	Contact area	Gold pla	ated
Contact Flating/Fenomance Level	Compliant area	Sn	
Contact Normal Force		0.8 Newtons (N)/contact

Vertical Females

Wafer (8+2) and (5+2) Material		LCP 30% glass filled
CTI value per IEC 112		CTI 175
Contact Material		Phosphor bronze
	Contact area	Gold plated
Contact Plating/Performance Level	Compliant area	Sn
	Extended Terminals	Gold plated

2.0 mm ERmet Hard Metric Connector System Mechanical Specifications and Performance



Ground Return Shields for Right Angle Female Connectors

	•	
Base material		Copper alloy
Contact plating per	Contact fingers	Gold plated
IEC 512 Test 9A		
Performance level 2 per IEC 61076-4-101		≥ 250 mating cycles
Hole requirements for daughter card		0.6 ±0.05 mm after plating

Ground Return Shields for Vertical Female Connectors

Base material		Copper alloy
Contact plating per Contact fingers		Gold plated
IEC 512 Test 9A		
Terminal plating per	Extended terminals	Gold plated
IEC 512 Test 9A		
Performance level 2 per IEC 61076-4-101		≥ 250 mating cycles
Hole requirements for daughter card		0.6 ±0.05 mm after plating

Shrouds

Temperature range	-55°C to +125°C			
Housing material	PBT 30% glass filled			
Flammability	UL 94 V-O			

Coding Keys

Temperature range	-55°C to +125°C			
Housing material	Polycarbonate 30% glass filled			
Flammability	UL 94 HB			
Mechanical strength	≥ 300 Newtons (N)			
Weight	0.3 Grams (G) average			

Latch Arm

Temperature range	-65°C to +125°C			
Housing material	LCP 2000 30% glass filled			
Flammability	UL 94 V-O			

Cable Connectors

Female contact housing	Material	30% glass filled LCP
I emale contact housing	Flammability	UL94VO
Over molding	Material	30% glass filled LCP
Overmolding	Flammability	UL94VO
Locking combs	Material	30% glass filled LCP
Total weight of plastic material		1.0 grams
Shield	Material	phosphor bronze
Ghield	Plating	Gold plated
Contact	Material	phosphor bronze
	Plating	Gold plated

2.0 mm ERmet Hard Metric Connector System 7-Row Electrical Performance



The ERmet line of 2mm H.M. connectors set a new, higher standard for 2.0 mm electrical performance. A collection of test reports is available which completely characterizes the connectors' mechanical and high frequency performance. In addition, ERNI can provide a SPICE (Simulator Program for Integrated Circuit Emulation) model to customers, utilizing advanced circuit simulation methods. In the Time Domain Reflectometry (TDR) plot shown below, note the connector exhibits an almost ideal, 50 ohm characteristic impedance. This smooth, discontinuity-free, impedance progression is due, in part, to both the uniform contact spacing and constant cross section, as well as the uniform dielectric constant. This is a result of the encapsulated terminals of the right angle female connector.



TDR plot showing the impedance progression from a 2mm H.M. connector. Signal ground pattern as shown.

High Frequency Characteristics

The chart below summarizes the electrical characteristics of a test board with similar pin assignments. Note the remarkably low propagation delay (132 ps) and low total skew (a-e = 46 ps). These factors, combined with the low capacitance and low inductance of the connector, make the ERmet 2mm H.M. Connector the best choice for demanding, high speed applications.

parameter		CO	nnec	tor p	oin rov	N		
	a		b		C	d		e
capacitance C (f = 100 MHz)	2.5 pF	2.8 pF		2.9 pF		3.1 pF		3.2 pF
inductance L (f = 100 MHz)	6.8 nH	7.6	nH	8.3 nH		8.7	' nH	10.5 nH
characteristic impedance	52 Ω	52	Ω	53	3Ω	2 53 Ω		57 Ω
propagation delay*	111 ps	ps 119 ps		12	6 ps	14	1 ps	157 ps
	(86) ps	(94) ps		(101) ps		(116) ps		(132) ps
signal skew	8 ps		os 9 ps 14 p		ps 15 ps		ps	
			ma	ximı	um 46	ps		
crosstalk	-	57	dB	-	۲			
(f = 100 MHz)				-	-	53	dB	\rightarrow
Reflection factor	0.02	٥	02	6	.03	0	03	0.065
(50 Ω and f = 100 MHz)	0.02	0.	02	0.05		0.00		0.000
VSWR (f = 100 MHz)	1.04	1.	04	1	.06	1.	06	1.14
Reflection loss [dB] (f = 100 MHz)	34	3	4	3	0.5	3(0.5	24

* The higher value of the propagation delay is measured from solder-side to solder-side (rear side). The value in parenthesis is calculated from component-side to component-side (front side).



The measurement values are based on this pin configuration.

2.0 mm ERmet Hard Metric Connector System 7-Row Electrical Performance



The specifications for contact current rating, dielectric withstanding voltages and creepage and clearance distances are all dependent on the contact loading configuration. For example, if contacts are loaded in a "chessboard pattern," each contact can carry more current than if every contact is loaded.

Current Rating For Various Contact Mounting Configurations



Dielectric Withstanding Voltage								
Contact/Contact:								
Row Designation Fully Loaded Every Other Position Chessboard Pattern								
Row a + c + e	Within the row	750Veff	1500Veff	-				
Row b + d	Between the rows	1500Veff	1500Veff	-				
Row a + b + c	Within the row	750V _{eff}	1500Veff	1500Veff				
Row $a + b + c + d$ Row $a + b + c + d + e$	Between the rows	750V _{eff}	750Veff	1200Veff				
Contact to grounding rows or shielding frame: 750Ver								

Creepage Distances And Clearances Dependent On Contact Layout								
Contact/Contact:								
Fully Loaded Every Other Position Chessboard Pattern								
Row Designation	Backplane Male Connector	Daughter Card Female Connector	Backplane Male Connector	Daughter Card Female Connector	Backplane Male Connector	Daughter Card Female Connector		
Row a + c + e	Within the row	0.8	0.6	2.5	2.5	-	-	
Row b + d	Between the rows	2.5	2.5	2.5	2.5	-	-	
Row a + b + c	Within the row	0.8	0.6	2.5	2.5	2.5	2.5	
Row $a + b + c + d$ Row $a + b + c + d + e$	Between the rows	0.8	0.6	0.8	0.6	1.5	1.2	

2.0 mm ERmet Hard Metric Connector System 10-Row Electrical Performance



The ERmet line of 2mm H.M. connectors set a new, higher standard for 2.0 mm electrical performance. A collection of test reports is available which completely characterizes the connectors' mechanical and high frequency performance. In addition, ERNI can provide a SPICE (Simulator Program for Integrated Circuit Emulation) model to customers, utilizing advanced circuit simulation methods. In the Time Domain Reflectometry (TDR) plot shown below, note the connector exhibits an almost ideal, 50 ohm characteristic impedance. This smooth, discontinuity-free, impedance progression is due, in part, to both the uniform contact spacing and constant cross section, as well as the uniform dielectric constant. This is a result of the encapsulated terminals of the right angle female connector.

High Frequency Characteristics

The chart below summarizes the electrical characteristics of a test board with similar pin assignments.

These factors, combined with the low capacitance and

low inductance of the connector, make the ERmet 2mm H.M. Connector the best choice for demanding, high speed applications.

parameter				connection	pin row			
	а	b	С	d	e	f	g	h
capacitance C [pF] f = 300 MHz	1.9	2.3	2.5	2.7	2.8	2.8	3.7	4.0
inductance L [nH] f = 100 MHz	5.4	6.3	6.9	7.5	8.1	8.9	11.9	15.5
characteristic impedance $z = \sqrt{L/C}$	53	52	53	53	54	56	57	62
propagation delay [ps]	110	120	130	140	150	160	175	190
signal skew [ps]	10		10		10		15	
orginar okow (poj		1	0	1	0	1	5	
crosstalk [dB] f=300 MHz	34	.9	32	7	30.2		-28.61	
Reflection factor 50 Ohm f = 300 MHz	0.03	0.02	0.02	0.03	0.04	0.06	0.06	0.11
VSWR f = 300 MHz	1.06	1.04	1.04	1.06	1.08	1.13	1.13	1.25
Reflection loss [dB] f = 300 MHz	30.5	34.0	34.0	30.5	28.0	24.4	24.4	19.2



The measurement values are based on this pin configuration.

2.0 mm ERmet Hard Metric Connector System 10-Row Electrical Performance



The specifications for contact current rating, dielectric withstanding voltages and creepage and clearance distances are all dependent on the contact loading configuration. For example, if contacts are loaded in a "chess-board pattern," each contact can carry more current than if every contact is loaded.

Current Rating For Various Contact Mounting Configurations



Dielectric Withstanding Voltage							
Contact/Contact:		-	-				
Row Designation		Fully Loaded	Every Other Position	Chessboard Pattern			
Row a+c+e+g	Within the row	750Veff	1500Veff	-			
Row b+d+f+h	Between the rows	1500Veff	1500Veff	-			
Row a+b+c							
Row a+b+c+d	Within the row	750Veff	1500Veff	1500Veff			
Row a+b+c+d+e							
Row a+b+c+d+e+f							
Row a+b+c+d+e+f+g	Between the rows	750Veff	750Veff	1200Veff			
Row a+b+c+d+e+f+g+h							
Contact to grounding rows of	pr shielding frame: 750Veff			1			

Contact/Contact:								
Fully Loaded Every Other Position Chessboard Pattern								
Row Designation		Backplane Male Connector	Daughter Card Female Connector	Backplane Male Connector	Daughter Card Female Connector	Backplane Male Connector	Daughter Carc Female Connector	
Row a+c+e+g	Within the row	0.8	0.6	2.5	2.5	-	-	
Row b+d+f+h	Between the rows	2.5	2.5	2.5	2.5	-	-	
Row a+b+c Row a+b+c+d Row a+b+c+d+e	Within the row	0.8	0.6	2.5	2.5	2.5	2.5	
Row a+b+c+d+e+f Row a+b+c+d+e+f+g Row a+b+c+d+e+f+g+h	Between the rows	0.8	0.6	0.8	0.6	1.5	1.2	



Approval Certificates, Performance Levels And Ordering Information

Approval Certificates

UL Approved by the American approvals authority (Underwriters Laboratories Inc.) File number E 84703. ISO 9001 All ERmet connectors are designed and produced in fully approved ERNI ISO 9001 facilities. Bellcore GR 1217 CORE ERmet connectors are available that meet the requirements of Bellcore GR-1217-CORE for large systems in uncontrolled environments. ECTF ERmet connectors are also available to meet the requirements of the Enterprise Computer Telephony Forum's (ECTF) H.110 specification. IEC 917 And IEC 61076-4-101 The ERmet Connector System meets the requirements of IEC 61076-4-101 which was developed in accordance with the requirements of IEC 917 the standard for for Hard Metric mounting systems. IEEE 1301 And IEEE 1101 And IEEE 1101.10 ERmet connectors were developed to meet the demanding board to backplane physical architecture of IEEE 1301 and have been adapted to meet the requirements of IEEE 1101 and IEEE 1101.10.

PICMG ERmet connectors have been adapted to meet the requirements of the CompactPCI specification as defined by the PICMG. Special length connectors with the required loading have been molded and assembled for these applications. Type AB connectors have been developed for rear transition card applications.

Performance Levels

- 207 Conforms to the requirements of IEC 61076-4-101 performance level 2 (≥ 250 mating cycles) in the contact area. For detailed information, see Mechanical Specifications and Performance.
- 201 Conforms to the requirements of IEC 61076-4-101 performance level 2 (≥ 250 mating cycles) in both contact and terminal areas.

For additional performance levels, consult ERNI Customer Service.

Edition 9

Ordering Information

All ERNI ERmet 2mm H.M. Connectors for CompactPCI and VME64 Extensions are assigned a six digit part number. The following pages contain part numbers, along with product descriptions of many popular ERNI 2mm H.M. Connectors, complementary components, application, repair and installation tooling. In addition to the configurations listed in this catalog, others are available. Please consult ERNI customer service for more information.

1

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type A for Daughter Cards



110 signal contacts50 mm with multifunction block (for positioning and coding)



Dimensional drawings and board hole pattern

The ERmet type A female connector provides 110 contacts in a 5 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration. This connector is used in the J1 and J4 positions of the CompactPCI® daughter card. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated upper ground return shields and without integrated upper ground return shields. Lower ground return shields are available separately.

The ERmet type A female connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either a type B, C, L, M or N ERmet connector. The type A female is also available with a locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type A for Daughter Cards



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type A Without Shield, Without Peg	CompactPCI™ J1, J4	110	044146
Type A Without Shield, With Peg		110	044766
Type A With Shield, Without Peg	CompactPCI''' J1, J4	110	064176
Type A With Split Shield, Partially Loaded	J4 Telecom	90	104512
Type A With Split Shield, Partially Loaded	rJ4 Telecom	90	104697
Lower Shield For Type A And AB	CompactPCI™ J1, J4		



110 signal contacts 50 mm with multifunction block (for positioning and coding)



Dimensional drawings and board hole pattern

The ERmet type A vertical male connector provides 110 signal contacts and 44 ground shield contacts in 5+2 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration. This connector is used in the P1 and P4 positions of a CompactPCI® backplane. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type A male connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either type B, C, L, M or N ERmet connectors.

\$

8



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type A With Peg		110	043136
Type A With Peg		110	043190
Type A With Peg And Extended Terminals For Shrouding		110	043477
Type A Without Peg		110	044148
Type A With Peg		110	044149

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type A With Peg		154	053007
Type A With Peg And Extended Terminals For Shrouding		154	054034
Type A With Peg And Extended Terminals For Shrouding		154	054185
Type A With Peg		154	054528
Type A With Peg 25 24 23 22 12 00 19 10 17 16 15 TCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCC	CompactPCI" P1 Per PICMG 2.0 R2.1	154	064097

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





Ordering Information

Configuration	Used For	No. of Pins	Part Number
	CompactPCI'' P4	154	064688
Type A With Peg And Extended Terminals For Shrouding	CompactPCI™ P4	154	103968
Type A With Peg And Extended Terminals For Shrouding	CompactPCI™ P4	154	103975
Type A Without Peg	P4 Telecom	100	923160
Type A With Peg	CompactPCI™ P1	154	923190

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



T



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type A With Peg And Extended Terminals For Shrouding	CompactPCI ^{**}	154	923197
Type A Without Peg And With Extended Terminals 23 24 23 22 12 01 91 81 71 61 5 PPPPPPPPPPPPPPPPPPPPPPPPPPPPPPPPPPPP	P4 Telecom	100	923212
Type A Without Peg And With Extended Terminals	<i>CompactPCI''</i> P1	154	923342
Type A With Extended Terminals For Shrouding	CompactPCI'' P4	132	923347

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Vertical Female Connectors Type A



110 signal contacts

50 mm with multifunction block (for positioning and coding)



The ERmet type A vertical female connector provides 110 contacts in a 5 row x 22 position fully loaded configuration. Versions with optional "z" and "f" row shields are available as well as extended terminals for use in stacking applications with rear shrouds.

Two spacer heights are also available: 3.1 mm and 9.6 mm to provide additional component clearance.

The ERmet type A female connector has a multifunctional cavity that incorporates pre-alignment pins and optional coding keys. The pressfit terminals provide a convenient and reliable gas tight connection.

This connector may be used alone or in conjunction with Type B and C vertical female connectors.

Dimensional drawings and board hole pattern

فمفمفمفهم *** ERNI 104702 id für Le 10 x 2 = 10 40 (20 An 05 0.6 ±0.05 rchkontaktier loch 0.7 0 Ř

2.0 mm ERmet Hard Metric Connector System Vertical Female Connectors Type A

* Termination + Board To Board Distance



ERN

Vote: All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Vertical Female Connectors Type A



Ordering Information

Configuration	Used For No. Pin	
Type A Without Shield, Without Peg Version 1 *		
		10 104702
Type A Without Shield, Without Peg Version 2 *		10 114007
Type A Without Shield, Without Peg Version 3 *		
Daagaagaagaaga <u>Daagaagaagaagaagaagaagaagaagaagaagaagaag</u>		10 114009
Type A Without Shield, Without Peg Version 4 *		10 114011
Type A Without Shield, Without Peg Version 5 *		
		10 114013

1


Configuration		Used For	No. of Pins	Part Number
Type A With Shield, Without Peg Version 6 *				
			110	104112
Type A With Shield, Without Peg Version 7 *				
fondondonda Time Time Time Time Time Time Time Time Time Time Time Time Time			110	114008
Type A With Shield, Without Peg Version 8 *				
			110	114010
Type A With Shield, Without Peg Version 9 *	4 6			
ionationaliania Herritarianiania Herritarianianiani Herritarianianiani			110	114012
Type A With Shield, Without Peg Version 10 *				
			110	114014

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type B for Daughter Cards



125 signal contacts50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type B female connector provides 125 contacts in a 5 row x 25 position fully loaded configuration. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated ground return shields and without integrated upper ground return shields. Lower ground return shields are available separately.

The ERmet type B female connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but is intended to be used in conjunction with either a type A, C, L, M or N ERmet connector.



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type B for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type B Without Shield, Without Peg		125	044767
Type B With Upper Shield, Without Peg		125	064179
Type B Without Shield, Without Peg	J2, J5	11 0	914797
Type B With Upper Shield	J2, J5	110	064785
Type B Without Shield, Without Peg	J3	m 95	914794
Type B With Upper Shield	J3	95	064784

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type B for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Lower Shield For Type B			044452
Lower Shield For Type B	CompactPCI™ J2, J5		064783
Lower Shield For Type B	<i>CompactPCI™</i> J3		064782



125 signal contacts 50 mm without multifunction block



The ERmet CompactPCI type B vertical male connector provides 125 signal contacts and 50 ground shield contacts in a 5+2 row x 25, fully loaded configuration. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type B vertical male connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but it is intended to be used in conjunction with either a type A, C, L, M or N ERmet connector.

Dimensional drawings and board hole pattern





2



Ordering Information

Configuration	Used For No. of Pins	Part Number
Type B 25 24 23 22 21 20 19 19 17 16 15 14 19 12 11 10 9 8 7 6 5 4 3 2 1 BEER FOR BEACHINE BEER BEREFORE BEER FEELENDER BEER BEER BEREFORE BEER FEELENDER BEER BEER BEER BEER BEER FEELENDER BEER	125	043137
Type B 25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4 4	125	053088
Type B 25 24 23 22 120 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 5 4 3 2 1 TCICICICICICICICICICICICICICICICICICICI	175	053008
Type B 25 24 23 22 12 01 91 81 71 61 55 44 131 21 11 09 8 7.6 5.5 4.3 2.1 TCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCCC	175	054293
Type B	175	054392

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



T



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type B With Extended Terminals	ŊŊ			
			125	043476
Type B With Extended Terminals				
25 24 23 22 12 18 17 16 5 14 32 11 10 </td <td></td> <td></td> <td>175</td> <td>054186</td>			175	054186
Type B With Extended Terminals	~ ~			
25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 TTTTTTTTTTTTTTTTTTTTTTTTTTTTTTTTTTTT			175	064522
Туре В		<i>CompactPCI™</i>		
$\begin{array}{c} 22222019191716154413221110987654321\\ \hline \\ \hline$		P2, P5	154	914796
Туре В		ECTF		
22 22 28 19 49 79 48 57 48 57 49 19 49 4 7 4 5 4 3 2 1 CICICICICICICICICICICICICICICICICICICI		P5 Telecom	154	923162

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type B With Extended Terminals	<i>CompactPCI™</i> P2, P5	154	064690
Type B With Extended Terminals For Shrouding	CompactPCI™ P2	154	923131
Type B (AB Compatible) With Extended Terminals For Shrouding	P5 Telecom	132	923339
Type B (AB Compatible) With Extended Terminals For Shrouding	CompactPCI™ P2	154	923340
Type B (AB Compatible) With Extended Terminals For Shrouding	CompactPCI™ P2	132	923345

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



T



Ordering Information

Configuration	Use	d For	No. of Pins	Part Number
Туре В	Com	npactPCI™		
$\begin{array}{c c c c c c c c c c c c c c c c c c c $		P3	133	103670
Type B With Extended Terminals	Com	<i>ipactPCI™</i>		
		P3	133	914793
Type B With Extended Terminals For Shrouding	Con	npactPCI"		
		P3	133	923132
Type B (AB Compatible) With Extended Terminals For Shrou	ding Com	<i>ipactPCI™</i>		
Image: Signal		P3	133	923341
Type B (AB Compatible) With Extended Terminals For Shrou	ding Com	<i>ipactPCI™</i>		
		P3	114	923346

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type B Increase Addata Addata		112	064766

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





125 signal contacts50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type B vertical female connector provides 125 contacts in a 5 row x 25 position fully loaded configuration. Versions with optional "z" and "f" row shields are available as well as extended terminals for use in stacking applications with rear shrouds.

Two spacer heights are also available: 3.1 mm and 9.6 mm to provide additional component clearance.

The ERmet type B vertical female connector has an uninterrupted contact field and no multifunction cavity. This connector is not designed to be used alone, but is intended to be used with either a Type A or C female ERmet connector.



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.



Version 5

* Termination + Board To Board Distance



m

Board To Board Distance

Version	Board To Board Distance *
	Diotarioo
1	15-16.5
2	15-16.5
3	18.4-20.0
4	18.4-20.0
5	25-26.5



other board to board distances for

remaining levels on request

(Please contact our Customer Service)



(Please contact our Customer Service)



Configuration	Used For No. Pins	
Type B Without Shield, Without Peg Version 1 *		
00000000000000000000000000000000000000		25 104703
Type B Without Shield, Without Peg Version 2 *		
		25 114015
Type B Without Shield, Without Peg Version 3 *		
		25 114017
Type B Without Shield, Without Peg Version 4 *		
Daadaaadaaadaaadaaadaadaadaadaa 2		25 114019
Type B Without Shield, Without Peg Version 5 *		
000000000000000000000000000000000000		25 114021



Configuration	Used For No. of Pins	Part Number
Type B With Shield, Without Peg Version 6 *		
0000000000000000000000000000000000000	125 T	104113
Type B With Shield, Without Peg Version 7 *		
	125	114016
Type B With Shield, Without Peg Version 8 *		
1000000000000000000000000000000000000	125	114018
Type B With Shield, Without Peg Version 9 *	_	
		114020
Type B With Shield, Without Peg Version 10 *		
	125	114022



Configuration	Used For	No. of Pins	Part Number
Type B With Shield, Without Peg Version 6 *			
00000000000000000000000000000000000000		110	114114
Type B With F-row Shield, Without Peg Version 6 *	<i>CompactPCI</i> "		
NODOODOOODOOOOOOOOOOOOOOOOOOOOOOOOOOOO	P2 / P4	110	114134
Type B Without Shield, Without Peg Version 1 *			
ФФФФФФФФФФФФФФФ		95	114111
Type B With Shield, Without Peg Version 6 *			
8888888888888888888888 1997-1997-1997		95	114112
Type B With F-row Shield, Without Peg Version 6 *	<i>CompactPCI™</i>		
	P2 / P4	95	114133

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type AB for Daughter Cards



125 signal contacts50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type AB female connector provides 125 contacts in a 5 row x 25 fully loaded configuration, 110 contacts in a 5 row x 22 position fully loaded configuration or 95 pins in a 5 row x 19 position configuration. The 19 position connector is used in the rJ3 location and the 22 position connector is used in the rJ2 and rJ5 locations of the CompactPCI® rear transition card. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated ground return shields and without integrated upper ground return shields. Lower ground return shields are available separately. The ERmet type AB female connector has an uninterrupted

The EHmet type AB temale connector has an uninterrupted pin field with no multifunction cavity but does have integral pre-alignment guides. This connector can be used alone or in conjunction with either a type A, B or C ERmet connector. This connector will provide the necessary alignment for rear transition applications.



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type AB for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type AB Without Shield, Without Peg		125	114154
Type AB With Shield, Without Peg		125	114538
Type AB Without Shield, Without Peg	CompactPCI''' rJ2, rJ5	110	104933
Type AB With Shield, Without Peg	CompactPCI''' rJ2, rJ5	110	114809
Type AB Without Shield, Without Peg	CompactPCI'' rJ3	95	114529
Type AB With Shield, Without Peg	CompactPCI''' rJ3	95	114810

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type AB for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Lower Shield For Type A And AB			044446
Lower Shield For Type A And Type AB			114231
Lower Shield For Type A And Type AB			923110



125 signal contacts50 mm without multifunction block



The ERmet type AB vertical male connector provides 125 signal contacts and 44 ground shield contacts in 5+2 row x 25 position, fully loaded configuration. This connector is used in the P1 and P4 positions of a CompactPCI® backplane. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation. The ERmet type AB male connector has an uninterrupted pin field with pre-alignment guides, but does not accept coding keys. This connector can be used alone, or it can be used with either type A, C, L, M or N ERmet connectors.

Dimensional drawings and board hole pattern







Ordering Information

Configuration	Used For No. of Pins	Part Number
Type AB Without Shield, Without Peg	125	114236
Type AB With Shield, Without Peg	169	114153
Type AB With Shield, Without Peg	169	114539

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type C for Daughter Cards



55 signal contacts 25 mm extension module



Dimensional drawings and board hole pattern

The ERmet type C female connector provides 55 contacts in a 5 row x 11 position fully loaded configuration. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated upper ground return shields and without integrated upper ground return shields. Lower ground return shields are available separately.

The ERmet type C female connector has pre-alignment guides. This connector can be used alone or in conjunction with either a type A, B, L, M or N ERmet connector, however, it can only be installed at the lower end of a connector row.

The type C female is also available with a locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).





l www.erni.com



| Edition 9

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type C for Daughter Cards



Ordering Information

Configuration	Used For No. of Pins	Part Number
Type C Without Shield, Without Peg		
	55	044145
Type C With Shield, Without Peg		
	55	064198
- Type C Without Shield, With Peg		
	55	044768
Type C With Shield, With Peg		
	55	064556
Lower Shield For Type C		
		044458



55 signal contacts 25 mm extension module



Dimensional drawings and board hole pattern

The ERmet type C vertical male connector provides 55 signal contacts and 22 ground shield contacts in 5+2 row x 11 position, fully loaded configuration. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type C vertical male connector incorporates pre-alignment guides but has no multi function cavity. This connector is designed to be used alone or in conjunction with either type B, L, M or N ERmet connectors, however it can only be installed at the lower end of a connector row.





X2⊨ (12)

•••



Ordering Information

Configuration	Used For No. of Pins	Part Number
Type C Without Shield, With Peg	55	043138
Type C Without Shield, With Peg	55	044147
Type C With Shield, Without Peg	77	054546
Type C With Shield, With Peg	77	053009

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



I



Ordering Information

Configuration	Used For	No. of Pins	Part Number
- Type C Without Shield, With Peg And With Extended Terminals			
		55	054129
Type C With Shield, With Peg And With Extended Terminals			
		77	064550
Type C With Shield, With Peg And With Extended Terminals			
11 10 9 8 7 6 5 4 3 2 1 PMMMMMMMMMMM K K K K K K K K 6 K K K K K K K K 6 MMMMMMMMMM C K K K K K K K 6 MMMMMMMMMM r K K K K K K K 6 MMMMMMMMMMM r		77	064572
Type C With Shield, With Peg And With Extended Terminals			
		77	103926

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





55 signal contacts 25 mm extension module



The ERmet type C vertical female connector provides 55 contacts in a 5 row x 11 position fully loaded configuration. Versions with optional "z" and "f" row shields are available as well as extended terminals for use in stacking applications with rear shrouds.

Two spacer heights are also available: 3.1 mm and 9.6 mm to provide necessary component clearance.

The ERmet type C vertical female has no multifunctional cavity but is equipped with pre-alignment guides. The pressfit terminals provide a convenient and reliable gas tight connection.

This connector may be used alone or in conjunction with either a type A or B vertical female connector, however it can only be installed at the lower end of a connector row.

Dimensional drawings and board hole pattern





* Termination + Board To Board Distance



(Please contact our Customer Service)

I





Configuration	Used For	No. of Pins	Part Number
Type C Without Shield, Without Peg Version 1 *			
00000000000000000000000000000000000000		55	104704
Type C Without Shield, Without Peg Version 2 *			111000
		55	114023
Type C Without Shield, Without Peg Version 3 *			
		55	114025
Type C Without Shield, Without Peg Version 4 *			
		55	114027
Type C Without Shield, Without Peg Version 5 *			
		55	114029



Configuration	Used For	No. of Pins	Part Number
Type C With Shield, Without Peg Version 6 *		55	104114
Type C With Shield, Without Peg Version 7 *		55	114024
Type C With Shield, Without Peg Version 8 *		55	114026
Type C With Shield, Without Peg Version 9 *		55	114028
Type C With Shield, Without Peg Version 10 *		55	114030

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type D for Daughter Cards



176 signal contacts 50 mm with multifunction block (for positioning and coding)



Dimensional drawings and board hole pattern

The ERmet type D female connector provides 176 signal contacts and 44 ground shield contacts in a 8 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with integrated upper ground return shields and without integrated upper ground return shields.

The ERmet type D female connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used by itself or in conjunction with either a type E or F ERmet 2mm H.M. connector.

The type D female is also available with locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type D for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type D Without Shield, With Peg			
		176	104086
Type D With Shield, Without Peg			
		176	104935
Type D With Upper Shield, With Peg			
		176	104415
Lower Shield For Type D And DE			
			103847



176 signal contacts 50 mm with multifunction block (for positioning and coding)



The ERmet type D vertical male connector provides up to 176 signal contacts and 44 ground shield contacts in 8+2 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type D male connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either type E, DE or F ERmet 2mm H.M. connectors.

Dimensional drawings and board hole pattern





9×2⊨ (18)



Ordering Information

Configuration	Used For No. of Pins	Part Number
Type D With Peg	220	104152
Type D With Peg	220	104517
Type D With Peg and Extended Terminals	220	933008

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.





176 signal contacts

50 mm with multifunction block (for positioning and coding)



The ERmet type D vertical female connector provides 176 signal contacts in a 8 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration. The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with and

without integrated ground return shields. The ERmet type D vertical female connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used by itself or in conjunction with either a type E or F ERmet 2mm H.M. connector.

Dimensional drawings and board hole pattern

18.25 Datum ld.-Nr. Anforderungsstufe 17.4 date class 面面如 xxxx ERNI 124093 2 °ни°ни°ни°ни°ни "HIA" HIA" HIA" HIA 50 0.6 3.7 ±0.2 max 1 max 3 1 max 3.65 10 x 2 = 20 10 x 2 = 20 8 Lochbild für Leiterpl Board hole pattern (Bestückungsseite) (Component mounting side 8 10 x2= 10 x 2= (20) (20 ⊕0.05 2 0.6 ±0.05 durchkontaktiert Bohrloch 0.7 ±0.02 plated thru drill hole 0.7 000 2 N ******** * * * * * * * * * ٠ ------



Configuration		Used For	No. of Pins	Part Number
Type D Without Shield, Without Peg			176	124093
Type D With Shield, Without Peg	A			
			176	124094

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type E for Daughter Cards



200 signal contacts 50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type E female connector provides 200 signal contacts and 50 ground shield contacts in a 8 row x 25 position fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with integrated upper ground return shields and without integrated upper ground return shields.

The ERmet type E female connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but is intended to be used in conjunction with either a type D, DE or F ERmet 2mm H.M. connector.



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.
2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type E for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type E Without Shield, Without Peg		200	104087
Type E With Upper Shield, Without Peg		200	104416
Lower Shield For Type E			103849

2.0 mm ERmet Hard Metric Connector System Verticale Male Conneactors Type E for Backplanes



200 signal contacts50 mm without multifunction block



The ERmet type E vertical male connector provides 200 signal contacts and 50 ground shield contacts in an 8+2 row x 25 position fully loaded configuration. This connector is also available in an 8+2 row x 22 positions and 8+2 row x 19 positions. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type E vertical male connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but is intended to be used in conjunction with either type D, DE or F ERmet 2mm H.M. connectors.

Dimensional drawings and board hole pattern





21.4

2.0 mm ERmet Hard Metric Connector System Verticale Male Conneactors Type E for Backplanes



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type E Without Peg		200	104518
Type E Without Peg		250	104153
Type E Without Peg, With Extended Terminals		250	933007

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Verticale Female Connectors Type E



200 signal contacts50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type E vertical female connector provides 200 signal contacts in a 8 row x 25 position fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with and without integrated ground return shields.

The ERmet type E vertical female connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but is intended to be used in conjunction with either a type D or F ERmet 2mm H.M. connector.



2.0 mm ERmet Hard Metric Connector System Verticale Female Connectors Type E



Configuration	Used For	No. of Pins	Part Number
Type E Without Shield, Without Peg		200	124095
Type E With Shield, Without Peg		200	124096

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type DE for Daughter Cards



200 signal contacts50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type DE female connector provides 200 signal contacts and 25 ground shield contacts in an 8 row x 25 position fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with integrated upper ground return shields and without integrated upper ground return shields.

The ERmet type DE female connector has an uninterrupted pin field and integral pre-alignment guide. This connector can be used alone or in conjunction with type D, E or F ERmet 2mm H.M. connector.



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type DE for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type DE Without Shield, Without Peg		200	114281
Type DE With Shield, Without Peg		200	124118
Lower Shield For Type D And DE			103847

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type DE for Backplanes



200 signal contacts 50 mm without multifunction block



Dimensional drawings and board hole pattern

The ERmet type DE vertical male connector provides 200 signal contacts and 44 ground shield contacts in a 8+2 row x 25 position fully loaded configuration. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type DE vertical male connector has an uninterrupted pin field with pre-alignment guides but does not accept coding keys. This connector can be used alone, or it can be used with either type D or F ERmet connectors.





~

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type DE for Backplanes

Ordering Information

Configuration	Used For	No. of Pins	Part Number
Туре DE Without Peg		244	114279
Туре DE Without Peg		200	124335

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type F for Daughter Cards



88 signal contacts 25 mm extension module



Dimensional drawings and board hole pattern

The ERmet type F female connector provides 88 signal contacts and 22 ground shield contacts in an 8 row x 11 position fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with and without integrated ground return shields.

The ERmet type F female connector has integral pre-alignment guides but no multifunction cavity.

The type F female is also available with optional locating and strain relief pegs that help secure the connector to the printed circuit board (PCB). This connector is designed to be used alone or with either type D, DE or E ERmet connectors, however it can only be installed at the lower end of a connector field.

.....



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type F for Daughter Cards



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Type F Without Shield, With Peg		88	104088
Type F With Shield, With Peg		88	104417
Lower Shield For Type F			103851

I

2.0 mm ERme Hard Metric Connector System Verticale Male Connectors Type F for Backplanes



88 signal contacts 25 mm extension module



Dimensional drawings and board hole pattern

The ERmet type F vertical male connector provides 88 signal contacts and 22 ground shield contacts in a 8+2 row x 11, fully loaded configuration. With 15 different standard pin lengths to choose from, this is one of the most versatile connectors available. The connector is designed for gas tight pressfit installation.

The ERmet type F vertical male connector incorporates pre-alignment guides but has no multifunction cavity. This connector is designed to be used alone. The type F connector can also be used in conjunction with either a type D, e, or DE ERmet connector, however, it can only be installed at the lower end of a connector row.





2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type F for Backplanes



Ordering Information

Configuration	Used For No. of Pins	Part Number
Type F With Peg	88	104519
Type F With Peg	110	104154
Type F With Peg And Extended Terminals	110	933006

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Verticale Female Connectors Type F



88 signal contacts 25 mm extension module



Dimensional drawings and board hole pattern

The ERmet type F vertical female connector provides 88 signal contacts and in an 8 row x 11 position fully loaded configuration.

The connector provides for a gas tight, pressfit installation and is designed for two different configurations: with and without integrated ground return shields.

The ERmet type F vertical female connector has integral pre-alignment guides but no multifunction cavity. This connector is designed to be used alone or with either type D or E ERmet connectors, however it can only be installed at the lower end of a connector field.





4 7 x 2 =

nent mounting side

€0.05

2 10

2.0 mm ERmet Hard Metric Connector System Verticale Female Connectors Type F



Configuration	Used For	No. of Pins	Part Number
Type F Without Shield, Without Peg		88	124097
Type F With Shield, Without Peg		88	124098

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type L for Daughter Cards



6 special contacts

50 mm with multifunction block (for positioning and coding)



Dimensional drawings and board hole pattern

100

The ERmet type L female is an insulator that provides up to 6 contact positions for special power or coax contacts in a fully loaded configuration.

The ERmet type L female connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either a type B, C, M or N ERmet connector.

The type L female is also available with a locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).









2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type L for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type L with 6 cavities for special contacts			
			044579

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type L for Backplanes



6 special contacts 50 mm with multifunction block



The ERmet type L male connector is an insulation body that could be loaded with up to 6 special power or coax contacts in a fully loaded configuration. The ERmet type L male connector has a multifunction cavity that incorporates prealignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either a type B, C, M, or N ERmet connector. The type L male is available with a locating peg that helps secure the connector to the printed circuit board (PCB).

Dimensional drawings and board hole pattern





| Catalog E 074484 | 04/10

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type L for Backplanes



Ordering Information



Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type M for Daughter Cards



3 special and 55 signal contacts 50 mm with multifunction block



The ERmet type M female connector provides 55 contacts in a 5 row x 11 position (3 positions used by multifunction cavity), and also 3 contact positions for special power or coax contacts in a fully loaded configuration. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with and without integrated upper ground return shields. Lower ground return shields are also available separately. The ERmet type M female connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector can be used alone or in conjunction with either a type A, B, C, L, or N Ermet connector.

The type M female is also available with a center pair of locating and strain relief pegs that help secure the connector to the printed circuit board (PCB).

Dimensional drawings and board hole pattern







| Edition 9

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type M for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type M With 3 Cavities For Special Contacts		55-3	053792
Type M With 3 Cavities For Special Contacts With Upper Shield With Peg		55-3	103804
Lower Shield For Type M			054354

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type M for Backplanes



3 special and 55 signal contacts 50 mm with multifunction block



Dimensional drawings and board hole pattern

The ERmet male connector type M provides a maximum of 77 contacts in 7 rows by 11 positions. The two outer rows, z and f are for the shielding contacts of the male connector, along with 3 contact positions for special power or coax contacts. This type contains a multifunction cavity for coding and pre-alignment in the center position. This connector is designed to be used alone or in conjunction with either a type B, C, L, or N ERmet connector.

The type M male is available with a locating peg that helps secure the connector to the printed circuit board (PCB).



2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type M for Backplanes





Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



ΞſΝ

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type N for Daughter Cards



3 cavities for special contacts 25 mm extension module



The ERmet female connector type N is a connector housing with 3 contact positions for special power or coax contacts. The type N female is available with a locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).

Dimensional drawings and board hole pattern





plated the

2.0 mm ERmet Hard Metric Connector System Right Angle Female Connectors Type N for Daughter Cards



Configuration	Used For	No. of Pins	Part Number
Type N With 3 Cavities For Special Contacts			
			044581

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type N for Backplanes



3 cavities for special contacts 25 mm extension module



Dimensional drawings and board hole pattern

6.25

The ERmet type N male connector is a connector housing with 3 contact positions for special coax or high power contacts.

The type N male is available with a locating and strain relief peg that helps secure the connector to the printed circuit board (PCB).

3.45





Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Verticale Male Connectors Type N for Backplanes



Ordering Information



Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.







The ERmet shroud type A is possible for a maximum of 175 contacts in 7 rows by 25 positions. The two outer rows, z and f are for the shielding contacts of the female connector. This type contains a multifunction block for coding and pre-alignment which uses 3 positions.

For CompactPCI applications the shroud type A is used on the position rP1 and rP4.

Dimensional drawings





н	Ident-Nr. / Part No.
14.35	114436
14.95	054795
15.75	054794
16.55	054793

Sammelzeichnung Combination Drawing



Configuration		Used For	No. of Pins	Part Number
Type A Shroud 25 Positions	Height 14.35	CompactPCI™ rP1, rP4		114436
Type A Shroud 25 Positions	Height 14.95	CompactPCI''' rP1, rP4		054795
Type A Shroud 25 Positions	Height 15.75	CompactPCI™ rP1, rP4		054794
Type A Shroud 25 Positions	Height 16.55	<i>CompactPCI™</i> rP1, rP4		054793



Configuration		Used For	No. of Pins	Part Number
Type A Shroud 19 Positions	Height 14.35			124312
Type A Shroud 19 Positions	Height 14.95			923109
Type A Shroud 19 Positions	Height 15.75			923108
Type A Shroud 19 Positions	Height 16.55			923107





The ERmet[™] shroud type B is possible for a maximum of 175 contacts in 7 rows by 25 positions. The two outer rows, z and f are for the shielding contacts of the female connector. For this type , without multifuntion block for coding and pre-alignment, we recommend use only in combination with types A or C.

-

Dimensional drawings





н	Ident-Nr. / Part No.
14.35	114437
14.95	054797
15.75	054798
16.55	054799

Sammelzeichnung Combination Drawing



Configuration		Used For	No. of Pins	Part Number
Type B Shroud 25 Positions	Height 14.35			114437
Type B Shroud 25 Positions	Height 14.95			054797
Type B Shroud 25 Positions	Height 15.75			054798
Type B Shroud 25 Positions	Height 16.55			054799



Configuration		Used For	No. of Pins	Part Number
Type B Shroud 22 Positions	Height 14.35			
				114619
Type B Shroud 22 Positions	Height 14.95			
				064692
Type B Shroud 22 Positions	Height 15.75			
				064693
Type B Shroud 22 Positions	Height 16.55			
				064694



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type B Shroud 19 Positions	Height 14.35			114618
Type B Shroud 19 Positions	Height 14.95			064622
Type B Shroud 19 Positions	Height 15.75			064623
Type B Shroud 19 Positions	Height 16.55			064624





The ERmet shroud type C is possible for a maximum of 77 contacts in 7 rows by 11 positions with the length of 25 mm. The two outer rows, z and f are for the shielding contacts of the female connector.

Dimensional drawings





Н	Ident-Nr. / Part No.
14.35	114438
14.95	064172
15.75	064171
16.55	064170

Sammelzeichnung Combination Drawing



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type C Shroud 11 Positions	Height 14.35			114438
Type C Shroud 11 Positions	Height 14.95			064172
Type C Shroud 11 Positions	Height 15.75			064171
Type C Shroud 11 Positions	Height 16.55			064170




The ERmet shroud type AB is possible for a maximum of 169 contacts in 7 rows by 25 positions. The two outer rows, z and f are for the shielding contacts of the female connector. This type has pre-alignment flanges but no multifunction block for coding.

The male shroud type AB, is also available in a smaller version for planned CompactPCI applications, it is used at the locations rP2 and rP5 with 154, respectively,110 contacts at 22 positions and on location rP3 with 133 respectively, 95 contacts at 19 positions.

Dimensional drawings





Н	Ident-Nr. / Part No.
14.35	114425
14.95	114426
15.75	114427
16.55	114428

Sammelzeichnung Combination Drawing

Note: All dimensions in mm.



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type AB Shroud 25 Positions	Height 14.35			
				114482
Type AB Shroud 25 Positions	Height 14.95			
				114483
Type AB Shroud 25 Positions	Height 15.75			
				114484
Type AB Shroud 25 Positions	Height 16.55			
				114485



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type AB Shroud 22 Positions	Height 14.35	<i>CompactPCI™</i>		
		rP2, rP5		114425
Type AB Shroud 22 Positions	Height 14.95	<i>CompactPCI™</i>		
		rP2, rP5		114426
Type AB Shroud 22 Positions	Height 15.75	<i>CompactPCI™</i>		
		rP2, rP5		114427
Type AB Shroud 22 Positions	Height 16.55	<i>CompactPCI™</i>		
		rP2, rP5		114428



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type AB Shroud 19 Positions	Height 14.35	<i>CompactPCI™</i>		
		rP3		114487
Type AB Shroud 19 Positions	Height 14.95	<i>CompactPCI™</i>		
		rP3		114488
Type AB Shroud 19 Positions	Height 15.75	<i>CompactPCI™</i>		
		rP3		114489
Type AB Shroud 19 Positions	Height 16.55	<i>CompactPCI™</i>		
		rP3		114490





The ERmet shroud type D is possible for a maximum of 220 contacts in 10 rows by 25 positions with the length of 50 mm. The two outer rows, z and y are for the shielding contacts of the female connector. This type contains a multi-function block for coding and pre-alignment which uses 3 positions

Dimensional drawings

	00



н	Ident-Nr. / Part No.
14.35	114467
14.95	114468
15.75	114469
16.55	114470



I



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type D Shroud 25 Positions	Height 14.35			114467
Type D Shroud 25 Positions	Height 14.95			114468
Type D Shroud 25 Positions	Height 15.75			114469
Type D Shroud 25 Positions	Height 16.55			114470





The ERmet shroud type E is possible for a maximum of 220 contacts in 10 rows by 25 positions with the length of 50 mm. The two outer rows, z and y are for the shielding contacts of the female connector. For this type; without multifunction block for coding and pre-alignment, we recommend use only in combination with types D or F.

Dimensional drawings

2000	000	0 0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
) [a]	0 0 0 8 8	0 0	0	0	0	0	0	0		0	0				0	٥	۵	0



Ē												24	*2 =	45												-
1	l e	μ	÷	÷	لما	L.	l.	J.	e	l e	l e	l ÷	÷	l ⊕	÷	l e l	e l	e	لمل	L.	l a	Ų.	÷.	μŧ	μŧ	*
	e	ł	•	•	F	÷	P	•	e					÷	÷	e	•		5		R.		÷		.	I I
	e	١I	•	÷	÷	÷	•					۰	۰	÷	æ				e			۰	÷	Ð	⊕	
	e	١I	Ф	Ф	æ	æ	•	۰	•		¢	Ф	Ф	÷	æ	•		•	e	¢	æ	ф	¢	•	e	
٠	4	١I	ф	ф	Ф	æ	•	۰	۰	¢	¢	Ф	ф			•	۰	•	œ	¢	Ф	ф	ф	•	•	
٠	-	١I	Ф	ф	æ		•	۰	۰	¢	ф	Ф	ф	\$	¢	•	۰	•	æ	¢	ф	ф		•	 •	9 × 2
	•	ł	÷	ф	æ		•	۰	۰	æ	æ	æ	÷	æ	æ		۰		æ	æ	Ф	æ		•	•	
	∉	١I	#	⊕	æ		•	۰	æ										æ		÷				•	
æ	∉	١I	⊕	•	₽		e	•	e	Ð				÷	÷		•	e	e	#	∎			•	e	-
l e	'n∉	h	•	•	ዘቅገ	۲w	Te 1	h⇒	e	n⊕	n⊕	₽	•	n⊕	÷	n e i	n e	n e i	빤	۱wi	Ψ	h⊕	•	n⊕	h⊨	<u> </u>

н	Ident-Nr. / Part No.
14.35	114472
14.95	114473
15.75	114474
16.55	114475

Note: All dimensions in mm.



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type E Shroud 25 Positions	Height 14.35			
				114472
Type E Shroud 25 Positions	Height 14.95			
				114473
Type E Shroud 25 Positions	Height 15.75			
				114474
Type E Shroud 25 Positions	Height 16.55			
				114475





The ERmet shroud type F is possible for a maximum of 110 contacts in 10 rows by 11 positions with the length of 25 mm. The two outer rows, z and y are for the shielding contacts of the female connector.

Dimensional drawings

ſ	0		0	0				
				 4,55		ž	•	
		• • • • • • • • • • • • • • • • • • •			 	4 8 8 8 8 8 8 8 8 4 <u>8</u>		2

н	Ident-Nr. / Part No.	
14.35	114477	
14.95	114478	
15.75	114479	
16.55	114480	



Ordering Information

Configuration		Used For	No. of Pins	Part Number
Type F Shroud 11 Positions	Height 14.35			114477
Type F Shroud 11 Positions	Height 14.95			114478
Type F Shroud 11 Positions	Height 15.75			114479
Type F Shroud 11 Positions	Height 16.55			114480

2.0 mm ERmet Hard Metric Connector System Right Angle Female Monoblock Modules



220 signal contacts 94 mm with multifunction block



The ERmet[™] female monoblock connector integrates the type A and the type B modules into one single piece. The monoblock provides a maximum of 220 contacts in 5 rows by 44 positions. The monoblock has integrated pre-centering and as an option integrated coding, acc. to PICMG Spec. for 3.3V or 5.0V, which requires 3 positions. For applications requiring the use of shielding, the female connector is supplied with a with an upper shield. Lower shield may be ordered separately. The monoblock has been designed especially for CompactPCI applications for the positions P1/P2 and for the positions P4/P5. The monoblock has a length of 94mm (3U) and can also be used for other applications in 19° rack systems.

Dimensional drawings



Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

5×2= (10

2.0 mm ERmet Hard Metric Connector System Right Angle Female Monoblock Modules



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Monoblock With Shield, Without Peg	<i>CompactPCI</i> ™		
	J4/J5	308	104732
Monoblock With Shield, Without Peg, With Cadmium Yellow Coding Key	<i>CompactPCI™</i>		
	J4/J5	308	104733
Monoblock With Shield, Without Peg, With Brillant Blue Coding Key	CompactPCI"		
	J4/J5	308	104734

2.0 mm ERmet Hard Metric Connector System Vertical Male Monoblock Modules



220 signal contacts 94 mm with multifunction block



The ERmet[™] vertical male monoblock connector integrates the type A and the type B in one single piece. The monoblock provides a maximum of 308 contacts in 7 rows by 44 positions. The two outer rows, z and f are for the shielding contacts of the female connector. The monoblock has integrated pre-centering and as option integrated coding acc. to PICMG Spec. for 3.3V or 5.0V, which requires 3 positions. The monoblock has been designed especially for CompactPCI applications. Available are versions with standard pin length for the positions P1 and P2 and versions with extended terminals for rear I/O for the positions P4 and P5. The monoblock has a length of 94mm (3U) and can also be used for other applications in 19" rack systems.

Dimensional drawings





Note: The numbering on the connectors themselves is in accordance with the IEC 61076-4-101 standard. All dimensions in mm.

2.0 mm ERmet Hard Metric Connector System Vertical Male Monoblock Modules



Ordering Information

Configuration	Used For	No. of Pins	Part Number
Monoblock With Peg, With Shield	<i>CompactPCI™</i>		
	P1/P2	308	104735
Monoblock With Shield, Without Peg, With Cadmium Yellow Coding Key	<i>CompactPCI</i> ™		
	P1/P2	308	104736
Monoblock With Shield, Without Peg, With Brillant Blue Coding Key	<i>CompactPCI</i> ™		
	P1/P2	308	104737
Monoblock With Peg, With Shield And With Extended Terminals	<i>CompactPCI™</i>		
	P1 Per PICMG 2.0 R 2.1 P2	308	104765
Monoblock With Peg, With Shield And With Extended Terminals	<i>CompactPCI™</i>		
	P1 Per PICMG 2.0 R 2.1 P2	308	104766

Contact versions

ERNI can accommodate any pattern of male connector contact loading.

For shield rows z and f (7 row connectors) or z and y (10 row connectors), level 3 contacts should be specified. For rear I/O and shrouds, choose contacts with the R1, R2 or R3 terminal length. Each contact has a unique letter designation. Use this letter designation when filling in the contact loading requirements on the ERNI Customer Request Form.



T

2.0 mm ERmet Hard Metric Connector System Dust Covers For Type A, B, AB, D, E and DE





The dust and protection cover for the male connectors for the ERmet[™] 2.0 mm connector system acc. to IEC 61076-4-101 protect the mating area at the frontside of the backplane and what is more important the transfer area on the rearside of the backplane against damage of the contacts. They are also a protection for transportation and against dust. The dust and protection cover is available in two versions for type A, B, AB and for type D, E, DE with or without grip.

Dimensional Drawings



I

2.0 mm ERmet Hard Metric Connector System Dust Covers For Type A, B, AB, D, E and DE



Ordering Information

Configuration	Used For	No. of Pins	Part Number
A, B, AB Dust Cover Without Handle For Vacuum Pickup			104070
D, E, DE Dust Cover Without Handle For Vacuum Pickup			104939
A, B, AB Dust Cover With Handle For Hand Placement			114039
D, E, DE Dust Cover With Handle For Hand Placement			114040

2.0 mm ERmet Hard Metric Connector System Coding Keys



Ordering Information

Coding keys for male connectors and shrouds

Coding Key	Code No.	Colour	Part Number
8 6 5	3568	Pastel Orange RAL 2003 Fincke 00233197	043342
<u>43</u> <u>87</u>	3478	Steel Blue RAL 5011 Fincke 00251197	043343
	· 3467	Slate Grey RAL 7015 Fincke 00235197	043344
43	· 3456	Cadmium Yellow RAL 1021 Fincke 00252197	043345
875	- 2578	Reseda Green RAL 6011 Fincke 00237197	043346
	• 1567	Brilliant Blue RAL 5007 Fincke 00245197	043347
	• 1356	Blue/Lilac RAL 4005 Fincke 00246197	043348
<u>4</u> <u>8 7 6</u>	4678	Ocher Yellow RAL 1024 Fincke 00313197	043349
4 2 1	• 1248	Strawberry Red RAL 3018 Fincke 00312197	043350
	- 1236	Nut Brown RAL 8011 Fincke 00272197	043351

Coding keys for female connectors

Coding Key	Code No.	Colour	Part Number
	1247	Pastel Orange RAL 2003 Fincke 00233197	043332
	1256	Steel Blue RAL 5011 Fincke 00251197	043333
	1258	Slate Grey RAL 7015 Fincke 00235197	043334
	1278	Cadmium Yellow RAL 1021 Fincke 00252197	043335
	1346	Reseda Green RAL 6011 Fincke 00237197	043336
	2348	Brilliant Blue RAL 5007 Fincke 00245197	043337
	2478	Blue/Lilac RAL 4005 Fincke 00246197	043338
	1235	Ocher Yellow RAL 1024 Fincke 00313197	043339
<u>3</u> <u>5 6 7</u>	3567	Strawberry Red RAL 3018 Fincke 00312197	043340
	4578	Nut Brown RAL 8011 Fincke 00272197	043341

Mounting Device For Coding-Keys

2.0 mm ERmet Hard Metric Connector System Guide Pin for ERmet 10 Row Type D





The optional applicable guide pin for the 10 row ERmet type D connector made of stainless steel is suited for the secure pre-centering when mating. The guide pin will be screwed with the connector and the pcb after the male connector has been pressed-in.

Ordering Information

Description	Part Number
Guide Pin	104790
Toothed Lock Washer	104788
Hexagon Nut #2-56 UNC-2A	104789
Kit (Including Guide Pin, Toothed Lock Washer and Hexagon Nut)	104791

2.0 mm ERmet Hard Metric Connector System Special Contacts for Type L, M and N

ERN



Ordering Information For Coax Contacts

Characteristic Impedance	Contact Version	Cable Type	Part Number
50 Ohm	Male; Crimp-Version	RG 178 B/U; RG 196 A/U	013686
50 Ohm	Female; Crimp-Version	RG 178 B/U; RG 196 A/U	013687
50 Ohm	Male; PCB-Solder-Version; Right Angle		053299
50 Ohm	Female; Crimp-Version	RG 316 Protected	053395
50 Ohm	Male; Crimp-Version	RG 316 Protected	053400
50 Ohm	Female; Crimp-Version	RG 174 /U; RG 188 A/U; RG 316 /U	054238
50 Ohm	Male; Press-Fit-Version; Right Angle		104875
50 Ohm	Female; Crimp-Version	RG 174 /U; RG 188 A/U; RG 316 /U	594207
50 Ohm	Male; Crimp-Version	RG 174 /U; RG 188 A/U; RG 316 /U	594213
50 Ohm	Female; PCB-Solder-Version		914382
75 Ohm	Male; PCB-Solder-Version; Right Angle		053306
75 Ohm	Male; Crimp-Version	RG 179 B/U; RG 187 A/U	053408
75 Ohm	Female; Crimp-Version	RG 179 B/U; RG 187 A/U	053410

Ordering Information for High Power Contacts

Max. Current	Contact Version	Comments	Part Number	
10 A	Female; Crimp-Version	Female; Crimp-Version		
20 A	Female; Crimp-Version		594180	
30 A	Female; Crimp-Version		053452	
40 A	Female; Crimp-Version		594182	
40 A	Female; Press-Fit-Version R3		044965	
10 A	Female; Solder-Version		594172	
20 A	Female; Solder-Version		594174	
40 A	Female; Solder-Version		594176	
40 A	Female; Solder-Version; Right	Angle	053298	
10 A	Male; Crimp-Version		594227	
20 A	Male; Crimp-Version	First Made Last Break; Only Usable With Part No. 044965	053430	
20 A	Male; Crimp-Version		594229	
30 A	Male; Crimp-Version		033319	
40 A	Male; Crimp-Version		594231	
10 A	Male; Press-Fit-Version R1	First Made Last Break	103855	
40 A	Male; Press-Fit-Version R1	First Made Last Break; Only Usable With Part No. 044965	044846	
40 A	Male; Press-Fit-Version R1	i de la companya de l	044847	
10 A	Male; Solder- Version		594221	
20 A	Male; Solder- Version		594223	
40 A	Male; Solder- Version		594225	
10 A	Male; Solder-Version	First Made Last Break; Only Usable With Part No. 044965	053444	

T

<u>ERNI</u>

Modular press-fit tools for male and female connectors





Modular press-fit tool male connector modules 5+2

ERmet connectors can be end to end mounted in modular layout. To be able to press-fit the selected connector layout for your application in a rationalized way, we have designed the necessary press-fit tools to be modular too. This is true of the tools both for male connectors and for female connectors. The tool bases, also termed anvils, are fixed in a tool holder. Each connector module requires an appropriately sized tool module. Modular press-fit tool for female connector modules 5+2

The standard tool holders are designed for two 50 mm modules (modules A, B, L and M), press-fitting a total module length of 100 mm. Due to the modular tool configuration, press-fitting can be carried out in any order. Using filler elements, it is also possible to press-fit just individual modules.

For details on how to order press-fit tools, please contact the factory.

Т

Press-In-Tools For The Female Connectors

Ordering Information

Design	Module	Upper Tools	Lower Tools	Comments
Female	А	220006	220020	Standard
Female	B/AB	220006	220021	Standard
Female	С	220007	220022	Standard
Female	L	220008	220023	Standard; High Power Contact, Press-fit
Female	L	220008	220402	Standard; Coax-Contact, Press-fit
Female	М	220009	220024	Standard; High Power Contact, Press-fit
Female	М	220009	220323	Standard; Coax-Contact, Press-fit
Female	М	220009	220415	Standard; Coax-Contact, Solder
Female	Ν	220010	220025	Standard; High Power Contact, Press-fit
Female	N	220010	220287	Standard; Coax-Contact, Press-fit
Female	A	220093	220020	Upper Shield
Female	B/AB	220093	220021	Upper Shield
Female	С	220096	220022	Upper Shield
Female	М	220322	220024	Upper Shield ; High Power Contact, Press-fit
Female	М	220322	220323	Upper Shield ; Coax- Contact, Press-fit
Female	A	220436	220437	Lower Shield
Female	A/AB	220436	220437	Lower Shield
Female	С	220453	220454	Lower Shield
Female	D	220253	220250	Standard
Female	E/DE	220253	220251	Standard
Female	F	220254	220252	Standard
Female	D	220256	220250	Upper Shield
Female	E/DE	220256	220251	Upper Shield
Female	F	220257	220252	Upper Shield
Female	D	220455	220458	Lower Shield
Female	E/DE	220455	220456	Lower Shield
Female	F	220457	220458	Lower Shield
Female	B19/AB19	220175	220176	VME/64
Female	B19/AB19	220179	220176	VME/64 Upper Shield
Female	B19/AB19	220449	220450	VME/64 Lower Shield
Female	B22/AB22	220183	220184	PCI
Female	B22/AB22	220187	220184	PCI Upper Shield
Female	B22/AB22	220451	220452	PCI Lower Shields
Vertical Fem.	A	220204	220026	Standard
Vertical Fem.	В	220204	220027	Standard
Vertical Fem.	B19	220356	220174	VME/64
Vertical Fem.	B22	220357	220182	PCI
Vertical Fem.	С	220341	220028	Standard
Vertical Fem.	D	220477	220247	Standard
Vertical Fem.	E	220477	220248	Standard
Vertical Fem.	F	220478	220249	Standard



Press-In-Tools For The Male Connectors

Ordering Information

Design	Module	Upper Tools	Lower Tool	Comment
Male	А	220011	220026	Standard
Male	А	220469	220026	Standard; Integrated Coding
Male	В	220012	220027	Standard
Male	AB25	220376	220027	Standard
Male	AB22	220401	220182	Standard
Male	AB19	220400	220174	Standard
Male	С	220013	220028	Standard
Male	L	220014	220029	Standard; High Power Contact, Press-fit
Male	L	220420	220421	Standard; Coax-Contact, Press-fit
Male	М	220015	220030	Standard; High Power Contact, Press-fit
Male	М	220422	220423	Standard; Coax-Contact, Press-fit
Male	Ν	220016	220031	Standard; High Power Contact, Press-fit
Male	Ν	220424	220425	Standard; Coax-Contact, Press-fit
Male	B19	220173	220174	VME/64
Male	B22	220181	220182	PCI
Male	D	220244	220247	Standard
Male	E	220245	220248	Standard
Male	F	220246	220249	Standard
Male	DE	220410	220248	Standard

Toolholder

Ordering Information

Description	Part Number	Length	Comment	
Holder Upper Tool	220001	100mm long	with monting pivot Ø 20	
Holder Upper Tool	220002	100 mm long	with quick change	
Holder Upper Tool	220188	150 mm long	with monting pivot Ø 20	
Holder Upper Tool	220003	150 mm long	with quick change	
Holder Upper Tool	220004	250 mm long	with monting pivot Ø20	
Holder Upper Tool	220005	250 mm long	with quick change	
Holder Lower Tool	220191	100 mm long	for lowerable table	
Holder Lower Tool	220267	150 mm long	for lowerable table	
Holder Lower Tool	220268	250 mm long	for lowerable table	

I

2.0 mm ERmet Hard Metric Connector System 3U CompactPCI[®] Daughter Card Layout



The 3U CompactPCI® backplane and daughter card layouts are provided to clarify the contact numbering and connector nomenclature used within the specification. As is typical of some telecommunication applications, the CompactPCI® specification numbers the signals and connectors from the bottom up. Manufacturers and users should note that the connectors themselves are labeled in accordance to IEC 61076-4-101 and prevailing industry practice from the top down.



Note that the backplane and daughter card are numbered in accordance with the CompactPCI® specification. The numbering on the connectors themselves is different and in accordance with the IEC 61076-4-101 standard. All dimensions are in millimeters (mm) unless otherwise noted.

2.0 mm ERmet

2.0 mm ERmet Hard Metric Connector System 3U CompactPCI[®] Backplane Layout



The 3U CompactPCI® backplane layout is provided to clarify the contact numbering and connector nomenclature used within the specification.

As is typical of some telecommunication applications, the CompactPCI® specification numbers the signals and con-

nectors from the bottom up. Manufacturers and users should note that the connectors themselves are labeled in accordance to IEC 61076-4-101 and prevailing industry practice from the top down.



Note that the backplane is numbered in accordance with the CompactPCI® specification. The numbering on the connectors themselves is different and in accordance with the IEC 61076-4-101 standard. All dimensions are in millimeters (mm) unless otherwise noted.

2.0 mm ERmet Hard Metric Connector System 6U CompactPCI[®] Daughter Card Layout



The 6U CompactPCI® backplane layout is provided to clarify the contact numbering and connector nomenclature used within the specification.

As is typical of some telecommunication applications, the CompactPCI® specification numbers the signals and connectors from the bottom up. Manufacturers and users should note that the connectors themselves are labeled in accordance to IEC 61076-4-101 and prevailing industry

practice from the top down.

In many applications, the J3, J4 and J5 connectors are used for user I/O. The J3 connector matches the VME64 extensions P0 connector exactly and falls symmetrically on the centerline of the daughter card. Designers should note that this connector is not on the same grid as the J1, J2, J4 and J5 connectors.



Note that the daughter card is numbered in accordance with the CompactPCI® specification. The numbering on the connectors themselves is different and in accordance with the IEC 61076-4-101 standard. All dimensions are in millimeters (mm) unless otherwise noted.

2.0 mm ERmet Hard Metric Connector System 6U CompactPCI[®] Backplane Layout



The 6U CompactPCI® backplane layout is provided to clarify the contact numbering and connector nomenclature used within the specification.

As is typical of some telecommunication applications, the CompactPCI® specification numbers the signals and connectors from the bottom up. Manufacturers and users should note that the connectors themselves are labeled in accordance to IEC 61076-4-101 and prevailing industry practice from the top down.

In many applications, the P3, P4 and P5 connectors are designed for user I/O. Therefore connectors with 16 mm rear tails are used with shrouds installed on the rear side. The P3 connector matches the VME64 extensions J0 connector exactly, and falls symmetrically on the centerline of the backplane. Designers should note that this connectors is not on the same grid as the P1, P2, P4 and P5 connectors.



Note that the backplane is numbered in accordance with the CompactPCI® specification. The numbering on the connectors themselves is different and in accordance with the IEC 61076-4-101 standard. All dimensions are in millimeters (mm) unless otherwise noted.

2.0 mm ERmet Hard Metric Connector System 9U 10-Row 2mm Daughter Card Layout



This 9U eurocard compatible daughtercard layout is provided for designers who need over 1400 signal pins in a eurocard format. This is one of the highest I/O densities that is currently available in a eurocard format. This design is to be used with the ERmet 8+2 row connectors.



Note that the numbering scheme conforms with the Type V numbering as defined in VITA30-199x Draft 0.5 dated 9 June 1999 and is from the top down. This numbering scheme is identical to the numbering established for the connector within the IEC 61076-4-101 standard.

| Edition 9

I

2.0 mm ERmet Hard Metric Connector System 9U 10-Row 2mm Backplane Layout



This 9U eurocard compatible backplane layout is provided for designers who need over 1400 signal pins in a eurocard format. This is one of the highest I/O densities that is currently available in a eurocard format. This design is to be used with the ERmet 8+2 row connectors. Note that the backplane connectors have a 5HP or 25.4 mm slot to slot spacing.



Note that the numbering scheme conforms with the Type V numbering as defined in VITA30-199x Draft 0.5 dated 9 June 1999 and is from the top down. This numbering scheme is identical to the numbering established for the connector within the IEC 61076-4-101 standard.

Т

2.0 mm ERmet Hard Metric Connector System IEEE 1301 Daughter Cards for IEC 61076-4-101 2mm HM Connectors



The 2mm HM Connector was originally developed to be used within subrack and backplanes designed in accordance with IEEE 1301 Standard for Metric Equipment Practices for Microcomputers.

This was a standard that was popular with the large telecommunication companies.

Although IEEE 1301 never became as popular as the IEEE

1101 line of Eurocard Packaging, engineers still may occasionally need to layout daughter cards and backplanes to this standard.

Note that this layout is drawn to show both the connector grid for 5+2 row connectors and 8+2 row connectors.



2.0 mm ERmet Hard Metric Connector System IEEE 1301 Backplane Layouts For IEC 61076-4-101 2mm HM Connectors



The 2mm HM Connector was originally developed to be used within subrack and backplanes designed in accordance with IEEE 1301 Standard for Metric Equipment

Practices for Microcomputers. This was a standard that was popular with the large telecommunication companies.

Although IEEE 1301 never became as popular as the IEEE

1101 line of Eurocard Packaging, engineers still may occasionally need to layout daughter cards and backplanes to this standard.

Note that this layout is drawn to show both the connector grid for 8+2 connectors and 5+2 row connectors. Although this standard defines multiple heights, this drawing is for the popular 12 SU height.



2.0 mm ERmet Hard Metric Connector System VME64 Extensions Daughter Card



nectors.

The 6U VME64 Extensions document, IEEE 1101.10 defines the daughter card locations for a 2mm HM P0 connector.

This connector is the same connector defined as the J3 connector defined in the VITA 30 2mm equipment practice and used for CompactPCI daughter cards.

Note that the 2mm HM connector is located symmetrically

in between the upper P1 and lower P2 connectors. This connector is mounted 1.5 mm from the rear board edge but the 160 pin VME64x connector is mounted 2.76 mm from the rear board edge.



Note that the numbering of the P0 connector conforms to IEEE 1101.1 and 1101.10 and is from the top down. This also is the same numbering scheme established by the connector standard IEC 61076-4-101.

2.0 mm ERmet Hard Metric Connector System VME64 Extensions Backplane



The 6U VME64 Extensions backplane layout depicts the nomenclature and numbering conventions used in the IEEE 1101.10 draft standard. The J0 center connector is the same 19 position ERmet 2mm H. M. connector used in CompactPCI®.

CompactPCI®. The design of this connector allows it to mate properly with the J1 and J2 connectors which are in accordance with

DIN 41612. Note that there is a 1.85 mm offset between the "C" row of the J0 connector and the "B" row of the 2.54 mm (.100") J1/J2 connectors. On the daughter card, pin 10 of the P0 connector falls exactly on the board's centerline, and pin "A 1" is placed 1.5 mm from the board's edge.



Note that the numbering of the P0 connector conforms to IEEE 1101.1 and 1101.10 and is from the top down. This also is the same numbering scheme established by the connector standard IEC 61076-4-101.

2.0 mm ERmet Hard Metric Connector System 64 Bit CompactPCI[®] System Slot Pin Assignments



In the case of the 64 bit CompactPCI®, both the P1 and P2 connectors are fully assigned with no pins available for user defined I/O. For such systems, only 6U designs can have rear panel I/O.

3U cards, 6U implementations provide optional P3, P4 and P5 connectors, which all have undefined pins for user I/O. 6U CompactPCI® provides more user defined pins than any other bus structure today.

Although CompactPCI® is designed to be accomplished on

PIN	7(10)	A	В	C	D	E	F	
22	GND	GA4 ⁽⁶⁾	GA3 ⁽⁶⁾	GA2 ⁽⁶⁾	GA1 ⁽⁶⁾	GA0®	GND	
21	GND	CLK6	GND	RSV	BSV	RSV	GND	
20	GND	CLK5	GND	RSV	GND	RSV	GND	
19	GND	GND	GND	RSV®	RSV®	RSV ⁽⁹⁾	GND	P2
18	GND	BRSVP2A18	BRSVP2B18	BRSVP2C18	GND ⁽⁸⁾	BRSVP2E18	GND	
17	GND	BRSVP2A17	GND	PRST#	REQ6#	GNT6#	GND	
16	GND	BRSVP2A16	BRSVP2B16	DEG#	GND	BRSVP2E16	GND	
15	GND	BRSVP2A15	GND	FAL#	REQ5#	GNT5#	GND	
14	GND	AD[35]	AD[34]	AD[33]	GND	AD[32]	GND	С
13	GND	AD[38]	GND	V(I/O) ⁽³⁾	AD[37]	AD[36]	GND	0
12	GND	AD[42]	AD[41]	AD[40]	GND	AD[39]	GND	N
11	GND	AD[45]	GND	V(I/O)(3)	AD[44]	AD[43]	GND	N
10	GND	AD[49]	AD[48]	AD[47]	GND	AD[46]	GND	E
9	GND	AD[52]	GND	V(I/O) ⁽³⁾	AD[51]	AD[50]	GND	c
8	GND	AD[56]	AD[55]	AD[54]	GND	AD[53]	GND	т
7	GND	AD[59]	GND	V(I/O) ⁽³⁾	AD[58]	AD[57]	GND	
6	GND	AD[63]	AD[62]	AD[61]	GND	AD[60]	GND	0
5	GND	C/BE[5]#	GND	V(I/O)(3)	C/BE[4]#	PAR64	GND	R
4	GND	V(I/O) ⁽³⁾	BRSVP2B4	C/BE[7]#	GND	C/BE[6]#	GND	
3(3)	GND	CLK4	GND	GNT3#	REQ4#	GNT4#	GND	
2(3)	GND	CLK2	CLK3	SYSEN#(4)	GNT2#	REQ3#	GND	
1(3)	GND	CLK1	GND	REQ1#	GNT1#	REQ2#	GND	
25	GND	5V	REQ64#	ENUM#	3.3V	5V	GND	
24	GND	AD[1]	5V	V(I/O)(3) (1)	AD[0]	ACK64#	GND	
23	GND	3.3V	AD[4]	AD[3]	5V(1)	AD[2]	GND	
22	GND	AD[7]	GND	3.3V ⁽¹⁾	AD[6]	AD[5]	GND	
21	GND	3.3V	AD[9]	AD[8]	M66EN (5)	C/BE[0]#	GND	
20	GND	AD[12]	GND	V(I/O)(3)	AD[11]	AD[10]	GND	P1
19	GND	3.3V	AD[15]	AD[14]	GND ⁽¹⁾	AD[13]	GND	
18	GND	SERR#	GND	3.3V	PAR	C/BE[1]#	GND	
17	GND	3.3V	IPMBSCL	IPMBSDA	GND ⁽¹⁾	PERR#	GND	
16	GND	DEVSEL#	GND	V(I/O)(1).(3)	STOP#	LOCK#	GND	с
15	GND	3.3V	FRAME#	IRDY#	GND ⁽²⁾	TRDY#	GND	ŏ
12-14				KEY AREA				N
11	GND	AD[18]	AD[17]	AD[16]	GND ⁽¹⁾	C/BE[2]#	GND	
10	GND	AD[21]	GND	3.3V	AD[20]	AD[19]	GND	N
9	GND	C/BE[3]#	GND ⁽²⁾	AD[23]	GND	AD[22]	GND	E
8	GND	AD[26]	GND	V(I/O)(3)	AD[25]	AD[24]	GND	C
7	GND	AD[30]	AD[29]	AD[28]	GND ⁽¹⁾	AD[27]	GND	Т
6	GND	REQ0#	GND	3.3V ⁽¹⁾	CLKO	AD[31]	GND	o
5	GND	BRSVP1A5	BRSVP1B5	RST#	GND ⁽¹⁾	GNTO#	GND	B
4	GND	IPMB PWR	HEALTHY#	V(I/O)(3)(1)	INTP	INTS	GND	"
3	GND	INTA#	INTB#	INTC#	5V(1)	INTD#	GND	1
2	GND	TCK®	5V	TMS ⁽⁸⁾	TDO ⁽⁸⁾	TDI ⁽⁸⁾	GND	1
1	GND	5V	-12V	TRST#®	+12V	5V	GND	1
PIN	Z ⁽¹⁰⁾	A	В	C	D	E	F	

Per CompactPCI® Specification 2.0 R3.0, October 1, 1999, Tabelle 15

(1) Early mate pins.

(2) Late mate pins.

(3) 3.3 V or 5.0 V.

(4) Grounded in system slot.

(5) Ground for a 33 MHz backplane. Bussed slot to slot in 66 MHz systems.

(6) Each slot may have a unique geographic address encoding. See the CompactPCI® specification for details.

(7) Backplane must leave pin open and provide # bypass capacitor.

(8) JTAG is being discouraged. These pins will be redefined.
(9) To be used for I^oC bus.

(10) Daughtercards do not make use of "z" row grounds.

Note: Chart numbering conforms to the CompactPCI® specification. Connector numbering is from top to bottom in accordance with the IEC standard.

2.0 mm ERmet Hard Metric Connector System 64 Bit CompactPCI[®] Peripheral Slot Pin Assignments



T

In the case of the 64 bit CompactPCI®, both the P1 and P2 connectors are fully assigned with no pins available for user defined I/O. For such systems, only 6U designs can have rear panel I/O.

on 3U cards, 6U implementations provide optional P3, P4 and P5 connectors, which all have undefined pins for user I/O. 6U CompactPCI® provides more user defined pins than any other bus structure today.

Although CompactPCI® is designed to be accomplished

PIN	Z ⁽¹⁰⁾	А	В	C	D	E	F	
22	GND	GA4 ⁽⁶⁾	GA3 ⁽⁶⁾	GA2 ⁽⁶⁾	GA1 ⁽⁶⁾	GA0 ⁽⁶⁾	GND	
21	GND	RSV	RSV	RSV	RSV	RSV	GND	
20	GND	RSV	RSV	RSV	GND	RSV	GND	
19	GND	RSV	RSV	RSV	RSV	RSV	GND	P2
18	GND	BRSVP2A18	BRSVP2B18	BRSVP2C18	GND	BRSVP2E18	GND	
17	GND	BRSVP2A17	GND	RSV	RSV	RSV	GND	
16	GND	BRSVP2A16	BRSVP2B16	RSV	GND®	BRSVP2E16	GND	
15	GND	BRSVP2A15	GND	RSV	RSV	RSV	GND	_
14	GND	AD[35]	AD[34]	AD[33]	GND	AD[32]	GND	С
13	GND	AD[38]	GND	V(I/O) ⁽³⁾	AD[37]	AD[36]	GND	0
12	GND	AD[42]	AD[41]	AD[40]	GND	AD[39]	GND	N
11	GND	AD[45]	GND	V(I/O)(3)	AD[44]	AD[43]	GND	N
10	GND	AD[49]	AD[48]	AD[47]	GND	AD[46]	GND	Е
9	GND	AD[52]	GND	V(I/O)(3)	AD[51]	AD[50]	GND	c
8	GND	AD[56]	AD[55]	AD[54]	GND	AD[53]	GND	T
7	GND	AD[59]	GND	V(I/O)(3)	AD[58]	AD[57]	GND	
6	GND	AD[63]	AD[62]	AD[61]	GND	AD[60]	GND	0
5	GND	C/BE[5]#	GND	V(I/O) ⁽³⁾	C/BE[4]#	PAR64	GND	R
4	GND	V(I/O)(3)	BRSVP2B4	C/BE[7]#	GND	C/BE[6]#	GND	
3(3)	GND	RSV	GND	RSV	RSV	RSV	GND	
2(3)	GND	RSV	RSV	UNC ⁽⁴⁾	RSV	RSV	GND	
1(3)	GND	RSV	GND	RSV	RSV	RSV	GND	
25	GND	5V	REQ64#	ENUM#	3.3V	5V	GND	
24	GND	AD[1]	5V	V(I/O) ^{(3) (1)}	AD[0]	ACK64#	GND	
23	GND	3.3V	AD[4]	AD[3]	5V ⁽¹⁾	AD[2]	GND	
22	GND	AD[7]	GND	3.3V ⁽¹⁾	AD[6]	AD[5]	GND	
21	GND	3.3V	AD[9]	AD[8]	M66EN(4) (5)	C/BE[0]#	GND	
20	GND	AD[12]	GND	V(I/O)(3)	AD[11]	AD[10]	GND	P1
19	GND	3.3V	AD[15]	AD[14]	GND ⁽¹⁾	AD[13]	GND	
18	GND	SERR#	GND	3.3V	PAR	C/BE[1]#	GND	
17	GND	3.3V	IPMBSCL	IPMBSDA	GND ⁽¹⁾	PERR#	GND	
16	GND	DEVSEL#	GND	V(I/O)(3)	STOP#	LOCK#	GND	с
15	GND	3.3V	FRAME#	IRDY#	BD SEL#(2)	TRDY#	GND	
12-14	unb	0.01		KEY AREA	55 0225		ditb	0
11	GND	AD[18]	AD[17]	AD[16]	GND ⁽¹⁾	C/BE[2]#	GND	N
10	GND	AD[21]	GND	3.3V	AD[20]	AD[19]	GND	N
9	GND	C/BE[3]#	IDSEL ⁽²⁾	AD[23]	GND ⁽¹⁾	AD[22]	GND	E
8	GND	AD[26]	GND	V(I/O)(3)	AD[25]	AD[24]	GND	с
7	GND	AD[30]	AD[29]	AD[28]	GND ⁽¹⁾	AD[27]	GND	т
6	GND	REQ#	GND	3.3V ⁽¹⁾	CLK	AD[31]	GND	o
5	GND	BRSVP1A5	BRSVP1B5	RST#	GND ⁽¹⁾	GNT#	GND	R
4	GND	IPMB PWR	HEALTHY ⁽⁷⁾	V(I/O) ^{(3) (1)}	INTP	INTS	GND	к
3	GND	INTA#	INTB#	INTC#	5V(1)	INTD#	GND	
2	GND	TCK ⁽⁸⁾	5V	TMS®	TDO(8)	TDI ⁽⁸⁾	GND	
1	GND	5V	-12V	TRST#®	+12V	5V	GND	
PIN	Z ⁽¹⁰⁾	A	B	C	D	E	F	
	2	~		U		-		

Per CompactPCI® Specification 2.0 R3.0, October 1, 1999, Tabelle 13

(1) Early mate pins.

(2) Late mate pins.

(3) 3.3 V or 5.0 V.

(4) Grounded in system slot.

(5) Ground for a 33 MHz backplane. Bussed slot to slot in 66 MHz systems.

(6) Each slot may have a unique geographic address encoding. See the CompactPCI® specification for details.

(7) Backplane must leave pin open and provide # bypass capacitor.

(8) JTAG is being discouraged. These pins will be redefined.

(9) To be used for I2C bus.

(10) Daughtercards do not make use of "z" row grounds.

Note: Chart numbering conforms to the CompactPCI® specification. Connector numbering is from top to bottom in accordance with the IEC standard.

2.0 mm ERmet Hard Metric Connector System 32 Bit CompactPCI® System Slot Pin Assignments



The CompactPCI® specification defines a 32 bit implementation. The 32 bit implementation makes the entire P2/J2 connector (upper) available for user defined I/O for slots 2-8. The controller card slot (usually slot 1) makes use of some P2 pins for such functions as clock, arbitration.

grant/requests and some other system functions. In many 32 bit systems, the backplane connector in the P2 position will have 16 mm rear tails and a shroud so I/O signals may pass through the backplane to rear mounted cards or cable assemblies.

	5 101 Out	in functions as c		00100	or cable assertit	//////		
PIN	Z ⁽⁶⁾	A	В	C	D	E	F	
22	GND	GA4 ⁽⁵⁾	GA3 ⁽⁵⁾	GA2 ⁽⁵⁾	GA1 ⁽⁵⁾	GA0 ⁽⁵⁾	GND	
21	GND	CLK6#	GND	BP(I/0)	BP(I/0)	BP(I/0)	GND	
20	GND	CLK5#	GND	BP(I/0)	BP(I/0)	BP(I/0)	GND	
19	GND	GND	GND	BP(I/O)(9)	BP(I/0)(9)	BP(I/O)(9)	GND	
18	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	P2
17	GND	BP(I/0)	BP(I/0)	PRST#	REQ6#	GNT6#	GND	
16	GND	BP(I/0)	BP(I/0)	DEG#	GND	BP(I/0)	GND	
15	GND	BP(I/0)	BP(I/0)	FAL#	REQ5#	GNT5#	GND	
14	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	с
13	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	0
12	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	N
11	GND	BP(I/0)	BP(I/0)	BP(I/O)	BP(I/0)	BP(I/O)	GND	
10	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	Ν
9	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	E
8	GND	BP(I/O)	BP(I/O)	BP(I/O)	BP(I/0)	BP(I/O)	GND	С
7	GND	BP(I/O)	BP(I/0)	BP(I/0)	BP(I/O)	BP(I/O)	GND	т
6	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	0
5	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	R
4	GND	V(I/O)	BP(I/0)	BP(I/O)	BP(I/O)	BP(I/O)	GND	n
3	GND	CLK4	GND	GNT3#	REQ4#	GNT4#	GND	
2	GND	CLK2	CLK3	SYSEN# (10)	GNT2#	REQ3#	GND	
1	GND	CLK1	GND	REQ1#	GNT1#	REQ2#	GND	
25	GND	5V	REQ64#	ENUM#	3.3V	5V	GND	
24	GND	AD[1]	5V	V(I/O)(3) (1)	AD[0]	ACK64#	GND	
23	GND	3.3V	AD[4]	AD[3]	5V ⁽¹⁾	AD[2]	GND	
22	GND	AD[7]	GND	3.3V ⁽¹⁾	AD[6]	AD[5]	GND	
21	GND	3.3V	AD[9]	AD[8]	M66EN(4)	C/BE[0]#	GND	
20	GND	AD[12]	GND	V(I/O)(3)	AD[11]	AD[10]	GND	P1
19	GND	3.3V	AD[15]	AD[14]	GND ⁽¹⁾	AD[13]	GND	
18	GND	SERR#	GND	3.3V	PAR	C/BE[1]#	GND	
17	GND	3.3V	IPMBSCL	IPMBSDA	GND ⁽¹⁾	PERR#	GND	
16	GND	DEVSEL	GND	V(I/O)(1).(3)	STOP#	LOCK#	GND	с
15	GND	3.3v	FRAME#	IRDY	GND ⁽²⁾	TRDY#	GND	ō
12-14				KEY AREA				N
11	GND	AD[18]	AD[17]	AD[16]	GND ⁽¹⁾	C/BE[2]#	GND	
10	GND	AD[21]	GND	3.3V	AD[20]	AD[19]	GND	N
9	GND	C/BE[3]#	GND ⁽²⁾	AD[23]	GND ⁽¹⁾	AD[22]	GND	E
8	GND	AD[26]	GND	V(I/O)(3)	AD[25]	AD[24]	GND	С
7	GND	AD[30]	AD[29]	AD[28]	GND ⁽¹⁾	AD[27]	GND	т
6	GND	REQ0#	GND	3.3V ⁽¹⁾	CLK	AD[31]	GND	о
5	GND	BRSVP1A5	BRSVP1B5	RST#	GND ⁽¹⁾	GNT0#	GND	B
4	GND	IPMB PWR	HEALTHY#(7)	V(I/O)(3) (1)	INTP	INTS	GND	
3	GND	INTA#	INTB#	INTC#	5V(1)	INTD#	GND	
2	GND	TCK ⁽⁸⁾	5V	TMS ⁽⁸⁾	TDO ⁽⁸⁾	TDI ⁽⁸⁾	GND	
1	GND	5V	-12V	TRST# ⁽⁸⁾	+12V	5V	GND	
PIN	Z ⁽⁶⁾	A	В	C	D	E	F	

Per CompactPCI® Specification 2.0 R3.0, October 1, 1999, Tabelle 16

(1) Early mate pins.

(2) Late mate pins.

(3) 3.3 V or 5.0 V.

(4) Grounded in 33 MHz backplane. Bussed slot to slot in 66 MHz systems

(5) Each slot may have a unique geographic address encoding. See the CompactPCI[®] specification for details.
(6) Daughter cards do not make use of the "Z" row grounds.

(7) Backplane must leave pin open and provide # bypass capacitor.

(8) JTAG is being discouraged. These pins will be redefined.

(9) To be used for I2C bus.

(10) Grounded in system slot.

Notes: All P2 terminals should be 16 mm long with shroud installed unless they are used for a secondary bus. Chart numbering conforms to the CompactPCI® specification. Connector numbering is from top to bottom in accordance with the IEC standard.

| Edition 9

www.erni.com

1

2.0 mm ERmet Hard Metric Connector System 32 Bit CompactPCI® Peripheral Slot Pin Assignments



The CompactPCI® specification defines a 32 bit implementation. The 32 bit implementation makes the entire P2/J2 connector (upper) available for user defined I/O for slots 2-8. The controller card slot (usually slot 1) makes use of some P2 pins for such functions as clock, arbitration.

grant/requests and some other system functions. In many 32 bit systems, the backplane connector in the P2 position will have 16 mm rear tails and a shroud so I/O signals may pass through the backplane to rear mounted cards or cable assemblies.

PIN	Z ⁽⁶⁾	А	В	C	D	E	F	
22	GND	GA4 ⁽⁵⁾	GA3 ⁽⁵⁾	GA2 ⁽⁵⁾	GA1 ⁽⁵⁾	GA0 ⁽⁵⁾	GND	
21	GND	BP(I/O)	BP(I/O)	BP(I/O)	BP(I/O)	BP(I/O)	GND	
20	GND	BP(I/O)	BP(I/0)	BP(I/O)	BP(I/O)	BP(I/O)	GND	
19	GND	BP(I/0)	BP(I/O)	BP(I/0)	BP(I/0)	BP(I/O)	GND	
18	GND	BP(I/0)	BP(I/O)	BP(I/0)	BP(I/0)	BP(I/O)	GND	P2
17	GND	BP(I/0)	BP(I/O)	BP(I/O)	BP(I/O)	BP(I/0)	GND	
16	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	
15	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/O)	GND	
14	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	с
13	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	o
12	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	N
11	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	N
10	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	
9	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	Е
8	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	С
7	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	т
6	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	0
5	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	в
4	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	
3	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	
2	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	
1	GND	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	BP(I/0)	GND	
25	GND	5V	REQ64#	ENUM#	3.3V	5V	GND	
24	GND	AD[1]	5V	V(I/O)(3) (1)	AD[0]	ACK64#	GND	
23	GND	3.3V	AD[4]	AD[3]	5V ⁽¹⁾	AD[2]	GND	
22	GND	AD[7]	GND	3.3V ⁽¹⁾	AD[6]	AD[5]	GND	
21	GND	3.3V	AD[9]	AD[8]	M66EN ⁽⁴⁾	C/BE[0]#	GND	
20	GND	AD[12]	GND	V(I/O)(3)	AD[11]	AD[10]	GND	P1
19	GND	3.3V	AD[15]	AD[14]	GND ⁽¹⁾	AD[13]	GND	
18	GND	SERR#	GND	3.3V	PAR	C/BE[1]#	GND	
17	GND	3.3V	IPMBSCL	IPMBSDA	GND ⁽¹⁾	PERR#	GND	
16	GND	DEVSEL	GND	V(I/O)(1).(3)	STOP#	LOCK#	GND	с
15	GND	3.3v	FRAME#	IRDY	BD SEL#(2)	TRDY#	GND	o
12-14				KEY AREA			-	Ň
11	GND	AD[18]	AD[17]	AD[16]	GND ⁽¹⁾	C/BE[2]#	GND	N
10	GND	AD[21]	GND	3.3V	AD[20]	AD[19]	GND	
9	GND	C/BE[3]#	IDSEL ⁽²⁾	AD[23]	GND ⁽¹⁾	AD[22]	GND	E
8	GND	AD[26]	GND	V(I/O) ⁽³⁾	AD[25]	AD[24]	GND	С
7	GND	AD[30]	AD[29]	AD[28]	GND ⁽¹⁾	AD[27]	GND	т
6	GND	REQ#	GND	3.3V ⁽¹⁾	CLK	AD[31]	GND	0
5	GND	BRSVP1A5	BRSVP1B5	RST#	GND ⁽¹⁾	GNT#	GND	R
4	GND	IPMB PWR	HEALTHY#(7)	V(I/O)(3) (1)	INTP	INTS	GND	
3	GND	INTA#	INTB#	INTC#	5V ⁽¹⁾	INTD#	GND	
2	GND	TCK ⁽⁸⁾	5V	TMS ⁽⁸⁾	TDO ⁽⁸⁾	TDI ⁽⁸⁾	GND	
1	GND	5V	-12V	TRST# ⁽⁸⁾	+12V	5V	GND	
PIN	Z ⁽⁶⁾	Α	B	C	D	E	F	

Per CompactPCI® Specification 2.0 R3.0, October 1, 1999, Tabelle 14

(1) Early mate pins.

(2) Late mate pins. (3) 3.3 V or 5.0 V.

(4) Grounded in 33 MHz backplane. Bussed slot to slot in 66 MHz systems

(5) Each slot may have a unique geographic address encoding. See the CompactPCI[®] specification for details.
(6) Daughter cards do not make use of the "Z" row grounds.

(7) Backplane must leave pin open and provide # bypass capacitor.

(8) JTAG is being discouraged. These pins will be redefined.

Notes: All P2 terminals should be 16 mm long with shroud installed unless they are used for a secondary bus.

Chart numbering conforms to the CompactPCI® specification. Connector numbering is from top to bottom in accordance with the IEC standard.

T
2.0 mm ERmet Hard Metric Connector System cPCI Computer Telephony P4 Pin Assignments

Pos#	Row Z	Row A		Row B		Row C		Row D		Row E		Row	E
													F
25	NP	SGA4	M	SGA3	M	SGA2	M	SGA1	M	SGA0	M	FG	
24	NP	GA4	M	GA3	M	GA2	M	GA1	M	GAO	M	FG	
23	NP	+12V	М	/CT_Reset	M	/CT_EN	S	-12v	M	CT_MC	M	FG	L
22	NP	PFS0#	М	RSVD	M	RSVD	М	RSVD	M	RSVD	M	FG	L
21	NP	-SELbat	L	PFS1#	М	RSVD	М	RSVD	М	SELVbatRtN	L	FG	L
20	NP	NP		NP		NP		NP		NP		NP	
19	NP	NP		NP		NP		NP		NP		NP	
18	NP	VRG	М	NP		NP		NP		VRGTN	М	NP	
17	NP	NP		NP		NP		NP		NP		NP	
16	NP	NP		NP		NP		NP		NP		NP	
15	NP	-VBAT	L	NP		NP		NP		VBATRTN	L	NP	
12-14				KEY AREA (I	keep unobs	tructed on backr	lane to ease	routing con:	straints)				
11	NP	CT_D29	М	CT_D30	M	CT_D31	М	V(I/0)	L	/CT_FRAME_A	М	GND	L
10	NP	CT_D27	М	+3.3V	M	CT_D28	М	+5V	L	/CT FRAME B	М	GND	L
9	NP	CT D24	М	CR D25	М	CT D26	М	GND	L	/FR_COMP	М	GND	L
8	NP	CT_D21	М	CT_D22	М	CT_D23	М	+5V	L	CT_C8_A	М	GND	L
7	NP	CT_D19	М	+5V	М	CT_D20	М	GND	L	CT C8 B	М	GND	L
6	NP	CT_D16	М	CT_C17	М	CT_D18	М	GND	L	CT_NETREF_1	М	GND	L
5	NP	CT_D13	М	CT_D14	М	CT_D15	М	+3.3V	L	CT_NETREF_2	М	GND	L
4	NP	CT_D11	М	+5V	М	CT_D12	М	+3.3V	L	SCLK	М	GND	L
3	NP	CT D8	М	CT_D9	М	CT D10	М	GND	L	SCLK-D	М	GMD	L
2	NP	CT D4	М	CT D5	М	CT D6	М	CT D7	М	GND	L	GND	L
1	NP	CT DO	М	+3.3V	М	CTP_D1	М	CT D2	M	CT_D3	М	GND	L

Mechanical Specifications - Backplane and Chassis

Per CompactPCI® Specification PICMG 2.5 R1.0, April 3, 1998, Table 1

Key to P4 Pin Assignments

Ct_name	= H.110 TDM bus signals
+5V	= +5V power
+3.3V	= +3.3V power
GND	= LOGIC GROUND
V(I/O)	= I/O cell power
FG	= Frame Ground
RSVD	= reserved for future use
NP	= a pin and pad to Not be Populated
-SELVbat	= short loop battery
SELVbatRtn	= short loop battery return
-Vbat	= telecom power distribution bus
VbatRtn	= return bus pin for -Vbat
SGA0-SGA4	 shelf enumeration bus signals
GA0-GA4	= slot ID signals; not bussed
VRG	 bus for ringing voltage
VRGRtn	 bus for ringing voltage
PFS0#-PFS1#	= busses for power fail sense
KEY AREA	 area utilized for key
S	= Short (Level 1) front side pins
M	= Medium (Level 2) front side pins
L	= Long (Level 3) front side pins



Pos#	Row Z	Row A	Row B	Row C	Row D	Row E	Row F
25							
24							
23				SELV			
22							
21	ND	ND	ND	ND	ND	ND	ND
20	NP	NP	NP	NP	NP	NP	NP
19	NP	NP	NP	NP	NP	NP	NP
18	NP	HAZ	IN/C-NP	IN/C-NP	IN/C-NP	HAZ	NP
17	NP	NP	NP	NP	NP	NP	NP
16	NP	NP	NP	NP	NP	NP	NP
15	NP	HAZ	IN/C-NP	IN/C-NP	IN/C-NP	HAZ	NP
14							
13		KEY AREA (keep und	obstructed on backplan	e to ease routing cons	traints)		
12				-			
11							
10							
9							
8							
7				SELV			
6							
5							
4							

Per CompactPCI® Computer Telephony Specification PICMG 2.5 R1.0, April 3, 1998, Table 11

2.0 mm ERme Hard Metric Connector System cPCI Computer Telephony P5 Pin Assignments

Pos#	Row Z		Row A		Row B		Row C		Row D		Row E		Row F	
22	NP-IN/C	U	T1	S	T9	S	T17	S	T25	S	IN/C	S	GND-IN/C	L
21	NP-IN/C	U	R1	S	R9	S	R17	S	R25	S	IN/C	S	GND-IN/C	L
20	NP-IN/C	U	T2	S	T10	S	T18	S	T26	S	IN/C	S	GND-IN/C	L
19	NP-IN/C	U	R2	S	R10	S	R18	S	R26	S	IN/C	S	GND-IN/C	L
18	NP-IN/C	U	T3	S	T11	S	T19	S	T27	S	IN/C	S	GND-IN/C	L
17	NP-IN/C	U	R3	S	R11	S	R19	S	R27	S	IN/C	S	GND-IN/C	L
16	NP-IN/C	U	T4	S	T12	S	T20	S	T28	S	IN/C	S	GND-IN/C	L
15	NP-IN/C	U	R4	S	R12	S	R20	S	R28	S	IN/C	S	GND-IN/C	L
13	NP-IN/C	U	R5	S	R13	S	R21	S	R29	S	IN/C	S	GND-IN/C	L
12	NP-IN/C	U	T6	S	T14	S	T22	S	T30	S	IN/C	S	GND-IN/C	L
11	NP-IN/C	U	R6	S	R14	S	R22	S	R30	S	IN/C	S	GND-INC	L
10	NP-IN/C	U	T7	S	T15	S	T23	S	T31	S	IN/C	S	GND-IN/C	L
9	NP-IN/C	U	R7	S	R15	S	R23	S	R31	S	IN/C	S	GND-IN/C	L
8	NP-IN/C	U	T8	S	T16	S	T24	S	T32	S	IN/C	S	GND-IN/C	L
7	NP-IN/C	U	R8	S	R16	S	R24	S	R32	S	IN/C	S	GND-IN/C	L
6	NP-IN/C	U	IN/C	S	IN/C	S	IN/C	S	IN/C	S	IN/C	S	GND-IN/C	L
5	NP-IN/C	U	IN/C	S	IN/C	S	IN/C	S	IN/C	S	IN/C	S	GND-IN/C	L
4	Np-IN/C	U	Uo0	М	Uo1	M	GND_Ft	М	GND_Ft	М	GND_Ft	М	GND-IN/C	L
3	NP-In/C	U	Ui0	М	Ui1	M	Uo4	М	Uo5	Μ	U06	Μ	GND-IN/C	L
2	NP-IN/C	U	Uo2	M	Uo3	M	Ui4	M	Ui5	М	Ui6	Μ	GND-IN/C	L
1	NP-In/C	U	Ui2	M	Ui3	M	+5V_FT	M	+12V_FT	М	-12V_FT	М	GND-IN/C	L

Per CompactPCI® Computer Telephony Specification PICMG 2.5 R1.0, April 3, 1998, Table 3

Key to P5 Pin Assignments

T <i>n</i> B <i>n</i>	= Tip = Ring
IN/C	= No Connect required for safety agency Insulation requirements
NP	 a position required to be Not Populated (i.e., no conductive element present
NP-IN/C	= a position which may be either Not Populated or Insulation No Connect
GND-IN/C	= a position which may be either LOGIC GROUND or Insulation No Con- nect
+nV FT	= positive supply voltage feed-through from CT Front Card
- <i>n</i> V_FT	= negative supply voltage feed-through from CT Front Card
GND_FT	= logic ground feed-through from CT Front Card
Ui <i>n</i>	= Universal Input - user defined input signal
	(input to CT Front Card)
Uo <i>n</i>	 Universal Output - user defined input signal (output to CT Front Card)
U	= a pin of unspecified length

S = Short (Level 1) front side pins M = Medium (Level 2) front side pins

= Long (Level 3) front side pins

= Eong (Eover o) none side pins

2.3.2.1. P5 Telephony I/O Pins

L

- Tn Tip short (Level 1) pins for connecting to the nominally positive side of a balanced pair telephony connection
- Rn Ring short (Level 1) pins for connecting to the nominally negative side of a balanced pair telephony connection



Pos#	Row Z	Row A	Row B		Row C		Row D		Row E	Row F	
22	NP-IN/C							S	IN/C		L
21	NP-IN/C							S	IN/C		L
20	NP-IN/C							S	IN/C		L
19	NP-IN/C							S	IN/C		L
18	NP-IN/C							S	IN/C		L
17	NP-IN/C							S	IN/C		L
16	NP-IN/C							S	IN/C		L
15	NP-IN/C		TNV3-S				TNV1-	S	IN/C		L
14	NP-IN/C		11443-3	EL	v		SELV	S	IN/C		L
13	NP-IN/C						OLL	S	IN/C	-	L
12	NP-IN/C							S	IN/C	SELV	L
11	NP-IN/C							S	IN/C	OLLV	L
10	NP-IN/C							S	IN/C		L
9	NP-IN/C							S	IN/C		L
8	NP-IN/C							S	IN/C		L
7	NP-IN/C							S	IN/C		L
6	NP-IN/C	IN/C	IN/C		IN/C		IN/C	S	IN/C		L
5	NP-IN/C	IN/C	IN/C		IN/C		IN/C	S	IN/C		L
4	Np-IN/C										L
3	NP-In/C					E	V				L
2	NP-IN/C						N.				L
1	NP-In/C										L

Per CompactPCI® Computer Telephony Specification PICMG 2.5 R1.0, April 3, 1998, Table 12

2.0 mm ERmet Hard Metric Connector System **PXI Generic Peripheral Slot Pinout**

	PMC Slot	Row A	Row B	Row C	Row D	Row E	Row F	PIN
	GND	PXI RSVE22	PXI RSVD22	PXI RSVC22	PXI RSVB22	PXI RSVA22	GND	22
P2/J2	GND	PXI LBR3	PXI LBR2	PXI LBR1	GND	PXI LBRO	GND	21
F 2/ J2	GND	PXI LBL1	GND	PXI LBLO	PXI LBR5	PXI LBL4	GND	20
с	GND	PXI LBL5	PXI LBL4	PXI LBL3	GND	PXI LBL2	GND	19
Ŭ	GND	PXI TRIG6	GND	PXI TRIG5	PXI TRIG4	PXI TRIG3	GND	18
0	GND	PXI CLK10	PXI STAR	PRST#	GND	PXI TRIG2	GND	17
	GND	PXI TRIG7	GND	DEG#	PXI TRIGO	PXI TRIG1	GND	16
N	GND	PXI-LBR6	PXI LBL6	FAL#	GND	PXI BRSVA15	GND	15
	GND	AD[32]	GND	AD[33]	AD[34]	AD[35]	GND	14
N	GND	AD[36]	AD[37]	V(I/0)	GND	AD[38]	GND	13
	GND	AD[39]	GND	AD[40]	AD[41]	AD[42]	GND	12
E	GND	AD[43]	AD[44]	V[I/0]	GND	AD[45]	GND	11
_	GND	AD[46]	GND	AD[47]	AD[48]	AD[49]	GND	10
с	GND	AD[50]	AD[51]	V[1/0]	GND	AD[52]	GND	9
	GND	AD[53]	GND	AD[54]	AD[55]	AD[56]	GND	8
т	GND	AD[57]	AD[58]	V[I/0]	GND	AD[59]	GND	7
	GND	AD[60]	GND	AD[61]	AD[62]	AD[63]	GND	6
0	GND	PAR64	C/BE[4]#	V[1/0]	GND	C/BE[5]#	GND	5
	GND	C/BE [6]#	GND	C/BE[7]#	PXI BRSVB4	V[1/0]	GND	4
R	GND	PXI LBR10	PXI LBR9	PXI LBR8	GND	PXI LBR7	GND	3
	GND	PXI LBL8	PXI LBL7	SYSEN#	PXI LBR12	PXI LBR11	GND	2
	GND	PXI LBL12	PXI LBL11	PXI LBL10	GND	PXI LBL9	GND	1
	GND	5V	3.3V	ENUM#	REQ64#	5V	GND	25
	GND	ACK64#	AD[0]	V[1/0]	5V	AD[1]	GND	23
D4/14	GND	AD[2]	5V	AD931	AD[4]	3.3V	GND	24
P1/J1	GND	AD[2] AD[5]	AD[6]	3.3V	GND	AD[7]	GND	23
	GND	C/BE[0]#	M66EN	AD[8]	AD[9]	3.3V	GND	21
С	GND	AD[10]	AD[11]	V[1/0]	GND	AD[12]	GND	20
	GND		GND			3.3V	GND	19
0		AD[13]	PAR	AD[14]	AD[15]	SERR#	GND	19
N	GND	C/BE[1]#	-	3.3V	GND			
N	GND	PERR#	GND CTOD#	SBO#	SDONE	3.3V	GND	17
N	GND	LOCK# TRDY#	STOP# GND	V[I/0] IRDY	GND FRAME#	DEVSEL# 3.3V	GND	16 15
	GND	TRU I#	GND		FRAIVIE#	3.3V		-
Е	OND	0.0000011	OND	Key Area	40(47)	40(0)	GND	12-14
-	GND	C/BE[2]#	GND	AD[16]	AD[17]	AD[8]	GND	11
с	GND	AD[19]	AD[20]	3.3V	GND	AD[21]	GND	10
Ŭ	GND	AD[22]	GND	AD[23]	IDSEL	C/BE[3]#	GND	9
т	GND	AD[24]	AD[25]	V[I/0]	GND	AD[26]	GND	8
	GND	AD[27]	GND	AD[28]	AD[29]	AD[30]	GND	7
0	GND	AD[31]	CLK	3.3V	GND	REQ#	GND	6
	GND	GNT#	GND	RST#	BRSVP1B5	BRSVP1A5	GND	5
R	GND	INTS	INTP	V[I/0]	GND	BRSVP1A4	GND	4
	GND	INTD#	5V	INTC#	INTB#	INTA#	GND	3
	GND	TDI	TDO	TMS	5V	TCK	GND	2
	GND	5V	+12V	TRST#	-12V	5V	GND	1
	PMC Slot	Row A	Row B	Row C	Row D	Row E	Row F	PIN

Per PXI Specification R1.0 August 20, 1997, Table 4.9 Signals in Bold are PXI specific

2.0 mm ERmet Hard Metric Connector System **PXI System Slot Pinout**



1	F	E	D	C	В	Α	Z	PIN
1	GND	PXI RSVE22	PXI RSVD22	PXI RSVC22	PXI RSVB22	PXI RSVA22	GND	22
P2/J2	GND	RSV	RSV	RSV	GND	CLK6	GND	21
P2/J2	GND	RSV	GND	RSV	GND	CLK5	GND	20
c	GND	RSV	RSV	RSV	GND	GND	GND	19
	GND	PXI TRIG6	GND	PXI TRIG5	PXI TRIG4	PXI TRIG3	GND	18
0	GND	GNT6#	REQ6#	PRST#	GND	PXI TRIG2	GND	17
1	GND	PXI TRIG7	GND	DEG#	PXI TRIGO	PXI_TRIG1	GND	16
N	GND	GBT5#	REQ5#	FAL#	GND	PXI BRSVA15	GND	15
	GND	AD[32]	GND	AD[33]	AD[34]	AD[35]	GND	14
N	GND	AD[36]	AD[37]	V[I/0]	GND	AD[38]	GND	13
1 "	GND	AD[39]	GND	AD[40]	AD[41]	AD[42]	GND	12
E	GND	AD[43]	AD[44]	V[I/0]	GND	AD[45]	GND	11
1 -	GND	AD[46]	GND	AD[47]	AD[48]	AD[49]	GND	10
c	GND	AD[50]	AD[51]	V[1/0]	GND	AD[52]	GND	9
	GND	AD[53]	GND	AD[54]	AD[55]	AD[56]	GND	8
Т	GND	AD[57]	AD[58]	V[I/0]	GND	AD[59]	GND	7
1	GND	AD[60]	GND	AD[61]	AD[62]	AD[63]	GND	6
0	GND	PAR64	C/BE[4]#	V[1/0]	GND	C/BE[5]#	GND	5
-	GND	C/BE[6]#	GND	C/BE[7]#	PXI BRSVB4	V[1/0]	GND	4
R	GND	GNT4#	REQ4#	GNT3#	GND	CLK4	GND	3
1	GND	REQ3#	GNT2#	SYSEN#	CLK3	CLK2	GND	2
1	GND	REQ2#	GNT1#	REQ1#	GND	CLK1	GND	1
	GND	5V	3.3V	ENUM#	REQ64#	5V	GND	25
1	GND	ACK64#	AD[0]	V[1/0]	5V	AD[1]	GND	24
1	GND	AD[2]	5V	AD[3]	AD[4]	3.3V	GND	23
P1/J1	GND	AD[5]	AD[6]	3.3V	GND	AD[7]	GND	22
	GND	C/BE[0]#	M66EN	AD[8]	AD[9]	3.3V	GND	21
c	GND	AD[10]	AD[11]	V[I/0]	GND	AD[12]	GND	20
	GND	AD[13]	GND	AD[14]	AD[15]	3.3V	GND	19
0	GND	C/BE[1]	PAR	3.3V	GND	SERR#	GND	18
N	GND	PERR#	GND	SB0#	SDONE	3.3V	GND	17
. N	GND	LOCK#	STOP#	V[1/0]	GND	DEVSEL#	GND	16
N	GND	TRDY#	GND	IRDY#	FRAME#	3.3V	GND	15
	unb	mon	GIND	Key Area	TTUUVIE	0.01	GIVE	12-14
E	GND	C/BE[2]#	GND	AD[16]	AD[17]	AD[18]	GND	11
-	GND	AD[19]	AD[20]	3.3V	GND	AD[21]	GND	10
c	GND	AD[22]	GND	AD[23]	IDSEL	C/BE[3]#	GND	9
Ŭ	GND	AD[24]	AD[25]	V(I/O)	GND	AD[26]	GND	8
T	GND	AD [27]	GND	AD[28]	AD[29]	AD[30]	GND	7
	GND	AD [31]	CLK	3.3V	GND	REQ#	GND	6
0	GND	GNT#	GND	RST#	BRSVP1B5	BRSVP1A5	GND	5
-	GND	INTS	INTP	V(I/0)	GND	BRSVP1A4	GND	4
B	GND	INTS INTD#	5V	INTC#	INTB#	INTA#	GND	3
1	GND	TDI	TDO	TMS	5V	TCK	GND	2
	GND	5V	+12V	TRST#	-12V	5V	GND	1
-	F	E	+12V D	C	-12V B	A	UND Z	PIN

Per PXI Specification R1.0 August 20, 1997, Table 4.10 Signals in Bold are PXI specific

| www.erni.com

2.0 mm ERmet Hard Metric Connector System **PXI Star Trigger Slot Pinout**

	F	E	D	C	В	Α	Z	PIN
-	GND	PXI RSVE22	PXI RSVD22	PXI RSVC22	PXI RSVB22	PXI RSVA22	GND	22
P2/J2	GND	PXI LBR3	PXI LBR2	PXI LBR1	GND	PXI LBRO	GND	21
P2/J2	GND	PXI STAR1	GND	PXI STARO	PXI LBR5	PXI LBR4	GND	20
с	GND	PXI STAR5	PXI STAR4	PXI STAR3	GND	PXI STAR2	GND	19
- U	GND	PXI_TRIG6	GND	PXI TRIG5	PXI TRIG4	PXI TRIG3	GND	18
0	GND	PXI CLK10	PXI CLK10 IN	PRST#	GND	PXI_TRIG2	GND	17
	GND	PXI_CLK10 PXI_TRIG7	GND	DEG#	PXI TRIGO	PXI_TRIG1	GND	16
N	GND	PXILBR6	PXI STAR6	FAL#	GND	PXI BRSVA15	GND	15
	GND	AD[32]	GND	AD[33]	AD[34]	AD[35]	GND	13
N	GND	AD[32] AD[36]	AD[37]	V[I/0]	GND	AD[33]	GND	14
					-			
E	GND	AD[39]	GND	AD[40]	AD[41]	AD[42]	GND	12
	GND	AD[43]	AD[44]	V[I/0]	GND	AD[45]	GND	11
с	GND	AD[46]	GND	AD[47]	AD[48]	AD[49]	GND	10
	GND	AD[50]	AD[51]	V(I/O)	GND	AD[52]	GND	9
т	GND	AD[53]	GND	AD[54]	AD[55]	AD[56]	GND	8
	GND	AD[57]	AD[58]	V(I/O)	GND	AD[59]	GND	7
	GND	AD[60]	GND	AD[61]	AD[62]	AD[63]	GND	6
0	GND	PAR64	C/BE[4]#	V(I/0)	GND	C/BE[5]#	GND	5
_	GND	C/BE[6]#	GND	C/BE[7]#	PXI_BRSVB4	V(I/0)	GND	4
R	GND	PXI_LBR10	PXI_LBR9	PXI_LBR8	GND	PXI_LBR7	GND	3
	GND	PXI_STAR8	PXI_STAR7	SYSEN#	PXI_LBR12	PXI_LBR11	GND	2
	GND	PXI_STAR12	PXI_STAR11	PXI_STAR10	GND	PXI_STAR9	GND	1
	GND	5V	3.3V	ENUM#	REQ64#	5V	GND	25
1	GND	ACK64#	AD[0]	V[I/0]	5V	AD[1]	GND	24
P1/J	GND	AD[2]	5V	AD[3]	AD[4]	3.3V	GND	23
F 1/5	GND	AD[5]	AD[6]	3.3V	GND	AD[7]	GND	22
с	GND	C/BE[0]#	M66#N	AD[8]	AD[9]	3.3V	GND	21
Ĭ	GND	AD[10]	AD[11]	V[I/0]	GND	AD[12]	GND	20
0	GND	AD[13]	GND	AD[14]	AD[15]	3.3V	GND	19
Ĭ	GND	C/BE[1]#	PAR	3.3V	GND	SERR#	GND	18
N	GND	PERR#	GND	SB0#	SDONE	3.3V	GND	17
	GND	LOCK#	STOP#	V(I/O)	GND	DEVSEL#	GND	16
N	GND	TRDY#	GND	IRDY#	FRAME#	3.3V	GND	15
	UND	IIID1#	UND	Key Area	T TPANIE#	0.01	UND	12-14
E	GND	C/BE[2]#	GND	AD[16]	AD[17]	AD[18]	GND	11
	GND	AD[19]	AD[20]	3.3V	GND	AD[10] AD[21]	GND	10
с	GND	AD[19] AD[22]	GND		IDSEL	C/BE[3]#	GND	9
	GND	AD[22] AD[24]	AD[25]	AD[23] V[1/0]	GND	AD[26]	GND	8
т				17.1				7
-	GND	AD[27]	GND	AD[28]	AD[29]	AD[30]	GND	
0	GND	AD[31]	CLK	3.3V	GND	REQ#	GND	6
	GND	GNT#	GND	RST#	BRSVP1B5	BRSVP1A5	GND	5
R	GND	INTS	INTP	V[I/0]	GND	BRSVP1A4	GND	4
- n	GND	INTD#	5V	INTC#	INTB#	INTA#	GND	3
-	GND	TDI	TDO	TMS	5V	TCK	GND	2
	GND	5V	+12V	TRST#	-12V	5V	GND	1
1	F	E	D	C	В	A	Z	PIN

Per PXI Specification R1.0 August 20, 1997, Table 4.11 Signals in Bold are PXI specific

2.0 mm ERmet Hard Metric Connector System VME64x on CompactPCI® J4/P4 and J5/P5 Pin Assignments



	F	E	D	C	В	A	PIN
	GND	D01	D08	D00	+3.3V	ResU(1)	22
P5/J5	GND	D02	D09	+3.3V	ACFAIL*	ResU(1)	21
	GND	BERR*	+3.3V	D10	SYSCLK	GND	20
С	GND	D04	D11	D03	+3.3V	MPR	19
7	GND	D05	D12	+3.3V	SYSFAIL	MCLK	18
0	GND	RTRY1*	+3.3V	D13	SYSRST*	GND	17
1	GND	D07	D14	D06	+3.3V	MSD	16
N	GND	LWORD*	D15	+3.3V	AM5	MMD	15
	GND	DS1*	+3.3V	A23	WRITE*	GND	14
N	GND	A20	A21	A22	+3.3V	MCTL	13
	GND	A18	A19	+V1	AMO	BCLR*	12
E	GND	DS0*	+V2	A17	AMI	GND	11
	GND	A07	A15	A16	+3.3V	BBSY*	10
С	GND	A06	A14	-V1	AM2	BGOIN*	9
	GND	DTACK*	-V2	A13	AM3	GND	8
Т	GND	A04	A12	A05	GAP*	BG00UT*	7
-	GND	A03	A11	GAO*	AM4	BG1IN*	6
0	GND	AS*	GA1*	A10	ResB[z13](2)	GND	5
-	GND	A01	A09	A02	GA2*	BG10UT*	4
R	GND	A24	A08	GA3*	RsvB[z15]	BG2IN*	3
-	GND	RETRY*	GA4*	A25	RsvB[z17]	GND	2
-	GND	A28	A27	A26	+5V	BG20UT*	1
_	GND	A30	A29	+5V	RsvB[z19]	BG3IN*	25
-	GND	RsvB[d19]	+5V	A31	RsvB[z21]	GND	24
P4/J4	GND	D18	D17	D16	+5V	BG30UT*	23
	GND	D20	D19	+5V	RsvB[z23]	BRO*	22
l c	GND	RsvB[d21]	+5V	D21	RsvB[z25]	GND	21
-1 °	GND	D24	D23	D22	+5V	BR1*	20
0	GND	D26	D25	+5V	SERA	BR2*	19
-1 Ŭ	GND	RsvB[d23]	+12V	D27	SERB	GND	18
N	GND	D30	D29	D28	-12V	BR3*	17
	GND	ResB[d25](2)	D31	VPC(2)	SBB	LI/I*(1)	16
N	GND	ResB[z27] ⁽²⁾	GND(3)	ResU(1)	SBA	LI/0*(1)	15
1				Key Are		-/* (/)	12-14
E	GND	IRQ6*	IRQ7*	IACKOUT*	IACKIN*	IACK*	11
1	GND	IRQ1*	IRQ2*	IRQ3*	IRQ4*	IRQ5*	10
c	GND	GND	GND	GND	GND	GND	9
1	GND	UD	UD	UD	UD	UD	8
Т	GND	UD	UD	UD	UD	UD	7
1	GND	UD	UD	UD	UD	UD	6
0	GND	UD	UD	UD	UD	UD	5
-	GND	UD	UD	UD	UD	UD	4
R	GND	UD	UD	UD	UD	UD	3
-	GND	UD	UD	UD	UD	UD	2
1	GND	UD	UD	UD	UD	UD	1
	une	00	00	05	00	00	

Per PICMG 2.2 R1.0 August 7, 1998, Table 1

Notes:

(1) These signals are not bused (feed through the backplane).

(2) ResB is the ResBus (reserved bused) signal pins

Connector Key is Reseda Green (ERNI P/N 043346 male, 043336 female)

2.0 mm ERmet Hard Metric Connector System PMC Mezzanine Card I/O Pin Assignments



PIN	Row F	Row E	Row D	Row C	Row B	Row A	
22	GND	UD	UD	UD	UD	UD	
21	GND	UD	UD	UD	UD	UD	J2
20	GND	UD	UD	UD	UD	UD	
19	GND	UD	UD	UD	UD	UD	С
18	GND	UD	UD	UD	UD	UD	
17	GND	UD	UD	UD	UD	UD	0
16	GND	UD	UD	UD	UD	UD	
15	GND	UD	UD	UD	UD	UD	N
14	GND	+5V	+5V	+3.3V	+3.3V	+3.3V	
13	GND	1	2	3	4	5	N
12	GND	6	7	8	9	10	
11	GND	11	12	13	14	15	E
10	GND	16	17	18	19	20	
9	GND	21	22	23	24	25	С
8	GND	26	27	28	29	30	-
7	GND	31	32	33	34	35	Т
6	GND	36	37	38	39	40	
5	GND	41	42	43	44	45	0
4	GND	46	47	48	49	50	
3	GND	51	52	53	54	55	R
2	GND	56	57	58	59	60	
1	GND	61	62	63	64	VI/O	
PIN	Row F	Row E	Row D	Row C	Row B	Row A	

Single PMC's I/O Signal Mapping to CompactPCI® 3U J2 Connector

Per PICMG 2.3 R1.0 August 7, 1998, Table 1

Notes: 1. Entries in table are of the PMC Jn4 pin number.

2. UD are the remaining user defined I/O pins that can be used for other I/O functions.

Dual PMC Slot's I/O Signal Mapping to CompactPCI® 6U J3/P3 & J4/P4 Connectors

PIN	Row F	Row E	Row D	Row C	Row B	Row A	PMC Slot	J4
9	GND	GND	GND	GND	GND	GND		c
8	GND	1	2	3	4	5	A	ŏ
7	GND	6	7	8	9	10	A	Ň
6	GND	11	12	13	14	15	A	Ν
5	GND	16	17	18	19	20	A	E
4	GND	21	22	23	24	25	A	C T
3	GND	26	27	28	29	30	A	Т
2	GND	31	32	33	34	35	A	0
1	GND	36	37	38	39	40	A	R
19	GND	41	42	43	44	45	A	
18	GND	46	47	48	49	50	A	
17	GND	51	52	53	54	55	A	J3
16	GND	56	57	58	59	60	A	с
15	GND	61	62	63	64	VI/0	A	U U
14	GND	+5V	+5V	+3.3V	+3.3V	+3.3V	A&B	0
13	GND	1	2	3	4	5	В	
12	GND	6	7	8	9	10	В	N
11	GND	11	12	13	14	15	В	N
10	GND	16	17	18	19	20	В	
9	GND	21	22	23	24	25	В	E
8	GND	26	27	28	29	30	В	с
7	GND	31	32	33	34	35	В	Ŭ
6	GND	36	37	38	39	40	В	Т
5	GND	41	42	43	44	45	В	0
4	GND	46	47	48	49	50	В	0
3	GND	51	52	53	54	55	В	R
2	GND	56	57	58	59	60	В	
1	GND	61	62	63	64	VI/O	В	
PIN	Row F	Row E	Row D	Row C	Row B	Row A	PMC Slot	

Per PICMG 2.3 R1.0 August 7, 1998, Table 2

Notes: 1. Entries in table are of the PMC Jn4 pin number.

2.0 mm ERmet Hard Metric Connector System PMC Mezzanine Card I/O Pin Assignments



PIN	Row F	Row E	Row D	Row C	Row B	Row A	
22	GND	1	2	3	4	5	
21	GND	6	7	8	9	10	J5
20	GND	11	12	13	14	15	
19	GND	16	17	18	19	20	С
18	GND	21	22	23	24	25	
17	GND	16	17	18	19	30	0
16	GND	31	32	33	34	35	
15	GND	36	37	38	39	40	N
14	GND	41	42	43	44	45	
13	GND	46	47	48	49	50	N
12	GND	51	52	53	54	55	1
11	GND	1	2	3	4	5	E
10	GND	6	7	8	9	10	
9	GND	11	12	13	14	15	С
8	GND	16	17	18	19	20	_
7	GND	21	22	23	24	25	Т
6	GND	26	27	28	29	30	
5	GND	31	32	33	34	35	0
4	GND	36	37	38	39	40	
3	GND	41	42	43	44	45	R
2	GND	46	47	48	49	50	
1	GND	51	52	53	54	55	
PIN	Row F	Row E	Row D	Row C	Row B	Row A	

Single PMC Slot's I/O Signal Mapping to CompactPCI® J5/P5 Connector

Per PICMG 2.3 R1.0 August 7, 1998, Table 3

Notes: 1. Entries in table are of the PMC Jn4 pin number.

2. UD are the remaining user defined I/O pins that can be used for other I/O functions.

Dual PMC Slot's I/O Signal Mapping to CompactPCI® J5/P5 Connector

PIN	Row F	Row E	Row D	Row C	Row B	Row A	PMC Slot	
22	GND	1	2	3	4	5	A	
21	GND	6	7	8	9	10	A	J5
20	GND	11	12	13	14	15	A	
19	GND	16	17	18	19	20	A	С
18	GND	21	22	23	24	25	A	
17	GND	16	17	18	19	30	A	0
16	GND	31	32	33	34	35	A	
15	GND	36	37	38	39	40	A	N
14	GND	41	42	43	44	45	A	
13	GND	46	47	48	49	50	A	N
12	GND	51	52	53	54	55	A	
11	GND	1	2	3	4	5	В	E
10	GND	6	7	8	9	10	В	
9	GND	11	12	13	14	15	В	C
8	GND	16	17	18	19	20	В	
7	GND	21	22	23	24	25	В	Т
6	GND	26	27	28	29	30	В	
5	GND	31	32	33	34	35	В	0
4	GND	36	37	38	39	40	В	
3	GND	41	42	43	44	45	В	R
2	GND	46	47	48	49	50	В	
1	GND	51	52	53	54	55	В	
PIN	Row F	Row E	Row D	Row C	Row B	Row A	PMC Slot	

Per PICMG 2.3 R1.0 August 7, 1998, Table 4

Notes:

1. Entries in table are of the PMC Jn4 pin number.

2.0 mm ERmet Hard Metric Connector System IP Mezzanine Module I/O Pin Assignments

ERNI

						•		•
	IP Module	Row A	Row B	Row C	Row D	Row E	Row F	PIN
	IP-B	B1	B2	B3	B4	B5	GND	22
J2	IP-B	B6	B7	B8	B9	B10	GND	21
	IP-B	B11	B12	B13	B14	B15	GND	20
С	IP-B	B16	B17	B18	B19	B20	GND	19
	IP-B	B21	B22	B23	B24	B25	GND	18
0	IP-B	B26	B27	B28	B29	B30	GND	17
	IP-B	B31	B32	B33	B34	B35	GND	16
Ν	IP-B	B36	B37	B38	B39	B40	GND	15
	IP-B	B41	B42	B43	B44	B45	GND	14
N	IP-B	B46	B47	B48	B49	B50	GND	13
		+3.3V	+3.3V	+3.3V	+5V	+5V	GND	12
E	IP-A	A1	A2	A3	A4	A5	GND	11
	IP-A	A6	A7	A8	A9	A10	GND	10
С	IP-A	A11	A12	A13	A14	A15	GND	9
_	IP-A	A16	A17	A18	A19	A20	GND	8
т	IP-A	A21	A22	A23	A24	A25	GND	7
_	IP-A	A26	A27	A28	A29	A30	GND	6
0	IP-A	A31	A32	A33	A34	A35	GND	5
_	IP-A	A36	A37	A38	A39	A40	GND	4
R	IP-A	A41	A42	A43	A44	A45	GND	3
	IP-A	A46	A47	A48	A49	A50	GND	2
		+3.3V	+3.3V	+3.3V	+5V	+5V	GND	1
	IP Module	Row A	Row B	Row C	Row D	Row E	Row F	PIN

I/O Signal Mapping to CompactPCI® J2 Connector

Per PICMG 2.4 R1.0 August 7, 1998, Table 1

2.0 mm ERmet Hard Metric Connector System IP Mezzanine Module I/O Pin Assignments



PIN Row F Row E Row D Row C Row B Row A **IP Module** 22 GND D5 D4 D2 D1 IP-D J5 21 GND D10 D9 D7 D6 IP-D D8 С D14 D11 IP-D 20 GND D15 19 GND D20 D19 D18 D17 D16 IP-D ο 18 GND D25 D24 D23 D21 IP-D 17 GND D30 D29 D28 D27 D26 IP-D Ν IP-D GND D34 16 D35 D32 D31 GND D40 D39 D38 D37 IP-D Ν 15 D36 14 GND D45 D44 D43 D42 D41 IP-D Е 13 GND D50 D49 D48 D47 D46 IP-D 12 GND +5V +5V +3.3V +3.3V +3.3V С IP-C 11 GND C5 C4 C3 C2 C1 C7 IP-C 10 C10 C9 C8 C6 GND т C14 IP-C GND 9 C18 C17 IP-C 8 GND C20 C19 C16 ο C23 IP-C 7 GND C25 C24 C21 R 6 GND C30 C29 C28 C27 C26 IP-C 5 GND C35 C34 C33 C32 C31 IP-C 4 GND C40 C39 C38 C37 C36 IP-C 3 GND C45 C44 C43 C42 C41 IP-C GND C48 C47 IP-C 2 C50 C49 C46 GND ±5\/ ±5\/ +3.3V +3.3V +3.3V 25 GND B5 B4 B3 B2 B1 IP-B B7 IP-B 24 GND B10 B9 B8 B6 23 GND B15 B14 B13 B12 B11 IP-B J4 IP-B 22 GND B20 B19 B18 B17 B16 IP-B 21 GND B25 B24 B23 B22 B21 С IP-B 20 GND B30 B29 B28 B27 B26 19 GND B35 B34 B33 B32 B31 IP-B 0 18 GND B40 B39 B38 B37 B36 IP-B 17 GND B45 B44 B43 B42 B41 IP-B Ν 16 GND B50 B49 B48 B47 B46 IP-B Ν 15 GND +5V +5V +3.3V +3.3V +3.3V 12 - 14 Key Area Е GND ΔΔ A2 A1 IP-A 11 A5 A3 10 GND A10 A9 A8 A7 A6 IP-A С A14 A12 IP-A 9 GND A15 A13 A11 8 GND A20 A19 A18 A17 A16 IP-A т 7 GND A25 A24 A23 A22 A21 IP-A ο 8 GND A20 A19 A18 A17 A16 IP-A 7 GND A25 A24 A23 A22 A21 IP-A R 6 GND A30 A29 A28 A27 A26 IP-A A34 A32 IP-A 5 GND A35 A33 A31 4 IP-A GND A40 A39 A38 A37 A36 3 GND A45 A44 A43 A42 A41 IP-A 2 GND A50 A49 A48 A47 A46 IP-A +3.3V +3.3V +3.3V 1 GND +5V +5V IP Module PIN Row C Row F Row E Row D Row B Row A

I/O Signal Mapping to CompactPCI® J5 and J4 Connector

Per PICMG 2.4 R1.0 August 7, 1998, Table 2

I



BELLCORE Requirements Summary

In accordance with Bellcore GR-1217

	CENTRAL OFFICE	UNCONTROLLED ENVIRONMENT
Prequalification Tests for Quality Level II, Level III	Shocks and Vibration - 24 hr., 18 shocks Temperature Life - 500 hr., 85°C Humidity and Temp Cycle - 25°C – 65°C MFG TEST - 10 days, less gas concentration	Shocks and Vibration - 24 hr., 18 shocks Temperature Life - 1,000 hr., 105°C Humidity and Temp Cycle - 5°C – 85°C MFG TEST - 20 days, more gas concentration
Level I	Commercial Grade Vendor Qualification Process	Commercial Grade Vendor Qualification Process
Level II	Level I with: • Tested for less than 1 in 1,000 failures over 10 year life • Monitor parametric attributes • Approved by OEM • Ship to stock allowed • Requalify every 5 years	Level I with: • Tested for less than 1 in 1,000 failures over 10 year life • Monitor parametric attributes • Approved by OEM • Ship to stock allowed • Requalify every 5 years
Level III	Level II with: • Tested for less than 1 in 10,000 failures over 25 year life • Monitor parametric attributes • Ship to stock allowed, provided that connector manufacturer's data are reviewed on lot-on-lot basis • Requalify every 3 years	Level II with: • Tested for less than 1 in 10,000 failures over 25 year life • Monitor parametric attributes • Ship to stock allowed, provided that connector manufacturer's data are reviewed on lot-on-lot basis • Requalify every 3 years

2.0 mm ERmet Hard Metric Connector System Glossary Of Terminology



Annular Ring – The circular area around a hole that is measured by the difference between the radius of the wall of the hole, subtracted from the radius of the clearance or pad around the hole.

ANSI - Abbreviation for American National Standards Institute.

Artwork – The representation of the electrical layout of a printed circuit on a transparency.

 ${\bf Attenuation}$ – When a signal travels along the bus, its amplitude decreases due to energy losses from heating, radiation, and so forth.

AWG – Abbreviation for American Wire Gage. A particular series of specified diameters and thicknesses established as a standard in the U.S.A. and used for nonferrous sheets, rods and wires.

Backplane – (1) A wiring board usually constructed as a printed circuit, used in micro and mini computers to provide the required connections between logic, memory and I/O modules. (2) A two-sided or multilayer printed circuit board into which function cards can be plugged. The backplane transfers signals between the function cards. Mounted on the component side of the backplane are connectors into which function cards can be plugged.

On the solder side of the backplane are termination points (studs, power bugs, quick disconnects) for the distribution of power and ground.

Bellcore – Bell Research Corporation, originally the research division for AT&T.

Bus - A circuit over which data or power is transmitted.

Bus Structure – A set of rules governing the circuit design of a system such as: CompactPCI®, VME, Multibus I, Multibus II and Q-Bus, to name a few.

Characteristic Impedance – Impedance is referred to as Z_o, in ohms. It is the resistance seen by a digital signal and is measured between the signal line and the reference plane. This impedance is a function of the signal line geometry and is independent of the line length. Impedance is the key parameter which interrelates all performance characteristics of the backpanel, including delay, noise and distributed capacitance.

CompactPCI® – A bus structure developed by the PICMG based on the desktop PCI architecture.

Compliant – A pin whose physical structure is designed to elastically deform upon insertion into a hole.

Component Side – The side of a printed wiring board or backplane into which connectors, resistors, capacitors and so forth are inserted.

Component Density – The ratio of the number of components to a given area of a board.

Conductor Width - The width of a given trace.

Conductor Spacing – The distance between adjacent traces on a printed wiring board.

Crosstalk – (1) The interaction observed due to electromagnetic coupling of adjacent conductors. (2) A false signal picked up by a signal line (in an inductive manner) from an adjacent signal line.

Current – The net transfer of electric charge, per unit time, along a conductor. An amount equal to the voltage/resistance and measured in Amperes.

Data Bus – A bus structure used specifically to transmit data, or bits of information.

Date Code – Stamped or printed on a component the week and year the component was made (i.e. 9023 is the 23rd week of the year 1990, or June 3rd-7th, 1990).

Daughter Card - Same as function card or function board.

Decommitted – To physically remove material from an area of a board so as to break the electrical connection to that plane.

Decouple – To prevent transfer or feedback of energy from one circuit to another.

Dielectric – (1) A material which is an electrical insulator that can sustain an electrical field with minimum power loss. (2) Any insulating medium that intervenes between two conductors.

Dielectric Constant – The property of a material that governs the propagation delay of a signal it surrounds, denoted by er.

DIN – (1) Stands for Deutsches Institut fur Normung, a German organization which established many mechanical specifications for connectors and packaging. (2) Vernacular for Standard European connector having 96 pins arranged in 3 rows of 32 pins each. The rows are labeled A, B, C.

DIP – Abbreviation for Dual-In-line Package. A device that has two rows or parallel pins. Usually the pins in each row are on .100" centers.

Discrete Resistor – An individual resistor, as opposed to a resistor network.

Distributed Capacitance – Distributed capacitance, referred to as Co, is the amount of capacitance per unit length of a signal line.

ECL – Abbreviation for Emitter-Coupled-Logic, a form of current-mode logic in which the emitters of two transistors are connected to a current carrying resistor in such a way that only one will turn on at time.

ECTF – The Enterprise Computer Telephony Forum is a trade association that has developed a number of specifications related to computer telephony. Their web address is: http://www.ectf.org.

EIA – Electronics Industry Association.

Т

2.0 mm ERmet Hard Metric Connector System Glossary Of Terminology



2.0 mm ERmet

Etch – To incise an area of a printed wiring board by immersing the board in an acid batch. The parts of the board not covered with an acid-resistant coating will be eroded.

ERNIPRESS – The particular compliant section design utilized by ERNI for many DIN 41612 and D-Sub pressfit contacts. This coined, elastic section provides a very reliable gas tight connection with the plated through hole in the backplane or daughter card.

Eye of the Needle – This is the compliant section design utilized by ERNI for our 2 mm ERmet pressfit contacts. This pierced and colined elastic section provides a very reliable gas tight connection with the plated through hole in the backplane or daughter card.

Function Card – A printed circuit board that plugs into a slot position of a backplane. Function cards can be custom designed by the user or bought as a standard off-the-shelf item. A series of these cards can make up a system or subsystem to run machinery or many other electronic functions.

GND – An abbreviation for ground. The potential referred to as zero volts. An electrical connection between any circuit and the reference potential.

Ground Guard – The pair of traces which surround a third conductor to minimize crosstalk.

Ground Plane – A common conductive surface that receives and returns power/signal transmissions.

Ground Shield – A conductor (usually a plane), at some reference potential (e.g. zero volts), which surrounds some other insulated conductor.

IEC 61076-4-101 – Global specification that governs 2mm Hard Metric equipment practices.

IEC 917 (DIN 43355) – Defines a basic pitch of 0.5 mm, with n x 0.5 mm as the multiple pitch, and a system unit of 25 mm. This, in turn, relates to Hard Metric Equipment practices, IEE 1301 and DIN 43356, used for mechanical arrangement of electrical/electronic equipment, including associated board lay-out and connections.

I/O - Abbreviation for input/output.

IEEE – Abbreviation for the Institute of Electronic and Electrical Engineers.

Impedance – Resistance of a signal line measured in ohms. One of the important electrical characteristics of a backplane, impedance is determined by the physical dimensions of trace width, dielectric thickness, dielectric constant, and so forth.

Inductance – The ratio of the voltage to the rate of change of current in a circuit (V/ Δ L).

Layer – A plane in a printed wiring board which has a copper covering in some specified pattern (e.g. plane, traces and pads).

Microstrip – (1) The name given to a signal line referenced above a single ground plane. (2) The outer etched portion of a backplane transmission line.

Output – The current, voltage, power, or signal which a circuit or device delivers.

Terminals where a device delivers its information.

Pad – The circular area that commits a hole to an uncommitted layer or trace.

PCMCIA – (Personal Computer Memory Card International Association). A standard for removable cards.

PICMG – The PCI Industrial Computer Manufacturer's Group is a trade association that has developed a number of specifications related to personal computer architectures and CompactPCI. Their web address is http://www.picmg.org.

Pin-out – A term used to describe the actual connections for each pin of a connector on a printed wiring board.

Plated through-hole – A hole in a printed wiring board, used to commit external or internal layers to one another produced by electro deposition of a conductive pattern.

Plating – To form a thin, adherent layer of material (usually metal) on an object.

PMC - PCI mezzanine card interface, defined by IEEE 1386

Pressfit – An interference connection used in the assembly process to eliminate the need for solder to make the electrical connection.

Propagation Delay – (1) Referred to as tpd, commonly expressed in nanoseconds per inch (ns/in.). It is the time required for a pulse to travel through a transmission line system. (2) The time it takes for a signal to spread or distribute across an entire circuit.

Rack – (See Subrack) – A sheet metal assembly that is made up of mounting bars and side plates to which a backplane can be mounted and printed wiring boards can be inserted

Resistance – The opposition that a material or device offers to the flow of current, equal to the voltage drop across the element, divided by the current through the element.

RFI - Radio Frequency Interference.

Risetime – Often designated as tr, in picoseconds. It is the time it takes the signal to transition from 10 percent to 90 percent of its' final value.

Skew – The time difference between the arrival of two related signals, often due to differences in their propagation paths.

Shroud – A male connector body designed to fit over the extended tails of a long tail connector which allows a female connector to be mated from the rear side for midplane or rear I/O applications.

2.0 mm ERmet Hard Metric Connector System Glossary Of Terminology



Signal – An electrical pulse which conducts across a backplane.

Solder or Extended Tail – A term used to specify the length of the pins on any connector. Typically the pins will protrude through the printed wiring board. Extended pins extend much further.

Solder Mask – The coating on a printed wiring board, placed there for protection. Also aids in assembly and soldering.

S-Parameters – A popular mathematical representation of high frequency characteristics of a component such as a connector utilized for signal integrity measurement and analytical techniques. Often utilized in applications where SPICE modeling is not practical.

SPICE – Software Program for Integrated Circuit Emulation. One of several computer based techniques for simulating the electrical performance of various circuit components such as connectors and integrated circuits within a actual or theoretical circuit configuration.

Stripline – (1) The name given to a signal, referenced between two ground planes, at a defined spacing. (2) The etched portion of a backplane transmission line that is between two ground planes in a multilayer printed circuit board.

Subrack – A card cage assembly, usually designed to support a backplane, card guides and daughter cards.

Terminated – A line or trace is considered terminated at any point there is a resistor connected to it.

Tolerance – The permissible variations in the dimensions of manufactured parts or electrical components.

Trace – The conductor that physically joins two or more points on a printed wiring board.

Transition Board - A perpendicular board assembly used to plug into extended connector terminals on the rear side of the backplane as in mid plane chassis designs or when it is not desirable to utilize cables to interface to the rear connectors.

Transmission Line – A line is referred to as a transmission line when its capacitance and inductance are distributed over the line. Such a line will convey a signal without distortion and will appear as a purely resistive input impedance. TTL – Transistor-Transistor Logic. A logic circuit containing two transistors, for driving large output capacitances at high speed.

Two Sided – A printed wiring board with only the outer layers containing traces. This product may or may not contain plated through holes.

 ${\rm \textbf{U}}$ – An EIA unit of measurement equal to 1.75" for equipment racks.

Un-terminated - Any bussed trace that is not connected.

Vcc – Typically, the collector voltage level for a transistor. The designation of the primary voltage level on a printed wiring board, usually at the potential of +5 volts.

Via – A plated through-hole that is there for the sole purpose of conducting a signal trace or potential from one layer of the printed wiring board to another.

VITA – The VME International Trade Association is a trade association that supports VME and other imbedded industry computer manufacturers. It also supports an ANSI recognized standards producing organization, the VSO. VITA's web address is http://www.vita.com

VME – The initials for the backplane bus architecture known as Versa-Module -Europa.

Voltage – The electromotive force determined by the potential difference between two conductors, measured in volts.

VSO – The VITA Standards Organization. An ANSI recognized standards producing organization concerned with computer architectures. See VITA.

Wirewrap – A termination technique, used mainly to prototype computers and computer systems, identifiable by the presence of elongated pins to which signal wires and voltage and ground connections can be created.

2.0 mm ERmet Hard Metric Connector System ERNI Customer Request Form

If you need a specially loaded configuration for your application, please use this form. Fill out the grid diagram for the connector style you desire (A, B, C, or M) and mark which pin (A, B, C, D, E, F, K, L, M, N, P, Q, R, S or T) is required in each position. Unloaded positions or rows may be left blank.

Connector Type A



Connector Type B

25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	
Γ) z
																									a
]b
] c
] d
																									e
Ľ																									ļf

Connector Type C

_
]z
a
b
C
d
e
ļf

Connector with location peg

Connector Type M

2	25	24	23	22	21	20	19	18	17	16	15	
Ì												2
												ΠĪ.
ļ												i
╞		_						_				j
ł						_	_	_				D٢
ł								-				4
4												

Connector without location peg

	Name:		Tel:	Ext
	Title:		Fax:	
	Company:		E-mail:	
	Address:			
	City:		State:	Zip:
I	Catalog E 074484 04/10	Edition 9	www.erni.com	

Date Submitted



Sam	ole Qty	. Requi	red		
Date	Sampi	les Nee	ded		
Estin	nated A	Innual L	Jsage		
Spec	ial Man	kings or	Other I	Requirer	ments

297



2.0 mm ERmet Hard Metric Connector System **ERNI Customer Request Form**



If you need a specially loaded configuration for your application, please use this form. Fill out the grid diagram for the connector style you desire and mark which pin (A, B, C, D, E, F, K, L, M, N, P, Q, R, S or T) is required in each position. Unloaded positions or rows may be left blank.

Connector Type D





115

Connector Type E

25	24	23	22	21	20	19	18	17	16	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	
Γ																								Γ) z
																									a
																									b
																									C
								_			-	_										_			d
\vdash								_	-	_	-	-	_			-					_	-	_		e e
	-							-	-	-	⊢	-	-	-		-					-	-	-	-	
	-								-	-	\vdash	-	-	-								-	-		g h
																									J''

Connector Type F



	Connector	with	location	peg
--	-----------	------	----------	-----

Connector without location peg

Name:	Tel:		Ext
Title:	Fax:		
Company:	E-mail:		
Address:			
City:	State:		Zip:
298	Catalog E 074484 04/10	Edition 9	www.erni.com



Special Markings or Other Requirements

I

2.0 mm ERmet Hard Metric Connector System ERNI Customer Request Form

If you need a specially loaded configuration for your application, please use this form. Fill out the grid diagram for the connector style you desire and mark which pin (A, B, C, D, E, F, K, L, M, N, P, Q, R, S or T) is required in each position. Unloaded positions or rows may be left blank.

Date Submitted

Monoblock Connector

47 46	45 4	14 43	3 42	41	40	39	38	37	1	33	32	31	30	29	28	27	26	25	24	23	22	21	20	19 1	81	7 16	6 1 5	14	13	12 -	111	0	9	8	7	6	5	4	3	2	1	
\square			Ι						Ċ,																		Ι						Т	Т	Т	Т					-	Z
										-																																а
																																		Τ								b
									, ta																																	С
									¬凶r																																	d
																																										е
Ш																																									_	f
																																		-	_	_		_	_	_		



Samp	le Qty. Requir	ed
Date S	Samples Nee	ded
Estima	ated Annual L	Isage
Specia	al Markings or	Other Requirements

Name:		Tel:	Ext
Title:		Fax:	
Company:		E-mail:	
Address:			
City:		State:	Zip:
Catalog E 074484 04/10	Edition 9	www.erni.com	:

ΞN







2.0 mm ERmet Hard Metric Connector System Right Angle Male Connectors Type A for Daughter Cards





Dimensional Drawing

The ERmet type A right angle male connector provides 110 contacts in a 5 row x 25 position (3 positions used by multifunction cavity), fully loaded configuration.

The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated upper ground return shield and without integrated upper ground return shield.

The ERmet type A right angle male connector has a multifunction cavity that incorporates pre-alignment guides and accepts optional coding keys. This connector is designed to be used alone or in conjunction with either a type B or C.

Sequential mating can be achieved by the use of the three available configurations listed below. The available chicklet configurations are denoted A, B, and C, to correspond with the contact mating lengths found in ERmet 2mm male connectors. Within each chicklet, the contact mating length will always be the same and the shield pins will always be Level 3.







2.0 mm ERmet Hard Metric Connector System **Right Angle Male Connectors Type A for Daughter Cards**



Part Number

923761

Ordering Information

Configuration





Shielding

without shield

Positions

25

2.0 mm ERmet Hard Metric Connector System **Right Angle Male Connectors Type B for Daughter Cards**





The ERmet type B right angle male connector provides 125 contacts in a 5 row x 25 position fully loaded configuration. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated upper ground return shield and without integrated upper around return shield.

The ERmet type B right angle male connector has an uninterrupted pin field with no multifunction cavity. This connector is not designed to be used alone, but is intended to be used in conjunction with either a type A or C ERmet connector.

Sequential mating can be achieved by the use of the three available configurations listed below. The available chicklet configurations are denoted A, B, and C, to correspond with the contact mating lengths found in ERmet 2mm male connectors. Within each chicklet, the contact mating length will always be the same and the shield pins will always be Level 3.

Dimensional Drawing





CONTACT LENGTH EXAMPLES



\$ 0.1

All dimensions in mm

2.0 mm ERmet Hard Metric Connector System Right Angle Male Connectors Type B for Daughter Cards



Ordering Information

Configuration	Shielding	Positions	Part Number
Туре В	without shield	25	923766
Туре В	without shield	25	923764
25 24 22 21 20 19 18 17 16 15 14 13 12 11 10 9 7 6 5 4 3 2 1 B			
Туре В	without shield	25	923768
Туре В	with shield	25	923767
Туре В	with shield	25	923765
25 24 23 22 12 19 18 17 16 15 14 13 12 11 10 9 7 6 5 4 3 2 1 0			
Туре В	with shield	25	923769
25 24 23 22 21 20 19 18 17 16 15 14 13 12 11 10 9 8 7 6 5 4 3 2 1 C C C C C C C C C C C C C C C C C C C			

2.0 mm ERmet Hard Metric Connector System Right Angle Male Connectors Type C for Daughter Cards





The ERmet type C male connector provides 55 contacts in a 5 row x 11 position fully loaded configuration. The connector is designed for gas tight, pressfit installation and is provided in two different configurations: with integrated upper ground return shield and without integrated upper ground return shield.

The ERmet type C female connector has pre-alignment guides. This connector can be used alone or in conjunction with either a type A, B, L, M or N ERmet connector, however it can only be installed at the lower end of a connector row.

Sequential mating can be achieved by the use of the three available configurations listed below. The available chicklet configurations are denoted A, B, and C, to correspond with the contact mating lengths found in ERmet 2mm male connectors. Within each chicklet, the contact mating length will always be the same and the shield pins will always be Level 3.

Dimensional Drawing



BOARD HOLE PATTERN (COMPONENT MOUNTING SIDE)





CONTACT LENGTH EXAMPLES



2.0 mm ERmet Hard Metric Connector System Right Angle Male Connectors Type C for Daughter Cards



Ordering Information



T





General

In the case of modern boards with SMT population, 2.0 mm H.M. ERmet thru hole reflow (THR) female connectors have been developed. The connectors have been designed for fully automatic SMT assembly. Safe positioning before the SMT soldering process is ensured by means of kinked terminations.

For fully automatic feed-in into the automatic assembly machines, the connectors are supplied in a tray packaging. The high temperature resistant thermoplastic of the insulation body allows for the use of all standard reflow processes.

Technical Characteristics

- Pitch: 2.0 mm
- Modules: A, B, C, AB
- Current rating: 1.5 A (20 °C)
- Air- and creepage distance: 0.6 mm
- Mating cycles: > 250
- Materials: Insulator: LCP Contact: Cu alloy
- Plating: Mating area: Gold plated Termination area: Sn
- PCB-Layout: conform to pressfit Female Connectors
- Tray packaging

2.0 mm ERmet Hard Metric Connector System ERmet Thru Hole Reflow (THR) Female Connectors



Ordering Information

Configuration	Number of Pins	Termination	Partnumber
Type A without Shield	110	THR	124698
Type A with Shield	110	THR	223214
Type AB without Shield	125	THR	123700
Type AB with Shield	125	THR	154876
Type AB 22 with Shield	110	THR	174402
Type B without Shield	125	THR	124699
Type B with Shield	125	THR	154875
Type B 22 without Shield	110	THR	123768
Type B 22 with Shield	110	THR	154872
Type B 19 without Shield	95	THR	154673
Type B 19 with Shield	95	THR	123796
Type C without Shield	55	THR	223385
Type C with Shield	55	THR	223386

2.0 mm ERmet Hard Metric Connector System CompactPCI Connectors acc. to PIGMG 2.0 Rev. 3.0





General

Late in 1999 PCI Industrial Computer Manufacturers Group (PICMG) introduced the new revision 3.0 of the CompactPCI Core Specification. Version 3.0 of this specification comprises a.o. hot swap and computer telephony specifications such as pin sequencing. For CompactPCI, the metric ERmet connectors are specified in accordance with IEC 61076-4-101 which are available in build types A. B. AB, and as monoblock versions. This new version of the CompactPCI specification has the consequence a.o. that for 3 HE backplanes on position P2 a male connector, build type B with long connection pins for AB transfer and AB

shrouds are inserted into position rP2. At the rear card end, on position rJ2, a sheilded female connector in build type AB is specified. For 6 HE backplanes, on P3 and P5, the male connector - build type B with long connection pins for AB transfer and AB shrouds have to be inserted into positions rP3 and rP5. At the rear card end, on positions rJ3 and rJ5, a shielded female connector, build type AB, has been specified here. On P4, a blade contact strip, build type A with long connection pins for A shroud and A shroud frames, has been specified on position rP4. For the rear card end, a shielded female connector, build type A, has been defined on rJ4. For male connectors with shrouds in build types A and B, the specification only requires a series a grounding for the upper screening panel. All necessary connectors required in accordance with the new CompactPCI specification are available from FRNI. In addition, for CompactPCI applications, ERNI also offers an

economic solution for a male connector with long terminal pins, which is populated with shield contacts on row a only. In addition to the new AB compatible male connectors for CompactPCI, ERNI also supplies shrouds. Here, all shrouds are available in four different heights (3.9 mm, 4.5 mm, 5.3 mm, and 6.1 mm) in order to adapt to the printed circuit board thickness of the backplanes.



309

2.0 mm ERmet Hard Metric Connector System CompactPCI Connectors acc. to PIGMG 2.0 Rev. 3.0



Ordering Informations

Male Connectors For Backplanes	Location On The PCB	Number Of Positions*	Contact Loading*	Part Number
Type A With Peg	P1	25	CBBC	923190
Type A With Peg And Extended Terminals				
For Shrouding	P1 Special	25	TPPT	923197
Type A Without Peg And With Extended Terminals				
For Shrouding	P1	25	TSST	923342
Type B (AB Compatible) With Extended Terminals				
For Shrouding	P2, P5	22	TSSSSS-	923345
Type B (AB Compatible) With Extended Terminals				
For Shrouding	P3	19	TSSSSST	923341
Type B (AB Compatible) With Extended Terminals				
For Shrouding	P3	19	TSSSSS-	923346
Type A With Extended Terminals For Shrouding	P4	25	SST	923347
Type A With Peg And Extended Terminals				
For Shrouding	P4	25	TRRRRRT	064688
Type A With Peg And Extended Terminals				
For Shrouding	P4	25	TSSSSST	103975
Type A Without Peg	P4 Telecom	25		923160
Type A Without Peg And With Extended Terminals				
For Shrouding	P4 Telecom	25		923212
Type B (AB Compatible) With Extended Terminals				
For Shrouding	P5 Telecom	22		923339
Type B (AB Compatible) With Extended Terminals				
For Shrouding	P2, P5	22	TSSSSST	923340

Female Connectors For Daughter Cards	Location On The PCB	Number Of Positions*	Part Number
Type A With Shield, Without Peg	J1, J4	25	064176
Type A With Split Shield, Partially Loaded	J4 Telecom	25	140512
Type A With Split Shield, Partially Loaded	rJ4 Telecom	25	104697
Type AB With Shield, Without Peg	rJ2, rJ5	22	114809
Type AB With Shield, Without Peg	rJ3	19	114810
Type B With Upper Shield	J2, J5	22	064785
Type B With Upper Shield	J3	19	064784

Shrouds For Male Connectors	Location On The PCB	Number Of Positions*	Height	Part Number
Type A Shroud 25 Positions	rP1, rP4	25	14.35	114436
Type A Shroud 25 Positions	rP1, rP4	25	14.95	054795
Type A Shroud 25 Positions	rP1, rP4	25	15.75	054794
Type A Shroud 25 Positions	rP1, rP4	25	16.55	054793
Type AB Shroud 22 Positions	rP2, rP5	22	14.95	114426
Type AB Shroud 22 Positions	rP2, rP5	22	15.75	114427
Type AB Shroud 22 Positions	rP2, rP5	22	16.55	114428
Type AB Shroud 19 Positions	rP3	19	14.35	114487
Type AB Shroud 19 Positions	rP3	19	14.95	114488
Type AB Shroud 19 Positions	rP3	19	15.75	114489
Type AB Shroud 19 Positions	rP3	19	16.55	114490

Coding Keys	Application	Code Number	Color	Part Number
Coding Keys For Male Connectors And Shrouds	5.0 Volts P1	1567	Brilliant Blue	043347
Coding Keys For Male Connectors And Shrouds	3.3 Volts P1	3456	Cadmium Yellow	043345
Coding Keys For Male Connectors And Shrouds	Telecom P4	1248	Strawberry Red	043350
Coding Keys For Female Connectors	5.0 Volts J1	2348	Brilliant Blue	043337
Coding Keys For Female Connectors	3.3 Volts P1	1278	Cadmium Yellow	043335
Coding Keys For Female Connectors	Telecom J4	3567	Strawberry Red	043340

* Length = 50mm Pitch = 2.0mm => 50 / 2 = 25 Positions

**Cross Sectional Loading From Z To F

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

ERNI Electronics:

<u>114437</u> <u>114015</u> <u>104790</u> <u>064219</u> <u>114231</u> <u>064690</u> <u>220012</u> <u>064783</u> <u>220027</u> <u>220174</u> <u>220173</u>



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный) **Факс:** 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.