DATASHEET

3mm Infrared LED

EAILP03RDAA7



Features

- High reliability
- 2.54mm lead spacing
- Low forward voltage
- Good spectral matching to Si photodetector
- High radiant intensity
- Pb free
- The product itself will remain within RoHS compliant version.

Description

Everlight Americas infrared emitting (EAILP03RDAA7)
is a high intensity diode, molded in a water cleat plastic package.
The device is spectrally matched with phototransistor, photodiode and infrared receive module.

Applications

- Infrared applied system

Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx

Device Selection Guide

LED Part No.	Chip Material	Lens Color
EAILP03RDAA7	GaAlAs	Water clear

Absolute Maximum Ratings (Ta=25℃)

Parameter	Symbol	Rating	Unit
Continuous Forward Current	I_F	100	mA
Peak Forward Current *1	I_{FP}	1.0	A
Reverse Voltage	V_R	5	V
Operating Temperature	T_{opr}	-40~ +85	℃
Storage Temperature	T_{stg}	-40 ~ +100	℃
Soldering Temperature *2	T_{sol}	260	℃
Power Dissipation at(or below) 25℃ Free Air Temperature	P_d	150	mW

Notes: *1:I_{FP} Conditions--Pulse Width≦100μs and Duty≦1%.

*2:Soldering time≦5 seconds.


Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx

Electro-Optical Characteristics (Ta=25℃)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Condition
Radiant Intensity	IE	2.8	4.0	-	mW/sr	I_F=20mA
Peak Wavelength	λp	-	940	-	nm	I_F=20mA
Spectral Bandwidth	Δλ	-	45	-	nm	I_F=20mA
Forward Voltage	V_F	-	1.2	1.5	V	I_F=20mA
Reverse Current	I_R	-	-	10	μA	V_R=5V
View angle	2θ1/2	-	50	-	degree	I_F=20mA


Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx

Fig.1 Forward Current vs. Ambient Temperature



Ambient Temperature(℃)

Fig.2 Spectral Distribution



Wavelength λ (nm)

Fig.3 Radiant Intensity vs. Forward Current






Fig.4 Relative Radiant Intensity vs. Angular Displacement



Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx


Package Dimension



Notes: 1. All dimensions are in millimeters
2. Tolerances unless dimensions ±0.25mm

Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx


Label Form Specification




- CPN: Customer's Product Number
- P/N: Product Number
- QTY: Packing Quantity
- CAT: Luminous Intensity Rank
- HUE: Dom. Wavelength Rank
- REF: Forward Voltage Rank
- LOT No: Lot Number
- Reference: Identify Label Number

Packing Specification


■ Anti-electrostatic bag



■ Inner Carton



■ Outside Carton



■ Packing Quantity

1. 1000 PCS/1 Bag, 4 Bags/1 Inner Carton
2. 10 Inner Cartons/1 Outside Carton

Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx

Notes


1. Lead Forming
   - During lead formation, the leads should be bent at a point at least 3mm from the base of the epoxy bulb.
   - Lead forming should be done before soldering.
   - Avoid stressing the LED package during leads forming. The stress to the base may damage the LED's characteristics or it may break the LEDs.
   - Cut the LED lead frames at room temperature. Cutting the lead frames at high temperatures may cause failure of the LEDs.
   - When mounting the LEDs onto a PCB, the PCB holes must be aligned exactly with the lead position of the LED. If the LEDs are mounted with stress at the leads, it causes deterioration of the epoxy resin and this will degrade the LEDs.

2. Storage
   - The LEDs should be stored at 30°C or less and 70%RH or less after being shipped from Everlight Americas and the storage life limits are 3 months. If the LEDs are stored for 3 months or more, they can be stored for a year in a sealed container with a nitrogen atmosphere and moisture absorbent material.
   - Please avoid rapid transitions in ambient temperature, especially, in high humidity environments where condensation can occur.

3. Soldering
   - Careful attention should be paid during soldering. When soldering, leave more then 3mm from solder joint to epoxy bulb, and soldering beyond the base of the tie bar is recommended.
   - Recommended soldering conditions:

Hand Soldering		DIP Soldering	
Temp. at tip of iron	300℃ Max. (30W Max.)	Preheat temp.	100℃ Max. (60 sec Max.)
Soldering time	3 sec Max.	Bath temp. & time	260 Max., 5 sec Max
Distance	3mm Min.(From solder joint to epoxy bulb)	Distance	3mm Min. (From solder joint to epoxy bulb)

   - Recommended soldering profile



Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx

- Avoiding applying any stress to the lead frame while the LEDs are at high temperature particularly when soldering.
- Dip and hand soldering should not be done more than one time
- After soldering the LEDs, the epoxy bulb should be protected from mechanical shock or vibration until the LEDs return to room temperature.
- A rapid-rate process is not recommended for cooling the LEDs down from the peak temperature.

Although the recommended soldering conditions are specified in the above table, dip or hand soldering at the lowest possible temperature is desirable for the LEDs.

- Wave soldering parameter must be set and maintain according to recommended temperature and dwell time in the solder wave.

4. Cleaning
   - When necessary, cleaning should occur only with isopropyl alcohol at room temperature for a duration of no more than one minute. Dry at room temperature before use.
   - Do not clean the LEDs by the ultrasonic. When it is absolutely necessary, the influence of ultrasonic cleaning on the LEDs depends on factors such as ultrasonic power and the assembled condition. Ultrasonic cleaning shall be pre-qualified to ensure this will not cause damage to the LED
5. Heat Management
   - Heat management of LEDs must be taken into consideration during the design stage of LED application. The current should be de-rated appropriately by referring to the de-rating curve found in each product specification.
   - The temperature surrounding the LED in the application should be controlled. Please refer to the data sheet de-rating curve.
6. ESD (Electrostatic Discharge)
   - Electrostatic discharge (ESD) or surge current (EOS) can damage LEDs.
   - An ESD wrist strap, ESD shoe strap or antistatic gloves must be worn whenever handling LEDs.
   - All devices, equipment and machinery must be properly grounded.
   - Use ion blower to neutralize the static charge which might have built up on surface of the LEDs plastic lens as a result of friction between LEDs during storage and handing.
7. Other
   - Above specification may be changed without notice. Everlight Americas will reserve authority on material change for above specification.
   - When using this product, please observe the absolute maximum ratings and the instructions for using outlined in these specification sheets. Everlight Americas assumes no responsibility for any damage resulting from use of the product which does not comply

     with the absolute maximum ratings and the instructions included in these specification sheets.
   - These specification sheets include materials protected under copyright of Everlight Americas corporation. Please don't reproduce or cause anyone to reproduce them without t Everlight Americas's consent.

Copyright © 2010, Everlight Americas Inc. Release Date : 05.13.2014. Issue No:DIR-000xxx


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.