

SPECIFICATION

| | |
|--------------|--|
| Part No. | : FXP831.07.0100C |
| Product Name | : FXP.831 Freedom 2.4/4.9-6GHz Ground Coupled Antenna |
| Feature | : Flexible Ultra Low Profile 45mm*7mm*0.1mm Adheres directly to inside of product plastic or glass housing Form factor and cable routing convenient for integration High Efficiency IPEX MHF Connector (U.FL compatible) 100m 1.37mm co-axial cable RoHS Compliant |



1. Introduction

The FXP831 is a high efficiency, small, dual-band, dipole antenna for 2.4/4.9-6GHz band including DSRC, V2V, WiFi, Bluetooth, Zigbee and other applications in these bands. The FXP.831 has a peak gain of 2.5dBi at 2.4GHz and efficiencies of 56%, and 4.5dBi and 55% along bands 4.9GHz to 6GHz.

This Taoglas patent pending antenna is unique in the market because it is made from poly-flexible material, has a tiny form factor (45*7*.01mm) and has double-sided 3M tape for easy “peel and stick” mounting.

The cable routes conveniently directly out of the bottom of the antenna, reducing the volume the antenna takes up in the device to an absolute minimum compared to other designs. The FXP.831 is the ideal all-round antenna solution for squeezing into narrow spaces and still maintaining high performance, for example on the inside top or adjacent side applied directly to the plastic housing of LCD devices.

Many module manufacturers specify peak gain limits for any antennas that are to be connected to that module. Those peak gain limits are based on free-space conditions. In practice, the peak gain of an antenna tested in free-space can degrade by at least 1 or 2dBi when put inside a device. So ideally you should go for a slightly higher peak gain antenna than mentioned on the module specification to compensate for this effect, giving you better performance.

Upon testing of any of our antennas with your device and a selection of appropriate layout, integration technique, or cable, Taoglas can make sure any of our antennas' peak gain will be below the peak gain limits. Taoglas can then issue a specification and/or report for the selected antenna in your device that will clearly show it complying with the peak gain limits, so you can be assured you are meeting regulatory requirements for that module.

For example, a module manufacturer may state that the antenna must have less than 2dBi peak gain, but you don't need to select an embedded antenna that has a peak gain of less than 2dBi in free-space. This will give you a less optimized solution. It is better to go for a slightly higher free-space peak gain of 3dBi or more if available. Once




that antenna gets integrated into your device, performance will degrade below this 2dBi peak gain due to the effects of GND plane, surrounding components, and device housing. If you want to be absolutely sure, contact Taoglas and we will test. Choosing a Taoglas antenna with a higher peak gain than what is specified by the module manufacturer and enlisting our help will ensure you are getting the best performance possible without exceeding the peak gain limits.

2. Specification

| ELECTRICAL | | |
|---------------------------|----------------------------|--------------|
| Frequency | 2.4 ~ 2.5GHz, | 4.9 ~ 6.0GHz |
| Peak Gain (free space) | 2.5dBi | 4.5dBi |
| Peak Gain (on plastic*) | 3.0dBi | 5.5dBi |
| Average Gain (free space) | -2.6dBi | -2.6dBi |
| Average Gain (on plastic) | -2.6dBi | -1.8dBI |
| Efficiency (free space) | 56% | 55% |
| Efficiency (on plastic) | 56% | 75% |
| VSWR | ≤2.5 : 1 | |
| Impedance | 50 Ohms | |
| Polarization | Linear | |
| Radiation Pattern | Omni | |
| Input Power | 2W max. | |
| MECHANICAL | | |
| Dimensions | 45mm x 7mm | |
| Antenna Body Material | Polymer | |
| Cable | Gray 100mm 1.37 co-axial | |
| Connector | Ipex MHF | |
| ENVIRONMENTAL | | |
| Temperature Range | -40°C to 85°C | |
| Humidity | Non-condensing 65°C 95% RH | |

3. Electrical Characteristic


3.1 S11




3.2 Test Setup

A ETS AMS-8500 test chamber is used for the free space radiation testing for FXP831.07.0100A. The measurement is taken with the antenna properly mounted in the designated device

Device tested in AMS-8500 Rectangular test chamber.




FXP831 on Baxter device to indicate the testing coordinate




FXP831 on Baxter device to indicate the testing coordinate

3.3 Radiation Pattern


3.3.1 XZ plane (at 2400MHz)




3.3.2 XZ plane (at 2500MHz)




3.3.3 XZ plane (at 5000MHz)




3.3.4 XZ plane (at 5500MHz)




3.3.5 XZ plane (at 6000MHz)




3.3.6 YZ plane (at 2400MHz)




3.3.7 YZ plane (at 2500MHz)




3.3.8 YZ plane (at 5000MHz)




3.3.9 YZ plane (at 5500MHz)




3.3.10 YZ plane (at 6000MHz)




3.3.11 XY plane (at 2400MHz)




3.3.12 XY plane (at 2500MHz)




3.3.13 XY plane (at 5000MHz)




3.3.14 XY plane (at 5500MHz)




3.3.15 XY plane (at 6000MHz)



3.4 Peak Gain





3.5 Efficiency



4. Mechanical


4.1 Antenna Dimension



| | Name | Material | Finish | QTY |
|---|-------------------------|-----------|-------------|-----|
| ① | FXP831 PCB | FPCB 0.1t | Black | 1 |
| ② | 1.37 Mini-Coaxial Cable | FEP | Gray | 1 |
| ③ | IPEX MHF1 | Brass | Gold | 1 |
| ④ | Double-Sided Adhesive | 3M 467 | Brown Liner | 1 |

5. Packaging

5.1 Package



Taoglas makes no warranties based on the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice.

Taoglas reserves all rights to this document and the information contained herein. Reproduction, use or disclosure to third parties without express permission is strictly prohibited. Copyright © 2012, Taoglas Ltd.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.