19-3020; Rev 1; 4/10

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

General Description

The MAX6921/MAX6931 are 20-output, 76V, vacuum-fluorescent display (VFD) tube drivers that interface a multiplexed VFD tube to a VFD controller, such as the MAX6850–MAX6853, or to a microcontroller. The MAX6921/MAX6931 are also ideal for driving static VFD tubes or telecom relays.

Data is input using an industry standard 4-wire serial interface (CLOCK, DATA, LOAD, BLANK), compatibile with either Maxim's or industry-standard VFD driver and controller.

For easy display control, the active-high BLANK input forces all driver outputs low, turning the display off, and automatically puts the MAX6921/MAX6931 into shut-down mode. Display intensity can also be controlled by directly pulse-width modulating the BLANK input.

The MAX6921 has a serial interface data output, DOUT, allowing any number of devices to be cascaded on the same serial interface.

The MAX6931 has a negative supply voltage input, V_{SS}, allowing the drivers' output swing to be made bipolar to simplify filament biasing in many applications.

The MAX6921 is available in 28-pin TSSOP, SO, and PLCC packages. The MAX6931 is available in a 28-pin TSSOP package.

Maxim also offers 12-output VFD drivers (MAX6920) and 32-output VFD drivers (MAX6922/MAX6932).

Features

- **5MHz Industry-Standard 4-Wire Serial Interface**
- **3V to 5.5V Logic Supply Range**
- **8V to 76V Grid/Anode Supply Range**
- **-11V to 0V Filament Bias Supply (MAX6931 Only)**
- **Push-Pull CMOS High-Voltage Outputs**
- **Outputs can Source 40mA, Sink 4mA Continuously**
- **Outputs can Source 75mA Repetitive Pulses**
- **Outputs can be Paralleled for Higher Current Drive**
- **Any Output can be Used as a Grid or an Anode Driver**
- **Blank Input Simplifies PWM Intensity Control**
- **Small 28-Pin TSSOP Package**
- **-40°C to +125°C Temperature Range**

Ordering Information


PART	TEMP RANGE	PIN-PACKAGE
MAX6921AUI+	-40°C to +125°C	28 TSSOP
MAX6921AWI/V+	-40°C to +125°C	28 Wide SO
MAX6921AQI+	-40°C to +125°C	28 PLCC
MAX6931AUI+	-40°C to +125°C	28 TSSOP

+Denotes a lead-free(Pb)/RoHS-compliant package.
/V denotes an automotive qualified part.

Applications

White Goods	Industrial Weighing
Gaming Machines	Security
Automotive	Telecom
Avionics	VFD Modules
Instrumentation	Industrial Control

Typical Operating Circuit



Pin Configurations appear at end of data sheet.

For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

ABSOLUTE MAXIMUM RATINGS

Voltage (with respect to GND)
V_{BB} .....-0.3V to +80V
V_{CC} .....-0.3V to +6V
V_{SS} (MAX6931 only).....-12V to +0.3V
V_{BB} - V_{SS} (MAX6931 only) .....-0.3V to +80V
OUT_ (MAX6921 only) .....(GND - -0.3V) to (V_{BB} + 0.3V)
OUT_ (MAX6931 only) .....(V_{SS} - -0.3V) to (V_{BB} + 0.3V)
All Other Pins.....-0.3V to (V_{CC} + 0.3V)
OUT_ Continuous Source Current .....-45mA
OUT_ Pulsed (1ms max, 1/4 max duty) Source Current ...-80mA
Total OUT_ Continuous Source Current .....-540mA
Total OUT_ Continuous Sink Current 90mA
Total OUT_ Pulsed (1ms max, 1/4 max duty)
Source Current .....-960mA
OUT_ Sink Current 15mA
CLK, DIN, LOAD, BLANK, DOUT Current .....±10mA

Continuous Power Dissipation (T_A = +70°C)
28-Pin TSSOP (derate 12.8mW/°C over +70°C).....1025mW
28-Pin Wide SO (derate 12.5mW/°C over +70°C).....1000mW
28-Pin PLCC (derate 10.5mW/°C over +70°C).....842mW
Operating Temperature Range (T_{MIN} to T_{MAX}) .....-40°C to +125°C
Junction Temperature.....+150°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering, 10s) .....+300°C
Soldering Temperature (reflow)
Wide SO, TSSOP lead(Pb)-free .....+260°C
PLCC lead(Pb)-free.....+245°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(*Typical Operating Circuit*, V_{BB} = 8V to 76V, V_{CC} = 3V to 5.5V, V_{SS} = -11V to 0V, V_{BB} - V_{SS} ≤ 76V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Logic Supply Voltage	V_{CC}			3		5.5	V
Tube Supply Voltage	V_{BB}			8		76	V
Bias Supply Voltage (MAX6931 Only)	V_{SS}			-11		0	V
Total Supply Voltage (MAX6931 Only)	V_{BB} - V_{SS}					76	V
Logic Supply Operating Current	I_{CC}	All outputs OUT_ low, CLK = idle	T_A = +25°C		78	170	µA
			T_A = -40°C to +125°C			200	
		All outputs OUT_ high, CLK = idle	T_A = +25°C		540	900	
			T_A = -40°C to +125°C			1000	
Tube Supply Operating Current	I_{BB}	All outputs OUT_ low	T_A = +25°C		1.65	3.0	mA
			T_A = -40°C to +125°C			6.9	
		All outputs OUT_ high	T_A = +25°C		0.85	1.3	
			T_A = -40°C to +125°C			1.4	
Bias Supply Operating Current (MAX6931 Only)	I_{SS}	All outputs OUT_ low	T_A = +25°C	-0.8	-0.38		mA
			T_A = -40°C to +125°C	-1.9			
		All outputs OUT_ high	T_A = +25°C	-1.4	-0.87		
			T_A = -40°C to +125°C	-1.5			

ELECTRICAL CHARACTERISTICS (continued)

(*Typical Operating Circuit*, V_{BB} = 8V to 76V, V_{CC} = 3V to 5.5V, V_{SS} = -11V to 0V, V_{BB} - V_{SS} ≤ 76V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted.) (Note 1)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
High-Voltage OUT_		V_{BB} ≥ 15V, I_{OUT} = -25mA	T_A = +25°C	V_{BB} - 2			V
			T_A = -40°C to +85°C	V_{BB} - 2.5			
			T_A = -40°C to +125°C				
		V_{BB} ≥ 15V, I_{OUT} = -40mA	T_A = -40°C to +85°C	V_{BB} - 3.5			
			T_A = -40°C to +125°C	V_{BB} - 4.0			
		8V < V_{BB} < 15V, I_{OUT} = -25mA	T_A = +25°C		V_{BB} - 1.2		
			T_A = -40°C to +85°C	V_{BB} - 2.5			
			T_A = -40°C to +125°C	V_{BB} - 3.0			
Low-Voltage OUT_ (MAX6921 Only)	V_L	V_{BB} ≥ 15V, I_{OUT} = 1mA	T_A = +25°C		0.75	1	V
			T_A = -40°C to +85°C			1.5	
			T_A = -40°C to +125°C			1.9	
		8V < V_{BB} < 15V, I_{OUT} = 1mA	T_A = +25°C		0.8	1.1	
			T_A = -40°C to +85°C			1.6	
			T_A = -40°C to +125°C			2.0	
Low-Voltage OUT_ (MAX6931 Only)	V_L	V_{BB} ≥ 15V, I_{OUT} = 1mA	T_A = +25°C		V_{SS} + 0.75	V_{SS} + 1	V
			T_A = -40°C to +85°C			V_{SS} + 1.5	
			T_A = -40°C to +125°C			V_{SS} + 1.9	
		8V < V_{BB} < 15V, I_{OUT} = 1mA	T_A = +25°C		V_{SS} + 0.8	V_{SS} + 1.1	
			T_A = -40°C to +85°C			V_{SS} + 1.6	
			T_A = -40°C to +125°C			V_{SS} + 2.0	
Rise Time OUT_ (20% to 80%)	t_R	V_{BB} = 60V, C_L = 50pF, R_L =2.3kΩ			0.9	2	µs
Fall Time OUT_ (80% to 20%)	t_F	V_{BB} = 60V, C_L = 50pF, R_L =2.3kΩ			0.6	1.5	µs
SERIAL INTERFACE TIMING CHARACTERISTICS							
LOAD Rising to OUT_ Falling Delay		(Notes 2, 3)			0.9	1.8	µs
LOAD Rising to OUT_ Rising Delay		(Notes 2, 3)			1.2	2.4	µs
BLANK Rising to OUT_ Falling Delay		(Notes 2, 3)			0.9	1.8	µs
BLANK Falling to OUT_ Rising Delay		(Notes 2, 3)		0.5	1.3	2.5	µs
Input Leakage Current CLK, DIN, LOAD, BLANK	I_{IH}, I_{IL}				0.05	10	µA
Logic-High Input Voltage CLK, DIN, LOAD, BLANK	V_{IH}			0.8 x V_{CC}			V
Logic-Low Input Voltage CLK, DIN, LOAD, BLANK	V_{IL}					0.3 x V_{CC}	V
Hysteresis Voltage DIN, CLK, LOAD, BLANK	ΔV_I				0.6		V
High-Voltage DOUT	V_{OH}	I_{SOURCE} = -1.0mA		V_{CC} - 0.5			V
Low-Voltage DOUT	V_{OL}	I_{SINK} = 1.0mA				0.5	V

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

ELECTRICAL CHARACTERISTICS (continued)

(*Typical Operating Circuit*, V_{BB} = 8V to 76V, V_{CC} = 3V to 5.5V, V_{SS} = -11V to 0V, V_{BB} - V_{SS} ≤ 76V, T_A = T_{MIN} to T_{MAX}, unless otherwise noted.) (Note 1)


PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Rise and Fall Time DOUT		C_{DOUT} = 10pF (Note 2)	3V to 4.5V		60	100	ns
			4.5V to 5.5V		30	80	
CLK Clock Period	t_{CP}			200			ns
CLK Pulse-Width High	t_{CH}			90			ns
CLK Pulse-Width Low	t_{CL}			90			ns
CLK Rise to LOAD Rise Hold	t_{CSH}	(Note 2)		100			ns
DIN Setup Time	t_{DS}			5			ns
DIN Hold Time	t_{DH}	3.0V to 4.5V		20			ns
		4.5V to 5.5V		15			
DOUT Propagation Delay	t_{DO}	C_{DOUT} = 10pF	3.0V to 4.5V	25	120	240	ns
			4.5V to 5.5V	20	75	150	
LOAD Pulse High	t_{CSW}			55			ns

Note 1: All parameters are tested at T_A = +25°C. Specifications over temperature are guaranteed by design.
Note 2: Guaranteed by design.
Note 3: Delay measured from control edge to when output OUT_ changes by 1V.


Typical Operating Characteristics

(V_{CC} = 5.0V, V_{BB} = 76V, and T_A = +25°C, unless otherwise noted.)


TUBE SUPPLY CURRENT (I_{BB}) vs. TEMPERATURE (OUTPUTS LOW)



TUBE SUPPLY CURRENT (I_{BB}) vs. TEMPERATURE (OUTPUTS HIGH)




LOGIC SUPPLY CURRENT (I_{CC}) vs. TEMPERATURE (OUTPUTS LOW)




Typical Operating Characteristics (continued)

(V_{CC} = 5.0V, V_{BB} = 76V, and T_A = +25°C, unless otherwise noted.)


LOGIC SUPPLY CURRENT (I_{CC}) vs. TEMPERATURE (OUTPUTS HIGH)




OUTPUT VOLTAGE (V_{BB} - V_H) vs. TEMPERATURE (OUTPUT HIGH)



OUTPUT VOLTAGE vs. TEMPERATURE (OUTPUT LOW)



OUTPUT RISE AND FALL WAVEFORM



Pin Description

PIN			NAME	FUNCTION
TSSOP		WIDE SO/PLCC		
MAX6921	MAX6931	MAX6921		
1–5	1–5	—	OUT4 to OUT0	VFD Anode and Grid Drivers. OUT4 to OUT0 are push-pull outputs swinging from V_{BB} to GND (MAX6921 only), and from V_{BB} to V_{SS} (MAX6931 only).
6	6	27	DIN	Serial-Data Input. Data is loaded into the internal shift register on CLK's rising edge.
7	7	28	V_{CC}	Logic Supply Voltage. Bypass to GND with 100nF capacitor.
8	8	1	V_{BB}	VFD Tube Supply Voltage. Bypass to GND with 100nF capacitor.
9	—	2	DOUT	Serial-Clock Output. Data is clocked out of the internal shift register to DOUT on CLK's rising edge.

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

Pin Description (continued)

PIN			NAME	FUNCTION
TSSOP		WIDE SO/PLCC		
MAX6921	MAX6931	MAX6921		
—	9	—	V_{SS}	Filament Bias Supply Voltage. Bypass to GND with a 100nF capacitor.
10–19	10–19	—	OUT19 to OUT10	VFD Anode and Grid Drivers. OUT19 to OUT10 are push-pull outputs swinging from V_{BB} to GND (MAX6921 only), and from V_{BB} to V_{SS} (MAX6931 only).
—	—	3-12	OUT19 to OUT10	VFD Anode and Grid Drivers. OUT19 to OUT10 are push-pull outputs swinging from V_{BB} to GND.
20	20	13	BLANK	Blanking Input. High forces outputs OUT0 to OUT19 low, without altering the contents of the output latches. Low enables outputs OUT0 to OUT19 to follow the state of the output latches.
21	21	14	GND	Ground
22	22	15	CLK	Serial-Clock Input. Data is loaded into the internal shift register on CLK's rising edge.
23	23	16	LOAD	Load Input. Data is loaded transparently from the internal shift register to the output latch while LOAD is high. Data is latched into the output latch on LOAD's rising edge, and retained while LOAD is low.
24–28	24–28	—	OUT9 to OUT5	VFD Anode and Grid Drivers. OUT9 to OUT5 are push-pull outputs swinging from V_{BB} to GND (MAX6921 only), and from V_{BB} to V_{SS} (MAX6931 only).
—	—	17-26	OUT9 to OUT0	VFD Anode and Grid Drivers. OUT9 to OUT0 are push-pull outputs swinging from V_{BB} to GND.




Figure 1. MAX6921/MAX6931 Functional Diagram




Figure 2. MAX6921 CMOS Output Driver Structure




Figure 3. MAX6931 CMOS Output Driver Structure

Detailed Description

The MAX6921/MAX6931 are VFD tube drivers comprising a 4-wire serial interface driving 20 high-voltage rail-to-rail output ports. The driver is suitable for both static and multiplexed displays.

The output ports feature high current-sourcing capability to drive current into grids and anodes of static or multiplex VFDs. The ports also have active current sinking for fast discharge of capacitive display electrodes in multiplexing applications.

The 4-wire serial interface comprises a 20-bit shift register and a 20-bit transparent latch. The shift register is written through a clock input CLK and a data input DIN. For the MAX6921, the data propagates to a data output DOUT. The data output allows multiple drivers to be cascaded and operated together. The output latch is transparent to the shift register outputs when LOAD is high, and latches the current state on the falling edge of LOAD.

Each driver output is a slew-rated controlled CMOS push-pull switch driving between V_{BB} and GND (MAX6921) or V_{SS} (MAX6931). The output rise time is always slower than the output fall time to avoid shoot-through currents during output transitions. The output slew rates are slow enough to minimize EMI, yet are fast enough so as not to impact the typical 100µs digit multiplex period and affect the display intensity.

Initial Power-Up and Operation

An internal reset circuit clears the internal registers of the MAX6921/MAX6931 on power-up. All outputs OUT0 to OUT19 and the interface output DOUT (MAX6921 only) initialize low regardless of the initial logic levels of the CLK, DIN, BLANK, and LOAD inputs.

4-Wire Serial Interface

The MAX6921/MAX6931 use 4-wire serial interface with three inputs (DIN, CLK, LOAD) and a data output (DOUT, MAX6921 only). This interface is used to write output data to the MAX6921/MAX6931 (Figure 4) (Table 1). The serial interface data word length is 20 bits, D0–D19.

The functions of the four serial interface pins are:

- CLK input is the interface clock, which shifts data into the MAX6921/MAX6931s' 20-bit shift register on its rising edge.
- LOAD input passes data from the MAX6921/MAX6931s' 20-bit shift register to the 20-bit output latch when LOAD is high (transparent latch), and latches the data on LOAD's falling edge
- DIN is the interface data input, and must be stable when it is sampled on the rising edge of CLK.
- DOUT is the interface data output, which shifts data out from the MAX6921's 20-bit shift register on the rising edge of CLK. Data at DIN is propagated through the shift register and appears at DOUT (20 CLK cycles + t_{DO}) later.

A fifth input, BLANK, can be taken high to force outputs OUT0 to OUT19 low, without altering the contents of the output latches. When the BLANK input is low, outputs OUT0 to OUT19 follow the state of the output latches. A common use of the BLANK input is PWM intensity control.

The BLANK input's function is independent of the operation of the serial interface. Data can be shifted into the serial interface shift register and latched regardless of the state of BLANK.

20-Output, 76V, Serial-Interfaced VFD Tube Drivers




Figure 4. 4-Wire Serial Interface Timing Diagram

Table 1. 4-Wire Serial Interface Truth Table

SERIAL DATA INPUT DIN	CLOCK INPUT	SHIFT REGISTER CONTENTS						LOAD INPUT	LATCH CONTENTS						BLANKING INPUT	OUTPUT CONTENTS					
	CLK	D0	D1	D2	…	Dn-1	Dn	LOAD	D0	D1	D2	…	Dn-1	Dn	BLANK	D0	D1	D2	…	Dn-1	Dn
H	↑	H	R0	R1	…	Rn-2	Rn-1														
L	↑	L	R0	R1	…	Rn-2	Rn-1														
X	↓	R0	R1	R2	…	Rn-1	Rn														
		X	X	X	…	X	X	L	R0	R1	R2	…	Rn-1	Rn							
		P0	P1	P2	…	Pn-1	Pn	H	P0	P1	P2	…	Pn-1	Pn	L	P0	P1	P2	…	Pn-1	Pn
									X	X	X	…	X	X	H	L	L	L	…	L	L

L = Low logic level.
H = High logic level.
X = Don't care.
P = Present state (shift register).
R = Previous state (latched).

Writing Device Registers Using the 4-Wire Serial Interface

The MAX6921/MAX6931 are normally written using the following sequence:

1) Take CLK low.
2) Clock 20 bits of data in order D19 first to D0 last into DIN, observing the data setup and hold times.
3) Load the 20 output latches with a falling edge on LOAD.

LOAD can be high or low during a transmission. If LOAD is high, then the data shifted into the shift register at DIN appear at the OUT0 to OUT19 outputs.

CLK and DIN can be used to transmit data to other peripherals. Activity on CLK always shifts data into the MAX6921/MAX6931s' shift register. However, the MAX6921/MAX6931 only update their output latch on the rising edge of LOAD, and the last 20 bits of data are loaded. Therefore, multiple devices can share CLK and DIN, as long as they have unique LOAD controls.

Determining Driver Output Voltage Drop

The outputs are CMOS drivers, and have a resistive characteristic. The typical and maximum sink and source output resistances can be calculated from the V_H and V_L electrical characteristics. Use this calculated resistance to determine the output voltage drop at different output currents.

Output Current Ratings

The continuous current-source capability is 40mA per output. Outputs can drive up to 75mA as a repetitive peak current, subject to the on-time (output high) being no longer than 1ms, and the duty cycle being such that the output power dissipation is no more than the dissipation for the continuous case. The repetitive peak rating allows outputs to drive a higher current in multiplex grid driver applications, where only one grid is on at a time, and the multiplex time per grid is no more than 1ms.

Since dissipation is proportional to current squared, the maximum current that can be delivered for a given multiplex ratio is given by:

$$I_{PEAK} = (grids \times 1600)^{1/2}\ mA$$

where grids is the number of grids in a multiplexed display.

This means that a duplex application (two grids) can use a repetitive peak current of 56.5mA, a triplex (three grids) application can use a repetitive peak current of 69.2mA, and higher multiplex ratios are limited to 75mA.

Paralleling Outputs

Any number of outputs within the same package can be paralleled in order to raise the current drive or reduce the output resistance. Only parallel outputs directly (by shorting outputs together) if the interface control can be guaranteed to set the outputs to the same level. Although the sink output is relatively weak (typically 750Ω), that resistance is low enough to dissipate 530mW when shorted to an opposite level output at a V_{BB} voltage of only 20V. A safe way to parallel outputs is to use diodes to prevent the outputs from sinking current (Figure 5). Because the outputs cannot sink current from the VFD tube, an external discharge resistor, R, is required. For static tubes, R can be a large value such as 100kΩ. For multiplexed tubes, the value of the resistor can be determined by the load capacitance and timing characteristics required. Resistor R discharges tube capacitance C to 10% of the initial voltage in 2.3 x RC seconds. So, for example, a 15kΩ value for R discharges 100pF tube grid or anode from 40V to 4V in 3.5µs, but draws an additional 2.7mA from the driver when either output is high.




Figure 5. Paralleling Outputs

Power Dissipation

Take care to ensure that the maximum package dissipation ratings for the chosen package are not exceeded. Over-dissipation is unlikely to be an issue when driving static tubes, but the peak currents are usually higher for multiplexed tubes. When using multiple driver devices, try to share the average dissipation evenly between the drivers.

Determine the power dissipation (P_D) for the MAX6921/MAX6931 for static tube drivers with the following equation:

$$P_D = (V_{CC} \times I_{CC}) + (V_{BB} \times I_{BB}) + ((V_{BB} - V_H) \times I_{ANODE} \times A)$$

where:

A = number of anodes driven (the MAX6921/MAX6931 can drive a maximum of 20).

I_{ANODE} = maximum anode current.

(V_{BB} - V_H) is the output voltage drop at the given maximum anode current I_{OUT}.

A static tube dissipation example follows:

V_{CC} = 5V ±5%, V_{BB} = 10V to 18V, A = 20, I_{OUT} = 2mA

P_D = (5.25V x 1mA)+ (18V x 1.4mA) + ((2.5V x 2mA/25mA) x 2mA x 20) = 38mW

Determine the power dissipation (P_D) for the MAX6921/MAX6931 for multiplex tube drivers with the following equation:

$$P_D = (V_{CC} \times I_{CC}) + (V_{BB} \times I_{BB}) + ((V_{BB} - V_H) \times I_{ANODE} \times A) + ((V_{BB} - V_H) \times I_{GRID})$$

where:

A = number of anodes driven.

G = number of grids driven.

I_{ANODE} = maximum anode current.

I_{GRID} = maximum grid current.

The calculation presumes all anodes are on, but only one grid is on. The calculated P_D is the worst case, presuming one digit is always being driven with all its anodes lit. Actual P_D can be estimated by multiplying this P_D figure by the actual tube drive duty cycle, taking into account interdigit blanking and any PWM intensity control.

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

A multiplexed tube dissipation example follows:

V_{CC} = 5V ±5%, V_{BB} = 36V to 42V, A = 12, G = 8, I_{ANODE} = 0.4mA, I_{GRID} = 24mA

P_D = (5.25V x 1mA)+ (42V x 1.4mA) + ((2.5V x 0.4mA/25mA) x 0.4mA x 12) + ((2.5V x 24mA/25mA) x 24mA) = 122mW

Thus, for a 28-pin wide TSSOP package (T_{JA} = 1 / 0.0128 = 78.125°C/W from *Absolute Maximum Ratings*), the maximum allowed ambient temperature T_A is given by:

$T_{J(MAX)} = T_A + (P_D \times T_{JA}) = 150°C = T_A + (0.122 \times 78.125°C/W)$

So T_A = +140.5°C.

This means that the driver can be operated in this application up to the MAX6921/MAX6931s' +125°C maximum operating temperature.

Power-Supply Considerations

The MAX6921/MAX6931 operate with multiple power-supply voltages. Bypass the V_{CC}, V_{BB}, and V_{SS} (MAX6931 only) power-supply pins to GND with 0.1µF capacitors close to the device. The MAX6931 can be operated with V_{SS} connected to GND if a negative bias supply is not required. For multiplex applications, it may be necessary to add an additional bulk electrolytic capacitor of 1µF or greater to the V_{BB} supply.


Power-Supply Sequencing

The order of the power-supply sequencing is not important. The MAX6921/MAX6931 will not be damaged if any combination of V_{CC}, V_{BB}, and V_{SS} (MAX6931 only) is grounded while the other supply or supplies are maintained up to their maximum ratings. However, as with any CMOS device, do not drive the MAX6921/MAX6931s' logic inputs if the logic supply V_{CC} is not operational because the input protection diodes clamp the signals.

Cascading Drivers (MAX6921 Only)


Multiple MAX6921s can be cascaded, as shown in the *Typical Application Circuit*, by connecting each driver's DOUT to DIN of the next drivers. Devices can be cascaded at the full 5MHz CLK speed when $V_{CC} \geq 4.5V$. When V_{CC} <4.5V, the longer propagation delay (t_{DO}) limits the maximum cascaded CLK to 4MHz.

Typical Application Circuit




Pin Configurations


TOP VIEW




WIDE SO



TSSOP



TSSOP



PLCC

20-Output, 76V, Serial-Interfaced VFD Tube Drivers

Chip Information

PROCESS: BiCMOS

Package Information

For the latest package outline information and land patterns, go to **www.maxim-ic.com/packages**. Note that a "+", "#", or "-" in the package code indicates RoHS status only. Package drawings may show a different suffix character, but the drawing pertains to the package regardless of RoHS status.

PACKAGE TYPE	PACKAGE CODE	DOCUMENT NO.
28 TSSOP	U28+1	**21-0066**
28 Wide SO	W28+1	**21-0042**
28 PLCC	Q28+1	**21-0049**

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	10/03	Initial release	—
1	4/10	Added automotive and lead-free parts to *Ordering Information*	1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2010 Maxim Integrated Products Maxim is a registered trademark of Maxim Integrated Products, Inc.


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.