



# **TLV705x 200-mA, Low $I_Q$ , Low-Noise, Low-Dropout Regulator in Ultra-Small, 0.8-mm × 0.8-mm DSBGA and PicoStar™**

## 1 Features

- Very Low Dropout:
  - 105 mV at  $I_{OUT} = 150$  mA
  - 145 mV at  $I_{OUT} = 200$  mA
- Accuracy: 0.5% Typical
- Low  $I_Q$ : 35  $\mu$ A
- Available in Fixed-Output Voltages From 0.7 V to 4.8 V
- $V_{IN}$  Range: 2 V to 5.5 V
- High PSRR: 70 dB at 1 kHz
- Stable With Effective Capacitance of 0.1  $\mu$ F
- Thermal Shutdown and Overcurrent Protection
- Available in an Ultra-Low Profile (0.2-mm Max Height) PicoStar Package Option

## 2 Applications

- Wireless Handsets
- Smart Phones
- Zigbee® Networks
- Bluetooth® Devices
- Other Li-Ion Operated Hand-Held Products
- WLAN and Other PC Add-On Cards

## 3 Description

The TLV705 series of low-dropout (LDO) linear regulators are low quiescent current devices with excellent line and load transient performance. These devices are designed for power-sensitive applications, with a precision band gap. An error amplifier provides typical accuracy of 0.5%. Low output noise, very high power-supply rejection ratio (PSRR), and low dropout voltage make this series of LDOs ideal for a wide selection of battery-operated hand-held equipment. All devices have a thermal shutdown and current limit for safety.

Furthermore, the TLV705 series is stable with an effective output capacitance of only 0.1  $\mu$ F. This feature enables the use of cost-effective capacitors that have higher bias voltage and temperature derating. The devices regulate to the specified accuracy with zero output load. The TLV705P series also provides an active pulldown circuit to quickly discharge output.


The TLV705 and TLV705P series are both available in 0.8-mm × 0.8-mm DSBGA and PicoStar packages with three height options that are optimal for hand-held applications.

### Device Information<sup>(1)</sup>

| PART NUMBER | PACKAGE      | BODY SIZE (NOM)   |
|-------------|--------------|-------------------|
| TLV705x     | DSGBA (4)    | 0.80 mm × 0.80 mm |
|             | PicoStar (4) | 0.77 mm × 0.77 mm |

(1) For all available packages, see the orderable addendum at the end of the data sheet.

### Typical Application Circuit (Fixed-Voltage Versions)



## Table of Contents

|                                                |           |                                                                  |           |
|------------------------------------------------|-----------|------------------------------------------------------------------|-----------|
| <b>1 Features</b> .....                        | <b>1</b>  | 8.2 Typical Application .....                                    | 15        |
| <b>2 Applications</b> .....                    | <b>1</b>  | 8.3 Do's and Don'ts .....                                        | 16        |
| <b>3 Description</b> .....                     | <b>1</b>  | <b>9 Power Supply Recommendations</b> .....                      | <b>16</b> |
| <b>4 Revision History</b> .....                | <b>2</b>  | <b>10 Layout</b> .....                                           | <b>17</b> |
| <b>5 Pin Configuration and Functions</b> ..... | <b>4</b>  | 10.1 Layout Guidelines .....                                     | 17        |
| <b>6 Specifications</b> .....                  | <b>5</b>  | 10.2 Layout Example .....                                        | 17        |
| 6.1 Absolute Maximum Ratings .....             | 5         | 10.3 Power Dissipation .....                                     | 17        |
| 6.2 ESD Ratings .....                          | 5         | 10.4 Power Dissipation and Junction Temperature .....            | 17        |
| 6.3 Recommended Operating Conditions .....     | 5         | 10.5 Estimating Junction Temperature .....                       | 18        |
| 6.4 Thermal Information .....                  | 5         | <b>11 Device and Documentation Support</b> .....                 | <b>19</b> |
| 6.5 Electrical Characteristics .....           | 6         | 11.1 Device Support .....                                        | 19        |
| 6.6 Typical Characteristics .....              | 7         | 11.2 Documentation Support .....                                 | 19        |
| <b>7 Detailed Description</b> .....            | <b>12</b> | 11.3 Related Links .....                                         | 19        |
| 7.1 Overview .....                             | 12        | 11.4 Community Resources .....                                   | 20        |
| 7.2 Functional Block Diagrams .....            | 12        | 11.5 Trademarks .....                                            | 20        |
| 7.3 Feature Description .....                  | 13        | 11.6 Electrostatic Discharge Caution .....                       | 20        |
| 7.4 Device Functional Modes .....              | 14        | 11.7 Glossary .....                                              | 20        |
| <b>8 Application and Implementation</b> .....  | <b>15</b> | <b>12 Mechanical, Packaging, and Orderable Information</b> ..... | <b>20</b> |
| 8.1 Application Information .....              | 15        | 12.1 Package Mounting .....                                      | 20        |

## 4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

| Changes from Revision D (April 2015) to Revision E                                                                                   | Page |
|--------------------------------------------------------------------------------------------------------------------------------------|------|
| • Added new package (YFM) to document .....                                                                                          | 1    |
| • Added PicoStar to title .....                                                                                                      | 1    |
| • Changed last Features bullet .....                                                                                                 | 1    |
| • Changed last sentence of <i>Description</i> section .....                                                                          | 1    |
| • Added second row to <i>Device Information</i> table .....                                                                          | 1    |
| • Added YFM pin out drawing .....                                                                                                    | 4    |
| • Added YFM package to <i>Thermal Information</i> table .....                                                                        | 5    |
| • Changed $V_O$ parameter units in <i>Electrical Characteristics</i> table: % for first row, mV for second row .....                 | 6    |
| • Changed first sentence of Overview section: removed <i>new</i> .....                                                               | 12   |
| • Changed fifth sentence of <i>Internal Current Limit</i> section to clarify description of the shutdown circuit functionality ..... | 13   |
| • Changed $V_{\mu s}$ to $V/\mu s$ in second paragraph of <i>Start-Up Current</i> section .....                                      | 13   |
| • Changed <i>it to the start-up current</i> in third paragraph of <i>Start-Up Current</i> section .....                              | 13   |
| • Changed <i>INPUT</i> to $V_{IN}$ in <i>Power Supply Recommendations</i> section .....                                              | 16   |
| • Added <i>Related Links</i> section .....                                                                                           | 19   |
| • Added YFM package to <i>Package Mounting</i> section .....                                                                         | 20   |

| Changes from Revision C (October 2012) to Revision D                                                                                                                                                                                                                                                                                                 | Page |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|------|
| • Added <i>ESD Ratings</i> table, <i>Feature Description</i> section, <i>Device Functional Modes</i> , <i>Application and Implementation</i> section, <i>Power Supply Recommendations</i> section, <i>Layout</i> section, <i>Device and Documentation Support</i> section, and <i>Mechanical, Packaging, and Orderable Information</i> section ..... | 1    |
| • Added <i>Features</i> bullet for $V_{IN}$ range .....                                                                                                                                                                                                                                                                                              | 1    |
| • Changed <i>Applications</i> list items .....                                                                                                                                                                                                                                                                                                       | 1    |
| • Deleted <i>Power Dissipation Ratings</i> table .....                                                                                                                                                                                                                                                                                               | 5    |


|                                                                                                                           |                    |
|---------------------------------------------------------------------------------------------------------------------------|--------------------|
| • Changed y-axis unit measurement from $I_{LIM}$ to $I_{CL}$ for <a href="#">Figure 11</a> .....                          | <a href="#">7</a>  |
| • Changed <a href="#">Figure 31</a> and deleted layout silkscreen images; replaced with image of PCB layout drawing. .... | <a href="#">17</a> |
| • Changed title for <a href="#">Figure 31</a> .....                                                                       | <a href="#">17</a> |
| • Changed title of <i>Thermal Protection</i> section .....                                                                | <a href="#">17</a> |

| <b>Changes from Revision B (December 2011) to Revision C</b> | <b>Page</b>       |
|--------------------------------------------------------------|-------------------|
| • Deleted last Features bullet.....                          | <a href="#">1</a> |


| <b>Changes from Revision A (August 2011) to Revision B</b>                                                   | <b>Page</b>       |
|--------------------------------------------------------------------------------------------------------------|-------------------|
| • Added last Features bullet.....                                                                            | <a href="#">1</a> |
| • Changed last sentence of Description section .....                                                         | <a href="#">1</a> |
| • Added <i>Mechanical Packages</i> section (removed June 2013; packages are now automatically appended)..... | <a href="#">1</a> |
| • Added YFP to title of pin out drawing .....                                                                | <a href="#">4</a> |
| • Added YFP package to Thermal Information table .....                                                       | <a href="#">5</a> |

## 5 Pin Configuration and Functions

**YFF, YFP Packages  
4-Pin DSBGA  
Top View**



**YFM Package  
4-Pin PicoStar  
Top View**



### Pin Functions

| PIN              |     | I/O | DESCRIPTION                                                                                                                                                                                                                           |
|------------------|-----|-----|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| NAME             | NO. |     |                                                                                                                                                                                                                                       |
| GND              | A1  | —   | Ground pin.                                                                                                                                                                                                                           |
| EN               | A2  | I   | Enable pin.<br>Driving EN over 0.9 V turns on the regulator. Driving EN below 0.4 V puts the regulator into shutdown mode, thus reducing operating current to 1 $\mu$ A, nominal.                                                     |
| V <sub>OUT</sub> | B1  | O   | Regulated output voltage pin.<br>A small 1- $\mu$ F ceramic capacitor is required to be placed from this pin to ground to assure stability. See the <a href="#">Input and Output Capacitor Requirements</a> section for more details. |
| V <sub>IN</sub>  | B2  | I   | Input pin.<br>A small 1- $\mu$ F ceramic capacitor is recommended to be placed from this pin to ground for good transient performance. See the <a href="#">Input and Output Capacitor Requirements</a> section for more details.      |

## 6 Specifications

### 6.1 Absolute Maximum Ratings

Specified at  $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ , unless otherwise noted. All voltages are with respect to GND.<sup>(1)</sup>

|                               |                           | MIN                | MAX | UNIT               |
|-------------------------------|---------------------------|--------------------|-----|--------------------|
| Voltage <sup>(2)</sup>        | $V_{IN}$                  | -0.3               | 6   | V                  |
|                               | $V_{EN}$                  | -0.3               | 6   | V                  |
|                               | $V_{OUT}$                 | -0.3               | 6   | V                  |
| Maximum output current        | $I_{OUT}$                 | Internally limited |     |                    |
| Output short-circuit duration |                           | Indefinite         |     |                    |
| Temperature                   | Operating junction, $T_J$ | -55                | 150 | $^{\circ}\text{C}$ |
|                               | Storage, $T_{stg}$        | -55                | 150 | $^{\circ}\text{C}$ |

- (1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions* is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
- (2) All voltages are with respect to network ground pin.

### 6.2 ESD Ratings

|                                     |                                                                                | VALUE | UNIT |
|-------------------------------------|--------------------------------------------------------------------------------|-------|------|
| $V_{(ESD)}$ Electrostatic discharge | Human body model (HBM), per ANSI/ESDA/JEDEC JS-001 <sup>(1)</sup>              | ±2000 | V    |
|                                     | Charged device model (CDM), per JEDEC specification JESD22-C101 <sup>(2)</sup> | ±500  |      |

- (1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
- (2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

### 6.3 Recommended Operating Conditions

over operating junction temperature range (unless otherwise noted)

|           |                      | MIN | NOM | MAX | UNIT               |
|-----------|----------------------|-----|-----|-----|--------------------|
| $V_{IN}$  | Input voltage        | 2   |     | 5.5 | V                  |
| $V_{OUT}$ | Output voltage       | 0.7 |     | 4.8 | V                  |
| $I_{OUT}$ | Output current       | 0   |     | 200 | mA                 |
| $T_J$     | Junction temperature | -40 |     | 125 | $^{\circ}\text{C}$ |

### 6.4 Thermal Information

| THERMAL METRIC <sup>(1)</sup> |                                              | TLV705x          |                | UNIT                 |
|-------------------------------|----------------------------------------------|------------------|----------------|----------------------|
|                               |                                              | YFF, YFP (DSBGA) | YFM (PicoStar) |                      |
|                               |                                              | 4 PINS           | 4 PINS         |                      |
| $R_{\theta JA}$               | Junction-to-ambient thermal resistance       | 160              | 191.7          | $^{\circ}\text{C/W}$ |
| $R_{\theta JC(top)}$          | Junction-to-case (top) thermal resistance    | 80               | 3.1            | $^{\circ}\text{C/W}$ |
| $R_{\theta JB}$               | Junction-to-board thermal resistance         | 90               | 36.5           | $^{\circ}\text{C/W}$ |
| $\Psi_{JT}$                   | Junction-to-top characterization parameter   | 0.5              | 2.8            | $^{\circ}\text{C/W}$ |
| $\Psi_{JB}$                   | Junction-to-board characterization parameter | 78               | 26.5           | $^{\circ}\text{C/W}$ |

- (1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report, [SPRA953](#).

## 6.5 Electrical Characteristics

At  $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ ,  $V_{IN} = V_{OUT(nom)} + 0.5\text{ V}$  or  $2\text{ V}$  (whichever is greater),  $I_{OUT} = 10\text{ mA}$ ,  $V_{EN} = 0.9\text{ V}$ , and  $C_{OUT} = 1\text{ }\mu\text{F}$ , unless otherwise noted. Typical values are at  $T_J = 25^{\circ}\text{C}$ .

| PARAMETER                        |                                | TEST CONDITIONS                                                                                     | MIN                                                | TYP         | MAX      | UNIT                |
|----------------------------------|--------------------------------|-----------------------------------------------------------------------------------------------------|----------------------------------------------------|-------------|----------|---------------------|
| $V_{IN}$                         | Input voltage range            |                                                                                                     | 2                                                  |             | 5.5      | V                   |
| $V_{OUT}$                        | Output voltage range           |                                                                                                     | 0.7                                                |             | 4.8      | V                   |
| $V_O$                            | DC output accuracy             | $-40^{\circ}\text{C} \leq T_J \leq 125^{\circ}\text{C}$                                             |                                                    |             |          |                     |
|                                  |                                | $0\text{ mA} \leq I_{OUT} \leq 200\text{ mA}$ , $V_{OUT} \geq 1\text{ V}$                           | -2%                                                | $\pm 0.5\%$ | 2%       |                     |
|                                  |                                | $0\text{ mA} \leq I_{OUT} \leq 200\text{ mA}$ , $V_{OUT} < 1\text{ V}$                              | -20                                                | $\pm 5$     | 20       | mV                  |
| $\Delta V_{OUT}(\Delta V_{IN})$  | Line regulation                | $V_{OUT(nom)} + 0.5\text{ V} \leq V_{IN} \leq 5.5\text{ V}$                                         |                                                    | 0.05        | 5        | mV                  |
| $\Delta V_{OUT}(\Delta I_{OUT})$ | Load regulation                | $0\text{ mA} \leq I_{OUT} \leq 200\text{ mA}$                                                       |                                                    | 1           |          | mV                  |
| $V_{DO}$                         | Dropout voltage <sup>(1)</sup> | $V_{IN} = 0.98 \times V_{OUT(nom)}$ , $I_{OUT} = 200\text{ mA}$                                     |                                                    | 145         | 250      | mV                  |
| $I_{CL}$                         | Output current limit           | $V_{OUT} = 0.9 \times V_{OUT(nom)}$ , $T_J = 25^{\circ}\text{C}$                                    | 260                                                | 400         | 550      | mA                  |
| $I_{GND}$                        | Ground pin current             | $I_{OUT} = 0\text{ mA}$                                                                             |                                                    | 35          | 55       | $\mu\text{A}$       |
|                                  |                                | $I_{OUT} = 200\text{ mA}$                                                                           |                                                    | 315         |          | $\mu\text{A}$       |
| $I_{SHUTDOWN}$                   | Shutdown ground pin current    | $V_{EN} \leq 0.4\text{ V}$ , $2\text{ V} \leq V_{IN} \leq 4.5\text{ V}$                             |                                                    | 1           | 1.8      | $\mu\text{A}$       |
| PSRR                             | Power-supply rejection ratio   | $V_{IN} = 2.3\text{ V}$ , $V_{OUT} = 1.8\text{ V}$ , $I_{OUT} = 10\text{ mA}$ , $f = 10\text{ kHz}$ |                                                    | 80          |          | dB                  |
|                                  |                                | $V_{IN} = 2.3\text{ V}$ , $V_{OUT} = 1.8\text{ V}$ , $I_{OUT} = 10\text{ mA}$ , $f = 1\text{ MHz}$  |                                                    | 55          |          | dB                  |
| $V_n$                            | Output noise voltage           | BW = 100 Hz to 100 kHz, $I_{OUT} = 10\text{ mA}$                                                    | $V_{IN} = 2.3\text{ V}$ , $V_{OUT} = 1.8\text{ V}$ | 26.6        |          | $\mu\text{V}_{RMS}$ |
|                                  |                                |                                                                                                     | $V_{IN} = 3.3\text{ V}$ , $V_{OUT} = 2.8\text{ V}$ | 26.7        |          | $\mu\text{V}_{RMS}$ |
|                                  |                                |                                                                                                     | $V_{IN} = 3.8\text{ V}$ , $V_{OUT} = 3.3\text{ V}$ | 28.2        |          | $\mu\text{V}_{RMS}$ |
|                                  |                                | BW = 10 Hz to 100 kHz, $I_{OUT} = 10\text{ mA}$                                                     | $V_{IN} = 2.3\text{ V}$ , $V_{OUT} = 1.8\text{ V}$ | 30.7        |          | $\mu\text{V}_{RMS}$ |
|                                  |                                |                                                                                                     | $V_{IN} = 3.3\text{ V}$ , $V_{OUT} = 2.8\text{ V}$ | 31.3        |          | $\mu\text{V}_{RMS}$ |
|                                  |                                |                                                                                                     | $V_{IN} = 3.8\text{ V}$ , $V_{OUT} = 3.3\text{ V}$ | 34.1        |          | $\mu\text{V}_{RMS}$ |
| $t_{STR}$                        | Start-up time <sup>(2)</sup>   | $C_{OUT} = 1\text{ }\mu\text{F}$ , $I_{OUT} = 200\text{ mA}$                                        |                                                    | 100         |          | $\mu\text{s}$       |
| $V_{HI}$                         | Enable high (enabled)          |                                                                                                     | 0.9                                                |             | $V_{IN}$ | V                   |
| $V_{LO}$                         | Enable low (disabled)          |                                                                                                     | 0                                                  |             | 0.4      | V                   |
| $I_{EN}$                         | EN pin current                 | $V_{EN} = 5.5\text{ V}$                                                                             |                                                    | 0.01        |          | $\mu\text{A}$       |
| UVLO                             | Undervoltage lockout           | $V_{IN}$ rising                                                                                     |                                                    | 1.9         |          | V                   |
| $t_{SD}$                         | Thermal shutdown temperature   | Shutdown, temperature increasing                                                                    |                                                    | 160         |          | $^{\circ}\text{C}$  |
|                                  |                                | Reset, temperature decreasing                                                                       |                                                    | 140         |          | $^{\circ}\text{C}$  |
| $T_J$                            | Operating junction temperature |                                                                                                     | -40                                                |             | 125      | $^{\circ}\text{C}$  |

(1)  $V_{DO}$  is measured for devices with  $V_{OUT(nom)} = 2.35\text{ V}$  so that  $V_{IN} = 2.3\text{ V}$ .

(2) Start-up time = time from EN assertion to  $0.98 \times V_{OUT(nom)}$ .

## 6.6 Typical Characteristics

Over operating temperature range ( $T_J = -40^\circ\text{C}$  to  $125^\circ\text{C}$ ),  $I_{OUT} = 10\text{ mA}$ ,  $V_{EN} = 0.9\text{ V}$ ,  $C_{OUT} = 1\text{ }\mu\text{F}$ , and  $V_{IN} = V_{OUT(nom)} + 0.5\text{ V}$  or  $2\text{ V}$ , whichever is greater, unless otherwise noted. Typical values are at  $T_J = 25^\circ\text{C}$ .




Figure 1. Line Regulation




Figure 2. Line Regulation




Figure 3. Load Regulation ( $0\text{ mA} \leq I_{OUT} \leq 200\text{ mA}$ )




Figure 4. Dropout Voltage vs Input Voltage




Figure 5. Dropout Voltage vs Output Current






Figure 6. Output Voltage vs Temperature

## Typical Characteristics (continued)


Over operating temperature range ( $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ ),  $I_{OUT} = 10\text{ mA}$ ,  $V_{EN} = 0.9\text{ V}$ ,  $C_{OUT} = 1\text{ }\mu\text{F}$ , and  $V_{IN} = V_{OUT(nom)} + 0.5\text{ V}$  or  $2\text{ V}$ , whichever is greater, unless otherwise noted. Typical values are at  $T_J = 25^{\circ}\text{C}$ .




**Figure 7. Ground Pin Current vs Input Voltage**




**Figure 8. Ground Pin Current vs Output Current**




**Figure 9. Ground Pin Current vs Temperature**



**Figure 10. Shutdown Pin Current vs Input Voltage**




**Figure 11. Current Limit vs Input Voltage**




**Figure 12. Power-Supply Rejection Ratio vs Frequency**

## Typical Characteristics (continued)


Over operating temperature range ( $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ ),  $I_{\text{OUT}} = 10\text{ mA}$ ,  $V_{\text{EN}} = 0.9\text{ V}$ ,  $C_{\text{OUT}} = 1\text{ }\mu\text{F}$ , and  $V_{\text{IN}} = V_{\text{OUT(nom)}} + 0.5\text{ V}$  or  $2\text{ V}$ , whichever is greater, unless otherwise noted. Typical values are at  $T_J = 25^{\circ}\text{C}$ .




**Figure 13. Power-Supply Rejection Ratio vs Input Voltage**




**Figure 14. Output Spectral Noise Density vs Frequency**




**Figure 15. Integrated Noise vs Output Voltage**



**Figure 16. Load Transient 0**




**Figure 17. Load Transient 1**




**Figure 18. Load Transient 3**

## Typical Characteristics (continued)


Over operating temperature range ( $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ ),  $I_{OUT} = 10\text{ mA}$ ,  $V_{EN} = 0.9\text{ V}$ ,  $C_{OUT} = 1\text{ }\mu\text{F}$ , and  $V_{IN} = V_{OUT(nom)} + 0.5\text{ V}$  or  $2\text{ V}$ , whichever is greater, unless otherwise noted. Typical values are at  $T_J = 25^{\circ}\text{C}$ .




**Figure 19. Small-Step Line Transient (10 mA)**




**Figure 20. Small-Step Line Transient (200 mA)**




**Figure 21.  $V_{IN}$  Inrush Current**



**Figure 22.  $V_{IN}$  Inrush Current**




**Figure 23. Line Transient (10 mA)**



**Figure 24. Line Transient (200 mA)**

## Typical Characteristics (continued)

Over operating temperature range ( $T_J = -40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ ),  $I_{\text{OUT}} = 10\text{ mA}$ ,  $V_{\text{EN}} = 0.9\text{ V}$ ,  $C_{\text{OUT}} = 1\text{ }\mu\text{F}$ , and  $V_{\text{IN}} = V_{\text{OUT(nom)}} + 0.5\text{ V}$  or  $2\text{ V}$ , whichever is greater, unless otherwise noted. Typical values are at  $T_J = 25^{\circ}\text{C}$ .




**Figure 25. Power-Up and Power-Down**

## 7 Detailed Description


### 7.1 Overview

The TLV705 and TLV705P series of devices belong to a family of next-generation value low-dropout (LDO) voltage regulators. These devices consume low quiescent current and deliver excellent line and load transient performance. This performance, combined with low noise, very good PSRR with little ( $V_{IN} - V_{OUT}$ ) headroom, makes these devices ideal for RF portable applications. This family of regulators offers sub-band-gap output voltages down to 0.7 V, current limit, and thermal protection, and are specified from  $-40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ . The TLV705P provides an active pulldown circuit to quickly discharge the outputs.

### 7.2 Functional Block Diagrams



**Figure 26. TLV705 Series**



**Figure 27. TLV705P Series**

## 7.3 Feature Description

### 7.3.1 Internal Current Limit

The internal current limits of the TLV705 series help protect the regulator during fault conditions. During current limit, the output sources a fixed amount of current that is largely independent of output voltage. In such a case, the output voltage is not regulated, and can be measured as  $V_{OUT} = I_{LIMIT} \times R_{LOAD}$ . The PMOS pass transistor dissipates  $[(V_{IN} - V_{OUT}) \times I_{LIMIT}]$  until a thermal shutdown is triggered and the device turns off. When the device cools down, the internal thermal shutdown circuit turns the device back on. If the fault condition continues, the device cycles between current limit and thermal shutdown; see the [Power Dissipation and Junction Temperature](#) section for more details.

The PMOS pass element in the TLV705 has a built-in body diode that conducts current when the voltage at  $V_{OUT}$  exceeds the voltage at  $V_{IN}$ . This current is not limited, so if extended reverse voltage operation is anticipated, external limiting to 5% of the rated output current is recommended.

### 7.3.2 Undervoltage Lockout (UVLO)

The TLV705 uses an UVLO circuit to keep the output shut off until the internal circuitry is operating properly.

### 7.3.3 Start-Up Current

The TLV705 uses a unique start-up architecture that creates a constant start-up time regardless of the output capacitor. The start-up current is given by [Equation 1](#). [Equation 1](#) shows that start-up current is directly proportional to  $C_{OUT}$ .

$$I_{STARTUP} = C_{OUT} (\mu F) \times 0.06 (V/\mu s) + I_{LOAD} (mA) \quad (1)$$

The output voltage ramp rate is independent of  $C_{OUT}$  and the load current, and has a typical value of 0.06 V/ $\mu$ s.

The TLV705 automatically adjusts the soft-start current to supply both the load current and the current to charge  $C_{OUT}$ . For example, if  $I_{LOAD} = 0$  mA upon enabling the LDO, then  $I_{STARTUP} = 1 \mu F \times 0.06 V/\mu s + 0 mA = 60 mA$ , which is the current that charges the output capacitor.

However, if  $I_{LOAD} = 200$  mA, then  $I_{STARTUP} = 1 \mu F \times 0.06 V/\mu s + 200 mA = 260 mA$ , which is the current required for charging the output capacitor and supplying the load current.

If the output capacitor and load are increased such that the start-up current exceeds the output current limit, the start-up current is clamped at the typical current limit of 400 mA. For example, if  $C_{OUT} = 10 \mu F$  and  $I_{OUT} = 200$  mA, then  $10 \mu F \times 0.06 V/\mu s + 200 mA = 800 mA$  is not supplied and is instead clamped at 400 mA.

### 7.3.4 Dropout Voltage

The TLV705 uses a PMOS pass transistor to achieve low dropout. When  $(V_{IN} - V_{OUT})$  is less than the dropout voltage ( $V_{DO}$ ), the PMOS pass device is in the linear region of operation and the input-to-output resistance is the  $R_{DS(on)}$  of the PMOS pass element.  $V_{DO}$  approximately scales with the output current because the PMOS device functions as a resistor in dropout.

As with any linear regulator, PSRR and transient response are degraded as  $(V_{IN} - V_{OUT})$  approaches dropout. This effect is shown in [Figure 13](#) in the [Typical Characteristics](#) section.

### 7.3.5 Shutdown

The enable pin (EN) is active high. The device is enabled when the EN pin goes above 0.9 V. This relatively lower value of voltage required to turn the LDO on can be used to power the device with the GPIO of recent processors with a GPIO voltage lower than traditional microcontrollers. The device is turned off when the EN pin is held at less than 0.4 V. When shutdown capability is not required, EN can be connected to the  $V_{IN}$  pin. The TLV705P version has internal active pulldown circuitry that discharges the output with a time constant of:

$$\tau = (120 \times R_L) / (120 + R_L) \times C_{OUT}$$

where

- $R_L$  = load resistance
  - $C_{OUT}$  = output capacitor
- (2)

## 7.4 Device Functional Modes

### 7.4.1 Normal Operation

The device regulates to the nominal output voltage under the following conditions:

- The input voltage is greater than the nominal output voltage added to the dropout voltage.
- The output current is less than the current limit.
- The input voltage is greater than the UVLO voltage.

### 7.4.2 Dropout Operation

If the input voltage is lower than the nominal output voltage plus the specified dropout voltage, but all other conditions are met for normal operation, the device operates in dropout mode. In this condition, the output voltage is the same the input voltage minus the dropout voltage. The transient performance of the device is significantly degraded because the pass device is in a triode state and no longer regulates the output voltage of the LDO. Line or load transients in dropout can result in large output voltage deviations.

[Table 1](#) lists the conditions that lead to the different modes of operation.

**Table 1. Device Functional Mode Comparison**

| OPERATING MODE | PARAMETER                        |                    |
|----------------|----------------------------------|--------------------|
|                | $V_{IN}$                         | $I_{OUT}$          |
| Normal mode    | $V_{IN} > V_{OUT(nom)} + V_{DO}$ | $I_{OUT} < I_{CL}$ |
| Dropout mode   | $V_{IN} < V_{OUT(nom)} + V_{DO}$ | $I_{OUT} < I_{CL}$ |
| Current limit  | $V_{IN} > UVLO$                  | $I_{OUT} > I_{CL}$ |

## 8 Application and Implementation


### NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

### 8.1 Application Information

The TLV705 is a LDO that offers very low dropout voltages in a tiny package. The operating junction temperature of this device is  $-40^{\circ}\text{C}$  to  $125^{\circ}\text{C}$ .

### 8.2 Typical Application



**Figure 28. Typical Application Circuit (Fixed-Voltage Versions)**

#### 8.2.1 Design Requirements

Table 2 lists the design parameters.

**Table 2. Design Parameters**

| PARAMETER      | DESIGN REQUIREMENT |
|----------------|--------------------|
| Input voltage  | 2.5 V to 3.3 V     |
| Output voltage | 1.8 V              |
| Output current | 100 mA             |

#### 8.2.2 Detailed Design Procedure

Select the desired device based on the output voltage.

Provide an input supply with adequate headroom to account for dropout and output current to account for the GND pin current, and power the load.

##### 8.2.2.1 Input and Output Capacitor Requirements

TI recommends using 1- $\mu\text{F}$  X5R- and X7R-type ceramic capacitors because these components have minimal variation in value and equivalent series resistance (ESR) over temperature. However, the TLV705 series is designed to be stable with an effective capacitance of 0.1  $\mu\text{F}$  or larger at the output. Thus, the device is also stable with capacitors of other dielectrics as long as the effective capacitance under the operating bias voltage and temperature is greater than 0.1  $\mu\text{F}$ . This effective capacitance refers to the capacitance that the LDO detects under operating bias voltage and temperature conditions (that is, the capacitance after taking the bias voltage and temperature derating into consideration). In addition to allowing the use of lower cost dielectrics, the effective capacitance also enables using smaller footprint capacitors that have higher derating in space-constrained applications.



Using a 0.1- $\mu\text{F}$  rating capacitor at the output of the LDO does not ensure stability because the effective capacitance under operating conditions is less than 0.1  $\mu\text{F}$ . Maximum ESR must be less than 200 m $\Omega$ .

Although an input capacitor is not required for stability, good analog design practice is to connect a 0.1- $\mu\text{F}$  to 1- $\mu\text{F}$  low ESR capacitor across the  $V_{\text{IN}}$  and GND pins of the regulator. This capacitor counteracts reactive input sources and improves transient response, noise rejection, and ripple rejection. A higher-value capacitor can be necessary if large, fast rise-time load transients are anticipated, or if the device is not located close to the power source. If source impedance is more than 2  $\Omega$ , a 0.1- $\mu\text{F}$  input capacitor may be necessary to ensure stability.

### 8.2.2.2 Transient Response

As with any regulator, increasing the size of the output capacitor reduces overshoot and undershoot magnitude, but increases the duration of the transient response.

### 8.2.3 Application Curves



## 8.3 Do's and Don'ts

Place input and output capacitors as close to the device as possible.

Do not exceed the device absolute maximum ratings.

## 9 Power Supply Recommendations

Connect a low output impedance power supply directly to the  $V_{\text{IN}}$  pin of the TLV705. Inductive impedances between the input supply and the  $V_{\text{IN}}$  pin can create significant voltage excursions at the  $V_{\text{IN}}$  pin during start-up or load transient events.

## 10 Layout

### 10.1 Layout Guidelines

Place input and output capacitors as close to the device pins as possible. To improve ac performance (such as PSRR, output noise, and transient response), TI recommends designing the board with the input and output capacitors on opposite sides of the device. In addition, connect the ground connection for the output capacitor directly to the GND pin of the device. High ESR capacitors can degrade PSRR.

### 10.2 Layout Example




Figure 31. Example PCB Layout

### 10.3 Power Dissipation

The ability to remove heat from the die is different for each package type, presenting different considerations in the printed-circuit-board (PCB) layout. The PCB area around the device that is free of other components moves the heat from the device to the ambient air. Performance data for JEDEC low and high-K boards are given in the [Thermal Information](#) table. Using heavier copper increases the effectiveness in removing heat from the device. The addition of plated through-holes to heat-dissipating layers also improves the thermal dissipation.

Refer to the section for thermal performance on the TLV705 evaluation module (EVM). The EVM is a 2-layer board with 2 ounces of copper per side.

Power dissipation depends on input voltage and load conditions. Power dissipation ( $P_D$ ) is equal to the product of the output current and the voltage drop across the output pass element, as shown in [Equation 3](#):

$$P_D = (V_{IN} - V_{OUT}) \times I_{OUT} \quad (3)$$

### 10.4 Power Dissipation and Junction Temperature

Thermal protection disables the output when the junction temperature rises to approximately 160°C, allowing the device to cool. When the junction temperature cools to approximately 140°C, the output circuitry is again enabled. Depending on power dissipation, thermal resistance, and ambient temperature, the thermal protection circuit can cycle on and off. This cycling limits the dissipation of the regulator, protecting it from damage as a result of overheating.

For reliable operation, limit junction temperature to 125°C, maximum. To estimate the margin of safety in a complete design, increase the ambient temperature until the thermal protection is triggered; use worst-case loads and signal conditions. For good reliability, trigger thermal protection at least 35°C above the maximum expected ambient condition of the particular application. This configuration produces a worst-case junction temperature of 125°C at the highest expected ambient temperature and worst-case load.

The internal protection circuitry of the TLV705 is designed to protect against overload conditions. Continuously running the TLV705 into thermal shutdown degrades device reliability.

## 10.5 Estimating Junction Temperature

The JEDEC standard now recommends the use of psi ( $\Psi$ ) thermal metrics to estimate the junction temperatures of the LDO when in-circuit on a typical PCB board application. These metrics are not strictly speaking thermal resistances; rather, these metrics offer practical and relative means of estimating junction temperatures. These psi metrics are determined to be significantly independent of the copper-spreading area. The key thermal metrics ( $\Psi_{JT}$  and  $\Psi_{JB}$ ) are given in the [Thermal Information](#) table and are used in accordance with [Equation 4](#).

$$\Psi_{JT}: T_J = T_T + \Psi_{JT} \times P_D$$

$$\Psi_{JB}: T_J = T_B + \Psi_{JB} \times P_D$$

where:

- $P_D$  is the power dissipated, as explained in the [Thermal Information](#) table,
- $T_T$  is the temperature at the center-top of the device package, and
- $T_B$  is the PCB surface temperature measured 1 mm from the device package and centered on the package edge.

(4)

## 11 Device and Documentation Support

### 11.1 Device Support

#### 11.1.1 Development Support

##### 11.1.1.1 Evaluation Modules

An evaluation module (EVM) is available to assist in the initial circuit performance evaluation using the TLV705. The [TLV70533EVM-596 evaluation module](#) (and [related user's guide](#)) can be requested at the TI website through the product folders or purchased directly from [the TI eStore](#).

##### 11.1.1.2 Spice Models

Computer simulation of circuit performance using SPICE is often useful when analyzing the performance of analog circuits and systems. A SPICE model for the TLV705 is available through the product folders under *Tools & Software*.

#### 11.1.2 Device Nomenclature

**Table 3. Available Options<sup>(1)</sup>**

| PRODUCT          | V <sub>OUT</sub>                                                                                                                                                                                                                                                                                                                                                                                                                                     |
|------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| TLV705xx(x)Pyyyz | <b>xx(x)</b> is the nominal output voltage. For output voltages with a resolution of 100 mV, two digits are used in the ordering number; otherwise, three digits are used (for example, 28 = 2.8 V; 475 = 4.75 V).<br><b>P</b> is optional; devices with P have an LDO regulator with an active output discharge.<br><b>yyy</b> is package designator.<br><b>z</b> is the package quantity. R is for reel (3000 pieces), T is for tape (250 pieces). |

(1) For the most current package and ordering information, see the Package Option Addendum at the end of this document, or visit the device product folder at [www.ti.com](#).

### 11.2 Documentation Support

#### 11.2.1 Related Documentation

- *TLV70533EVM-596 Evaluation Module User's Guide*, [SLVU439](#)

### 11.3 Related Links

The table below lists quick access links. Categories include technical documents, support and community resources, tools and software, and quick access to sample or buy.

**Table 4. Related Links**

| PARTS   | PRODUCT FOLDER             | SAMPLE & BUY               | TECHNICAL DOCUMENTS        | TOOLS & SOFTWARE           | SUPPORT & COMMUNITY        |
|---------|----------------------------|----------------------------|----------------------------|----------------------------|----------------------------|
| TLV705  | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |
| TLV705P | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> | <a href="#">Click here</a> |

## 11.4 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's [Terms of Use](#).

**TI E2E™ Online Community** *TI's Engineer-to-Engineer (E2E) Community*. Created to foster collaboration among engineers. At [e2e.ti.com](http://e2e.ti.com), you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

**Design Support** *TI's Design Support* Quickly find helpful E2E forums along with design support tools and contact information for technical support.

## 11.5 Trademarks

E2E is a trademark of Texas Instruments.

PicoStar is a trademark of Texas Instruments, Inc.

Bluetooth is a registered trademark of Bluetooth SIG, Inc.

Zigbee is a registered trademark of ZigBee Alliance.

All other trademarks are the property of their respective owners.

## 11.6 Electrostatic Discharge Caution



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

## 11.7 Glossary

[SLYZ022](#) — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

## 12 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

### 12.1 Package Mounting

Solder pad footprint recommendations for the TLV705 are available from the [Packaging Information](#) page on TI's website through the [TLV705 series product folders](#). The recommended land patterns for the YFF, YFP, and YFM packages are appended to this data sheet.

**PACKAGING INFORMATION**

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5) | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|-------------------------|-------------------------|
| TLV70512YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BU                      | <a href="#">Samples</a> |
| TLV70512YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BU                      | <a href="#">Samples</a> |
| TLV70515YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BV                      | <a href="#">Samples</a> |
| TLV70515YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BV                      | <a href="#">Samples</a> |
| TLV705185YFPR    | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | YS                      | <a href="#">Samples</a> |
| TLV705185YFPT    | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | YS                      | <a href="#">Samples</a> |
| TLV70518PYFPR    | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | EV                      | <a href="#">Samples</a> |
| TLV70518PYFPT    | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | EV                      | <a href="#">Samples</a> |
| TLV70518YFMR     | ACTIVE        | DSLGA        | YFM                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70518YFMT     | ACTIVE        | DSLGA        | YFM                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70518YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | WT                      | <a href="#">Samples</a> |
| TLV70518YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | WT                      | <a href="#">Samples</a> |
| TLV70525PYFPR    | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 85    | EK                      | <a href="#">Samples</a> |
| TLV70525PYFPT    | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 85    | EK                      | <a href="#">Samples</a> |
| TLV70525YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | YB                      | <a href="#">Samples</a> |
| TLV70525YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | YB                      | <a href="#">Samples</a> |
| TLV705285YFPR    | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BW                      | <a href="#">Samples</a> |

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5) | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|-------------------------|-------------------------|
| TLV705285YFPT    | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BW                      | <a href="#">Samples</a> |
| TLV70528YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | WU                      | <a href="#">Samples</a> |
| TLV70528YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | WU                      | <a href="#">Samples</a> |
| TLV70530YFMR     | ACTIVE        | DSLGA        | YFM                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70530YFMT     | ACTIVE        | DSLGA        | YFM                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70530YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | XA                      | <a href="#">Samples</a> |
| TLV70530YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | XA                      | <a href="#">Samples</a> |
| TLV70533YFFR     | ACTIVE        | DSBGA        | YFF                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | US                      | <a href="#">Samples</a> |
| TLV70533YFFT     | ACTIVE        | DSBGA        | YFF                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | US                      | <a href="#">Samples</a> |
| TLV70533YFMR     | ACTIVE        | DSLGA        | YFM                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70533YFMT     | ACTIVE        | DSLGA        | YFM                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70533YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | VV                      | <a href="#">Samples</a> |
| TLV70533YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | VV                      | <a href="#">Samples</a> |
| TLV70534YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | B4                      | <a href="#">Samples</a> |
| TLV70534YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | B4                      | <a href="#">Samples</a> |
| TLV70536YFMR     | ACTIVE        | DSLGA        | YFM                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70536YFMT     | ACTIVE        | DSLGA        | YFM                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   |                         | <a href="#">Samples</a> |
| TLV70536YFPR     | ACTIVE        | DSBGA        | YFP                | 4    | 3000           | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BX                      | <a href="#">Samples</a> |

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package<br>Qty | Eco Plan<br>(2)            | Lead/Ball Finish<br>(6) | MSL Peak Temp<br>(3) | Op Temp (°C) | Device Marking<br>(4/5) | Samples                 |
|------------------|---------------|--------------|--------------------|------|----------------|----------------------------|-------------------------|----------------------|--------------|-------------------------|-------------------------|
| TLV70536YFPT     | ACTIVE        | DSBGA        | YFP                | 4    | 250            | Green (RoHS<br>& no Sb/Br) | Call TI                 | Level-1-260C-UNLIM   | -40 to 125   | BX                      | <a href="#">Samples</a> |

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.


(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.


**TAPE AND REEL INFORMATION**


\*All dimensions are nominal

| Device        | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|---------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| TLV70512YFPR  | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70512YFPT  | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70515YFPR  | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70515YFPT  | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV705185YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV705185YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70518PYFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70518PYFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70518YFMR  | DSLGA        | YFM             | 4    | 3000 | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70518YFMT  | DSLGA        | YFM             | 4    | 250  | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70518YFPR  | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70518YFPT  | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70525PYFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70525PYFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70525YFPR  | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70525YFPT  | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV705285YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV705285YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |

| Device       | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|--------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| TLV70528YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70528YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70530YFMR | DSLGA        | YFM             | 4    | 3000 | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70530YFMT | DSLGA        | YFM             | 4    | 250  | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70530YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70530YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70533YFFR | DSBGA        | YFF             | 4    | 3000 | 180.0              | 8.4                | 0.85    | 0.85    | 0.64    | 4.0     | 8.0    | Q1            |
| TLV70533YFFT | DSBGA        | YFF             | 4    | 250  | 180.0              | 8.4                | 0.85    | 0.85    | 0.64    | 4.0     | 8.0    | Q1            |
| TLV70533YFMR | DSLGA        | YFM             | 4    | 3000 | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70533YFMT | DSLGA        | YFM             | 4    | 250  | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70533YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70533YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70534YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70534YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70536YFMR | DSLGA        | YFM             | 4    | 3000 | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70536YFMT | DSLGA        | YFM             | 4    | 250  | 180.0              | 8.4                | 0.88    | 0.88    | 0.22    | 4.0     | 8.0    | Q1            |
| TLV70536YFPR | DSBGA        | YFP             | 4    | 3000 | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |
| TLV70536YFPT | DSBGA        | YFP             | 4    | 250  | 180.0              | 8.4                | 0.86    | 0.86    | 0.59    | 4.0     | 8.0    | Q1            |

## TAPE AND REEL BOX DIMENSIONS




\*All dimensions are nominal

| Device        | Package Type | Package Drawing | Pins | SPQ  | Length (mm) | Width (mm) | Height (mm) |
|---------------|--------------|-----------------|------|------|-------------|------------|-------------|
| TLV70512YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70512YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70515YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70515YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV705185YFPR | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV705185YFPT | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70518PYFPR | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70518PYFPT | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70518YFMR  | DSLGA        | YFM             | 4    | 3000 | 210.0       | 185.0      | 35.0        |
| TLV70518YFMT  | DSLGA        | YFM             | 4    | 250  | 210.0       | 185.0      | 35.0        |
| TLV70518YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70518YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70525PYFPR | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70525PYFPT | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70525YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70525YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV705285YFPR | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV705285YFPT | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70528YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70528YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70530YFMR  | DSLGA        | YFM             | 4    | 3000 | 210.0       | 185.0      | 35.0        |
| TLV70530YFMT  | DSLGA        | YFM             | 4    | 250  | 210.0       | 185.0      | 35.0        |
| TLV70530YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70530YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70533YFFR  | DSBGA        | YFF             | 4    | 3000 | 210.0       | 185.0      | 35.0        |
| TLV70533YFFT  | DSBGA        | YFF             | 4    | 250  | 210.0       | 185.0      | 35.0        |
| TLV70533YFMR  | DSLGA        | YFM             | 4    | 3000 | 210.0       | 185.0      | 35.0        |
| TLV70533YFMT  | DSLGA        | YFM             | 4    | 250  | 210.0       | 185.0      | 35.0        |
| TLV70533YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70533YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70534YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70534YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |
| TLV70536YFMR  | DSLGA        | YFM             | 4    | 3000 | 210.0       | 185.0      | 35.0        |
| TLV70536YFMT  | DSLGA        | YFM             | 4    | 250  | 210.0       | 185.0      | 35.0        |
| TLV70536YFPR  | DSBGA        | YFP             | 4    | 3000 | 182.0       | 182.0      | 20.0        |
| TLV70536YFPT  | DSBGA        | YFP             | 4    | 250  | 182.0       | 182.0      | 20.0        |

YFP (S-XBGA-N4)

DIE-SIZE BALL GRID ARRAY



D: Max = 0.806 mm, Min = 0.746 mm

E: Max = 0.806 mm, Min = 0.746 mm


4206986-2/T 05/13

- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
  - B. This drawing is subject to change without notice.
  - C. NanoFree™ package configuration.

NanoFree is a trademark of Texas Instruments

YFF (S-XBGA-N4)

DIE-SIZE BALL GRID ARRAY



D: Max = 0.806 mm, Min = 0.746 mm


E: Max = 0.806 mm, Min = 0.746 mm

4207625-2/A0 12/13

- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
  - B. This drawing is subject to change without notice.
  - C. NanoFree™ package configuration.

YFM (S-pSTAR-N4)

PicoStar™



4209106-2/L 02/14

NOTES: A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.

B. This drawing is subject to change without notice.

C. PicoStar™ package configuration.

The package size (Dimension D and E) of a particular device is specified in the device Product Data Sheet version of this drawing, in case it cannot be found in the product data sheet please contact a local TI representative.

Reference Product Data Sheet for array population. 2 x 2 matrix pattern is shown for illustration only.

F. This package is a Pb-free solder land design.

PicoStar is a trademark of Texas Instruments.

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

|                              |                                                                                      |
|------------------------------|--------------------------------------------------------------------------------------|
| Audio                        | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers                   | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters              | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products                | <a href="http://www.dlp.com">www.dlp.com</a>                                         |
| DSP                          | <a href="http://dsp.ti.com">dsp.ti.com</a>                                           |
| Clocks and Timers            | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface                    | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                        | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt                   | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers             | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                         | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Applications Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity        | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |                                                                                          |
|-------------------------------|------------------------------------------------------------------------------------------|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.