


The World Leader in High Performance Signal Processing Solutions



iSensor®

ADIS16135 Evaluation Tool Overview




Mark Looney
***i*Sensor® Application Engineer**
January 22, 2010

ANALOG DEVICES

*i*Sensor® *The Simple Solution for Sensor Integration*
PC-Based Evaluation

- **The ADISUSBZ provides PC-based demonstration and basic evaluation support for the ADIS16135BMLZ.**
  - This system provides a simple USB interface, along with a simple graphical user interface (GUI) package, for evaluating most of the ADIS16135 functions and performance.
  - This system is most useful for basic data collection and performance validation.
  - This is not a real-time development system. No SDK available.
  - Part number for ordering: (1) ADIS16135BMLZ, (1) ADISUSBZ

ADIS16135BMLZ




ADISUSBZ

iSensor® *The Simple Solution for Sensor Integration*

Hooking up to the ADIS16135/PCBZ


Need to integrate J4 to a new PCB design?





ADISEVALUSBZ-135 uses the following J4 connector from Samtec:

CLM-112-02-LM-D-A



Master Processor *Connection*


ANALOG DEVICES


iSensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Software Installation

Installation Steps (continued)

4. Click **OK** on next screen
5. Click here to start installation






iSensor® The Simple Solution for Sensor Integration
ADIS163135 Demonstration Software Installation


Installation Steps (continued)


6. Click **Continue**

7. If this message comes up, click on **No**

8. Click **OK**









iSensor® The Simple Solution for Sensor Integration
ADIS16135 Demonstration Software Installation

Installation Steps (continued)

9. Open the newly created directory and double-click onto **GIVEIO.EXE**
10. Click **Install,** then **I agree**







iSensor® The Simple Solution for Sensor Integration
ADIS16135 Demonstration Software Installation

Installation Steps (continued)

11. Click **Yes**

12. Giveio Driver complete, click **OK**







iSensor® The Simple Solution for Sensor Integration
ADIS16135BMLZ Installation on ADISEVALUSBZ-135


Installation Steps (continued)

13. Install ADIS16135BMLZ on ADISEVALUSBZ
14. Remove ribbon cable and screws
15. Carefully insert the ADIS16135BMLZ into the J4 connector
16. Secure part with 2x18mm screws





1. Secure with 2x18mm screws



2. Attach 135/PCBZ to J4 Connector



3. Verify JP1 set to +5V



4. Hook USB cable up




*i*Sensor® The Simple Solution for Sensor Integration


ADIS16135 Demonstration Software Installation

Installation Steps (continued)

15. USB Driver screen will pop-up
    Click **Next** to start this process

16. Then click on
    Continue Anyway






This process will repeat for a second driver file. Just follow the instructions and allow it to go through one more time. After completing this, then the devices is ready for test.

*i*Sensor® The Simple Solution for Sensor Integration


ADIS16135 Demonstration Tips—Verify USB Driver



ANALOG DEVICES


*i*Sensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Tips— Initial Start up



*i*Sensor® The Simple Solution for Sensor Integration


ADIS16135 Demonstration Tips—AUTO-Null




ANALOG DEVICES

*i*Sensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Tips— Gyro






1. **Watch the Gyro Out response on screen.**

ANALOG DEVICES


*i*Sensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Tips— Alarms??



*i*Sensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Tips— Alarm Set up




1. **Set Alarm 1 source for Gyro Out.**
2. **Set the Trigger level to 50 and Greater Than**
3. **Click the Update button to accept changes**
4. **Click on Close Window to return to the main screen**

ANALOG DEVICES

*i*Sensor® The Simple Solution for Sensor Integration


ADIS16135 Demonstration Tips— Alarms Continued



5. **Alarm 1 is set when the Gyro level is above 50**
6. **The Plot Scale can be changed for a more accurate reading by moving the slider**

*i*Sensor® The Simple Solution for Sensor Integration

ADIS16135 Demonstration Tips— Collect Data



1. Select Datalog on the main screen
2. File Setup- enter # of samples delay and # of files
3. Data Selection- Choose the output data you want
4. File Information- Enter the file name and # of files
5. Start Datalog- Click the button to begin data processing

a. File is output to program file folder created during installation



- **CONTACTS:**
  - **MARKETING:** Bob Scannell, 1-336-605-4031
  - **APPLICATIONS ENGINEER:** Mark Looney, 1-336-605-4139

MORE INFORMATION:

- www.analog.com/isensor
- New Brochure: *i*Sensor Motion Sensor Products

Analog Devices, Inc.
7910 Triad Center Drive
Greensboro, NC 27409
EMAIL: mark.looney@analog.com

ANALOG DEVICES


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.