

## Ultra Low Noise Low Dropout Voltage Regulator

### ■ GENERAL DESCRIPTION

The NJM2863/64 is a low dropout voltage regulator designed for VCO Applications.

Advanced Bipolar technology achieves ultra low noise, high ripple rejection and low quiescent current.

### ■ PACKAGE OUTLINE





NJM2863F/64F


### ■ FEATURES

- High Ripple Rejection      75dB typ. (f=1kHz, Vo=3V Version)
- Output capacitor with 1.0μF ceramic capacitor
- Output Noise Voltage      Vno=19μVrms typ. (Cp=0.01μF, Co=1.0μF(Ceramic))  
Vno=12μVrms typ. (Cp=0.1μF, Co=10μF(Tantalum))
- Output Current      Io(max.)=100mA
- High Precision Output      Vo±1.0%
- Low Dropout Voltage      0.10V typ. (Io=60mA)
- ON/OFF Control      (Active High)
- Internal Short Circuit Current Limit
- Internal Thermal Overload Protection
- Bipolar Technology
- Package Outline      SOT-23-5

### ■ PIN CONFIGURATION



### ■ EQUIVALENT CIRCUIT



# NJM2863/64

## ■ OUTPUT VOLTAGE RANK LIST

| Device Name | V <sub>OUT</sub> | Device Name | V <sub>OUT</sub> |
|-------------|------------------|-------------|------------------|
| NJM286×F21  | 2.1V             | NJM286×F29  | 2.9V             |
| NJM286×F25  | 2.5V             | NJM286×F03  | 3.0V             |
| NJM286×F27  | 2.7V             | NJM286×F33  | 3.3V             |
| NJM286×F28  | 2.8V             | NJM286×F05  | 5.0V             |
| NJM286×F285 | 2.85V            |             |                  |

## ■ ABSOLUTE MAXIMUM RATINGS

(Ta=25°C)

| PARAMETER             | SYMBOL            | RATINGS                        | UNIT |
|-----------------------|-------------------|--------------------------------|------|
| Input Voltage         | V <sub>IN</sub>   | +14                            | V    |
| Control Voltage       | V <sub>CONT</sub> | +14(*1)                        | V    |
| Power Dissipation     | P <sub>D</sub>    | SOT-23-5<br>350(*2)<br>200(*3) | mW   |
| Operating Temperature | T <sub>opr</sub>  | -40 ~ +85                      | °C   |
| Storage Temperature   | T <sub>stg</sub>  | -40 ~ +125                     | °C   |

(\*1): When input voltage is less than +14V, the absolute maximum control voltage is equal to the input voltage.

(\*2): Mounted on glass epoxy board based on EIA/JEDEC. (114.3x76.2x1.6mm: 2Layers)

(\*3): Device itself.


## ■ ELECTRICAL CHARACTERISTICS (V<sub>IN</sub>=V<sub>O</sub>+1V, C<sub>IN</sub>=0.1μF, C<sub>O</sub>=1.0μF, C<sub>p</sub>=0.01μF, Ta=25°C)

| PARAMETER                                         | SYMBOL                            | TEST CONDITION                                                                                                          | MIN.  | TYP. | MAX.  | UNIT   |
|---------------------------------------------------|-----------------------------------|-------------------------------------------------------------------------------------------------------------------------|-------|------|-------|--------|
| Output Voltage                                    | V <sub>O</sub>                    | I <sub>O</sub> =30mA                                                                                                    | -1.0% | —    | +1.0% | V      |
| Quiescent Current                                 | I <sub>Q</sub>                    | I <sub>O</sub> =0mA, except I <sub>cont</sub>                                                                           | —     | 120  | 180   | μA     |
| Quiescent Current at Control OFF                  | I <sub>Q(OFF)</sub>               | V <sub>CONT</sub> =0V                                                                                                   | —     | —    | 100   | nA     |
| Output Current                                    | I <sub>O</sub>                    | V <sub>O</sub> -0.3V                                                                                                    | 100   | 130  | —     | mA     |
| Line Regulation                                   | ΔV <sub>O</sub> /ΔV <sub>IN</sub> | V <sub>IN</sub> =V <sub>O</sub> +1V ~ V <sub>O</sub> +6V, I <sub>O</sub> =30mA                                          | —     | —    | 0.10  | %/V    |
| Load Regulation                                   | ΔV <sub>O</sub> /ΔI <sub>O</sub>  | I <sub>O</sub> =0 ~ 100mA                                                                                               | —     | —    | 0.03  | %/mA   |
| Dropout Voltage                                   | ΔV <sub>I-O</sub>                 | I <sub>O</sub> =60mA                                                                                                    | —     | 0.10 | 0.18  | V      |
| Ripple Rejection                                  | RR                                | e <sub>in</sub> =200mVrms, f=1kHz, I <sub>O</sub> =10mA, V <sub>O</sub> =3V Version                                     | —     | 75   | —     | dB     |
| Average Temperature Coefficient of Output Voltage | ΔV <sub>O</sub> /ΔTa              | Ta=0~85°C, I <sub>O</sub> =10mA                                                                                         | —     | ± 50 | —     | ppm/°C |
| Output Noise Voltage1                             | V <sub>NO1</sub>                  | f=10Hz~80kHz, I <sub>O</sub> =10mA, C <sub>p</sub> =0.01μF, C <sub>O</sub> =1.0μF (Ceramic), V <sub>O</sub> =3V Version | —     | 19   | —     | μVrms  |
| Output Noise Voltage2                             | V <sub>NO2</sub>                  | f=10Hz~80kHz, I <sub>O</sub> =10mA, C <sub>p</sub> =0.1μF, C <sub>O</sub> =10μF (Tantalum), V <sub>O</sub> =3V Version  | —     | 12   | —     | μVrms  |
| Control Voltage for ON-state                      | V <sub>CONT(ON)</sub>             |                                                                                                                         | 1.6   | —    | —     | V      |
| Control Voltage for OFF-state                     | V <sub>CONT(OFF)</sub>            |                                                                                                                         | —     | —    | 0.6   | V      |

The above specification is a common specification for all output voltages.


Therefore, it may be different from the individual specification for a specific output voltage.

## ■ TEST CIRCUIT




## ■ TYPICAL APPLICATION

① In the case where ON/OFF Control is not required:



Connect control terminal to  $V_{IN}$  terminal

② In use of ON/OFF CONTROL:



State of control terminal:

- "H" → output is enabled.
- "L" or "open" → output is disabled.

### \*Noise bypass Capacitance $C_p$


Noise bypass capacitance  $C_p$  reduces noise generated by band-gap reference circuit. Noise level and ripple rejection will be improved when larger  $C_p$  is used. Use of smaller  $C_p$  value may cause oscillation. Use the  $C_p$  value of 0.01μF greater to avoid the problem.

### \*In the case of using a resistance "R" between $V_{IN}$ and control.







The current flow into the control terminal while the IC is ON state ( $I_{CONT}$ ) can be reduced when a pull up resistance "R" is inserted between  $V_{IN}$  and the control terminal.

The minimum control voltage for ON state ( $V_{CONT(ON)}$ ) is increased due to the voltage drop caused by  $I_{CONT}$  and the resistance "R". The  $I_{CONT}$  is temperature dependence as shown in the "Control Current vs. Temperature" characteristics. Therefore, the resistance "R" should be carefully selected to ensure the control voltage exceeds the  $V_{CONT(ON)}$  over the required temperature range.







POWER DISSIPATION vs. AMBIENT TEMPERATURE









## ELECTRICAL CHARACTERISTICS








## ELECTRICAL CHARACTERISTICS







## ELECTRICAL CHARACTERISTICS



## ELECTRICAL CHARACTERISTICS



## ELECTRICAL CHARACTERISTICS



**[CAUTION]**  
The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.