



Is Now Part of



ON Semiconductor®

To learn more about ON Semiconductor, please visit our website at
www.onsemi.com

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (_), the underscore (_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at www.onsemi.com. Please email any questions regarding the system integration to Fairchild_questions@onsemi.com.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

FPF1015/6/7/8 IntelliMAX™ 1V Rated Advanced Load Management Products

Features

- 0.8 to 1.8V Input Voltage Range
- Typical $R_{DS(ON)} = 34m\Omega$ @ $V_{ON} - V_{IN} = 2.0V$
- Output Discharge Function
- Internal Pull down at ON Pin
- Accurate Slew Rate Controlled Turn-on time
- Low < 1 μ A Quiescent Current
- ESD Protected, above 8000V HBM, 2000V CDM
- RoHS Compliant
- Free from Halogenated Compounds and Antimony Oxides

Applications

- PDAs
- Cell Phones
- GPS Devices
- MP3 Players
- Digital Cameras
- Notebook Computers




General Description

The FPF1015/6/7/8 series is an IntelliMAX advanced slew rate loadswitch offering a very low operating voltage. These devices consist of a 34m Ω N-channel MOSFET that supports an input voltage up to 2.0V. These slew rate devices control the switch turn-on and prevent excessive in-rush current from the supply rails. The input voltage range operates from 0.8V to 1.8V to fulfill today's lowest Ultraportable Device's supply requirements. Switch control is via a logic input (ON) capable of interfacing directly with low voltage control signals.

The FPF1016 and FPF1018 have an On-Chip pull down allowing for quick and controlled output discharge when switch is turned off. The FPF1015/6/7/8 series is available in a space-saving 2X2 MLP-6L package.

PIN 1




BOTTOM



TOP


Typical Application Circuit




Ordering Information

| Part | Switch | Turn-on Time | Output Discharge | ON Pin Activity | Package |
|---------|---------------------|--------------|------------------|-----------------|---------|
| FPF1015 | 34m Ω , NMOS | 43us | NA | Active HI | MLP 2x2 |
| FPF1016 | 34m Ω , NMOS | 43us | 60 Ω | Active HI | MLP 2x2 |
| FPF1017 | 34m Ω , NMOS | 165us | NA | Active HI | MLP 2x2 |
| FPF1018 | 34m Ω , NMOS | 165us | 60 Ω | Active HI | MLP 2x2 |

Functional Block Diagram



Pin Configuration



Pin Description

| Pin | Name | Function |
|------|------------------|---|
| 1 | ON | ON/OFF Control Input, 2nd Supply |
| 2, 3 | V _{IN} | Supply Input: Input to the power switch |
| 4, 5 | V _{OUT} | Switch Output. |
| 6 | GND | Ground |

Absolute Maximum Ratings

| Parameter | Min | Max | Unit |
|--|------|------|------|
| V _{IN} , V _{OUT} to GND | -0.3 | 2 | V |
| V _{ON} to GND | -0.3 | 4.2 | V |
| Maximum Continuous Switch Current | | 1.5 | A |
| Power Dissipation @ T _A = 25°C (Note 1) | | 1.2 | W |
| Operating Temperature Range | -40 | 85 | °C |
| Storage Temperature | -65 | 150 | °C |
| Thermal Resistance, Junction to Ambient | | 86 | °C/W |
| Electrostatic Discharge Protection | HBM | 8000 | V |
| | CDM | 2000 | V |

Recommended Operating Range

| Parameter | Min | Max | Unit |
|---|-----|-----|------|
| V _{IN} | 0.8 | 1.8 | V |
| Ambient Operating Temperature, T _A | -40 | 85 | °C |

Note 1: Package power dissipation on 1square inch pad, 2 oz. copper board

Electrical Characteristics

$V_{IN} = 0.8$ to $1.8V$, $T_A = -40$ to $+85^\circ C$ unless otherwise noted. Typical values are at $V_{IN} = 1.8V$ and $T_A = 25^\circ C$.

| Parameter | Symbol | Conditions | Min | Typ | Max | Unit |
|---|---------------|--|-----|-----|-----|------------|
| Basic Operation | | | | | | |
| Operating Voltage | V_{IN} | | 0.8 | | 1.8 | V |
| ON input Voltage | $V_{ON(MIN)}$ | $V_{IN} = 0.8V$ | 1.8 | 2.8 | 4.0 | V |
| | $V_{ON(MAX)}$ | $V_{IN} = 1.8V$ (Note2) | 2.8 | 3.8 | 4.0 | V |
| Operating Current | I_{CC} | $V_{IN} = 1V$, $V_{ON} = 3.3V$, $V_{OUT} = \text{Open}$ | | | 1 | μA |
| Quiescent Current | I_Q | $V_{IN} = 1V$, $V_{ON} = V_{OUT} = \text{Open}$ | | | 2 | μA |
| Off Switch Current | I_{SWOFF} | $V_{IN} = 1.8V$, $V_{ON} = GND$, $V_{OUT} = GND$ | | | 2 | μA |
| On-Resistance | R_{ON} | $V_{IN} = 1V$, $V_{ON} = 3V$, $I_{LOAD} = 1A$, $T_A = 25^\circ C$ | | 34 | 45 | m Ω |
| | | $V_{IN} = 1V$, $V_{ON} = 2.3V$, $I_{LOAD} = 1A$, $T_A = 25^\circ C$ | | 41 | 55 | |
| Output Pull Down Resistance | R_{PD} | $V_{IN} = 1V$, $V_{ON} = 0V$, $T_A = 25^\circ C$, $I_{LOAD} = 1mA$, FPF1016, FPF1018 | | 60 | 120 | Ω |
| ON Input Logic Low Voltage | V_{IL} | $V_{IN} = 0.8V$, $R_{LOAD} = 1K\Omega$ | | | 0.3 | V |
| | | $V_{IN} = 1.8V$, $R_{LOAD} = 1K\Omega$ | | | 0.8 | |
| ON Input Leakage | | $V_{ON} = V_{IN}$ or GND | -1 | | 1 | μA |
| Dynamic ($V_{IN} = 1.0V$, $V_{ON} = 3.0V$, $T_A = 25^\circ C$) | | | | | | |
| V_{OUT} Rise Time | T_R | FPF1015, FPF1016, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 28 | | μs |
| | | FPF1017, FPF1018, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 114 | | |
| | | FPF1015, FPF1016, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 38 | | |
| | | FPF1017, FPF1018, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 155 | | |
| Turn ON | T_{ON} | FPF1015, FPF1016, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 43 | | μs |
| | | FPF1017, FPF1018, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 165 | | |
| | | FPF1015, FPF1016, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 58 | | |
| | | FPF1017, FPF1018, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 228 | | |
| V_{OUT} Fall Time | T_F | FPF1015, FPF1017, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 105 | | μs |
| | | FPF1016, FPF1018, $R_{PD} = 60\Omega$, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 15 | | |
| | | FPF1015, FPF1017, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 80 | | |
| | | FPF1016, FPF1018, $R_{PD} = 60\Omega$, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 74 | | |
| Turn Off | T_{OFF} | FPF1015, FPF1017, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 150 | | μs |
| | | FPF1016, FPF1018, $R_{PD} = 60\Omega$, $R_L = 500\Omega$, $C_L = 0.1\mu F$ | | 53 | | |
| | | FPF1015, FPF1017, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 102 | | |
| | | FPF1016, FPF1018, $R_{PD} = 60\Omega$, $R_L = 3.3\Omega$, $C_L = 10\mu F$ | | 96 | | |

Note 2: $V_{ON(MAX)}$ is limited by the absolute rating.

Typical Characteristics




Figure 1. Supply Current vs. V_{IN}




Figure 2. Quiescent Current vs. Temperature




Figure 3. Operating Current vs. Temperature




Figure 4. Off Switch Current vs. Temperature




Figure 5. R_{ON} vs. Temperature




Figure 6. R_{ON} vs. $V_{ON} - V_{IN}$

Typical Characteristics




Figure 7. V_{IL} vs. V_{IN}




Figure 8. V_{IL} vs. Temperature




Figure 9. T_{RISE}/T_{FALL} vs. Temperature




Figure 10. T_{ON}/T_{OFF} vs. Temperature




Figure 11. FPF1015 / 16 Turn ON response




Figure 12. FPF1015 / 16 Turn ON response

Typical Characteristics




Figure 13. FPF1017 / 18 Turn On response




Figure 14. FPF1017 / 18 Turn On response




Figure 15. FPF1015 / 17 Turn OFF response




Figure 16. FPF1015 / 17 Turn OFF response




Figure 17. FPF1016 / 18 Turn OFF response




Figure 18. FPF1016 / 18 Turn OFF response

Typical Characteristics




Figure 19. FPF1016 / 18 Output Pull Down response

Description of Operation


The FPF1015/6/7/8 are low $R_{DS(ON)}$ N-Channel load switches with controlled turn-on. The core of each device is a 34m Ω ($V_{IN} = 1V$, $V_{ON} = 3V$) N-Channel MOSFET and is customized for a low input operating range of 0.8 to 1.8V. The ON pin controls the state of the switch.

The FPF1016 and FPF1018 contain a 60 Ω (typ) on-chip resistor which is connected internally from V_{OUT} to GND for quick output discharge when the switch is turned off.

On/Off Control

The ON pin is active high and it controls the state of the switch. Applying a continuous high signal will hold the switch in the ON state. In order to minimize the switch on resistance, the ON pin voltage should exceed the input voltage by 2V. This device is compatible with a GPIO (General Purpose Input/Output) port, where the logic voltage level can be configured to $4V \geq V_{ON} \geq V_{IN} + 2V$ and power consumed is less than 1 μ A in steady state.

Timing Diagram




where:

- t_{dON} = Delay On Time
- t_R = V_{OUT} Rise Time
- t_{ON} = Turn On Time
- t_{dOFF} = Delay Off Time
- t_F = V_{OUT} Fall Time
- t_{OFF} = Turn Off Time

Application Information

Typical Application



Input Capacitor

To limit the voltage drop on the input supply caused by transient in-rush currents when the switch turns-on, a capacitor must be placed between V_{IN} and GND. For minimized voltage drop, especially when the operating voltage approaches 1V and a fast slew rate part (FPF1015 and FPF1016) is selected, a 10 μ F ceramic capacitor should be placed close to the V_{IN} pins. Higher values of C_{IN} can be used to further reduce the voltage drop during higher current modes of operation.

Board Layout

For best performance, all traces should be as short as possible. To be most effective, the input and output capacitors should be placed close to the device to minimize the effects that parasitic trace inductances may have on normal and short-circuit operation. Using wide traces or large copper planes for all pins (V_{IN} , V_{OUT} , ON and GND) will help minimize the parasitic electrical effects along with minimizing the case to ambient thermal impedance.

Output Capacitor

A 0.1 μ F capacitor, C_L , should be placed between V_{OUT} and GND. This capacitor will prevent parasitic board inductance from forcing V_{OUT} below GND when the switch turns-off. If the application has a capacitive load, the FPF1016 and FPF1018 can be used to discharge that load through an on-chip output discharge path.

Improving Thermal Performance

An improper layout could result in higher junction temperature. This concern applies when the current is at its continuous maximum value and is then switched into a large capacitive load that introduces a large transient current. Since the FPF1015/6/7/8 does not have thermal shutdown capability, a proper layout is essential to improving power dissipation of the switch in transient events and prevents the switch from exceeding the maximum absolute power dissipation of 1.2W.

The following techniques have been identified to improve the thermal performance of this family of devices. These techniques are listed in order of the significance of their impact.

1. Thermal performance of the load switch can be improved by connecting pin7 of the DAP (Die Attach Pad) to the GND plane of the PCB.
2. Embedding two exposed through-hole vias into the DAP (pin7) provides a path for heat to transfer to the back GND plane of the PCB. A drill size of Round, 14 mils (0.35mm) with 1-ounce copper plating is recommended to result in appropriate solder reflow. A smaller size hole prevents the solder from penetrating into the via, resulting in device lift-up. Similarly, a larger via-hole consumes excessive solder, and may result in voiding of the DAP.




Figure 19: Two through hole open vias embedded in DAP

3. The V_{IN} , V_{OUT} and GND pins will dissipate most of the heat generated during a high load current condition. The layout suggested in Figure 20 provides each pin with adequate copper so that heat may be transferred as efficiently as possible out of the device. The ON pin trace may be laid-out diagonally from the device to maximize the area available to the ground pad. Placing the input and output capacitors as close to the device as possible also contributes to heat dissipation, particularly during high load currents.




Figure 20: Proper layout of output, input and ground copper area

Demo Board Layout

FPF1015/6/7/8 Demo board has the components and circuitry to demonstrate FPF1015/6/7/8 load switches functions. Thermal performance of the board is improved using a few techniques recommended in the layout recommendations section of datasheet.








Figure 21. FPF1015/6/7/8 Demo board TOP, SST, ASTOP and DRL layers



RECOMMENDED LAND PATTERN

NOTES:

- CONFORM TO JEDEC REGISTRATIONS MO-229, VARIATION VCCC, EXCEPT WHERE NOTED.
- DIMENSIONS ARE IN MILLIMETERS.
- LAND PATTERN RECOMMENDATION IS EXISTING INDUSTRY LAND PATTERN.
- DRAWING FILENAME: MKT-UMLP16ErevC

ON Semiconductor



ON Semiconductor and  are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada
Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800-282-9855 Toll Free
USA/Canada

Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

Japan Customer Focus Center
Phone: 81-3-5817-1050

ON Semiconductor Website: www.onsemi.com

Order Literature: <http://www.onsemi.com/orderlit>

For additional information, please contact your local
Sales Representative

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[ON Semiconductor:](#)

[FPF1018](#)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.