

DATA SHEET

SKY13438-374LF: 0.1-6.0 GHz DPDT Switch

Applications

- Dual-band wireless LANs (802.11 a/b/g/n)
- Diversity antenna switching

Features

- Broadband frequency range: 0.1 to 6.0 GHz
- Positive control voltage range: 1.8 to 5.0 V
- Low insertion loss:
 - 0.65 dB typical @ 2.5 GHz
 - 1.20 dB typical @ 6.0 GHz
- High isolation:
 - 27 dB typical @ 2.5 GHz
 - 25 dB typical @ 6.0 GHz
- P1dB:
 - +31 dBm typical @ 3 V, 2.5 GHz
 - +29 dBm typical @ 3 V, 6.0 GHz
- Small, MLPD (6-pin, 1.5 x 1.5 mm) Pb-free package (MSL1, 260 °C per JEDEC J-STD-020)



Skyworks Green™ products are compliant with all applicable legislation and are halogen-free. For additional information, refer to *Skyworks Definition of Green™*, document number SQ04-0074.




Figure 1. SKY13438-374LF Block Diagram

Description

The SKY13438-374LF is a pHEMT GaAs Double-Pole, Double-Throw (DPDT) switch designed for 2.4 and 6.0 GHz, dual-band wireless LAN applications. The switch provides high linearity performance, low insertion loss, and high isolation in both frequency bands.

Switching is controlled by two voltage inputs (V1 and V2). Depending on the logic voltage level applied to the control pins, the ANT1 and ANT2 pins connect to one of two switched RF outputs (RX or TX) through a low insertion loss path while maintaining a high isolation path to the alternate port.

The switch is manufactured in a compact, 1.5 x 1.5 mm, 6-pin exposed pad plastic Micro Leadframe Package Dual (MLPD) package.

A functional block diagram is shown in Figure 1. The pin configuration and package are shown in Figure 2. Signal pin assignments and functional pin descriptions are provided in Table 1.




Figure 2. SKY13438-374LF Pinout – 6-Pin MLPD (Top View)

Table 1. SKY13438-374LF Signal Descriptions

| Pin # | Name | Description | Pin # | Name | Description |
|-------|------|---|-------|------|---|
| 1 | ANT2 | Antenna 2 RF port. Must be DC-blocked for proper operation. | 4 | TX | Transmit RF port. Must be DC-blocked for proper operation. |
| 2 | V2 | DC control voltage 2 | 5 | V1 | DC control voltage 1 |
| 3 | RX | Receive RF port. Must be DC-blocked for proper operation. | 6 | ANT1 | Antenna 1 RF port. Must be DC-blocked for proper operation. |

Note: Exposed backside ground pad must be properly grounded through a low impedance path.

Table 2. SKY13438-374LF Absolute Maximum Ratings

| Parameter | Symbol | Minimum | Typical | Maximum | Units |
|-----------------------|------------------|---------|---------|---------|-------|
| Control voltage | V1, V2 | | | 6 | V |
| RF input power | P _{IN} | | | +32 | dBm |
| Storage temperature | T _{STG} | -40 | | +125 | °C |
| Operating temperature | T _{OP} | -40 | | +85 | °C |

Note: Exposure to maximum rating conditions for extended periods may reduce device reliability. There is no damage to device with only one parameter set at the limit and all other parameters set at or below their nominal value. Exceeding any of the limits listed here may result in permanent damage to the device.

CAUTION: Although this device is designed to be as robust as possible, Electrostatic Discharge (ESD) can damage this device. This device must be protected at all times from ESD. Static charges may easily produce potentials of several kilovolts on the human body or equipment, which can discharge without detection. Industry-standard ESD precautions should be used at all times.

Electrical and Mechanical Specifications

The absolute maximum ratings of the SKY13438-374LF are provided in Table 2. Electrical specifications are provided in Table 3.

The state of the SKY13438-374LF is determined by the logic provided in Table 4.

Typical performance characteristics are illustrated in Figures 3 to 9.

Table 3. SKY13438-374LF Electrical Specifications (Note 1)

($V_{CTL} = 0\text{ V}$ and $+3.0\text{ V}$, $T_{OP} = +25\text{ }^{\circ}\text{C}$, $P_{IN} = 0\text{ dBm}$, Characteristic Impedance $[Z_0] = 50\text{ }\Omega$, Unless Otherwise Noted)

| Parameter | Symbol | Test Condition | Min | Typical | Max | Units |
|---------------------------------|--------|--|-----------------|------------|------------|------------|
| RF Specifications | | | | | | |
| Insertion loss | IL | ANT1/ANT2 to RX/TX: | | | | |
| | | 0.1 to 1.0 GHz | | 0.50 | 0.75 | dB |
| | | 1.0 to 2.5 GHz | | 0.65 | 0.9 | dB |
| | | 2.5 to 4.9 GHz | | 1.00 | 1.30 | dB |
| | | 4.9 to 6.0 GHz | | 1.20 | 1.40 | dB |
| Isolation | Iso | ANT1/ANT2 to RX/TX: | | | | |
| | | 0.1 to 1.0 GHz | 30 | 34 | | dB |
| | | 1.0 to 2.5 GHz | 26 | 27 | | dB |
| | | 2.5 to 4.9 GHz | 23 | 24 | | dB |
| | | 4.9 to 6.0 GHz | 22 | 25 | | dB |
| Isolation | Iso | ANT1 to ANT2, RX to TX: | | | | |
| | | 2.4 to 2.5 GHz | 27 | 31 | | dB |
| | | 4.9 to 6.0 GHz | 24 | 29 | | dB |
| Return loss (Note 2) | IS11I | ANT1/ANT2 to RX/TX, 0.1 to 6.0 GHz | | 15 | | dB |
| 1 dB Input Compression Point | IP1dB | 0.1 to 2.4 GHz 4.9 to 6.0 GHz | | +31 +29 | | dBm dBm |
| Input IP3 | IIP3 | $P_{IN} = +20\text{ dBm/}$ tone, $\Delta f = 1\text{ MHz}$: 2.5 GHz 4.9 to 6.0 GHz | | | | |
| | | | | +54 +52 | | dBm dBm |
| 2 nd harmonic | 2fo | $P_{IN} = +20\text{ dBm}$, 0.1 to 6.0 GHz | | +72 | | dBc |
| 3 rd harmonic | 3fo | $P_{IN} = +20\text{ dBm}$, 0.1 to 6.0 GHz | | +73 | | dBc |
| Switching speed | | 50% V1/V2 to 90/10% RF | | 160 | | ns |
| | | 90/10% RF or 10/90% RF | | 75 | | ns |
| DC Specifications | | | | | | |
| Control voltage: high low | V1, V2 | | 1.8 -0.2 | 3.0 0 | 5.0 0.2 | V V |
| | | Control current | I _{cc} | | 5 | |

Note 1: Performance is guaranteed only under the conditions listed in this Table.

Note 2: Lower frequency return loss is dependent on the DC blocking capacitor value.

Table 4. SKY13438-374LF Truth Table

| V1 (Pin 5) | V2 (Pin 2) | ANT1 (Pin 6) to TX (Pin 4) | ANT1 (Pin 6) to RX (Pin 3) | ANT2 (Pin 1) to TX (Pin 4) | ANT2 (Pin 1) to RX (Pin 3) |
|------------|------------|----------------------------|----------------------------|----------------------------|----------------------------|
| High | Low | Isolation state | Insertion loss state | Insertion loss state | Isolation state |
| Low | High | Insertion loss state | Isolation state | Isolation state | Insertion loss state |

Note: High = +1.8 V to +5 V. Low = -0.2 V to +0.2 V.

Typical Performance Characteristics

($V_{CTL} = 0\text{ V}$ and $+3.0\text{ V}$, $T_{OP} = +25\text{ }^{\circ}\text{C}$, $P_{IN} = 0\text{ dBm}$, Characteristic Impedance [Z_0] = $50\ \Omega$, Unless Otherwise Noted)




Figure 3. Insertion Loss vs Frequency




Figure 4. Isolation vs Frequency (ANT1 or ANT2 to TX or RX)




Figure 5. Isolation vs Frequency (ANT1 to ANT2 and TX to RX)




Figure 6. Return Loss vs Frequency (ANT2 to TX, ANT1 to RX Active)




Figure 7. Return Loss vs Frequency (ANT2 to RX, ANT1 to TX Active)




Figure 8. Compression vs Input Power @ 2.50 GHz and 3 V




Figure 9. Compression vs Input Power @ 4.85 to 6.00 GHz and 3 V

Evaluation Board Description

The SKY13438-374LF Evaluation Board is used to test the performance of the SKY13438-374LF SPDT Switch. An Evaluation Board schematic diagram is provided in Figure 10. The Bill of Materials (BOM) for components on the Evaluation Board are listed in Table 5. An assembly drawing for the Evaluation Board is shown in Figure 11.

Package Dimensions


The PCB layout footprint for the SKY13438-374LF is provided in Figure 12. Typical case markings are shown in Figure 13. Package dimensions for the 6-pin MLPD are shown in Figure 14, and tape and reel dimensions are provided in Figure 15.

Package and Handling Information

Instructions on the shipping container label regarding exposure to moisture after the container seal is broken must be followed. Otherwise, problems related to moisture absorption may occur when the part is subjected to high temperature during solder assembly.

The SKY13438-374LF is rated to Moisture Sensitivity Level 1 (MSL1) at 260 °C. It can be used for lead or lead-free soldering.

Care must be taken when attaching this product, whether it is done manually or in a production solder reflow environment. Production quantities of this product are shipped in a standard tape and reel format.




S2074

Figure 10. SKY13438-374LF Evaluation Board Schematic


Table 5. SKY13438-374LF Evaluation Board Bill of Materials

| Component | Value | Size | Manufacturer | Characteristic |
|-----------|-------|------|-------------------|-----------------------|
| CBL | 47 pF | 0402 | Murata GRM Series | DC blocking capacitor |
| CBYP | 10 pF | 0402 | Murata GRM Series | Decoupling capacitor |



S2075

Figure 11. SKY13438-374LF Evaluation Board Assembly Diagram



S1635

Figure 12. SKY13438-374LF PCB Layout Footprint (Top View)





Figure 13. Typical Part Markings (Top View)



All measurements are in millimeters.
 Dimensioning and tolerancing according to ASME Y14.5M-1994.
 Coplanarity applies to the exposed heat sink slug as well as the terminals.
 Plating requirement per source control drawing (SCD) 2504.
 Dimension applies to metallized terminal and is measured between 0.15 mm and 0.30 mm from terminal tip.

S1536

Figure 14. SKY13438-374LF 6-Pin QFN Package Dimensions

Ordering Information

| Model Name | Manufacturing Part Number | Evaluation Board Part Number |
|----------------------------|---------------------------|------------------------------|
| SKY13438-374LF DPDT Switch | SKY13438-374LF | SKY13438-374LF-EVB |

Copyright © 2012, 2013 Skyworks Solutions, Inc. All Rights Reserved.

Information in this document is provided in connection with Skyworks Solutions, Inc. ("Skyworks") products or services. These materials, including the information contained herein, are provided by Skyworks as a service to its customers and may be used for informational purposes only by the customer. Skyworks assumes no responsibility for errors or omissions in these materials or the information contained herein. Skyworks may change its documentation, products, services, specifications or product descriptions at any time, without notice. Skyworks makes no commitment to update the materials or information and shall have no responsibility whatsoever for conflicts, incompatibilities, or other difficulties arising from any future changes.

No license, whether express, implied, by estoppel or otherwise, is granted to any intellectual property rights by this document. Skyworks assumes no liability for any materials, products or information provided hereunder, including the sale, distribution, reproduction or use of Skyworks products, information or materials, except as may be provided in Skyworks Terms and Conditions of Sale.

THE MATERIALS, PRODUCTS AND INFORMATION ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, WHETHER EXPRESS, IMPLIED, STATUTORY, OR OTHERWISE, INCLUDING FITNESS FOR A PARTICULAR PURPOSE OR USE, MERCHANTABILITY, PERFORMANCE, QUALITY OR NON-INFRINGEMENT OF ANY INTELLECTUAL PROPERTY RIGHT; ALL SUCH WARRANTIES ARE HEREBY EXPRESSLY DISCLAIMED. SKYWORKS DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. SKYWORKS SHALL NOT BE LIABLE FOR ANY DAMAGES, INCLUDING BUT NOT LIMITED TO ANY SPECIAL, INDIRECT, INCIDENTAL, STATUTORY, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS THAT MAY RESULT FROM THE USE OF THE MATERIALS OR INFORMATION, WHETHER OR NOT THE RECIPIENT OF MATERIALS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

Skyworks products are not intended for use in medical, lifesaving or life-sustaining applications, or other equipment in which the failure of the Skyworks products could lead to personal injury, death, physical or environmental damage. Skyworks customers using or selling Skyworks products for use in such applications do so at their own risk and agree to fully indemnify Skyworks for any damages resulting from such improper use or sale.

Customers are responsible for their products and applications using Skyworks products, which may deviate from published specifications as a result of design defects, errors, or operation of products outside of published parameters or design specifications. Customers should include design and operating safeguards to minimize these and other risks. Skyworks assumes no liability for applications assistance, customer product design, or damage to any equipment resulting from the use of Skyworks products outside of stated published specifications or parameters.

Skyworks, the Skyworks symbol, and "Breakthrough Simplicity" are trademarks or registered trademarks of Skyworks Solutions, Inc., in the United States and other countries. Third-party brands and names are for identification purposes only, and are the property of their respective owners. Additional information, including relevant terms and conditions, posted at www.skyworksinc.com, are incorporated by reference.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.