

Hawk 3 Digital Panel Meter/Controller



- All parameters set from easy to understand front panel access
- One, two or four 5-amp relays optional
- Five user-selectable brightness levels
- 1/8 DIN, shallow depth case, 3.24"
- RS485 digital communications optional (H345)
- 12 or 24 DCV power supply output optional
- 4-20mA or 0-10 DCV analog transmission optional
- NEMA 4X rated front panel

Specifications

| | |
|-----------------------|---|
| DISPLAY | |
| Type | 7-segment, red LED |
| Quantity | 4 or 5 |
| Brightness | 5 user-selectable levels |
| Height | 0.56" (14.2mm) |
| Decimal point | 4 or 5 position, user programmable |
| Overrange indication | Display flashes "EEEE" indicating Maximum Value Exceeded |
| Underrange indication | Display flashes "-EEEE" indicating Minimum Value Exceeded |
| Alarm Indicators | 4 LED indicators for up to four independent setpoints |

POWER REQUIREMENTS

| | |
|-----------|------------------------|
| AC | 120, 85-250 VAC @ 10VA |
| DC | 9-36 DCV @ 10VA |
| ISOLATION | 250V RMS MAX |

| ACCURACY @ 25°C as % of rdg | 4-1/2 digit | 3-1/2 digit |
|-----------------------------|-----------------|-----------------|
| DC Current | | |
| High (5A, 2A) | 0.2% ± 1 count | 0.3% ± 1 count |
| All Others | 0.05% ± 1 count | 0.1% ± 1 count |
| DC Volts | | |
| High (600 V) | 0.1% ± 1 count | 0.2% ± 1 count |
| All others | 0.05% ± 1 count | 0.1% ± 1 count |
| Resistance | | |
| All ranges | 0.1% ± 2 counts | 0.1% ± 2 counts |
| *AC Current | | |
| High (2A, 5A) | 0.2% ± 2 counts | 0.3% ± 2 counts |
| All others | 0.1% ± 2 counts | 0.2% ± 2 counts |
| *AC Volts | | |
| High (600V) | 0.1% ± 1 count | 0.2% ± 1 count |
| All others | 0.05% ± 1 count | 0.1% ± 1 count |

* AC functions measured at 50 Hz, include ± 1 count for each additional 100 Hz above 50 Hz

ENVIRONMENTAL

| | |
|-----------------------|------------------|
| Operating Temperature | 0 to 50°C |
| Storage Temperature | -10 to +60°C |
| Relative Humidity | <80% |
| Ambient Temperature | 25°C |
| Temperature Drift | 100 ppm/°C |
| Warmup Time | 10 minutes |
| Noise Rejection | |
| NMRR | 60 dB @ 50-60 Hz |
| CMRR | 70 dB @ 50-60 Hz |

A TO D CONVERSION

| | |
|--------------|--|
| Technique | Successive approximation with oversampling |
| Sample Rate | 10 conversions per second |
| Display Rate | User programmable 1-420 updates/min (240 default) |

MECHANICAL

| | |
|--------------|---|
| Bezel | 3.9" x 2.0" x 0.52" (99.8mm x 51.9mm x 13.2 mm) |
| Depth | 3.24" (82.3 mm) |
| Panel Cutout | 3.62" x 1.77" (92 mm x 45mm) |
| Weight | 10 oz (283.5g) |
| Cover | NEMA 4X Rated front panel |

more >>



Hawk 3 Digital Panel Meter/Controller

Ordering Information

Hawk 3 Indicators can be configured by making an entry into each section. Example: H335-3-71-0-4-1



Basic Unit Power Supply Function/Range Output Signal 5A Relay Excitation

| Selection | Description | Selection | Description |
|--------------------------|-------------------------|---------------------------------|---------------------|
| Basic Unit | | Function/Range continued | |
| H335 | 3-1/2 digit, Red LED | 51 | 200 ACmV TRMS |
| H345 | 4-1/2 digit, Red LED | 52 | 2 ACV TRMS |
| Power Supply | | 53 | 20 ACV TRMS |
| 1 | 120 ACV (3-1/2 only) | 54 | 200 ACV TRMS |
| 2 | 85-250 ACV (4-1/2 only) | 55 | 600 ACV* TRMS |
| 3 | 9-36 DCV | 61 | 200 ACμA TRMS |
| 4 | 85-250 ACV (3-1/2 only) | 62 | 2 ACmA TRMS |
| Function/Range | | 63 | 20 ACmA TRMS |
| 11 | 200 DCmv | 64 | 200 ACmA TRMS |
| 12 | 2 DCV | 65 | 2 ACA TRMS |
| 13 | 20 DCV | 66 | 5 ACA TRMS |
| 14 | 200 DCV | 71 | 4-20 DCmA Process |
| 15 | 600 DCV* | 72 | 0-10 DCV Process |
| 21 | 200 DCμA | 81 | 200 Ohm |
| 22 | 2 DCmA | 82 | 2K Ohm |
| 23 | 20 DCmA | 83 | 20K Ohm |
| 24 | 200 DCmA | 84 | 200K Ohm |
| 25 | 2 DCA | Output | |
| 26 | 5 DCA | 0 | None |
| 31 | 200 ACmV | 1 | 4-20 DCmA |
| 32 | 2 ACV | 2 | 0-10 DCV |
| 33 | 20 ACV | 6 | RS-485 (4-1/2 only) |
| 34 | 200 ACV | 5A Relays | |
| 35 | 600 ACV* | 0 | None |
| 41 | 200 ACμA | 1 | One |
| 42 | 2 ACmA | 2 | Two |
| 43 | 20 ACmA | 4 | Four |
| 44 | 200 ACmA | Excitation | |
| 45 | 2 ACA | 0 | None |
| 46 | 5 ACA | 1 | 12 DCV |
| Continued on next column | | 2 | 24 DCV |

* Awaiting UL approval



Hawk 3 Installation Instructions

Installation and Panel Cutout - H335, H340, H345



Mounting Requirements

The Hawk 3 Advanced Digital Controller 1/8 DIN meters require a panel cutout of 1.77" (45mm) high and 3.62" (92 mm wide). To install the Hawk 3 meter into the panel cutout, remove the clips from the side of the meter. Slide the meter through the panel cutout, then slide the mounting clips back on the meter. Press evenly to ensure a proper fit. Tighten screws.

Engineering Label Placement

To replace the engineering unit label, place the tip of a ballpoint pen into the small hole at the base of the engineering label in the bezel. Slide the label up until it pops out. Grasp and remove. Slide the new label half the distance in, then use the ballpoint pen to slide it into place.

Inputs

DC Voltage

| Range | Resolution 4.5 | Resolution 3.5 | Input Impedance | Overload |
|-------|----------------|----------------|-----------------|----------|
| 200mV | 10µV | .1mV | 1MΩ | 5DCV |
| 2V | .1mV | 1mV | 1MΩ | 5DCV |
| 20V | 1mV | 10mV | 1MΩ | 300DCV |
| 200V | 10mV | .1mV | 1MΩ | 300DCV |
| 600V | .1V | 1V | 1MΩ | 1KDCV |

DC Current

| Range | Resolution 4.5 | Resolution 3.5 | Input Impedance | Overload |
|-------|----------------|----------------|-----------------|----------|
| 200µA | 10nA | .1µA | 1KΩ | 45mADC |
| 2mA | .1µA | 1µA | 100Ω | 45mA DC |
| 20mA | 1µA | 10µA | 10Ω | 200mADC |
| 200mA | 10µA | .1mA | 1Ω | 600mA DC |
| 2A | .1mA | 1mA | .013Ω | 5.5A DC |
| 5A | .1mA | 1mA | .013Ω | 5.5A DC |

AC Current

| Range | Resolution 4.5 | Resolution 3.5 | Input Impedance | Overload |
|-------|----------------|----------------|-----------------|----------|
| 200µA | 10nA | .1µA | 1KΩ | 45mA DC |
| 2mA | .1µA | 1µA | 100Ω | 45mA DC |
| 20mA | 1µA | 10µA | 10Ω | 200mA DC |
| 200mA | 10µA | .1mA | 1Ω | 600mA DC |
| 2A | .1mA | 1mA | .013Ω | 5.5A DC |
| 5A | .1mA | 1mA | .013Ω | 5.5A DC |

AC Voltage

| Range | Resolution 4.5 | Resolution 3.5 | Input Impedance | Overload |
|-------|----------------|----------------|-----------------|----------|
| 200mV | 10µV | .1mV | 200KΩ | 5DCV |
| 2V | .1mV | 1mV | 200KΩ | 5DCV |
| 20V | 1mV | 10mV | 1MΩ | 300DCV |
| 200V | 10mV | .1V | 1MΩ | 300DCV |
| 600V | .1V | 1V | 1MΩ | 1KDCV |

Resistance

| Range | Resolution 4.5 | Resolution 3.5 | Input Impedance | Overload |
|-------|----------------|----------------|-----------------|----------|
| 200Ω | 10mΩ | .1Ω | 1.2KΩ | ± 5DCV |
| 2KΩ | .1Ω | 1Ω | 12KΩ | ± 5DCV |
| 20KΩ | 1Ω | 10Ω | 121K | ± 5DCV |
| 200KΩ | 10Ω | 100Ω | 1.2MΩ | ± 5DCV |



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.