



## 120 Watt Universal 3-Wire Input Adapter



### Features

- Level VI Efficiency Compliant
- Compliant with Ecodesign ErP Directive 2009/125/EC level 2 annex 1b
- Non-vented/Spill-proof Case
- Class B EMI

### Applications

- Networking
- Peripherals
- Industrial
- Test and Measurement

### Safety Approvals

- UL 60950-1
- CSA 22.2 60950-1
- CE
- CB

### Mechanical Characteristics

- Length: 152mm (5.98in)
- Width: 73mm (2.88in)
- Height: 37mm (1.45in)
- Weight: 800g (1.76lbs)

### Output Specifications

Model	DC Output Voltage	Load			Ripple <sup>2</sup> P-P (max.)	Regulation Line & Load
		Min.	Rated	Peak		
PSA120U-120L6-R <sup>1</sup>	12V	0A	9A	11A	200mV	±5%
PSA120U-240L6-R	24V	0A	5A	6A	380mV	±5%
PSA120U-480L6-R	48V	0A	2.5A	3A	480mV	±5%
PSA120U-540L6-R	54V	0A	2.22A	2.66A	500mV	±5%
PSA120U-560L6-R	56V	0A	2.14A	2.56A	560mV	±5%

(1) 12V model is 108W

(2) Measured using 12-inch twisted pair terminated with a 10uF capacitor and 0.1uF ceramic in parallel

Phihong is not responsible for any error, and reserves the right to make changes without notice. Please visit our website at [www.phihong.com](http://www.phihong.com) for the most up-to-date specifications and contact information.

**Input:**

**AC Input Voltage Rating**  
115 to 230VAC

**AC Input Voltage Range**  
90 to 264VAC

**AC Input Frequency**  
47 to 63Hz

**Input Current**  
1.5A at 115VAC  
0.75A at 230VAC

**Leakage Current**  
<250uA at 250VAC/50Hz

**Inrush Current**  
<220A at 115VAC  
(Cold Start at ambient 25°C)

**Input Power Saving**  
≤0.15W at 230VAC input

**Power Factor**  
>0.95 at 115VAC and >0.9 at 230VAC for both 50/60Hz frequency range at rated load output condition.

**OUTPUT:**

**Efficiency Level**  
DOE Level VI

**Over-Voltage Protection**  
<70V. Latch –off mode. Auto-recover

**Over-Load, Short-Circuit & Over-Temperature Protections**  
Auto-recover

**ENVIRONMENTAL****Temperature**

Operation	0°C to + 40°C
Non-operation	-20°C to ~ +80°C
Humidity	10°C to 90%

**Emissions**

Complies with FCC Class B  
Complies with EN55032 Class B  
EN61000-3-2 Class D  
EN61000-3-3

**Immunity**

ESD	EN61000-4-2
RS	EN61000-4-3
EFT	EN61000-4-4
Surge	EN61000-4-5
CS	EN61000-4-6
Power Frequency Magnetic Field	EN61000-4-8
Voltage Dips	EN61000-4-11

**Dielectric Withstand (Hi-Pot) Test**

Primary to Secondary: >3000V AC for 1 min.,  
10mA

**DC Output Connector (12V)**  
4 pin Mini DIN

**DC Plug Pin assignment(12V)**  
Pin 2,4 (+V)  
Pin 1,3 GND (-)

**DC Output Connector(24V,48V, 54V 56V)**  
2.5mm x 5.5mm x 10mm Center Positive  
Barrel Standard

**DC Plug pin assignment(24V,48V, 54V 56V)**  
Inner (+V)  
Outer GND (-)

**Input Connector**  
3-Wire IEC320-C14



**Supplier's Declaration of Conformity**  
**47 CFR § 2.1077 Compliance Information**

Phihong USA Corporation  
47800 Fremont Boulevard  
Fremont, CA 94538  
Telephone: (510) 445-0100  
[www.phihong.com](http://www.phihong.com)

NOTE: This model has/The models in this products series have been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications to equipment not expressly approved by PHIHONG could void the user's authority to operate the equipment.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.