


## Silicon N-Channel MOSFET Triode

- For high-frequency stages up to 300 MHz preferably in FM applications
- Pb-free (RoHS compliant) package<sup>1)</sup>
- Qualified according AEC Q101



**ESD (Electrostatic discharge) sensitive device, observe handling precaution!**

Type	Marking	Pin Configuration						Package
BF999	LBs	1=G	2=D	3=S	-	-	-	SOT23

### Maximum Ratings

Parameter	Symbol	Value	Unit
Drain-source voltage	$V_{DS}$	20	V
Continuous drain current	$I_D$	30	mA
Gate-source peak current	$\pm I_{GSM}$	10	mA
Total power dissipation $T_S \leq 76 \text{ }^\circ\text{C}$	$P_{tot}$	200	mW
Storage temperature	$T_{stg}$	-55 ... 150	$^\circ\text{C}$
Channel temperature	$T_{ch}$	150	

### Thermal Resistance

Parameter	Symbol	Value	Unit
Channel - soldering point <sup>2)</sup>	$R_{thchs}$	$\leq 370$	K/W

<sup>1</sup>Pb-containing package may be available upon special request

<sup>2</sup>For calculation of  $R_{thJA}$  please refer to Application Note Thermal Resistance

**Electrical Characteristics** at  $T_A = 25^\circ\text{C}$ , unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	

**DC Characteristics**

Drain-source breakdown voltage $I_D = 10 \mu\text{A}, -V_{GS} = 4 \text{ V}$	$V_{(\text{BR})\text{DS}}$	20	-	-	V
Gate-source breakdown voltage $\pm I_{GS} = 10 \text{ mA}, V_{DS} = 0$	$\pm V_{(\text{BR})\text{GSS}}$	6.5	-	12	
Gate-source leakage current $\pm V_{GS} = 5 \text{ V}, V_{DS} = 0$	$\pm I_{\text{GSS}}$	-	-	50	nA
Drain current $V_{DS} = 10 \text{ V}, V_{GS} = 0$	$I_{\text{DSS}}$	5	10	16	mA
Gate-source pinch-off voltage $V_{DS} = 10 \text{ V}, I_D = 20 \mu\text{A}$	$-V_{GS(\text{p})}$	-	0.8	1.5	V


**Electrical Characteristics** at  $T_A = 25^\circ\text{C}$ , unless otherwise specified

Parameter	Symbol	Values			Unit
		min.	typ.	max.	


**AC Characteristics**

Forward transconductance $V_{DS} = 10 \text{ V}, I_D = 10 \text{ mA}$	$g_{fs}$	14	20	-	mS
Gate input capacitance $V_{DS} = 10 \text{ V}, I_D = 10 \text{ mA}, f = 10 \text{ MHz}$	$C_{\text{gss}}$	-	2.5	-	pF
Output capacitance $V_{DS} = 10 \text{ V}, I_D = 10 \text{ mA}, f = 10 \text{ MHz}$	$C_{\text{dss}}$	-	0.9	-	pF
Power gain $V_{DS} = 10 \text{ V}, I_D = 10 \text{ mA}, f = 45 \text{ MHz}$	$G_p$	-	27	-	dB
Noise figure $V_{DS} = 10 \text{ V}, I_D = 10 \text{ mA}, f = 45 \text{ MHz}$	$F$	-	2.1	-	dB


**Total power dissipation**  $P_{\text{tot}} = f(T_S)$




**Output characteristics**  $I_D = f(V_{DS})$




**Gate transconductance**  $g_{fs} = f(V_{GS})$




**Drain current**  $I_D = f(V_{GS})$




**Gate input capacitance**  $C_{gss} = f(V_{GS})$



**Output capacitance**  $C_{dss} = f(V_{DS})$




## Package Outline




1) Lead width can be 0.6 max. in dambar area

## Foot Print




## Marking Layout (Example)



## Standard Packing

Reel ø180 mm = 3.000 Pieces/Reel  
Reel ø330 mm = 10.000 Pieces/Reel



---

Edition 2006-02-01

Published by

Infineon Technologies AG

81726 München, Germany

© Infineon Technologies AG 2007.

All Rights Reserved.

### **Attention please!**

The information given in this document shall in no event be regarded as a guarantee of conditions or characteristics ("Beschaffenheitsgarantie"). With respect to any examples or hints given herein, any typical values stated herein and/or any information regarding the application of the device, Infineon Technologies hereby disclaims any and all warranties and liabilities of any kind, including without limitation warranties of non-infringement of intellectual property rights of any third party.

### **Information**

For further information on technology, delivery terms and conditions and prices please contact your nearest Infineon Technologies Office ([www.infineon.com](http://www.infineon.com)).

### **Warnings**

Due to technical requirements components may contain dangerous substances.

For information on the types in question please contact your nearest Infineon Technologies Office.

Infineon Technologies Components may only be used in life-support devices or systems with the express written approval of Infineon Technologies, if a failure of such components can reasonably be expected to cause the failure of that life-support device or system, or to affect the safety or effectiveness of that device or system.

Life support devices or systems are intended to be implanted in the human body, or to support and/or maintain and sustain and/or protect human life. If they fail, it is reasonable to assume that the health of the user or other persons may be endangered.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

#### Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помошь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помошь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: [org@eplast1.ru](mailto:org@eplast1.ru)

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.