

FS100 SERIES

Low Current Flasher



Description

The FS100 Series (low current) may be used to control inductive, incandescent or resistive loads. This series offers a 1A (fullwave) or a 2A (halfwave) steady state, 10A inrush solid-state output and may be ordered with an input voltage of 24 or 120VAC. The FS100 Series offers a factory fixed flash rate of 75 FPM or may be ordered with a fixed, custom flash rate ranging from 45 to 150 FPM. Ideal for OEM applications where cost is a factor.

Operation

Upon application of input voltage, the T2 OFF time begins. At the end of the OFF time, the T1 ON time begins and the load energizes. At the end of T1, T2 begins and the load de-energizes. This cycle repeats until input voltage is removed.

Reset: Removing input voltage resets the output and the sequence to T2.

Wiring Diagram



V = Voltage
L = Load
R = Red Wire
B = Black Wire

Features & Benefits

| FEATURES | BENEFITS |
|--|---|
| Compact Size: 38 x 23.9mm (1.5" x 0.94") | Ideal for OEM applications |
| Custom Flash Rates Available | Tailor to specific application: custom rates range from 45 to 150 FPM |

Accessories



P1023-2 "P" Clamp
Mounting Bracket Alum. 15/16

Ordering Information

| MODEL | INPUT VAC | OUTPUT RATING A | OUTPUT TYPE AC | LOAD TYPE | FLASH RATE |
|------------|-----------|-----------------|----------------|--------------------------------------|------------|
| FS126 | 120 | 1 | Fullwave | Incandescent & Resistive | 75 FPM |
| FS126-45 | 120 | 1 | Fullwave | Incandescent & Resistive | 45 FPM |
| FS126-60 | 120 | 1 | Fullwave | Incandescent & Resistive | 60 FPM |
| FS126RC | 120 | 1 | Fullwave | Incandescent, Resistive, & Inductive | 75 FPM |
| FS126RC-45 | 120 | 1 | Fullwave | Incandescent, Resistive, & Inductive | 45 FPM |
| FS127 | 120 | 2 | Halfwave | Incandescent & Resistive | 75 FPM |
| FS146 | 24 | 1 | Fullwave | Incandescent & Resistive | 75 FPM |
| FS146RC | 24 | 1 | Fullwave | Incandescent, Resistive, & Inductive | 75 FPM |

If you don't find the part you need, call us for a custom product 800-843-8848

FS100 SERIES

Specifications

Technical Data

| | |
|-------------------------------------|---|
| Operation | OFF/ON solid-state flasher (continuous duty) |
| Flash Rate | Factory fixed at 75 FPM $\pm 20\%$ |
| Custom Flash Rates Available | From 45-150 FPM $\pm 20\%$ |
| ON/OFF Ratio | $\approx 50\%$ |
| Input | |
| Voltage | 24, 120VAC, $\pm 15\%$ |
| AC Line Frequency | 50/60Hz |
| Output | |
| Load Type | Fullwave AC or Halfwave rectified AC Incandescent, resistive, or inductive (Choose RC suffix for inductive loads) |
| Maximum Load Rating | Fullwave: 1A steady state Halfwave: 2A steady state 10A |
| Inrush | |
| Mechanical | |
| Mounting | Removable mounting bracket, use one #8 (M4 x 0.7) screw |
| Connection/Wires | 18 AWG (0.82mm ²) wires 6 in. (15.2cm) |
| Dimensions | H 38.1 mm (1.5"); W 23.9 mm (0.94") |
| Protection | |
| Circuitry | Encapsulated |
| Environmental | |
| Operating/Storage | |
| Temperature | -20° to 60°C / -40° to 85°C |
| Humidity | 95% relative, non-condensing |
| Weight | ≈ 1.1 oz (31 g) |

Flasher Function Diagram



V = Voltage
R = Reset
L = Load
T1 = ONTime
T2 = OFFTime
T1 \approx T2



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.