

Is Now Part of



# **ON Semiconductor**®

# To learn more about ON Semiconductor, please visit our website at <u>www.onsemi.com</u>

Please note: As part of the Fairchild Semiconductor integration, some of the Fairchild orderable part numbers will need to change in order to meet ON Semiconductor's system requirements. Since the ON Semiconductor product management systems do not have the ability to manage part nomenclature that utilizes an underscore (\_), the underscore (\_) in the Fairchild part numbers will be changed to a dash (-). This document may contain device numbers with an underscore (\_). Please check the ON Semiconductor website to verify the updated device numbers. The most current and up-to-date ordering information can be found at <a href="https://www.onsemi.com">www.onsemi.com</a>. Please email any questions regarding the system integration to <a href="https://www.onsemi.com">Fairchild\_questions@onsemi.com</a>.

ON Semiconductor and the ON Semiconductor logo are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized applications, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an equif prese



December 2013

# FPF2700 / FPF2701 / FPF2702 — AccuPower™ 0.4~2 A Adjustable Over-Current Protection Load Switches

#### Features

- 2.8 V to 36 V Input Voltage Range
- Typical R<sub>DS(ON)</sub>=88 mΩ
- 0.4 A to 2 A Adjustable Current Limit (Min.)
- Slew Rate Controlled
- ESD Protected, above 2000 V HBM
- Thermal Shutdown
- Active LOW Enable
- UVLO Protection
- Power-Good Output

## Applications

- Motor Drives
- Digital Cameras
- Consumer Electronics
- Industrial
- Computing
- Hard Disk Drives
- Telecom Equipment



Figure 1. MLP (Top View) Figure 2. MLP (Bottom View)



Figure 3. SO8 (Top View)

#### Description

The AccuPower™ FPF270X series is a family of current-limit load switches that provide full protection to systems and loads from excess current conditions. Minimum current limit is adjustable from 0.4 A to 2.0 A. The FPF270X contains a slew-rate-controlled N-channel MOSFET and slew-rated turn-on to prevent power bus disturbances from being caused by "hot plugging" loads or momentary excess load demands. The input voltage range is 2.8 V to 36 V. Loads can be activated or deactivated with a low-voltage logic-compatible ON pin. Fault conditions can be monitored using the error flag pin and/or the power-good pin.

Each member of the FPF270X family serves a category of load-fault response. All devices clamp the load current so that it cannot exceed an externally programmed current level. An over temperature feature provides further device protection in case of excessive levels of power dissipation.

FPF2700 responds to an overload condition that lasts longer than a fixed blanking period by turning off the load, followed by a retry after the auto-restart time.

FPF2701 responds to an overload condition that lasts longer than a fixed blanking period by latching off the load. The load remains off unless either the ON pin is toggled or the input voltage cycles through UVLO.

FPF2702 is intended to be used with external fault management. Like the FPF2700 and FPF2701, it sets the fault signal pin LOW when it activates current clamping. This device is intended for applications where external fault management coordinates the overload response with the FPF2702.

The FPF270X is available in a space-saving, Lead and Halogen free, 8-lead, MLP 3x3 mm and SO8 packages.

Ordering Information						
Part Number	Current Limit [A]	Current Limit Blanking Time [ms]	Auto-Restart Time [ms]	ON Pin Activity	Package	
FPF2700MPX	0.4 – 2.0	0.5	127.5	Active LOW	MLP3X3	
FPF2701MPX	0.4 – 2.0	0.5	NA	Active LOW	MLP3X3	
FPF2702MPX	0.4 – 2.0	NA	NA	Active LOW	MLP3X3	
FPF2700MX	0.4 – 2.0	0.5	127.5	Active LOW	SO8	
FPF2701MX	0.4 – 2.0	0.5	NA	Active LOW	SO8	
FPF2702MX	0.4 – 2.0	NA	NA	Active LOW	SO8	





# **Pin Definitions**

Pin #	Name	Description
1	VIN	Supply Input. Input to the power switch and the supply voltage for the IC.
2	PGOOD	Power-Good Output. Open-drain output to indicate that output voltage has reached 90% of input voltage.
3	ISET	Current Limit Set Input. A resistor from ISET to ground sets the current limit for the switch.
4	ON	ON Control Input. Active LOW.
5	GND	Ground
6	NC	No connection. Leave open or connect to ground.
7	FLAGB	Fault Output. Active LOW, open-drain output that indicates current limit, under-voltage, or over-temperature state.
8	VOUT	Switch Output. Output of the power switch.

# **Absolute Maximum Ratings**

Stresses exceeding the absolute maximum ratings may damage the device. The device may not function or be operable above the recommended operating conditions and stressing the parts to these levels is not recommended. In addition, extended exposure to stresses above the recommended operating conditions may affect device reliability. The absolute maximum ratings are stress ratings only.

Symbol	Parameter			Max.	Unit	
	PGOOD, FLAGB, VIN to GNE	)	-0.3	40	V	
	VOUT to GND		-0.3	V <sub>IN</sub> + 0.3	V	
	ON to GND		-0.3	6	V	
	Power Dissipation (T <sub>A</sub> =25°C)	MLP 3x3 <sup>(1)</sup> , See Figure 8		1.25	w	
PD		SO8 <sup>(1)</sup> , See Figure 10		1.00		
I <sub>SW</sub>	/ Maximum Continuous Switch Current			3.5	А	
TJ	Operating Junction Temperature		-40	+125	°C	
T <sub>STG</sub>	Storage Temperature		-65	+150	°C	
	ESD Electrostatic Discharge Protection Level	Human Body Model, JESD22-A114	2000		V	
E9D		Charged Device Model, JESD22-C101	2000		v	
$\Theta_{JA}$	Thermal Resistance, Junction to Ambient	MLP 3x3 <sup>(1)</sup> , See Figure 8		80	0000	
		SO8 <sup>(1)</sup> , See Figure 10		102	0/00	

#### Note:

1. Thermal resistance,  $\theta_{JA}$ , is determined with the device mounted on a one inch square pad, 2 oz copper pad, and a 1.5 x 1.5 in. board of FR-4 material.



Figure 8. 80°C/W Mounted on a 1in<sup>2</sup> Pad of 2-oz. Copper\_\_\_\_



Figure 10. 102°C/W mounted on a 1in<sup>2</sup> Pad of 2-oz. Copper



Figure 9. 226°C/W Mounted on a Minimum Pad of 2-oz. Copper



Figure 11. 181°C/W Mounted on a Minimum Pad of 2-oz. Copper

# **Recommended Operating Conditions**

The Recommended Operating Conditions table defines the conditions for actual device operation. Recommended operating conditions are specified to ensure optimal performance. Fairchild does not recommend exceeding them or designing to Absolute Maximum Ratings.

Symbol	Parameter		Max.	Unit
VIN	Input Supply Voltage	2.8	36.0	V
T <sub>A</sub>	Ambient Operating Temperature		85	°C

FPF2700 / FPF2701 / FPF2702 — AccuPower™ 0.4~2A Adjustable Over-Current Protection Load Switches

# **Electrical Characteristics**

 $V_{IN}$ =2.8 to 36 V and  $T_A$ =-40 to +85°C unless otherwise noted. Typical values are at  $V_{IN}$ =12 V and  $T_A$ =25°C.

Symbol	Parameter	Conditions	Min.	Тур.	Max.	Unit
Basic Oper	ation					
V <sub>IN</sub>	Operating Voltage		2.8		36.0	V
Ι <sub>Q</sub>	Quiescent Current	V <sub>IN</sub> =12 V, V <sub>ON</sub> =0 V, I <sub>OUT</sub> =0 A		92	140	μA
I <sub>SHDN</sub>	Shutdown Current	V <sub>IN</sub> =36 V, V <sub>ON</sub> =3.3 V, I <sub>OUT</sub> =0 A		5	14	μA
		T <sub>A</sub> =25°C, V <sub>IN</sub> =12 V		88	114	
		T <sub>A</sub> =-40 to +85°C, V <sub>IN</sub> =12 V			140	
RON	On Resistance	T <sub>A</sub> =25°C, V <sub>IN</sub> =5 V		88	114	mΩ
		$T_A$ =-40 to +85°C, $V_{IN}$ =5 V			140	
VIH	ON Input Logic HIGH Voltage	V <sub>IN</sub> =2.8 to 36 V	2.0			V
VIL	ON Input Logic LOW Voltage	V <sub>IN</sub> =2.8 to 36 V			0.8	V
I <sub>LK</sub>	ON Input Leakage	V <sub>ON</sub> =5.5 V or GND	-1		1	μA
ISWOFF	Off Switch Leakage	V <sub>IN</sub> =36 V, V <sub>ON</sub> =3.3 V, V <sub>OUT</sub> =0 V		0.01		μA
V <sub>FLAGB(LO)</sub>	FLAGB Output Logic LOW Voltage	V <sub>IN</sub> =5 V, I <sub>SINK</sub> =1 mA		0.1	0.2	V
I <sub>FLAGB(HI)</sub>	FLAGB Output Logic HIGH Leakage Current	V <sub>IN</sub> =36 V, Switch On, V <sub>FLAGB</sub> =36 V			1	μA
V <sub>PGOOD</sub>	PGOOD Trip Voltage	$V_{IN}$ =5 V, $V_{OUT}$ as Percent of $V_{IN}$ , $V_{OUT}$ Rising		90		%
V <sub>PGOOD(HYS)</sub>	PGOOD Hysteresis	$V_{IN}$ =5 V, $V_{OUT}$ as Percent of $V_{IN}$ , $V_{OUT}$ Falling		3		%
V <sub>PGOOD(LO)</sub>	PGOOD Output Logic LOW Voltage	V <sub>IN</sub> =5 V, I <sub>SINK</sub> =1 mA		0.1	0.2	V
I <sub>PGOOD(HI)</sub>	PGOOD Output High Leakage Current	V <sub>IN</sub> =36 V, Switch ON, V <sub>PGOOD</sub> =36 V			1	μA
Protections	5					
I <sub>LIM</sub>	Current Limit	T <sub>A</sub> =25°C	-20		+20	%
I <sub>SC</sub>	Short Circuit Current Limit	V <sub>OUT</sub> < 2 V, Switch in Over- Current Condition		0.75 х І <sub>NOM</sub>		А
		Shutdown Threshold	7	140		
TSD	Thermal Shutdown	Return from Shutdown		110		°C
		Hysteresis		30		
UVLO	Under-Voltage Shutdown	V <sub>IN</sub> Increasing	2.3	2.5	2.7	V
UVLO_HYST	Under-Voltage Shutdown Hysteresis			100		mV
Dynamic						
t <sub>don</sub>	Turn On Delay			2.7	10	-
t <sub>doff</sub>	Turn Off Delay	R <sub>L</sub> =500 Ω, C <sub>L</sub> =2 μF	1	0.1		ms
t <sub>R</sub>	V <sub>OUT</sub> Rise Time			7.5		
tF	Vout Fall Time			1.5		
t <sub>BLANK</sub>	Over-Current Blanking Time	FPF2700/1, T <sub>A</sub> =25°C	0.25	0.50	0.75	ms
t <sub>RESTART</sub>	Auto-Restart Time	FPF2700, T <sub>A</sub> =25°C	63.8	127.5	191.2	ms
t <sub>CLR</sub>	Current-Limit Response Time	V <sub>IN</sub> =12 V, V <sub>ON</sub> =0 V		50		μs



# **Typical Performance Characteristics**

 $V_{IN} = 12 \text{ V} \text{ and } T_A = 25^{\circ}\text{C}.$ 



Figure 17. On Resistance vs. Supply Voltage





Figure 18. On Resistance vs. Junction Temperature



















airchildsemi.com

an NMOS. Voc is the gate drive of the NMOS.

#### **Application Information**

#### **Description of Operation**

The FPF270X family of current limit load switches is designed to meet the power requirements of a variety of applications with wide input voltage range of 2.8 V to 36 V and adjustable current-limit value. The FPF270X family offers control and protection while providing optimum operation current for safe design practices. The core of each switch is a typical 88 m $\Omega$  (V<sub>IN</sub> = 12 V) N-channel MOSFET and a controller capable of functioning over an input voltage range of 2.8 V to 36 V.

FPF270X offers adjustable current limiting, undervoltage lockout (UVLO), power-good indicator (PGOOD), fault flag output (FLAGB), and thermal shutdown protection. In the event of an over-current condition, the load switch limits the load to the current limit value. The current limit value for each switch can be adjusted from 400 mA to 2 A through the ISET pin.

#### **On/Off Control**

The ON pin is active LOW for and controls the state of the switch. Pulling the ON pin continuously to LOW holds the switch in ON state. The switch moves into OFF state when the ON pin is pulled HIGH. The ON pin can be pulled HIGH to a maximum voltage of 5.5 V.

An under-voltage condition on the input voltage or a junction temperature in excess of 140°C overrides the ON control and turns off the switch. In addition, an overcurrent condition causes the switch to turn off in the FPF2700 and FPF2701 after the expiration of the blanking time. The FPF2700 has an auto-restart feature that automatically turns the switch ON again after the auto-restart time. For the FPF2701, the ON pin must be toggled to turn the switch on again. The FPF2702 does not turn off in response to an over-current condition; it remains operating in Constant-Current Mode as long as ON is enabled and the thermal shutdown or UVLO have not activated. The ON pin does not have internal pull-down or pull-up resistors and should not be left floating.

#### **Fault Reporting**

Upon detection of an over-current condition, an input UVLO, or an over-temperature condition, the FLAGB signals the Fault Mode by activating LOW. In the event of an over-current condition for the FPF2700 or FPF2701, the FLAGB goes LOW at the end of the blanking time (Figure 24 and Figure 25). FLAGB goes LOW immediately for the FPF2702 (Figure 29). If the over-current condition lasts longer than blanking time, FLAGB remains LOW through the auto-restart time for the FPF2700. For the FPF2701, FLAGB is latched LOW and ON must be toggled to release it.

For FPF2702, FLAGB is LOW during a fault and immediately returns HIGH at the end of the fault condition. FLAGB is an open-drain MOSFET that requires a pull-up resistor. The maximum pull-up voltage is 36 V (Figure 29).

During shutdown, the pull-down on FLAGB is disabled to reduce current draw from the supply. A 100 k $\Omega$  pull-up resistor is recommended in the application.

#### **Current Limiting**

The current limit ensures that the current through the switch doesn't exceed a maximum value while not limiting at less than a minimum value. The current-limit level is adjustable through an external resistor connected between the ISET pin and GND.

The typical current limit level is adjustable from 510 mA to 2.5 A. The minimum current limit (ILIM(MIN)) range is from 0.4 A to 2.0 A, including 20% current-limit tolerance. The FPF2700 and FPF2701 have a blanking time during which the switch acts as a constant-current source (Figure 27). If the over-current condition persists beyond the blanking time, the FPF2700 latches off and shuts the switch off (Figure 32). If the ON pin is kept active, an auto-restart feature releases the switch and turns the switch on again after the auto-restart time (Figure 33). If the over-current condition persists beyond the blanking time, the FPF2701 latch-off feature shuts the switch off. The switch is kept off until the ON pin is toggled or input power is cycled. The FPF2702 has no current-limit blanking period, so it remains in a constantcurrent state until the ON pin is deactivated or the thermal shutdown turns off the switch.

Besides the current-limiting functionality, the switch is protected by the thermal shutdown protection and an independent SOA protection circuit is available.

### SOA Protection Current Limit (I<sub>OUT</sub> > 12 A)

FPF270X has an SOA protection feature to protect the load switch in response to current surges exceeding 12 A in normal operation. If a short-circuit event occurs ( $I_{OUT}$ >12 A), the switch is turned off in about 1µs by an independent Safe Operating Area (SOA) protection circuit (Figure 26, Figure 28). This feature protects the switch in case of sudden, high-current events at the output, such as a short to GND. The switch turns on automatically after a turn-on delay of about 2.7 ms.

#### Short-Circuit Current Limit (Vout < VSCTH = 2 V)

When the output voltage drops below the short-circuit threshold voltage,  $V_{SCTH}$ , the current-limit value reconditions itself to the short-circuit current limit value, which is 75% of the nominal current limit (0.75 x I<sub>LIM</sub>) (Figure 24). This prevents early thermal shutdown by reducing the power dissipation of the device. The V<sub>SCTH</sub> value is set at 2 V. At about V<sub>OUT</sub> = 2.1 V, the switch is removed from short-circuit current-limiting mode and the current limit is set to the nominal current limit value.

#### Setting the Current Limit Value

FPF270X has an adjustable 0.4 A to 2.0 A minimum current limit set through an external resistor,  $R_{SET}$ , connected between ISET and GND. A precision  $R_{SET}$  value must be used, such as 1% tolerance or lower, to minimize the total current limit tolerance of the system.

Use the following equation to calculate the value of the resistor for intended typical current limit value:

$$R_{\text{SET}}(k\Omega) = \frac{277.5}{I_{LM(TVP)}(A)}$$
(1)

 $I_{\text{LIM}(\text{TYP})}$  is the typical current limit value based on a R<sub>SET</sub>.

R <sub>SET</sub>	Cur	Tol (%)		
(kΩ)	Min.	Тур.	Max.	101. (%)
111	2.00	2.50	3.00	20
124	1.79	2.24	2.69	20
147	1.51	1.89	2.27	20
182	1.22	1.52	1.83	20
220	1.01	1.26	1.51	20
274	0.81	1.01	1.22	20
374	0.59	0.74	0.89	20
549	0.40	0.51	0.61	20

#### Table 1. R<sub>SET</sub> Selection Guide



Figure 36. ILIM vs. RSET

#### **Under-Voltage Lockout (UVLO)**

The under-voltage lockout feature turns off the switch if the input voltage drops below the under-voltage lockout threshold. With the ON pin active (ON pin pulled LOW), the input voltage rising above the under-voltage lockout threshold causes a controlled turn-on of the switch (Figure 37). The UVLO threshold voltage is set internally at 2.5 V for V<sub>IN</sub> rising. The under-voltage lockout threshold has a 0.1 V hysteresis.



#### **Power Good**

FPF270X has a power good feature. The PGOOD pin is an open-drain MOSFET that asserts HIGH when the output voltage reaches 90% of the input voltage (Figure 26). A typical 3% PGOOD hysteresis is added to PGOOD to prevent PGOOD from chattering as  $V_{OUT}$ falls near the PGOOD threshold voltage.

The PGOOD pin requires an external pull-up resistor connected to an external voltage source compatible with input levels of other chips connected to this pin. PGOOD is kept LOW when the device is inactive. To save current in the OFF state, the pull-up resistor of the PGOOD pin can be connected to the output voltage when there is no battery, provided that compatibility with the input levels of other devices connected to PGOOD is observed. A typical value of 100 k $\Omega$  is recommended for the pull up resistor. When the power-good feature is not used in the application, the PGOOD pin can be connected to GND.

#### **Thermal Shutdown**

Thermal shutdown protects the die from internally or externally generated excessive temperatures. During an over-temperature condition; as the temperature increases above 140°C, FLAGB is activated and the switch is turned off.

When the die cools down sufficiently (die temperature drops below the threshold level), the switch automatically turns on again. To avoid unwanted thermal oscillations, a 30°C (typical) thermal hysteresis is implemented between thermal shutdown entry and exit temperatures. Proper board layout is required to prevent premature thermal shutdown (see Figure 38 for thermal shutdown behavior on FPF2702).



Figure 38. FPF2702 Thermal Shutdown Behavior

#### **SOA (FPF2702)**

During extended output-short conditions, excessive power dissipation occurs in the load switch. FPF2700 and PFP2701 are protected by turning off the load switch after blanking time. FPF2702 has no blanking time feature; please refer to Note 3. It is possible to estimate the SOA for the two FPF2702 packages, MPX and MX, through their respective SOA curves shown in Figure 39 and Figure 40. These curves provide a reference on how long the load switch survives under the worst-case scenario with minimum pad size of one square inch.<sup>(1)</sup>



# 3. To protect FPF2702 from an extended short condition, additional protection must be implemented in the system to protect the device. For example, the FLAGB and PGOOD signal can be used to monitor the short-circuit fault condition. In applications where FPF2702 can be exposed to persistent short-circuit conditions, it should be used only with external fault management control to protect the switch.

#### **Input Capacitor**

To limit the voltage drop on the input supply caused by transient inrush currents when the switch is turned on into a discharged load capacitor or short-circuit; an input capacitor,  $C_{IN}$ , is recommended between the IN and GND pins. The FPF270X features a fast current limit response time (50 µs). During this period, the device relies on the input capacitor to supply the load current. A 10 µF to 100 µF ceramic capacitor is adequate for  $C_{IN}$  in most cases. Larger  $C_{IN}$  values may be required in high-voltage or high-current applications. An electrolytic capacitor can be used in parallel to further reduce the voltage drop.

#### **Output Capacitor**

A 0.1  $\mu$ F to 1  $\mu$ F capacitor, C<sub>OUT</sub>, should be placed between the OUT and GND pins. This capacitor helps prevent parasitic board inductances from forcing the output voltage below ground when the switch turns off. This capacitor should have a low dissipation factor. An X7R Multilayer Ceramic Chip (MLCC) capacitor is recommended.

During startup, the total output current consists of both the load current and the charge current of the output capacitor. For the FPF2700 and FPF2701; if the total output current exceeds the set current limit threshold (determined via  $R_{SET}$ ) for longer than the blanking time, the device may not be able to start properly. This imposes an upper limit to the value of the output capacitor, given the load current and the selected current limit value. C<sub>OUT</sub> should not exceed the C<sub>OUTmax</sub> calculated in Equation 2 or the switch does not start properly due to the set current limit:

$$C_{OUT max} \le I_{LIM} MIN \times 500 \mu s/V$$
(2)

#### **High-Voltage Operation (Output Capacitor)**

During a hard short condition on the output while operating at greater than  $24 \text{ V} \text{ V}_{\text{IN}}$ , a large instantaneous inrush current is delivered to the shorted output. A capacitor must be placed at the OUTPUT pin, acting as a current source to support the instantaneous current draw (Table 2). A low-ESR capacitor is recommended. Once the value of the output capacitor is determined from Table 2, Equation 2 must be reevaluated.

Table 2.	Cout Selection	n Guide
----------	----------------	---------

V <sub>IN</sub> (V)	Capacitance (µF)
24< V <sub>IN</sub> ≤ 27	22
$27 < V_{IN} \le 32$	47
$32 < V_{IN} \le 36$	68

#### **Power Dissipation**

During normal operation as a switch, the power dissipation of the device is small and has little effect on the operating temperature of the part. The maximum power dissipation for the switch in normal operation occurs just before the switch enters into current limit. This may be calculated using the equation:

$$P_{D_{MAX}(NormalOperation)} = (I_{LIM(Max)})^2 \times R_{ON(MAX)}$$
(3)

The maximum junction temperature should be limited to 125°C under normal operation. Junction temperature can be calculated using the equation:

$$T_J = P_D \times \Theta_{JA} + T_A \tag{4}$$

where:

- T<sub>J</sub> is junction temperature;
- P<sub>D</sub> is power dissipation on the switch;
- Θ<sub>JA</sub> is the thermal resistance, junction-to-ambient of the package; and
- T<sub>A</sub> is ambient temperature.

#### **Design Example**

For a 12 V application and  $I_{LIM (Max)} = 1$  A, maximum power dissipation in a normal operation is calculated as:

$$P_{D MAX(Normal Operation)(VIN=12V)} = (1)^2 \times 0.140 = 140 \, \text{mW}$$
 (5)

FPF2702 P<sub>D(Max)</sub> during OC:

If device is in over-current condition and  $V_{OUT}$ >2 V, power dissipation can be calculated as:

$$P_{D} = (V_{IN} - V_{OUT}) \times I_{LIM (Max)}$$
(6)

If device is in short-circuit current limit and  $V_{OUT}$  < 2 V, power dissipation can be calculated as:

$$P_{D} = (V_{IN} - V_{OUT}) \times (0.75 \times I_{LIM (Max)})$$
(7)

#### **Design Example:**

Using FPF2702 in a V<sub>IN</sub> = 5 V application where  $I_{LIM (Max)}$  = 2 A, assuming V<sub>OUT</sub> = 2.5 V; power dissipation across the switch is calculated as:

$$P_{\rm D} = (5 - 2.5) \times 2 = 5 W \tag{8}$$

Whereas in a short-circuit current-limit condition ( $V_{OUT} \approx 0 V$ ), power dissipation is calculated as:

$$P_{D} = ((V_{IN} - V_{OUT}) \times (0.75 \times I_{LIM (Max)}) = (5 - 0) \times (0.75 \times 2) = 7.5W$$
(9)

## PCB Layout Recommendations

For the best performance, all traces should be as short as possible. To be most effective, the input and output capacitors should be placed close to the device to minimize the effects that parasitic trace inductances may have on normal and short-circuit operation (Figure 42). Using wide traces for IN, OUT, and GND pins helps minimize parasitic electrical effects as well as the caseto-ambient thermal impedance.

To minimize the interference between analog ground (chip ground, pin 5) and power ground during load current excursion, the ground terminal of the input and output capacitors and the  $R_{\text{SET}}$  resistor should be routed directly to chip ground and away from power ground.

#### **Improving Thermal Performance**

Improper layout could result in higher junction temperature and trigger thermal shutdown protection. This is particularly significant for the FPF2702, where the device operates in Constant Current Mode under overload conditions. During fault conditions, the power dissipation of the switch could exceed the maximum absolute power dissipation.

The following techniques improve the thermal performance of this family of devices. These techniques are listed in order of the significance of their impact.

- 1. Thermal performance of the load switch can be improved by connecting the Die Attach Pad (DAP) of the MLP 3x3 package to the GND plane of the PCB.
- 2. Embedding two exposed through-hole vias into the DAP provides a path for heat to transfer to the back GND plane of the PCB. A drill size of round, 15 mils (0.4 mm) with 1-ounce copper plating is recommended for appropriate solder reflow. A smaller-size hole prevents the solder from penetrating into the via, resulting in device lift-up. Similarly, a larger hole consumes excessive solder and may result in voiding the DAP.



3. The IN, OUT, and GND pins dissipate most of the heat generated during high-load current condition. The layout suggested in Figure 42 and Figure 43 is strongly recommended illustrating a proper layout for devices in MLP 3x3 packages. IN, OUT, and GND pins are connected to adequate copper so that heat may be transferred as efficiently as possible out of the device. The low-power FLAGB and ON pins traces may be laid-out diagonally from the device to maximize the area available to the ground pad. Place the input and output capacitors as close as possible to the device.



Figure 42. Proper Layout of Output and Ground Copper Area (Top, SST, and AST Layers)



Figure 43. Proper Layout (Bottom and ASB Layers)

## **FPF270x Demonstration Board**

The FPF270X demonstration board has components and circuitry to demonstrate the load switch's functions and features. Thermal performance of the board is improved using the techniques recommended in the layout recommendations section. Additional information about demonstration board can be found in the FPF270X board users guide.







18

#### FAIRCHILD SEMICONDUCTOR TRADEMARKS The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks. AccuPower™ E-PES™ Svnc-Lock™ **FRFET**<sup>®</sup> AX-CAP® BitSiC™ Global Power Resource<sup>8</sup> PowerTrench® GreenBridge™ Build it Now™ TinyBoost<sup>®</sup> PowerXS<sup>™</sup> CorePLUS™ Green FPS™ TinyBuck Programmable Active Droop™ Green FPS™ e-Series™ CorePOWER™ TinyCalc™ QFET **CROSSVOLT™** Gmax™ TinvLogic QS™ GTO™ TINYOPTO CTL™ Quiet Series™ IntelliMAX™ TinyPower™ Current Transfer Logic™ RapidConfigure™ TinyPWM™ DEUXPEED® ISOPLANAR™ Dual Cool™ Making Small Speakers Sound Louder TinyWire™ Saving our world, 1mW/W/kW at a time™ EcoSPARK<sup>®</sup> and Better<sup>⊤</sup> TranSiC™ SignalWise EfficientMax™ MegaBuck™ TriFault Detect™ SmartMax™ MIČROCOUPLER™ TRUECURRENT®\* **ESBC**™ SMART START™ R MicroFET™ uSerDes™ Solutions for Your Success™ MicroPak™ Fairchild® MicroPak2™ SPM Fairchild Semiconductor® STEALTH<sup>TM</sup> MillerDrive™ UHC® FACT Quiet Series™ SuperFET MotionMax™ Ultra FRFET™ SuperSOT™-3 FACT mWSaver UniFET™ FAST® SuperSOT™-6 OptoHiT™ VCX™ FastvCore™ SuperSOT™-8 **OPTOLOGIC<sup>®</sup>** VisualMax™ FETBench™ SupreMOS<sup>®</sup> **OPTOPLANAR<sup>®</sup>** VoltagePlus™ FPS™ SyncFET<sup>T</sup> XS™ \* Trademarks of System General Corporation, used under license by Fairchild Semiconductor. DISCLAIMER FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN: NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS. LIFE SUPPORT POLICY FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

#### As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

#### ANTI-COUNTERFEITING POLICY

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufacturers of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed applications, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handling and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address any warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

#### PRODUCT STATUS DEFINITIONS

Definition of Terms		
Datasheet Identification	Product Status	Definition
Advance Information	Formative / In Design	Datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.
No Identification Needed	Full Production	Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design.
Obsolete	Not In Production	Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only.

Rev. 166

FPF2700 / FPF2701 / FPF2702

I

AccuPower<sup>™</sup> 0.4~2A Adjustable Over-Current Protection Load Switches

ON Semiconductor and are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at <u>www.onsemi.com/site/pdf/Patent-Marking.pdf</u>. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor haves against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death a

#### PUBLICATION ORDERING INFORMATION

#### LITERATURE FULFILLMENT:

Literature Distribution Center for ON Semiconductor 19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada Fax: 303-675-2176 or 800-344-3867 Toll Free USA/Canada Email: orderlit@onsemi.com N. American Technical Support: 800–282–9855 Toll Free USA/Canada Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910

Japan Customer Focus Center Phone: 81-3-5817-1050 ON Semiconductor Website: www.onsemi.com

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative

© Semiconductor Components Industries, LLC

# **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

ON Semiconductor: FPF2702MPX FPF2702MX



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный) **Факс:** 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.