DUAL OPERATIONAL TRANSCONDUCTANCE AMPLIFIER

■ GENERAL DESCRIPTION

The NJM13600/13700 consist of two current controlled trans conductance amplifiers each with differential inputs and a push pull output. The two amplifiers share common supplies but otherwise operate independently. Linearizing diodes are provided at the inputs to reduce distortion and allow higher input levels. The result is a 10 dB signal-to-noise improvement referenced to 0.5 percent THD.Controlled impedance buffers are provided which are especially designed to complement the dynamic range of the amplifiers.

■ PACKAGE OUTLINE



NJM13600D
NJM13700D



NJM13600M
NJM13700M

■ FEATURES

- Package Outline DIP16,DMP16
- Bipolar Technology

■ PIN CONFIGURATION



NJM13600D,NJM13600M
NJM13700D,NJM13700M

PIN FUNCTION

1.	AMP BIAS INPUT A	9.	BUFFER OUTPUT B
2.	DIODE BIAS A	10.	BUFFER INPUT B
3.	+INPUT	11.	V^+
4.	–INPUT	12.	OUTPUT B
5.	OUTPUT A	13.	-INPUT B
6.	V^-	14.	+INPUT B
7.	BUFFER INPUT A	15.	DIODE BIAS B
8.	BUFFER OUTPUT A	16.	AMP BIAS INPUT B

■ EQUIVALENT CIRCUIT



■ ABSOLUTE MAXIMUM RATINGS

(Ta=25˚C)

PARAMETER	SYMBOL	RATINGS	UNIT
Supply Voltage	V^+/V^-	36 or ±18	V
Differential Input Voltage	V_{ID}	± 5	V
Diode Bias Current	I_D	2	mA
Amp Bias Current	I_{ABC}	2	mA
Buffer Output Current	I_O	20	mA
Power Dissipation	P_D	(DIP16) 570 (DMP16) 700 (note)	mW
DC Input Voltage	V_{IN}	V^+~V^-	V
Operating Temperature Range	T_{opr}	-40~+85	˚C
Storage Temperature Range	T_{stg}	-40~+125	˚C

(note) At on a ceramic PCB (10x20x0.635 mm)

■ ELECTRICAL CHARACTERISTICS

(V^+/V^-=±15V,Ta=25˚C,I_{ABC}=500μA)

PARAMETER	SYMBOL	TEST CONDITION	13600			13700			UNIT
			MIN.	TYP.	MAX.	MIN.	TYP.	MAX.	
Input Offset Voltage (V_{OS})	V_{IO}		-	0.4	5	-	0.4	4	mV
Input Offset Voltage		I_{ABC}=5μA	-	0.3	5	-	0.3	4	mV
V_{OS} Including Diodes		Diode Bias Current,I_D=500μA	-	0.5	5	-	0.5	5	mV
Input Offset Change		5μA≤I_{ABC}≤500μA	-	0.1	-	-	0.1	3	mV
Input Bias Current	I_B		-	0.4	5	-	0.4	5	μA
Input Bias Current		(-20~+75˚C)	-	1	8	-	1	8	μA
Forward Transconductance	gm		6700	9600	13000	6700	9600	13000	μS
		(-20~+75˚C)	5400	-	-	5400	-	-	μS
gm Tracking		R_L=0,I_{ABC}=5μA	-	0.3	-	-	0.3	-	dB
Peak Output Current	I_{OP}	R_L=0,I_{ABC}=5μA	-	5	-	-	0	-	μA
Peak Output Current		R_L=0,I_{ABC}=500μA	350	500	650	350	500	650	μA
Peak Output Current		R_L=0 (-20~+75˚C)	300	-	-	300	-	-	μA
Peak Output Voltage Positive	V_{OP}	R_L=∞,5μA≤I_{ABC}≤500μA	+12	+14.2	-	+12	+14.2	-	V
Peak Output Voltage Negative		R_L=∞,5μA≤I_{ABC}≤500μA	-12	-14.4	-	-12	-14.4	-	V
Operating Current	I_{CC}	I_{ABC}=500μA,two circuit	-	2.6	-	-	2.6	-	mA
V_{OS} Sensitivity Positive	SVR	$\Delta V_{OS}/\Delta V^+$	76.5	94	-	76.5	94	-	dB
V_{OS} Sensitivity Negative		$\Delta V_{OS}/\Delta V^-$	76.5	94	-	76.5	94	-	dB
Input Offset Current	I_{IO}		-	0.1	0.6	-	0.1	0.6	μA
CMRR	CMR		80	110	-	80	110	-	dB
Common Mode Range	V_{ICM}		± 12	± 13.5	-	± 12	± 13.5	-	V
Cross Talk	CT	20Hz<f<20kHz (note2)	-	-100	-	-	-100	-	dB
Differential Input Current	I_{ID}	I_{ABC}=0,Input=±4V	-	0.02	100	-	0.02	100	nA
Leakage Current	I_{LEAK}	I_{ABC}=0(Refer to Test Circuit)	-	0.2	100	-	0.2	100	nA
Input Resistance	R_{IN}		10	26	-	10	26	-	kΩ
Open Loop Bandwidth			-	2	-	-	2	-	MHz
Slew Rate	SR		-	50	-	-	50	-	V/μs
Buffer Input Current		(note2)	-	0.4	5	-	0.4	5	μA
Peak Buffer Output Voltage		(note2)	10	-	-	10	-	-	V

(note1) Open unless otherwise specified. The inputs to the buffers are grounded and outputs are open.

(note2) R_{OUT}=5kΩ connected from the buffer output to V^- and the input of buffer is connected to the transconductance amplifier output.

I_{ABC}=500μA

■ TEST CIRCUIT



Differential Input Current



Leakage Current

■ TYPICAL APPLICATIONS



■ TYPICAL CHARACTERISTICS

Distortion vs. Differential Input Voltage

(V^+/V^- = ±15V, R_L = 10kΩ, I_{ABC} = 1mA, Ta = 25℃)



Voltage vs. Amplifier Bias Current

(V^+/V^- = ±15V, R_L = 10kΩ, Ta = 25℃)



Output Noise Current vs. Frequency

(Ta = 25℃)



■ TYPICAL CHARACTERISTICS

Input Offset Voltage

($V^+/V^-=\pm15V$, Ta=25℃)



Input Offset Current

($V^+/V^-=\pm15V$, Ta=25℃)



Input Bias Current

($V^+/V^-=\pm15V$, Ta=25℃)



Peak Output Current

($V^+/V^-=\pm15V$, Ta=25℃)



Peak Output Voltage and Common Mode Range

($V^+/V^-=\pm15V$, $R_L=\infty$, Ta=25℃)



Leakage Current vs. Temperature

($+V_{IN}=-V_{IN}=V_O$)



■ TYPICAL CHARACTERISTICS

Input Leakage Current

(Ta=25℃)



Transconductance

($V^+/V^-=\pm15V$, Pin2.15 Open, Ta=25℃)



Input Resistance

(Pin2.15 Open, Ta=25℃)



Amplifier Bias Voltage vs. Amplifier Bias Current

(Ta=25℃)



Input and Output Capacitance

($V^+/V^-=\pm15V$, Ta=25℃)



Output Resistance

(Ta=25℃)



[CAUTION]
The specifications on this databook are only given for information , without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.

Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.