

VOLTAGE DETECTOR with Delay Function

■ GENERAL DESCRIPTION

The NJU7708/09 is a low quiescent current voltage detector with delay function featuring high precision detection voltage.

The detection voltage is internally fixed with an accuracy of 1.0%.

The NJU7708/09 are useful for preventing malfunction of microcomputer or DSP etc. through detect a drop in voltage of battery or power supply.


The delay function achieves set wait time when supply voltage is unstable. Moreover, the delay function can make a sequence that other devices in application work and stabilize before microcomputer or DSP works.

Delay time can be set by logical combination from 4-delay time.

NJU7708 is Nch. Open Drain and NJU7709 is a C-MOS output type.

Small packaging makes NJU7708 and NJU7709 suitable for space conscious applications.

■ PACKAGE OUTLINE




NJU7708/09F

■ FEATURES

- High Precision detection Voltage $\pm 1.0\%$
- Low Quiescent Current $1.3\mu\text{A}$
- Detection Voltage Range $1.3 \sim 6.0\text{V}$ (0.1V step)
- Delay Time (Built-in Fixed Type) 0ms/50ms/100ms/200ms: Logical selectable 4-delay time
- Output Configuration
NJU7708: Nch. Open Drain Type
NJU7709: C-MOS Output Type
- CMOS Technology
- Package Outline SOT-23-5



■ PIN CONFIGURATION



PIN FUNCTION

1. D1
2. V_{SS}
3. D2
4. V_{OUT}
5. V_{DD}

■ EQUIVALENT CIRCUIT



■ DETECTION VOLTAGERANK LIST

Device Name	V _{DET}
NJU7708/09F15	1.5V
NJU7708/09F27	2.7V
NJU7708/09F42	4.2V
NJU7708/09F06	6.0V

■ LOGICAL TABLE OF DELAY TIME

D1	D2	DELAY
H	H	0ms
H	L	50ms
L	H	100ms
L	L	200ms

■ NJU7708

■ ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Input Voltage	V _{DD}	+10	V
Output Voltage	V _{OUT}	V _{SS} -0.3 ~ +10	V
Output Current	I _{OUT}	50	mA
Power Dissipation	P _D	SOT-23-5 350(*1) 200(*2)	mW
Operating Temperature	Topr	-40 ~ +85	°C
Storage Temperature	Tstg	-40 ~ +125	°C

(*1) : Mounted on glass epoxy board based on EIA/JEDEC. (114.3x76.2x1.6mm: 2Layers)

(*2) : Device itself


■ ELECTRICAL CHARACTERISTICS (Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Detection Voltage	V _{DET}		-1.0%	—	+1.0%	V
Hysteresis Voltage	V _{HYS}		70	90	130	V
Quiescent Current	I _{SS}	V _{DD} =V _{DET} +1V				
		V _{DET} =1.5V ~ 2.5V Version	—	1.0	1.7	μA
		V _{DET} =2.6V ~ 6.0V Version	—	1.3	2.2	μA
Output Current	I _{OUT}	Nch, V _{DS} =0.5V				
		V _{DD} =1.2V	0.75	2.0	—	mA
		V _{DD} =2.4V (≥2.7V Version)	4.5	7.0	—	mA
Output Leak Current	I _{LEAK}	V _{DD} =V _{OUT} =9V	—	—	0.1	μA
Detection Voltage Temperature Coefficient	ΔV _{DET} /ΔTa	Ta=0 ~ +85°C	—	±100	—	ppm/°C
Delay Time	t _d	V _{DD} =V _{DET} +1V				
		D1=H, D2=H	25	100	300	μs
		D1=H, D2=L	42.5	50	57.5	ms
		D1=L, D2=H	85	100	115	ms
		D1=L, D2=L	170	200	230	ms
Delay Time Change	V _{D1 H} /V _{D2 H}		1.5	—	V _{DD}	V
Terminal Input Voltage	V _{D1 L} /V _{D2 L}		0	—	0.3	V
Operating Voltage(*3)	V _{DD}	R _L =100kΩ	0.7	—	9	V

(*3): The minimum operating voltage(V_{OPL}) indicates the same value of the input voltage(V_{DD}) on condition that V_{OUT} becomes 10% or less of the input voltage(V_{DD}).


■ TEST CIRCUIT

● Quiescent Current TEST CIRCUIT




● Detection Voltage


/Minimum Operating Voltage TEST CIRCUIT




● Leak Current/Output Current TEST CIRCUIT




● Delay Time=0mS TEST CIRCUIT



● Delay Time=50mS TEST CIRCUIT




● Delay Time=100mS TEST CIRCUIT




■ TEST CIRCUIT

● Delay Time=200mS TEST CIRCUIT




■ TYPICAL APPLICATION

① Power Supply Voltage Supervisory Circuit



② Power Supply Voltage Supervisory Circuit (Another Power Supply to Micro-Processor)



■ NJU7709

■ ABSOLUTE MAXIMUM RATINGS (Ta=25°C)

PARAMETER	SYMBOL	RATINGS	UNIT
Input Voltage	V_{DD}	+10	V
Output Voltage	V_{OUT}	$V_{SS}-0.3 \sim V_{DD}+0.3$	V
Output Current	I_{OUT}	50	mA
Power Dissipation	P_D	SOT-23-5 350(*4) 200(*5)	mW
Operating Temperature	Topr	-40 ~ +85	°C
Storage Temperature	Tstg	-40 ~ +125	°C

(*4) : Mounted on glass epoxy board based on EIA/JEDEC. (114.3x76.2x1.6mm: 2Layers)

(*5) : Device itself

■ ELECTRICAL CHARACTERISTICS


(Ta=25°C)

PARAMETER	SYMBOL	TEST CONDITION	MIN.	TYP.	MAX.	UNIT
Detection Voltage	V_{DET}		-1.0%	—	+1.0%	V
Hysteresis Voltage	V_{HYS}		70	90	130	V
Quiescent Current	I_{SS}	$V_{DD}=V_{DET}+1V$ $V_{DET}=1.5V \sim 1.9V$ Version $V_{DET}=2.0V \sim 6.0V$ Version	— —	1.0 1.3	1.7 2.2	μA
Output Current	I_{OUT}	Nch, $V_{DS}=0.5V$ $V_{DD}=1.2V$ $V_{DD}=2.4V(\geq 2.7V$ Version) $V_{DD}=4.8V(\leq 3.9V$ Version) Pch, $V_{DS}=0.5V$ $V_{DD}=6.0V(4.0V \sim 5.6V$ Version) $V_{DD}=8.4V(\geq 5.7V$ Version)	0.75 4.5 2.0 2.5 3.0	2.0 7.0 3.5 4.0 5.0	— — — — —	mA
Detection Voltage Temperature Coefficient	$\Delta V_{DET}/\Delta Ta$	Ta=0 ~ +85°C	—	± 100	—	ppm/°C
Delay Time	td	$V_{DD}=V_{DET}+1V$, D1=H, D2=H D1=H, D2=L D1=L, D2=H D1=L, D2=L	25 42.5 85 170	100 50 100 200	300 57.5 115 230	μs ms ms ms
Delay Time Change	V_{D1_H} / V_{D2_H}		1.5	—	V_{DD}	V
Terminal Input Voltage	V_{D1_L} / V_{D2_L}		0	—	0.3	V
Operating Voltage (*6)	V_{DD}	$R_L=100k\Omega$	0.8	—	9	V


(*6): The minimum Operating Voltage(V_{OPL}) indicates the same value of the output voltage(V_{OUT}) on condition that V_{OUT} becomes 10% or less of the input voltage(V_{DD}).

■ TEST CIRCUIT


● Quiescent Current TEST CIRCUIT




● Detection Voltage TEST CIRCUIT




● Nch Output Current TEST CIRCUIT




● Pch Output Current TEST CIRCUIT



● Delay Time=0mS TEST CIRCUIT




● Delay Time=50mS TEST CIRCUIT




■ TEST CIRCUIT


● Delay Time=100mS TEST CIRCUIT



● Delay Time=200mS TEST CIRCUIT




● Minimum Operating Voltage TEST CIRCUIT




■ TYPICAL APPLICATION

① Power Supply Voltage Supervisory Circuit



■ FUNCTIONAL DESCRIPTION

(1) Basic Operation



- (1) When supply voltage (V_{DD}) drops below detection voltage (V_{DET}), Output voltage (V_{OUT}) changes "H" to "L" to alert reset state.
- (2) The reset state is kept while V_{DD} is lower than release voltage. The release voltage is a sum of V_{DET} and Hysteresis voltage (V_{HY}). Please refer to the (*7) below.
- (3) When V_{DD} becomes higher than the release voltage and reset release delay time fixed by logical select is past, then V_{OUT} changes from "L" to "H" to resume normal state.

(*7) V_{HY} is to avoid unstable V_{OUT} state caused by rapid voltage change at nearby V_{DET} .

(*8): C-MOS output product (NJU7709) : When V_{DD} less than V_{OP} , V_{OUT} is free of the shaded region.

(2) Description of Delay Time

Delay time can be set by logical combination of D1 and D2 (see " LOGICAL TABLE OF DELAY TIME " on page2).

[CAUTION]

The specifications on this databook are only given for information, without any guarantee as regards either mistakes or omissions. The application circuits in this databook are described only to show representative usages of the product and not intended for the guarantee or permission of any right including the industrial rights.

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[NJR:](#)

[NJU7709F27-TE1](#) [NJU7709F06-TE1](#) [NJU7708F27-TE1](#) [NJU7709F15-TE1](#) [NJU7708F06-TE1](#) [NJU7708F15-TE1](#)
[NJU7708F42-TE1](#) [NJU7709F42-TE1](#)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.