

## LMH6642/LMH6643/LMH6644 Low Power, 130MHz, 75mA Rail-to-Rail Output Amplifiers

Check for Samples: [LMH6642](#), [LMH6643](#), [LMH6644](#)

### FEATURES

( $V_S = \pm 5V$ ,  $T_A = 25^\circ C$ ,  $R_L = 2k\Omega$ ,  $A_V = +1$ . Typical Values Unless Specified).

- **-3dB BW ( $A_V = +1$ ) 130MHz**
- **Supply Voltage Range 2.7V to 12.8V**
- **Slew Rate <sup>(1)</sup>, ( $A_V = -1$ ) 130V/ $\mu$ s**
- **Supply Current (no load) 2.7mA/amp**
- **Output Short Circuit Current +115mA/-145mA**
- **Linear Output Current  $\pm 75mA$**
- **Input Common Mode Volt. 0.5V Beyond  $V^-$ , 1V from  $V^+$**
- **Output Voltage Swing 40mV from Rails**
- **Input Voltage Noise (100kHz) 17nV/ $\sqrt{Hz}$**
- **Input Current Noise (100kHz) 0.9pA/ $\sqrt{Hz}$**
- **THD (5MHz,  $R_L = 2k\Omega$ ,  $V_O = 2V_{PP}$ ,  $A_V = +2$ ) -62dBc**
- **Settling Time 68ns**
- **Fully Characterized for 3V, 5V, and  $\pm 5V$**
- **Overdrive Recovery 100ns**
- **Output Short Circuit Protected <sup>(2)</sup>**
- **No Output Phase Reversal with CMVR Exceeded**

### APPLICATIONS

- **Active Filters**
- **CD/DVD ROM**
- **ADC Buffer Amp**
- **Portable Video**
- **Current Sense Buffer**

(1) Slew rate is the average of the rising and falling slew rates.

(2) Output short circuit duration is infinite for  $V_S < 6V$  at room temperature and below. For  $V_S > 6V$ , allowable short circuit duration is 1.5ms.

### DESCRIPTION

The LMH664X family true single supply voltage feedback amplifiers offer high speed (130MHz), low distortion (-62dBc), and exceptionally high output current (approximately 75mA) at low cost and with reduced power consumption when compared against existing devices with similar performance.

Input common mode voltage range extends to 0.5V below  $V^-$  and 1V from  $V^+$ . Output voltage range extends to within 40mV of either supply rail, allowing wide dynamic range especially desirable in low voltage applications. The output stage is capable of approximately 75mA in order to drive heavy loads. Fast output Slew Rate (130V/ $\mu$ s) ensures large peak-to-peak output swings can be maintained even at higher speeds, resulting in exceptional full power bandwidth of 40MHz with a 3V supply. These characteristics, along with low cost, are ideal features for a multitude of industrial and commercial applications.

Careful attention has been paid to ensure device stability under all operating voltages and modes. The result is a very well behaved frequency response characteristic (0.1dB gain flatness up the 12MHz under 150 $\Omega$  load and  $A_V = +2$ ) with minimal peaking (typically 2dB maximum) for any gain setting and under both heavy and light loads. This along with fast settling time (68ns) and low distortion allows the device to operate well in ADC buffer, and high frequency filter applications as well as other applications.

This device family offers professional quality video performance with low DG (0.01%) and DP (0.01°) characteristics. Differential Gain and Differential Phase characteristics are also well maintained under heavy loads (150 $\Omega$ ) and throughout the output voltage range. The LMH664X family is offered in single (LMH6642), dual (LMH6643), and quad (LMH6644) options.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

All trademarks are the property of their respective owners.

Closed Loop Gain vs. Frequency for Various Gain




Figure 1.

Large Signal Frequency Response




Figure 2.



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

### Absolute Maximum Ratings <sup>(1)(2)</sup>

|   |  |  |
|---|--|--|
| ESD Tolerance                                     |  | 2KV <sup>(3)</sup>                         |
|   |  | 200V <sup>(4)</sup>                        |
|   |  | 1000V <sup>(5)</sup>                       |
| VIN Differential                                  |  | ±2.5V                                      |
| Output Short Circuit Duration                     |  | See <sup>(6)</sup> , <sup>(7)</sup>        |
| Supply Voltage (V <sup>+</sup> - V <sup>-</sup> ) |  | 13.5V                                      |
| Voltage at Input/Output pins                      |  | V <sup>+</sup> +0.8V, V <sup>-</sup> -0.8V |
| Input Current                                     |  | ±10mA                                      |
| Storage Temperature Range                         |  | -65°C to +150°C                            |
| Junction Temperature <sup>(8)</sup>               |  | +150°C                                     |
| Soldering Information                             | Infrared or Convection Reflow (20 sec) | 235°C                                      |
|   | Wave Soldering Lead Temp.(10 sec)      | 260°C                                      |

- (1) Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.
- (2) If Military/Aerospace specified devices are required, please contact the TI Sales Office/Distributors for availability and specifications.
- (3) Human body model, 1.5kΩ in series with 100pF.
- (4) Machine Model, 0Ω in series with 200pF.
- (5) CDM: Charge Device Model
- (6) Applies to both single-supply and split-supply operation. Continuous short circuit operation at elevated ambient temperature can result in exceeding the maximum allowed junction temperature of 150°C.
- (7) Output short circuit duration is infinite for VS < 6V at room temperature and below. For VS > 6V, allowable short circuit duration is 1.5ms.
- (8) The maximum power dissipation is a function of TJ(MAX), θJA, and TA. The maximum allowable power dissipation at any ambient temperature is PD = (TJ(MAX) - TA) / θJA. All numbers apply for packages soldered directly onto a PC board.

## Operating Ratings <sup>(1)</sup>

|   |              |                |
|---|--------------|----------------|
| Supply Voltage ( $V^+ - V^-$ )                              |              | 2.7V to 12.8V  |
| Junction Temperature Range <sup>(2)</sup>                   |              | -40°C to +85°C |
| Package Thermal Resistance <sup>(2)</sup> ( $\theta_{JA}$ ) | 5-Pin SOT-23 | 265°C/W        |
|   | 8-Pin SOIC   | 190°C/W        |
|   | 8-Pin VSSOP  | 235°C/W        |
|   | 14-Pin SOIC  | 145°C/W        |
|   | 14-Pin TSSOP | 155°C/W        |

- (1) Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not guaranteed. For guaranteed specifications and the test conditions, see the Electrical Characteristics.
- (2) The maximum power dissipation is a function of  $T_{J(MAX)}$ ,  $\theta_{JA}$ , and  $T_A$ . The maximum allowable power dissipation at any ambient temperature is  $P_D = (T_{J(MAX)} - T_A) / \theta_{JA}$ . All numbers apply for packages soldered directly onto a PC board.

## 3V Electrical Characteristics

Unless otherwise specified, all limits guaranteed for at  $T_J = 25^\circ\text{C}$ ,  $V^+ = 3\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{CM} = V_O = V^+/2$ ,  $V_{ID}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to  $V^+/2$ . **Boldface** limits apply at the temperature extremes.

| Symbol       | Parameter                    | Conditions   | Min<br>(1) | Typ<br>(2) | Max<br>(1)                             | Units                        |
|--------------|------------------------------|--|------------|------------|--|------------------------------|
| BW           | -3dB BW                      | $A_V = +1$ , $V_{OUT} = 200\text{mV}_{PP}$   | 80         | 115        |  | MHz                          |
|              |                              | $A_V = +2$ , -1, $V_{OUT} = 200\text{mV}_{PP}$   |            | 46         |  |                              |
| $BW_{0.1dB}$ | 0.1dB Gain Flatness          | $A_V = +2$ , $R_L = 150\Omega$ to $V^+/2$ ,<br>$R_L = 402\Omega$ , $V_{OUT} = 200\text{mV}_{PP}$ |            | 19         |  | MHz                          |
| PBW          | Full Power Bandwidth         | $A_V = +1$ , -1dB, $V_{OUT} = 1\text{V}_{PP}$  |            | 40         |  | MHz                          |
| $e_n$        | Input-Referred Voltage Noise | $f = 100\text{kHz}$  |            | 17         |  | $\text{nV}/\sqrt{\text{Hz}}$ |
|              |                              | $f = 1\text{kHz}$  |            | 48         |  |                              |
| $i_n$        | Input-Referred Current Noise | $f = 100\text{kHz}$  |            | 0.90       |  | $\text{pA}/\sqrt{\text{Hz}}$ |
|              |                              | $f = 1\text{kHz}$  |            | 3.3        |  |                              |
| THD          | Total Harmonic Distortion    | $f = 5\text{MHz}$ , $V_O = 2\text{V}_{PP}$ , $A_V = -1$ ,<br>$R_L = 100\Omega$ to $V^+/2$        |            | -48        |  | dBc                          |
| DG           | Differential Gain            | $V_{CM} = 1\text{V}$ , NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$                          |            | 0.17       |  | %                            |
|              |                              | $R_L = 1\text{k}\Omega$ to $V^+/2$   |            | 0.03       |  |                              |
| DP           | Differential Phase           | $V_{CM} = 1\text{V}$ , NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$                          |            | 0.05       |  | deg                          |
|              |                              | $R_L = 1\text{k}\Omega$ to $V^+/2$   |            | 0.03       |  |                              |
| CT Rej.      | Cross-Talk Rejection         | $f = 5\text{MHz}$ , Receiver:<br>$R_f = R_g = 510\Omega$ , $A_V = +2$                            |            | 47         |  | dB                           |
| $T_S$        | Settling Time                | $V_O = 2\text{V}_{PP}$ , $\pm 0.1\%$ , 8pF Load,<br>$V_S = 5\text{V}$                            |            | 68         |  | ns                           |
| SR           | Slew Rate <sup>(3)</sup>     | $A_V = -1$ , $V_I = 2\text{V}_{PP}$  | 90         | 120        |  | V/ $\mu\text{s}$             |
| $V_{OS}$     | Input Offset Voltage         | For LMH6642 and LMH6644  |            | $\pm 1$    | $\pm 5$<br><b><math>\pm 7</math></b>   | mV                           |
|              |                              | For LMH6643  |            | $\pm 1$    | $\pm 3.4$<br><b><math>\pm 7</math></b> |                              |
| TC $V_{OS}$  | Input Offset Average Drift   | See <sup>(4)</sup>   |            | $\pm 5$    |  | $\mu\text{V}/^\circ\text{C}$ |
| $I_B$        | Input Bias Current           | See <sup>(5)</sup>   |            | -1.50      | -2.60<br><b>-3.25</b>                  | $\mu\text{A}$                |
| $I_{OS}$     | Input Offset Current         |  |            | 20         | 800<br><b>1000</b>                     | nA                           |
| $R_{IN}$     | Common Mode Input Resistance |  |            | 3          |  | M $\Omega$                   |

- (1) All limits are guaranteed by testing or statistical analysis.
- (2) Typical values represent the most likely parametric norm.
- (3) Slew rate is the average of the rising and falling slew rates.
- (4) Offset voltage average drift determined by dividing the change in  $V_{OS}$  at temperature extremes by the total temperature change.
- (5) Positive current corresponds to current flowing into the device.

### 3V Electrical Characteristics (continued)

Unless otherwise specified, all limits guaranteed for at  $T_J = 25^\circ\text{C}$ ,  $V^+ = 3\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{CM} = V_O = V^+/2$ ,  $V_{ID}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to  $V^+/2$ . **Boldface** limits apply at the temperature extremes.

| Symbol    | Parameter                             | Conditions   | Min<br>(1)        | Typ<br>(2) | Max<br>(1)          | Units |
|-----------|---------------------------------------|--|-------------------|------------|---------------------|-------|
| $C_{IN}$  | Common Mode Input Capacitance         |  |                   | 2          |                     | pF    |
| CMVR      | Input Common-Mode Voltage Range       | CMRR $\geq 50\text{dB}$  |                   | -0.5       | -0.2<br><b>-0.1</b> | V     |
|           |                                       |  | 1.8<br><b>1.6</b> | 2.0        |                     |       |
| CMRR      | Common Mode Rejection Ratio           | $V_{CM}$ Stepped from 0V to 1.5V   | 72                | 95         |                     | dB    |
| $A_{VOL}$ | Large Signal Voltage Gain             | $V_O = 0.5\text{V}$ to $2.5\text{V}$<br>$R_L = 2\text{k}\Omega$ to $V^+/2$ | 80<br><b>75</b>   | 96         |                     | dB    |
|           |                                       | $V_O = 0.5\text{V}$ to $2.5\text{V}$<br>$R_L = 150\Omega$ to $V^+/2$       | 74<br><b>70</b>   | 82         |                     |       |
| $V_O$     | Output Swing High                     | $R_L = 2\text{k}\Omega$ to $V^+/2$ , $V_{ID} = 200\text{mV}$               | 2.90              | 2.98       |                     | V     |
|           |                                       | $R_L = 150\Omega$ to $V^+/2$ , $V_{ID} = 200\text{mV}$                     | 2.80              | 2.93       |                     |       |
|           | Output Swing Low                      | $R_L = 2\text{k}\Omega$ to $V^+/2$ , $V_{ID} = -200\text{mV}$              |                   | 25         | 75                  | mV    |
|           |                                       | $R_L = 150\Omega$ to $V^+/2$ , $V_{ID} = -200\text{mV}$                    |                   | 75         | 150                 |       |
| $I_{SC}$  | Output Short Circuit Current          | Sourcing to $V^+/2$<br>$V_{ID} = 200\text{mV}$ (6)                         | 50<br><b>35</b>   | 95         |                     | mA    |
|           |                                       | Sinking to $V^+/2$<br>$V_{ID} = -200\text{mV}$ (6)                         | 55<br><b>40</b>   | 110        |                     |       |
| $I_{OUT}$ | Output Current                        | $V_{OUT} = 0.5\text{V}$ from either supply                                 |                   | $\pm 65$   |                     | mA    |
| +PSRR     | Positive Power Supply Rejection Ratio | $V^+ = 3.0\text{V}$ to $3.5\text{V}$ , $V_{CM} = 1.5\text{V}$              | 75                | 85         |                     | dB    |
| $I_S$     | Supply Current (per channel)          | No Load  |                   | 2.70       | 4.00<br><b>4.50</b> | mA    |

(6) Short circuit test is a momentary test. See [Note 7](#) under 5V Electrical Characteristics.

### 5V Electrical Characteristics

Unless otherwise specified, all limits guaranteed for at  $T_J = 25^\circ\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{CM} = V_O = V^+/2$ ,  $V_{ID}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to  $V^+/2$ . **Boldface** limits apply at the temperature extremes.

| Symbol       | Parameter                    | Conditions   | Min<br>(1) | Typ<br>(2) | Max<br>(1) | Units                  |
|--------------|------------------------------|--|------------|------------|------------|------------------------|
| BW           | -3dB BW                      | $A_V = +1$ , $V_{OUT} = 200\text{mV}_{PP}$   | 90         | 120        |            | MHz                    |
|              |                              | $A_V = +2$ , -1, $V_{OUT} = 200\text{mV}_{PP}$   |            | 46         |            |                        |
| $BW_{0.1dB}$ | 0.1dB Gain Flatness          | $A_V = +2$ , $R_L = 150\Omega$ to $V^+/2$ ,<br>$R_f = 402\Omega$ , $V_{OUT} = 200\text{mV}_{PP}$ |            | 15         |            | MHz                    |
| PBW          | Full Power Bandwidth         | $A_V = +1$ , -1dB, $V_{OUT} = 2V_{PP}$   |            | 22         |            | MHz                    |
| $e_n$        | Input-Referred Voltage Noise | $f = 100\text{kHz}$  |            | 17         |            | nV/ $\sqrt{\text{Hz}}$ |
|              |                              | $f = 1\text{kHz}$  |            | 48         |            |                        |
| $i_n$        | Input-Referred Current Noise | $f = 100\text{kHz}$  |            | 0.90       |            | pA/ $\sqrt{\text{Hz}}$ |
|              |                              | $f = 1\text{kHz}$  |            | 3.3        |            |                        |
| THD          | Total Harmonic Distortion    | $f = 5\text{MHz}$ , $V_O = 2V_{PP}$ , $A_V = +2$   |            | -60        |            | dBc                    |
| DG           | Differential Gain            | NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$   |            | 0.16       |            | %                      |
|              |                              | $R_L = 1\text{k}\Omega$ to $V^+/2$   |            | 0.05       |            |                        |
| DP           | Differential Phase           | NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$   |            | 0.05       |            | deg                    |
|              |                              | $R_L = 1\text{k}\Omega$ to $V^+/2$   |            | 0.01       |            |                        |

(1) All limits are guaranteed by testing or statistical analysis.

(2) Typical values represent the most likely parametric norm.

## 5V Electrical Characteristics (continued)

Unless otherwise specified, all limits guaranteed for at  $T_J = 25^{\circ}\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = 0\text{V}$ ,  $V_{\text{CM}} = V_O = V^+/2$ ,  $V_{\text{ID}}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to  $V^+/2$ . **Boldface** limits apply at the temperature extremes.

| Symbol             | Parameter                             | Conditions  | Min<br>(1)        | Typ<br>(2) | Max<br>(1)                             | Units                          |
|--------------------|---------------------------------------|---|-------------------|------------|--|--------------------------------|
| CT Rej.            | Cross-Talk Rejection                  | $f = 5\text{MHz}$ , Receiver:<br>$R_f = R_g = 510\Omega$ , $A_V = +2$       |                   | 47         |  | dB                             |
| $T_S$              | Settling Time                         | $V_O = 2V_{\text{PP}}$ , $\pm 0.1\%$ , $8\text{pF}$ Load                    |                   | 68         |  | ns                             |
| SR                 | Slew Rate <sup>(3)</sup>              | $A_V = -1$ , $V_I = 2V_{\text{PP}}$   | 95                | 125        |  | V/ $\mu\text{s}$               |
| $V_{\text{OS}}$    | Input Offset Voltage                  | For LMH6642 and LMH6644   |                   | $\pm 1$    | $\pm 5$<br><b><math>\pm 7</math></b>   | mV                             |
|                    |                                       | For LMH6643   |                   | $\pm 1$    | $\pm 3.4$<br><b><math>\pm 7</math></b> |                                |
| TC $V_{\text{OS}}$ | Input Offset Average Drift            | See <sup>(4)</sup>  |                   | $\pm 5$    |  | $\mu\text{V}/^{\circ}\text{C}$ |
| $I_B$              | Input Bias Current                    | See <sup>(5)</sup>  |                   | -1.70      | -2.60<br><b>-3.25</b>                  | $\mu\text{A}$                  |
| $I_{\text{OS}}$    | Input Offset Current                  |   |                   | 20         | 800<br><b>1000</b>                     | nA                             |
| $R_{\text{IN}}$    | Common Mode Input Resistance          |   |                   | 3          |  | M $\Omega$                     |
| $C_{\text{IN}}$    | Common Mode Input Capacitance         |   |                   | 2          |  | pF                             |
| CMVR               | Input Common-Mode Voltage Range       | CMRR $\geq 50\text{dB}$   |                   | -0.5       | -0.2<br><b>-0.1</b>                    | V                              |
|                    |                                       |   | 3.8<br><b>3.6</b> | 4.0        |  |                                |
| CMRR               | Common Mode Rejection Ratio           | $V_{\text{CM}}$ Stepped from 0V to 3.5V                                     | 72                | 95         |  | dB                             |
| $A_{\text{VOL}}$   | Large Signal Voltage Gain             | $V_O = 0.5\text{V}$ to $4.50\text{V}$<br>$R_L = 2\text{k}\Omega$ to $V^+/2$ | 86<br><b>82</b>   | 98         |  | dB                             |
|                    |                                       | $V_O = 0.5\text{V}$ to $4.25\text{V}$<br>$R_L = 150\Omega$ to $V^+/2$       | 76<br><b>72</b>   | 82         |  |                                |
| $V_O$              | Output Swing High                     | $R_L = 2\text{k}\Omega$ to $V^+/2$ , $V_{\text{ID}} = 200\text{mV}$         | 4.90              | 4.98       |  | V                              |
|                    |                                       | $R_L = 150\Omega$ to $V^+/2$ , $V_{\text{ID}} = 200\text{mV}$               | 4.65              | 4.90       |  |                                |
|                    | Output Swing Low                      | $R_L = 2\text{k}\Omega$ to $V^+/2$ , $V_{\text{ID}} = -200\text{mV}$        |                   | 25         | 100                                    | mV                             |
|                    |                                       | $R_L = 150\Omega$ to $V^+/2$ , $V_{\text{ID}} = -200\text{mV}$              |                   | 100        | 150                                    |                                |
| $I_{\text{SC}}$    | Output Short Circuit Current          | Sourcing to $V^+/2$<br>$V_{\text{ID}} = 200\text{mV}$ <sup>(6)(7)</sup>     | 55<br><b>40</b>   | 115        |  | mA                             |
|                    |                                       | Sinking to $V^+/2$<br>$V_{\text{ID}} = -200\text{mV}$ <sup>(6)(7)</sup>     | 70<br><b>55</b>   | 140        |  |                                |
| $I_{\text{OUT}}$   | Output Current                        | $V_O = 0.5\text{V}$ from either supply                                      |                   | $\pm 70$   |  | mA                             |
| +PSRR              | Positive Power Supply Rejection Ratio | $V^+ = 4.0\text{V}$ to $6\text{V}$  | 79                | 90         |  | dB                             |
| $I_S$              | Supply Current (per channel)          | No Load   |                   | 2.70       | 4.25<br><b>5.00</b>                    | mA                             |

(3) Slew rate is the average of the rising and falling slew rates.

(4) Offset voltage average drift determined by dividing the change in  $V_{\text{OS}}$  at temperature extremes by the total temperature change.

(5) Positive current corresponds to current flowing into the device.

(6) Short circuit test is a momentary test. See [Note 7](#).

(7) Output short circuit duration is infinite for  $V_S < 6\text{V}$  at room temperature and below. For  $V_S > 6\text{V}$ , allowable short circuit duration is 1.5ms.

## ±5V Electrical Characteristics

Unless otherwise specified, all limits guaranteed for at  $T_J = 25^\circ\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = -5\text{V}$ ,  $V_{CM} = V_O = 0\text{V}$ ,  $V_{ID}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to ground. **Boldface** limits apply at the temperature extremes.

| Symbol       | Parameter                       | Conditions   | Min<br>(1)        | Typ<br>(2) | Max<br>(1)                             | Units                        |
|--------------|---------------------------------|--|-------------------|------------|--|------------------------------|
| BW           | -3dB BW                         | $A_V = +1$ , $V_{OUT} = 200\text{mV}_{PP}$   | 95                | 130        |  | MHz                          |
|              |                                 | $A_V = +2$ , $-1$ , $V_{OUT} = 200\text{mV}_{PP}$  |                   | 46         |  |                              |
| $BW_{0.1dB}$ | 0.1dB Gain Flatness             | $A_V = +2$ , $R_L = 150\Omega$ to $V^+/2$ ,<br>$R_f = 806\Omega$ , $V_{OUT} = 200\text{mV}_{PP}$ |                   | 12         |  | MHz                          |
| PBW          | Full Power Bandwidth            | $A_V = +1$ , $-1\text{dB}$ , $V_{OUT} = 2V_{PP}$   |                   | 24         |  | MHz                          |
| $e_n$        | Input-Referred Voltage Noise    | $f = 100\text{kHz}$  |                   | 17         |  | $\text{nV}/\sqrt{\text{Hz}}$ |
|              |                                 | $f = 1\text{kHz}$  |                   | 48         |  |                              |
| $i_n$        | Input-Referred Current Noise    | $f = 100\text{kHz}$  |                   | 0.90       |  | $\text{pA}/\sqrt{\text{Hz}}$ |
|              |                                 | $f = 1\text{kHz}$  |                   | 3.3        |  |                              |
| THD          | Total Harmonic Distortion       | $f = 5\text{MHz}$ , $V_O = 2V_{PP}$ , $A_V = +2$   |                   | -62        |  | dBc                          |
| DG           | Differential Gain               | NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$   |                   | 0.15       |  | %                            |
|              |                                 | $R_L = 1\text{k}\Omega$ to $V^+/2$   |                   | 0.01       |  |                              |
| DP           | Differential Phase              | NTSC, $A_V = +2$<br>$R_L = 150\Omega$ to $V^+/2$   |                   | 0.04       |  | deg                          |
|              |                                 | $R_L = 1\text{k}\Omega$ to $V^+/2$   |                   | 0.01       |  |                              |
| CT Rej.      | Cross-Talk Rejection            | $f = 5\text{MHz}$ , Receiver:<br>$R_f = R_g = 510\Omega$ , $A_V = +2$                            |                   | 47         |  | dB                           |
| $T_S$        | Settling Time                   | $V_O = 2V_{PP}$ , $\pm 0.1\%$ , $8\text{pF}$ Load,<br>$V_S = 5\text{V}$                          |                   | 68         |  | ns                           |
| SR           | Slew Rate <sup>(3)</sup>        | $A_V = -1$ , $V_I = 2V_{PP}$   | 100               | 135        |  | $\text{V}/\mu\text{s}$       |
| $V_{OS}$     | Input Offset Voltage            | For LMH6642 and LMH6644  |                   | $\pm 1$    | $\pm 5$<br><b><math>\pm 7</math></b>   | mV                           |
|              |                                 | For LMH6643  |                   | $\pm 1$    | $\pm 3.4$<br><b><math>\pm 7</math></b> |                              |
| TC $V_{OS}$  | Input Offset Average Drift      | See <sup>(4)</sup>   |                   | $\pm 5$    |  | $\mu\text{V}/^\circ\text{C}$ |
| $I_B$        | Input Bias Current              | See <sup>(5)</sup>   |                   | -1.60      | -2.60<br><b>-3.25</b>                  | $\mu\text{A}$                |
| $I_{OS}$     | Input Offset Current            |  |                   | 20         | 800<br><b>1000</b>                     | nA                           |
| $R_{IN}$     | Common Mode Input Resistance    |  |                   | 3          |  | M $\Omega$                   |
| $C_{IN}$     | Common Mode Input Capacitance   |  |                   | 2          |  | pF                           |
| CMVR         | Input Common-Mode Voltage Range | CMRR $\geq 50\text{dB}$  |                   | -5.5       | -5.2<br><b>-5.1</b>                    | V                            |
|              |                                 |  | 3.8<br><b>3.6</b> | 4.0        |  |                              |
| CMRR         | Common Mode Rejection Ratio     | $V_{CM}$ Stepped from $-5\text{V}$ to $3.5\text{V}$  | 74                | 95         |  | dB                           |
| $A_{VOL}$    | Large Signal Voltage Gain       | $V_O = -4.5\text{V}$ to $4.5\text{V}$ ,<br>$R_L = 2\text{k}\Omega$                               | 88<br><b>84</b>   | 96         |  | dB                           |
|              |                                 | $V_O = -4.0\text{V}$ to $4.0\text{V}$ ,<br>$R_L = 150\Omega$                                     | 78<br><b>74</b>   | 82         |  |                              |
| $V_O$        | Output Swing High               | $R_L = 2\text{k}\Omega$ , $V_{ID} = 200\text{mV}$  | 4.90              | 4.96       |  | V                            |
|              |                                 | $R_L = 150\Omega$ , $V_{ID} = 200\text{mV}$  | 4.65              | 4.80       |  |                              |
|              | Output Swing Low                | $R_L = 2\text{k}\Omega$ , $V_{ID} = -200\text{mV}$   |                   | -4.96      | -4.90                                  | V                            |
|              |                                 | $R_L = 150\Omega$ , $V_{ID} = -200\text{mV}$   |                   | -4.80      | -4.65                                  |                              |

(1) All limits are guaranteed by testing or statistical analysis.

(2) Typical values represent the most likely parametric norm.

(3) Slew rate is the average of the rising and falling slew rates.

(4) Offset voltage average drift determined by dividing the change in  $V_{OS}$  at temperature extremes by the total temperature change.

(5) Positive current corresponds to current flowing into the device.

## ±5V Electrical Characteristics (continued)


Unless otherwise specified, all limits guaranteed for at  $T_J = 25^\circ\text{C}$ ,  $V^+ = 5\text{V}$ ,  $V^- = -5\text{V}$ ,  $V_{CM} = V_O = 0\text{V}$ ,  $V_{ID}$  (input differential voltage) as noted (where applicable) and  $R_L = 2\text{k}\Omega$  to ground. **Boldface** limits apply at the temperature extremes.

| Symbol    | Parameter                    | Conditions  | Min<br>(1)      | Typ<br>(2) | Max<br>(1)          | Units |
|-----------|------------------------------|---|-----------------|------------|---------------------|-------|
| $I_{SC}$  | Output Short Circuit Current | Sourcing to Ground<br>$V_{ID} = 200\text{mV}^{(6)(7)}$                      | 60<br><b>35</b> | 115        |                     | mA    |
|           |                              | Sinking to Ground<br>$V_{ID} = -200\text{mV}^{(6)(7)}$                      | 85<br><b>65</b> | 145        |                     |       |
| $I_{OUT}$ | Output Current               | $V_O = 0.5\text{V}$ from either supply                                      | $\pm 75$        |            |                     | mA    |
| PSRR      | Power Supply Rejection Ratio | $(V^+, V^-) = (4.5\text{V}, -4.5\text{V})$ to $(5.5\text{V}, -5.5\text{V})$ | 78              | 90         |                     | dB    |
| $I_S$     | Supply Current (per channel) | No Load   |                 | 2.70       | 4.50<br><b>5.50</b> | mA    |


(6) Short circuit test is a momentary test. See [Note 7](#).

(7) Output short circuit duration is infinite for  $V_S < 6\text{V}$  at room temperature and below. For  $V_S > 6\text{V}$ , allowable short circuit duration is 1.5ms.


## Connection Diagram




**Figure 3. 5-Pin SOT-23 (LMH6642)  
Top View  
Package Number DBV0005A**



**Figure 4. 8-Pin SOIC (LMH6642)  
Top View  
Package Number D0008A**



**Figure 5. SOIC and VSSOP 8-Pin  
(LMH6643)  
Top View  
Package Number DGK0008A**




**Figure 6. 14-Pin SOIC and 14-Pin TSSOP  
(LMH6644)  
Top View  
Package Numbers D0014A, PW0014A**

## Typical Performance Characteristics


At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5\text{V}$ ,  $V^- = -5\text{V}$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.

**Closed Loop Frequency Response for Various Supplies**




**Figure 7.**

**Closed Loop Gain vs. Frequency for Various Gain**




**Figure 8.**

**Closed Loop Gain vs. Frequency for Various Gain**




**Figure 9.**

**Closed Loop Frequency Response for Various Temperature**




**Figure 10.**

**Closed Loop Gain  
vs.  
Frequency for Various Supplies**



**Figure 11.**

**Closed Loop Frequency Response for Various Temperature**



**Figure 12.**



## Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5\text{V}$ ,  $V^- = -5\text{V}$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 13.

## Closed Loop Small Signal Frequency Response for Various Supplies




Figure 14.

## Closed Loop Frequency Response for Various Supplies




Figure 15.

## ±0.1dB Gain Flatness for Various Supplies




Figure 16.

## $V_{OUT}$ (Vpp) for THD < 0.5%




Figure 17.

## $V_{OUT}$ (Vpp) for THD < 0.5%




Figure 18.

### Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5$ ,  $V^- = -5$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 19.




Figure 20.




Figure 21.




Figure 22.




Figure 23.




Figure 24.

## Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5$ ,  $V^- = -5$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 25.




Figure 26.

### Settling Time vs. Input Step Amplitude (Output Slew and Settle Time)




Figure 27.




Figure 28.




Figure 29.




Figure 30.

### Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5\text{V}$ ,  $V^- = -5\text{V}$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 31.




Figure 32.




Figure 33.




Figure 34.




Figure 35.





Figure 36.

## Typical Performance Characteristics (continued)


At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5\text{V}$ ,  $V^- = -5\text{V}$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.

**Closed Loop Output Impedance vs. Frequency  $A_V = +1$**




**Figure 37.**

**PSRR vs. Frequency**




**Figure 38.**

**CMRR vs. Frequency**




**Figure 39.**

**Crosstalk Rejection vs. Frequency (Output to Output)**




**Figure 40.**

**$V_{OS}$  vs.  $V_{OUT}$  (Typical Unit)**



**Figure 41.**

**$V_{OS}$  vs.  $V_{CM}$  (Typical Unit)**



**Figure 42.**

### Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5$ ,  $V^- = -5$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 43.




Figure 44.




Figure 45.




Figure 46.




Figure 47.




Figure 48.

## Typical Performance Characteristics (continued)

At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5\text{V}$ ,  $V^- = -5\text{V}$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.




Figure 49.




Figure 50.




Figure 51.




Figure 52.




Figure 53.





Figure 54.

### Typical Performance Characteristics (continued)


At  $T_J = 25^\circ\text{C}$ ,  $V^+ = +5$ ,  $V^- = -5$ ,  $R_F = R_L = 2\text{k}\Omega$ . Unless otherwise specified.

**Small Signal Step Response**




**Figure 55.**

**Small Signal Step Response**




**Figure 56.**

**Large Signal Step Response**




**Figure 57.**

**Large Signal Step Response**



**Figure 58.**

**Large Signal Step Response**



**Figure 59.**



## APPLICATION INFORMATION

### CIRCUIT DESCRIPTION

The LMH664X family is based on proprietary VIP10 dielectrically isolated bipolar process.

This device family architecture features the following:

- Complimentary bipolar devices with exceptionally high  $f_t$  (~8GHz) even under low supply voltage (2.7V) and low bias current.
- A class A-B “turn-around” stage with improved noise, offset, and reduced power dissipation compared to similar speed devices (patent pending).
- Common Emitter push-push output stage capable of 75mA output current (at 0.5V from the supply rails) while consuming only 2.7mA of total supply current per channel. This architecture allows output to reach within milli-volts of either supply rail.
- Consistent performance over the entire operating supply voltage range with little variation for the most important specifications (e.g. BW, SR,  $I_{OUT}$ , etc.)
- Significant power saving (~40%) compared to competitive devices on the market with similar performance.

### Application Hints


This Op Amp family is a drop-in replacement for the AD805X family of high speed Op Amps in most applications. In addition, the LMH664X will typically save about 40% on power dissipation, due to lower supply current, when compared to competition. All AD805X family's guaranteed parameters are included in the list of LMH664X guaranteed specifications in order to ensure equal or better level of performance. However, as in most high performance parts, due to subtleties of applications, it is strongly recommended that the performance of the part to be evaluated is tested under actual operating conditions to ensure full compliance to all specifications.

With 3V supplies and a common mode input voltage range that extends 0.5V below  $V^-$ , the LMH664X find applications in low voltage/low power applications. Even with 3V supplies, the -3dB BW (@  $A_V = +1$ ) is typically 115MHz with a tested limit of 80MHz. Production testing guarantees that process variations will not compromise speed. High frequency response is exceptionally stable confining the typical -3dB BW over the industrial temperature range to  $\pm 2.5\%$ .

As can be seen from the typical performance plots, the LMH664X output current capability (~75mA) is enhanced compared to AD805X. This enhancement, increases the output load range, adding to the LMH664X's versatility.

Because of the LMH664X's high output current capability attention should be given to device junction temperature in order not to exceed the Absolute Maximum Rating.

This device family was designed to avoid output phase reversal. With input overdrive, the output is kept near supply rail (or as closed to it as mandated by the closed loop gain setting and the input voltage). See [Figure 60](#):



**Figure 60. Input and Output Shown with CMVR Exceeded**

However, if the input voltage range of -0.5V to 1V from  $V^+$  is exceeded by more than a diode drop, the internal ESD protection diodes will start to conduct. The current in the diodes should be kept at or below 10mA.

Output overdrive recovery time is less than 100ns as can be seen from [Figure 61](#) plot:




Figure 61. Overload Recovery Waveform

## INPUT AND OUTPUT TOPOLOGY

All input / output pins are protected against excessive voltages by ESD diodes connected to  $V^+$  and  $V^-$  rails (see Figure 62). These diodes start conducting when the input / output pin voltage approaches  $1V_{be}$  beyond  $V^+$  or  $V^-$  to protect against over voltage. These diodes are normally reverse biased. Further protection of the inputs is provided by the two resistors ( $R$  in Figure 62), in conjunction with the string of anti-parallel diodes connected between both bases of the input stage. The combination of these resistors and diodes reduces excessive differential input voltages approaching  $2V_{be}$ . The most common situation when this occurs is when the device is used as a comparator (or with little or no feedback) and the device inputs no longer follow each other. In such a case, the diodes may conduct. As a consequence, input current increases and the differential input voltage is clamped. It is important to make sure that the subsequent current flow through the device input pins does not violate the Absolute Maximum Ratings of the device. To limit the current through this protection circuit, extra series resistors can be placed. Together with the built-in series resistors of several hundred ohms, these external resistors can limit the input current to a safe number (i.e.  $< 10\text{mA}$ ). Be aware that these input series resistors may impact the switching speed of the device and could slow down the device.




Figure 62. Input Equivalent Circuit

## SINGLE SUPPLY, LOW POWER PHOTODIODE AMPLIFIER

The circuit shown in Figure 63 is used to amplify the current from a photodiode into a voltage output. In this circuit, the emphasis is on achieving high bandwidth and the transimpedance gain setting is kept relatively low. Because of its high slew rate limit and high speed, the LMH64X family lends itself well to such an application.

This circuit achieves approximately  $1\text{V}/\text{mA}$  of transimpedance gain and capable of handling up to  $1\text{mA}_{pp}$  from the photodiode. Q1, in a common base configuration, isolates the high capacitance of the photodiode ( $C_d$ ) from the Op Amp input in order to maximize speed. Input is AC coupled through C1 to ease biasing and allow single supply operation. With 5V single supply, the device input/output is shifted to near half supply using a voltage divider from  $V_{CC}$ . Note that Q1 collector does not have any voltage swing and the Miller effect is minimized. D1, tied to Q1 base, is for temperature compensation of Q1's bias point. Q1 collector current was set to be large enough to handle the peak-to-peak photodiode excitation and not too large to shift the U1 output too far from mid-supply.

No matter how low an  $R_f$  is selected, there is a need for  $C_f$  in order to stabilize the circuit. The reason for this is that the Op Amp input capacitance and Q1 equivalent collector capacitance together ( $C_{IN}$ ) will cause additional phase shift to the signal fed back to the inverting node.  $C_f$  will function as a zero in the feedback path counteracting the effect of the  $C_{IN}$  and acting to stabilize the circuit. By proper selection of  $C_f$  such that the Op Amp open loop gain is equal to the inverse of the feedback factor at that frequency, the response is optimized with a theoretical 45° phase margin.

$$C_F = \sim \text{SQRT} \left[ (C_{IN}) / (2\pi \cdot \text{GBWP} \cdot R_F) \right] \quad (1)$$

where GBWP is the Gain Bandwidth Product of the Op Amp

Optimized as such, the I-V converter will have a theoretical pole,  $f_p$ , at:

$$f_P = \text{SQRT} \left[ \text{GBWP} / (2\pi R_F \cdot C_{IN}) \right] \quad (2)$$

With Op Amp input capacitance of 3pF and an estimate for Q1 output capacitance of about 3pF as well,  $C_{IN} = 6\text{pF}$ . From the typical performance plots, LMH6642/6643 family GBWP is approximately 57MHz. Therefore, with  $R_f = 1\text{k}$ , from Equation 1 and Equation 2 above.

$C_f = \sim 4.1\text{pF}$  and  $f_p = 39\text{MHz}$




Figure 63. Single Supply Photodiode I-V Converter

For this example, optimum  $C_f$  was empirically determined to be around 5pF. This time domain response is shown in Figure 64 below showing about 9ns rise/fall times, corresponding to about 39MHz for  $f_p$ . The overall supply current from the +5V supply is around 5mA with no load.




Figure 64. Converter Step Response (1V<sub>pp</sub>, 20 ns/DIV)

## PRINTED CIRCUIT BOARD LAYOUT AND COMPONENT VALUES SECTION

Generally, a good high frequency layout will keep power supply and ground traces away from the inverting input and output pins. Parasitic capacitances on these nodes to ground will cause frequency response peaking and possible circuit oscillations (see Application Note OA-15 for more information). Texas Instruments suggests the following evaluation boards as a guide for high frequency layout and as an aid in device testing and characterization:

| Device    | Package      | Evaluation Board PN |
|-----------|--------------|---------------------|
| LMH6642MF | 5-Pin SOT-23 | LMH730216           |
| LMH6642MA | 8-Pin SOIC   | LMH730227           |
| LMH6643MA | 8-Pin SOIC   | LMH730036           |
| LMH6643MM | 8-Pin VSSOP  | LMH730123           |
| LMH6644MA | 14-Pin SOIC  | LMH730231           |
| LMH6644MT | 14-Pin TSSOP | LMH730131           |

Another important parameter in working with high speed/high performance amplifiers, is the component values selection. Choosing external resistors that are large in value will effect the closed loop behavior of the stage because of the interaction of these resistors with parasitic capacitances. These capacitors could be inherent to the device or a by-product of the board layout and component placement. Either way, keeping the resistor values lower, will diminish this interaction to a large extent. On the other hand, choosing very low value resistors could load down nodes and will contribute to higher overall power dissipation.

## REVISION HISTORY

| Changes from Revision O (March 2013) to Revision P         | Page               |
|--|--------------------|
| • Changed layout of National Data Sheet to TI format ..... | <a href="#">20</a> |

**PACKAGING INFORMATION**

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package Qty | Eco Plan<br>(2)            | Lead/Ball Finish | MSL Peak Temp<br>(3) | Op Temp (°C) | Top-Side Markings<br>(4) | Samples                 |
|------------------|---------------|--------------|--------------------|------|-------------|----------------------------|------------------|----------------------|--------------|--------------------------|-------------------------|
| LMH6642MA/NOPB   | ACTIVE        | SOIC         | D                  | 8    | 95          | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>42MA            | <a href="#">Samples</a> |
| LMH6642MAX/NOPB  | ACTIVE        | SOIC         | D                  | 8    | 2500        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>42MA            | <a href="#">Samples</a> |
| LMH6642MF        | ACTIVE        | SOT-23       | DBV                | 5    | 1000        | TBD                        | Call TI          | Call TI              | -40 to 85    | A64A                     | <a href="#">Samples</a> |
| LMH6642MF/NOPB   | ACTIVE        | SOT-23       | DBV                | 5    | 1000        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | A64A                     | <a href="#">Samples</a> |
| LMH6642MFX       | ACTIVE        | SOT-23       | DBV                | 5    | 3000        | TBD                        | Call TI          | Call TI              | -40 to 85    | A64A                     | <a href="#">Samples</a> |
| LMH6642MFX/NOPB  | ACTIVE        | SOT-23       | DBV                | 5    | 3000        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | A64A                     | <a href="#">Samples</a> |
| LMH6643MA        | ACTIVE        | SOIC         | D                  | 8    | 95          | TBD                        | Call TI          | Call TI              | -40 to 85    | LMH66<br>43MA            | <a href="#">Samples</a> |
| LMH6643MA/NOPB   | ACTIVE        | SOIC         | D                  | 8    | 95          | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>43MA            | <a href="#">Samples</a> |
| LMH6643MAX       | ACTIVE        | SOIC         | D                  | 8    | 2500        | TBD                        | Call TI          | Call TI              | -40 to 85    | LMH66<br>43MA            | <a href="#">Samples</a> |
| LMH6643MAX/NOPB  | ACTIVE        | SOIC         | D                  | 8    | 2500        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>43MA            | <a href="#">Samples</a> |
| LMH6643MM        | ACTIVE        | VSSOP        | DGK                | 8    | 1000        | TBD                        | Call TI          | Call TI              | -40 to 85    | A65A                     | <a href="#">Samples</a> |
| LMH6643MM/NOPB   | ACTIVE        | VSSOP        | DGK                | 8    | 1000        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | A65A                     | <a href="#">Samples</a> |
| LMH6643MMX       | ACTIVE        | VSSOP        | DGK                | 8    | 3500        | TBD                        | Call TI          | Call TI              | -40 to 85    | A65A                     | <a href="#">Samples</a> |
| LMH6643MMX/NOPB  | ACTIVE        | VSSOP        | DGK                | 8    | 3500        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | A65A                     | <a href="#">Samples</a> |
| LMH6644MA/NOPB   | ACTIVE        | SOIC         | D                  | 14   | 55          | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH6644MA                | <a href="#">Samples</a> |
| LMH6644MAX/NOPB  | ACTIVE        | SOIC         | D                  | 14   | 2500        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH6644MA                | <a href="#">Samples</a> |
| LMH6644MT        | ACTIVE        | TSSOP        | PW                 | 14   | 94          | TBD                        | Call TI          | Call TI              | -40 to 85    | LMH66<br>44MT            | <a href="#">Samples</a> |
| LMH6644MT/NOPB   | ACTIVE        | TSSOP        | PW                 | 14   | 94          | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>44MT            | <a href="#">Samples</a> |

| Orderable Device | Status<br>(1) | Package Type | Package<br>Drawing | Pins | Package Qty | Eco Plan<br>(2)            | Lead/Ball Finish | MSL Peak Temp<br>(3) | Op Temp (°C) | Top-Side Markings<br>(4) | Samples                 |
|------------------|---------------|--------------|--------------------|------|-------------|----------------------------|------------------|----------------------|--------------|--------------------------|-------------------------|
| LMH6644MTX       | ACTIVE        | TSSOP        | PW                 | 14   | 2500        | TBD                        | Call TI          | Call TI              | -40 to 85    | LMH66<br>44MT            | <a href="#">Samples</a> |
| LMH6644MTX/NOPB  | ACTIVE        | TSSOP        | PW                 | 14   | 2500        | Green (RoHS<br>& no Sb/Br) | CU SN            | Level-1-260C-UNLIM   | -40 to 85    | LMH66<br>44MT            | <a href="#">Samples</a> |

(1) The marketing status values are defined as follows:

**ACTIVE:** Product device recommended for new designs.

**LIFEBUY:** TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

**NRND:** Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

**PREVIEW:** Device has been announced but is not in production. Samples may or may not be available.

**OBSOLETE:** TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check <http://www.ti.com/productcontent> for the latest availability information and additional product content details.

**TBD:** The Pb-Free/Green conversion plan has not been defined.

**Pb-Free (RoHS):** TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

**Pb-Free (RoHS Exempt):** This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

**Green (RoHS & no Sb/Br):** TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) Only one of markings shown within the brackets will appear on the physical device.

**Important Information and Disclaimer:** The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

**TAPE AND REEL INFORMATION**


\*All dimensions are nominal

| Device          | Package Type | Package Drawing | Pins | SPQ  | Reel Diameter (mm) | Reel Width W1 (mm) | A0 (mm) | B0 (mm) | K0 (mm) | P1 (mm) | W (mm) | Pin1 Quadrant |
|-----------------|--------------|-----------------|------|------|--------------------|--------------------|---------|---------|---------|---------|--------|---------------|
| LMH6642MAX/NOPB | SOIC         | D               | 8    | 2500 | 330.0              | 12.4               | 6.5     | 5.4     | 2.0     | 8.0     | 12.0   | Q1            |
| LMH6642MF       | SOT-23       | DBV             | 5    | 1000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMH6642MF/NOPB  | SOT-23       | DBV             | 5    | 1000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMH6642MFX      | SOT-23       | DBV             | 5    | 3000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMH6642MFX/NOPB | SOT-23       | DBV             | 5    | 3000 | 178.0              | 8.4                | 3.2     | 3.2     | 1.4     | 4.0     | 8.0    | Q3            |
| LMH6643MAX      | SOIC         | D               | 8    | 2500 | 330.0              | 12.4               | 6.5     | 5.4     | 2.0     | 8.0     | 12.0   | Q1            |
| LMH6643MAX/NOPB | SOIC         | D               | 8    | 2500 | 330.0              | 12.4               | 6.5     | 5.4     | 2.0     | 8.0     | 12.0   | Q1            |
| LMH6643MM       | VSSOP        | DGK             | 8    | 1000 | 178.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMH6643MM/NOPB  | VSSOP        | DGK             | 8    | 1000 | 178.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMH6643MMX      | VSSOP        | DGK             | 8    | 3500 | 330.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMH6643MMX/NOPB | VSSOP        | DGK             | 8    | 3500 | 330.0              | 12.4               | 5.3     | 3.4     | 1.4     | 8.0     | 12.0   | Q1            |
| LMH6644MAX/NOPB | SOIC         | D               | 14   | 2500 | 330.0              | 16.4               | 6.5     | 9.35    | 2.3     | 8.0     | 16.0   | Q1            |
| LMH6644MTX      | TSSOP        | PW              | 14   | 2500 | 330.0              | 12.4               | 6.95    | 8.3     | 1.6     | 8.0     | 12.0   | Q1            |
| LMH6644MTX/NOPB | TSSOP        | PW              | 14   | 2500 | 330.0              | 12.4               | 6.95    | 8.3     | 1.6     | 8.0     | 12.0   | Q1            |



## TAPE AND REEL BOX DIMENSIONS




\*All dimensions are nominal

| Device          | Package Type | Package Drawing | Pins | SPQ  | Length (mm) | Width (mm) | Height (mm) |
|-----------------|--------------|-----------------|------|------|-------------|------------|-------------|
| LMH6642MAX/NOPB | SOIC         | D               | 8    | 2500 | 367.0       | 367.0      | 35.0        |
| LMH6642MF       | SOT-23       | DBV             | 5    | 1000 | 210.0       | 185.0      | 35.0        |
| LMH6642MF/NOPB  | SOT-23       | DBV             | 5    | 1000 | 210.0       | 185.0      | 35.0        |
| LMH6642MFX      | SOT-23       | DBV             | 5    | 3000 | 210.0       | 185.0      | 35.0        |
| LMH6642MFX/NOPB | SOT-23       | DBV             | 5    | 3000 | 210.0       | 185.0      | 35.0        |
| LMH6643MAX      | SOIC         | D               | 8    | 2500 | 367.0       | 367.0      | 35.0        |
| LMH6643MAX/NOPB | SOIC         | D               | 8    | 2500 | 367.0       | 367.0      | 35.0        |
| LMH6643MM       | VSSOP        | DGK             | 8    | 1000 | 210.0       | 185.0      | 35.0        |
| LMH6643MM/NOPB  | VSSOP        | DGK             | 8    | 1000 | 210.0       | 185.0      | 35.0        |
| LMH6643MMX      | VSSOP        | DGK             | 8    | 3500 | 367.0       | 367.0      | 35.0        |
| LMH6643MMX/NOPB | VSSOP        | DGK             | 8    | 3500 | 367.0       | 367.0      | 35.0        |
| LMH6644MAX/NOPB | SOIC         | D               | 14   | 2500 | 349.0       | 337.0      | 45.0        |
| LMH6644MTX      | TSSOP        | PW              | 14   | 2500 | 367.0       | 367.0      | 35.0        |
| LMH6644MTX/NOPB | TSSOP        | PW              | 14   | 2500 | 367.0       | 367.0      | 35.0        |

## DBV (R-PDSO-G5)

## PLASTIC SMALL-OUTLINE PACKAGE



4073253-4/K 03/2006

- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Body dimensions do not include mold flash or protrusion. Mold flash and protrusion shall not exceed 0.15 per side.
  - D. Falls within JEDEC MO-178 Variation AA.

DBV (R-PDSO-G5)

PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in millimeters.
  - B. This drawing is subject to change without notice.
  - C. Customers should place a note on the circuit board fabrication drawing not to alter the center solder mask defined pad.
  - D. Publication IPC-7351 is recommended for alternate designs.
  - E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Example stencil design based on a 50% volumetric metal load solder paste. Refer to IPC-7525 for other stencil recommendations.

## DGK (S-PDSO-G8)

## PLASTIC SMALL-OUTLINE PACKAGE



## NOTES:

- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 per end.
- D. Body width does not include interlead flash. Interlead flash shall not exceed 0.50 per side.
- E. Falls within JEDEC MO-187 variation AA, except interlead flash.

D (R-PDSO-G14)

PLASTIC SMALL OUTLINE



NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
- D. Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
- E. Reference JEDEC MS-012 variation AB.

PW (R-PDSO-G14)

PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M-1994.
  - B. This drawing is subject to change without notice.
  - C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
  - D. Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
  - E. Falls within JEDEC MO-153

D (R-PDSO-G8)

PLASTIC SMALL OUTLINE



- NOTES:
- A. All linear dimensions are in inches (millimeters).
  - B. This drawing is subject to change without notice.
  - $\triangle C$  Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
  - $\triangle D$  Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
  - E. Reference JEDEC MS-012 variation AA.

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

|                              |  |
|------------------------------|--|
| Audio                        | <a href="http://www.ti.com/audio">www.ti.com/audio</a>                               |
| Amplifiers                   | <a href="http://amplifier.ti.com">amplifier.ti.com</a>                               |
| Data Converters              | <a href="http://dataconverter.ti.com">dataconverter.ti.com</a>                       |
| DLP® Products                | <a href="http://www.dlp.com">www.dlp.com</a>   |
| DSP                          | <a href="http://dsp.ti.com">dsp.ti.com</a>   |
| Clocks and Timers            | <a href="http://www.ti.com/clocks">www.ti.com/clocks</a>                             |
| Interface                    | <a href="http://interface.ti.com">interface.ti.com</a>                               |
| Logic                        | <a href="http://logic.ti.com">logic.ti.com</a>                                       |
| Power Mgmt                   | <a href="http://power.ti.com">power.ti.com</a>                                       |
| Microcontrollers             | <a href="http://microcontroller.ti.com">microcontroller.ti.com</a>                   |
| RFID                         | <a href="http://www.ti-rfid.com">www.ti-rfid.com</a>                                 |
| OMAP Applications Processors | <a href="http://www.ti.com/omap">www.ti.com/omap</a>                                 |
| Wireless Connectivity        | <a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a> |

### Applications

|                               |  |
|-------------------------------|--|
| Automotive and Transportation | <a href="http://www.ti.com/automotive">www.ti.com/automotive</a>                         |
| Communications and Telecom    | <a href="http://www.ti.com/communications">www.ti.com/communications</a>                 |
| Computers and Peripherals     | <a href="http://www.ti.com/computers">www.ti.com/computers</a>                           |
| Consumer Electronics          | <a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>                   |
| Energy and Lighting           | <a href="http://www.ti.com/energy">www.ti.com/energy</a>                                 |
| Industrial                    | <a href="http://www.ti.com/industrial">www.ti.com/industrial</a>                         |
| Medical                       | <a href="http://www.ti.com/medical">www.ti.com/medical</a>                               |
| Security                      | <a href="http://www.ti.com/security">www.ti.com/security</a>                             |
| Space, Avionics and Defense   | <a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a> |
| Video and Imaging             | <a href="http://www.ti.com/video">www.ti.com/video</a>                                   |

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)





Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.