

# PCA21125

## SPI-bus Real-Time Clock and calendar

Rev. 2 — 25 November 2014

Product data sheet

### 1. General description

---

The PCA21125 is a CMOS<sup>1</sup> Real-Time Clock (RTC) and calendar optimized for low-power consumption and an operating temperature up to 125 °C. Data is transferred via a Serial Peripheral Interface (SPI-bus) with a maximum data rate of 6.0 Mbit/s. Alarm and timer functions are also available with the possibility to generate a wake-up signal on the interrupt pin.

For a selection of NXP Real-Time Clocks, see [Table 46 on page 41](#)

### 2. Features and benefits

---

- AEC Q100 compliant for automotive applications.
- Provides year, month, day, weekday, hours, minutes, and seconds based on 32.768 kHz quartz crystal
- Resolution: seconds to years
- Clock operating voltage: 1.3 V to 5.5 V
- Low supply current: typical 0.8  $\mu$ A at  $T_{amb} = 25\text{ °C}$
- 4-line SPI-bus with separate, but combinable data input and output
- Serial interface at  $V_{DD} = 1.6\text{ V to }5.5\text{ V}$
- 1 second or 1 minute interrupt output
- Freely programmable timer with interrupt capability
- Freely programmable alarm function with interrupt capability
- Integrated oscillator capacitor
- Internal Power-On Reset (POR)
- Open-drain interrupt pin

### 3. Applications

---

- Automotive time keeping
- Metering

---

1. The definition of the abbreviations and acronyms used in this data sheet can be found in [Section 21](#).



## 4. Ordering information

Table 1. Ordering information

Type number	Package		
	Name	Description	Version
PCA21125T	TSSOP14	plastic thin shrink small outline package; 14 leads; body width 4.4 mm	SOT402-1

### 4.1 Ordering options

Table 2. Ordering options

Product type number	Orderable part number	Sales item (12NC)	Delivery form	IC revision
PCA21125T/Q900/1	PCA21125T/Q900/1,1	935290408118	tape and reel, 13 inch	1

## 5. Marking

Table 3. Marking codes

Type number	Marking code
PCA21125T/Q900/1	PC21125

6. Block diagram





Fig 1. Block diagram of PCA21125

## 7. Pinning information

### 7.1 Pinning



### 7.2 Pin description

**Table 4. Pin description**

*Input or input/output pins must always be at a defined level ( $V_{SS}$  or  $V_{DD}$ ) unless otherwise specified.*

Symbol	Pin	Description
OSCI	1	oscillator input
OSCO	2	oscillator output
n.c.	3, 4	not connected; do not connect and do not use as feed through; connect to $V_{DD}$ if floating pins are not allowed
$\overline{\text{INT}}$	5	interrupt output (open-drain; active LOW)
CE	6	chip enable input (active HIGH) with 200 k $\Omega$ pull-down resistor
$V_{SS}$	7	ground supply voltage
SDO	8	serial data output, push-pull
SDI	9	serial data input; might float when CE inactive
SCL	10	serial clock input; might float when CE inactive
n.c.	11, 12	not connected; do not connect and do not use as feed through; connect to $V_{DD}$ if floating pins are not allowed
CLKOUT	13	clock output (open-drain)
$V_{DD}$	14	supply voltage

## 8. Functional description

The PCA21125 contains 16 8-bit registers with an auto-incrementing address register, an on-chip 32.768 kHz oscillator with one integrated capacitor, a frequency divider which provides the source clock for the RTC, a programmable clock output, and a 6 MHz SPI-bus.

All 16 registers are designed as addressable 8-bit parallel registers although not all bits are implemented:

- The first two registers at addresses 00h and 01h (Control\_1 and Control\_2) are used as control and status registers.
- Registers at addresses 02h to 08h (Seconds, Minutes, Hours, Days, Weekdays, Months, Years) are used as counters for the clock function. Seconds, minutes, hours, days, months, and years are all coded in Binary Coded Decimal (BCD) format. When one of the RTC registers is written or read, the contents of all counters are frozen. Therefore, faulty writing or reading of time and date during a carry condition is prevented.
- Registers at addresses 09h to 0Ch (Minute\_alarm, Hour\_alarm, Day\_alarm, and Weekday\_alarm) define the alarm condition.
- The register at address 0Dh (CLKOUT\_control) defines the clock output mode.
- Registers at addresses 0Eh and 0Fh (Timer\_control and Countdown\_timer) are used for the countdown timer function. The countdown timer has four selectable source clocks allowing for countdown periods in the range from less than 1 ms to more than 4 hours (see [Table 30](#)). There are also two pre-defined timers which can be used to generate an interrupt once per second or once per minute. These are defined in register Control\_2 (01h).

## 8.1 Register overview

The time, date, and alarm registers are encoded in BCD to simplify application use. Other registers are either bit-wise or standard binary.

**Table 5. Register overview**

Bits labeled - are not implemented and return logic 0 when read. Bit positions labeled N should always be written with logic 0. After reset, all registers are set according to [Table 38 on page 26](#).

Address	Register name	Bit							
		7	6	5	4	3	2	1	0
Control and status registers									
00h	Control_1	EXT_TEST	N	STOP	N	POR_OVRD	12_24	N	N
01h	Control_2	MI	SI	MSF	TI_TP	AF	TF	AIE	TIE
Time and date registers									
02h	Seconds	RF	SECONDS (0 to 59)						
03h	Minutes	-	MINUTES (0 to 59)						
04h	Hours	-	-	AMPM	HOURS (1 to 12) in 12-hour mode				
		-	-	HOURS (0 to 23) in 24-hour mode					
05h	Days	-	-	DAYS (1 to 31)					
06h	Weekdays	-	-	-	-	-	WEEKDAYS (0 to 6)		
07h	Months	-	-	-	MONTHS (1 to 12)				
08h	Years	YEARS (0 to 99)							
Alarm registers									
09h	Minute_alarm	AEN_M	MINUTE_ALARM (0 to 59)						
0Ah	Hour_alarm	AEN_H	-	AMPM	HOUR_ALARM (1 to 12) in 12-hour mode				
			-	HOUR_ALARM (0 to 23) in 24-hour mode					
0Bh	Day_alarm	AEN_D	-	DAY_ALARM (1 to 31)					
0Ch	Weekday_alarm	AEN_W	-	-	-	-	WEEKDAY_ALARM (0 to 6)		
CLKOUT control register									
0Dh	CLKOUT_control	-	-	-	-	-	COF[2:0]		
Timer registers									
0Eh	Timer_control	TE	-	-	-	-	-	CTD[1:0]	
0Fh	Countdown_timer	T[7:0]							

## 8.2 Control and status registers

### 8.2.1 Register Control\_1

**Table 6.** Control\_1 - control and status register 1 (address 00h) bit description

Bit	Symbol	Value	Description	Reference
7	EXT_TEST	0 <sup>[1]</sup>	normal mode	<a href="#">Section 8.8</a>
		1	external clock test mode	
6	N	0	unused	-
5	STOP	0 <sup>[1]</sup>	RTC source clock runs	<a href="#">Section 8.9</a>
		1	RTC clock is stopped <sup>[2]</sup>	
4	N	0	unused	-
3	POR_OVRD	0	Power-On Reset Override facility is disabled; <b>Remark:</b> set logic 0 for normal operation	<a href="#">Section 8.10.1</a>
		1 <sup>[1]</sup>	Power-On Reset Override sequence reception enabled	
2	12_24	0 <sup>[1]</sup>	24-hour mode selected	<a href="#">Table 11</a> and <a href="#">Table 19</a>
		1	12-hour mode selected	
1 to 0	N	00	unused	-

[1] Default value.

[2] CLKOUT at 32.768 kHz, 16.384 kHz or 8.192 kHz is still available; divider chain flip-flops are asynchronously set logic 0.

### 8.2.2 Register Control\_2

**Table 7.** Control\_2 - control and status register 2 (address 01h) bit description

Bit	Symbol	Value	Description	Reference
7	MI	0 <sup>[1]</sup>	minute interrupt disabled	<a href="#">Section 8.6.1</a>
		1	minute interrupt enabled	
6	SI	0 <sup>[1]</sup>	second interrupt disabled	<a href="#">Section 8.6.1</a>
		1	second interrupt enabled	
5	MSF	0 <sup>[1]</sup>	no minute or second interrupt generated	<a href="#">Section 8.6.1</a>
		1	flag set when minute or second interrupt generated	
4	TI_TP	0 <sup>[1]</sup>	interrupt pin follows TF and MSF (see <a href="#">Figure 9</a> )	<a href="#">Section 8.6</a> et seq. and <a href="#">Section 8.7</a> et seq.
		1	interrupt pin generates a pulse	
3	AF	0 <sup>[1]</sup>	no alarm interrupt generated	<a href="#">Section 8.4.5</a>
		1	flag set when alarm triggered; <b>Remark:</b> flag must be cleared to clear interrupt	
2	TF	0 <sup>[1]</sup>	no countdown timer interrupt generated	<a href="#">Section 8.6</a> et seq. and <a href="#">Section 8.7</a> et seq.
		1	flag set when countdown timer interrupt generated	
1	AIE	0 <sup>[1]</sup>	no interrupt generated from alarm flag	<a href="#">Section 8.7.3</a>
		1	interrupt generated when alarm flag set	
0	TIE	0 <sup>[1]</sup>	no interrupt generated from countdown timer flag	<a href="#">Section 8.7</a>
		1	interrupt generated when countdown timer flag set	

[1] Default value.

### 8.3 Time and date registers

Most of these registers are coded in the Binary Coded Decimal (BCD) format. BCD is used to simplify application use. An example is shown for register Seconds in [Table 9](#).

Loading these registers with values outside of the given range results in unpredictable time and date generation (see [Figure 3 "Data flow of the time function"](#)).

#### 8.3.1 Register Seconds

**Table 8. Seconds - seconds and clock integrity status register (address 02h) bit description**

Bit	Symbol	Value	Description
7	RF	0	clock integrity is guaranteed
		1 <sup>[1]</sup>	clock integrity is not guaranteed; chip reset has occurred since flag was last cleared
6 to 4	SECONDS	0 to 5	ten's place
3 to 0		0 to 9	unit place

[1] Start-up value.

**Table 9. Seconds coded in BCD format**

Seconds value in decimal	Upper-digit (ten's place)			Digit (unit place)			
	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
00	0	0	0	0	0	0	0
01	0	0	0	0	0	0	1
02	0	0	0	0	0	1	0
:	:	:	:	:	:	:	:
09	0	0	0	1	0	0	1
10	0	0	1	0	0	0	0
:	:	:	:	:	:	:	:
58	1	0	1	1	0	0	0
59	1	0	1	1	0	0	1

#### 8.3.2 Register Minutes

**Table 10. Minutes - minutes register (address 03h) bit description**

Bit	Symbol	Value	Description
7	-	0	unused
6 to 4	MINUTES	0 to 5	ten's place
3 to 0		0 to 9	unit place



### 8.3.3 Register Hours

Table 11. Hours - hours register (address 04h) bit description

Bit	Symbol	Value	Description
7 to 6	-	00	unused
12-hour mode <sup>[1]</sup>			
5	AMPM	0	indicates AM
		1	indicates PM
4	HOURS	0 to 1	ten's place
3 to 0		0 to 9	unit place
24-hour mode <sup>[1]</sup>			
5 to 4	HOURS	0 to 2	ten's place
3 to 0		0 to 9	unit place

[1] Hour mode is set by bit 12\_24 in register Control\_1 (see [Table 6](#)).

### 8.3.4 Register Days

Table 12. Days - days register (address 05h) bit description

Bit	Symbol	Value	Place value	Description
7 to 6	-	00	-	unused
5 to 4	DAYS <sup>[1]</sup>	0 to 3	ten's place	actual day coded in BCD format
3 to 0		0 to 9	unit place	

[1] The PCA21125 compensates for leap years by adding a 29th day to February if the year counter contains a value which is exactly divisible by 4, including the year 00.

### 8.3.5 Register Weekdays

Table 13. Weekdays - weekdays register (address 06h) bit description

Bit	Symbol	Value	Description
7 to 3	-	00000	unused
2 to 0	WEEKDAYS	0 to 6	actual weekday, values see <a href="#">Table 14</a>

Table 14. Weekday assignments

Day <sup>[1]</sup>	Bit		
	2	1	0
Sunday	0	0	0
Monday	0	0	1
Tuesday	0	1	0
Wednesday	0	1	1
Thursday	1	0	0
Friday	1	0	1
Saturday	1	1	0

[1] Definition may be reassigned by the user.

### 8.3.6 Register Months

Table 15. Months - months register (address 07h) bit description

Bit	Symbol	Value	Description
7 to 5	-	000	unused
4	MONTHS	0 to 1	ten's place
3 to 0		0 to 9	unit place

Table 16. Month assignments in BCD format

Month	Upper-digit (ten's place)	Digit (unit place)			
	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
January	0	0	0	0	1
February	0	0	0	1	0
March	0	0	0	1	1
April	0	0	1	0	0
May	0	0	1	0	1
June	0	0	1	1	0
July	0	0	1	1	1
August	0	1	0	0	0
September	0	1	0	0	1
October	1	0	0	0	0
November	1	0	0	0	1
December	1	0	0	1	0


### 8.3.7 Register Years

Table 17. Years - years register (08h) bit description

Bit	Symbol	Value	Place value	Description
7 to 4	YEARS	0 to 9	ten's place	actual year coded in BCD format
3 to 0		0 to 9	unit place	

### 8.3.8 Setting and reading the time

[Figure 3](#) shows the data flow and data dependencies starting from the 1 Hz clock tick.




**Fig 3. Data flow of the time function**

During read/write operations, the time counting circuits (memory locations 02h through 08h) are blocked.

This prevents

- Faulty reading of the clock and calendar during a carry condition
- Incrementing the time registers during the read cycle

After this read/write access is completed, the time circuit is released again and any pending request to increment the time counters that occurred during the read/write access is serviced. A maximum of 1 request can be stored; therefore, all accesses must be completed within 1 second (see [Figure 4](#)).



**Fig 4. Access time for read/write operations**

As a consequence of this method, it is very important to make a read or write access in one go, that is, setting or reading seconds through to years should be made in one single access. Failing to comply with this method could result in the time becoming corrupted.

As an example, if the time (seconds through to hours) is set in one access and then in a second access the date is set, it is possible that the time may increment between the two accesses. A similar problem exists when reading. A roll-over may occur between reads thus giving the minutes from one moment and the hours from the next. Therefore it is advised to read all time and date registers in one access.

## 8.4 Alarm registers

When one or several alarm registers are loaded with a valid minute, hour, day, or weekday value and its corresponding alarm enable bit (AEN\_X) is logic 0, then that information is compared with the current minute, hour, day, and weekday value.

### 8.4.1 Register Minute\_alarm

**Table 18. Minute\_alarm - minute alarm register (address 09h) bit description**

Bit	Symbol	Value	Place value	Description
7	AEN_M	0	-	minute alarm is enabled
		1 <sup>[1]</sup>	-	minute alarm is disabled
6 to 4	MINUTE_ALARM	0 to 5	ten's place	minute alarm information coded in BCD format
3 to 0		0 to 9	unit place	

[1] Default value.

### 8.4.2 Register Hour\_alarm

**Table 19. Hour\_alarm - hour alarm register (address 0Ah) bit description**

Bit	Symbol	Value	Description
7	AEN_H	0	hour alarm is enabled
		1 <sup>[1]</sup>	hour alarm is disabled
6	-	0	unused
12-hour mode <sup>[2]</sup>			
5	AMPM	0	indicates AM
		1	indicates PM
4	HOUR_ALARM	0 to 1	ten's place
3 to 0		0 to 9	unit place
24-hour mode <sup>[2]</sup>			
5 to 4	HOURS	0 to 2	ten's place
3 to 0		0 to 9	unit place

[1] Default value.

[2] Hour mode is set by bit 12\_24 in register Control\_1 (see [Table 6](#)).

### 8.4.3 Register Day\_alarm

Table 20. Day\_alarm - day alarm register (address 0Bh) bit description

Bit	Symbol	Value	Place value	Description
7	AEN_D	0	-	day alarm is enabled
		1 <sup>[1]</sup>	-	day alarm is disabled
6	-	0	-	unused
5 to 4	DAY_ALARM	0 to 3	ten's place	day alarm information coded in BCD format
3 to 0		0 to 9	unit place	

[1] Default value.

### 8.4.4 Register Weekday\_alarm


Table 21. Weekday\_alarm - weekday alarm register (address 0Ch) bit description

Bit	Symbol	Value	Description
7	AEN_W	0	weekday alarm is enabled
		1 <sup>[1]</sup>	weekday alarm is disabled
6 to 3	-	0000	unused
2 to 0	WEEKDAY_ALARM	0 to 6	weekday alarm information coded in BCD format

[1] Default value.

### 8.4.5 Alarm flag

By clearing the MSB, AEN\_X (Alarm Enable), of one or more of the alarm registers the corresponding alarm condition(s) are active. When an alarm occurs, AF (register Control\_2, see [Table 7](#)) is set logic 1. The asserted AF can be used to generate an interrupt (INT). The AF is cleared by command.




The registers at addresses 09h through 0Ch contain alarm information. When one or more of these registers is loaded with minute, hour, day, or weekday, and its corresponding Alarm Enable bit (AEN\_X) is logic 0, then that information is compared with the current minute, hour, day, and weekday. When all enabled comparisons first match, the Alarm Flag (AF) is set logic 1.

The generation of interrupts from the alarm function is controlled via bit AIE (register Control\_2, see [Table 7](#)). If bit AIE is enabled, the INT pin follows the condition of bit AF. AF remains set until cleared by the interface. Once AF has been cleared, it is only set again when the time increments to match the alarm condition once more. Alarm registers which have their AEN\_X bit logic 1 are ignored.

Generation of interrupts from the alarm function is described in [Section 8.7.3](#).

[Figure 6](#), [Table 22](#) and [Table 23](#) show an example for clearing bit AF, but leaving bit MSF and bit TF unaffected. The flags are cleared by a write command, therefore bits 7, 6, 4, 1 and 0 must be written with their previous values. Repeatedly rewriting these bits has no influence on the functional behavior.



To prevent the timer flags being overwritten while clearing bit AF, logic AND is performed during a write access. A flag is cleared by writing logic 0 while a flag is not cleared by writing logic 1. Writing logic 1 results in the flag value remaining unchanged.

**Table 22. Flag location in register Control\_2**

Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	MSF	-	AF	TF	-	-

[Table 23](#) shows what instruction must be sent to clear bit AF. In this example, bit MSF and bit TF are unaffected.

**Table 23. Example to clear only AF (bit 3) in register Control\_2**

Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	1	-	0	1	-	-

## 8.5 Register CLKOUT\_control and clock output

A programmable square wave is available at pin CLKOUT. Operation is controlled by control bits COF[2:0] in register CLKOUT\_control (0Dh); see [Table 24](#). Frequencies of 32.768 kHz (default) down to 1 Hz can be generated for use as a system clock, microcontroller clock, input to a charge pump, or for calibration of the oscillator.

**Table 24. CLKOUT\_control - CLKOUT control register (address 0Dh) bit description**

Bit	Symbol	Value	Description
7 to 3	-	00000	unused
2 to 0	COF[2:0]	see <a href="#">Table 25</a>	frequency output at pin CLKOUT

Pin CLKOUT is an open-drain output and enabled at power-on. When disabled the output is LOW.

The duty cycle of the selected clock is not controlled, but due to the nature of the clock generation, all clock frequencies, except 32.768 kHz, have a duty cycle of 50 : 50.

The stop function can also affect the CLKOUT signal, depending on the selected frequency. When STOP is active, the CLKOUT pin generates a continuous LOW for those frequencies that can be stopped. For more details, see [Section 8.9](#).

**Table 25. CLKOUT frequency selection**

Bits COF[2:0]	CLKOUT frequency (Hz)	Typical duty cycle <sup>[1]</sup> (%)	Effect of STOP
000 <sup>[2]</sup>	32768	60 : 40 to 40 : 60	no effect
001	16384	50 : 50	no effect
010	8192	50 : 50	no effect
011	4096	50 : 50	CLKOUT = LOW
100	2048	50 : 50	CLKOUT = LOW
101	1024	50 : 50	CLKOUT = LOW
110	1	50 : 50	CLKOUT = LOW
111	CLKOUT = LOW		

[1] Duty cycle definition: HIGH-level time (%) : LOW-level time (%).

[2] Default value.

## 8.6 Timer registers

The countdown timer has four selectable source clocks allowing for countdown periods in the range from less than 1 ms to more than 4 hours (see [Table 30](#)). There are also two pre-defined timers which can be used to generate an interrupt once per second or once per minute.

Registers Control\_2 (01h), Timer\_control (0Eh), and Countdown\_timer (0Fh) are used to control the timer function and output.

Table 26. Timer\_control - timer control register (address 0Eh) bit description

Bit	Symbol	Value	Description	Reference
7	TE	0 <sup>[1]</sup>	countdown timer is disabled	Section 8.6.2
		1	countdown timer is enabled	
6 to 2	-	00000	unused	
1 to 0	CTD[1:0]	00	4.096 kHz countdown timer source clock	
		01	64 Hz countdown timer source clock	
		10	1 Hz countdown timer source clock	
		11 <sup>[1]</sup>	1/60 Hz countdown timer source clock	

[1] Default value.

Table 27. Countdown\_timer - countdown timer register (address 0Fh) bit description

Bit	Symbol	Value	Description	Reference
7 to 0	T[7:0]	0h to FFh	countdown timer value <sup>[1]</sup>	Section 8.6.2

[1] Countdown period in seconds:  $CountdownPeriod = \frac{T}{SourceClockFrequency}$  where T is the countdown value.

### 8.6.1 Second and minute interrupt

The second and minute interrupts (bits SI and MI) are pre-defined timers for generating periodic interrupts. The timers can be enabled independently of one another, however a minute interrupt enabled on top of a second interrupt is not distinguishable since it occurs at the same time; see Figure 7.

The minute and second flag (MSF) is set logic 1 when either the seconds or the minutes counter increments according to the currently enabled interrupt. The flag can be read and cleared by the interface. The status of bit MSF does not affect the  $\overline{INT}$  pulse generation. If the MSF flag is not cleared prior to the next coming interrupt period, an  $\overline{INT}$  pulse will still be generated.

Table 28. Effect of bits MI and SI on  $\overline{INT}$  generation


Minute interrupt (bit MI)	Second interrupt (bit SI)	Result
0	0	no interrupt generated
1	0	an interrupt once per minute
0	1	an interrupt once per second
1	1	an interrupt once per second

Table 29. Effect of bits MI and SI on bit MSF

Minute interrupt (bit MI)	Second interrupt (bit SI)	Result
0	0	MSF never set
1	0	MSF set when <b>minutes</b> counter increments <sup>[1]</sup>
0	1	MSF set when <b>seconds</b> counter increments
1	1	MSF set when <b>seconds</b> counter increments

[1] If bit MI = 1 and bit SI = 0, bit MSF is cleared automatically after 1 second.





The purpose of the flag is to allow the controlling system to interrogate the PCA21125 and identify the source of the interrupt such as the minute/second or countdown timer.

### 8.6.2 Countdown timer function

The 8-bit countdown timer at address 0Fh is controlled by the timer control register at address 0Eh. The timer control register determines one of 4 source clock frequencies for the timer (4.096 kHz, 64 Hz, 1 Hz, or  $\frac{1}{60}$  Hz) and enables or disables the timer.


**Table 30. CTD[1:0] for timer frequency selection and countdown timer durations**

CTD[1:0]	Timer source clock frequency	Delay	
		Minimum timer duration T = 1	Maximum timer duration T = 255
00	4.096 kHz	244 $\mu$ s	62.256 ms
01	64 Hz	15.625 ms	3.984 s
10	1 Hz	1 s	255 s
11	$\frac{1}{60}$ Hz	60 s <sup>[1]</sup>	4 h 15 min

[1] When not in use, CTD[1:0] must be set to  $\frac{1}{60}$  Hz for power saving.

**Remark:** Note that all timings which are generated from the 32.768 kHz oscillator are based on the assumption that there is 0 ppm deviation. Deviation in oscillator frequency results in a corresponding deviation in timings. This is not applicable to interface timing.

The timer counts down from a software-loaded 8-bit binary value T. Loading the counter with 0 effectively stops the timer. Values from 1 to 255 are valid. When the counter reaches 1, the countdown timer flag (bit TF in register Control\_2, see [Table 7](#)) will be set and the counter automatically reloads and starts the next timer period. Reading the timer returns the current value of the countdown counter; see [Figure 8](#).



**Fig 8. General countdown timer behavior**

If a new value of T is written before the end of the current timer period, then this new value takes immediate effect. It is not recommended to change T without first disabling the counter (by setting bit TE = 0). The update of T is asynchronous with the timer clock, therefore changing it without setting bit TE = 0 results in a corrupted value loaded into the countdown counter which results in an undetermined countdown period for the first period. The countdown value T will however be correctly stored and correctly loaded on subsequent timer periods.

When the countdown timer flag is set, an interrupt signal on  $\overline{\text{INT}}$  is generated, if this mode is enabled. See [Section 8.7.2](#) for details on how the interrupt can be controlled.

When starting the timer for the first time, the first period has an uncertainty which is a result of the enable instruction being generated from the interface clock which is asynchronous with the timer source clock. Subsequent timer periods have no such delay. The amount of delay for the first timer period depends on the chosen source clock; see [Table 31](#).

**Table 31. First period delay for timer counter value T**

Timer source clock	Minimum timer period	Maximum timer period
4.096 kHz	T	T + 1
64 Hz	T	T + 1
1 Hz	$(T - 1) + \frac{1}{64} \text{ Hz}$	$T + \frac{1}{64} \text{ Hz}$
$\frac{1}{60} \text{ Hz}$	$(T - 1) + \frac{1}{64} \text{ Hz}$	$T + \frac{1}{64} \text{ Hz}$

At the end of every countdown, the timer sets the countdown timer flag (bit TF). Bit TF can only be cleared by command. The asserted bit TF can be used to generate an interrupt (INT). The interrupt can be generated as a pulsed signal every countdown period or as a permanently active signal which follows the condition of bit TF. Bit TI\_TP is used to control this mode selection and the interrupt output can be disabled with bit TIE.

For accurate read back of the count down value, it is recommended to read the register twice and check for consistent results, since it is not possible to freeze the countdown timer counter during read back.

### 8.6.3 Timer flags

When a minute or second interrupt occurs, bit MSF (register Control\_2, see [Table 7](#)) is set logic 1. Similarly, at the end of a timer countdown bit TF is set logic 1. These bits maintain their value until overwritten by command. If both countdown timer and minute/second interrupts are required in the application, the source of the interrupt can be determined by reading these bits. To prevent one flag being overwritten while clearing another, a logic AND is performed during a write access. A flag is cleared by writing logic 0 while a flag is not cleared by writing logic 1. Writing logic 1 results in the flag value remaining unchanged.

Three examples are given for clearing the flags. Flags MSF and TF are cleared by a write command, therefore bits 7, 6, 4, 1, and 0 must be written with their previous values. Repeatedly rewriting these bits has no influence on the functional behavior.

**Table 32. Flag location in register Control\_2**

Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	MSF	-	AF	TF	-	-

[Table 33](#), [Table 34](#), and [Table 35](#) show what instruction must be sent to clear the appropriate flag.

**Table 33. Example to clear only TF (bit 2) in register Control\_2**

Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	1	-	1	0	-	-

**Table 34. Example to clear only MSF (bit 5) in register Control\_2**

Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	0	-	1	1	-	-

**Table 35. Example to clear both TF and MSF (bits 2 and 5) in register Control\_2**


Register	Bit 7	Bit 6	Bit 5	Bit 4	Bit 3	Bit 2	Bit 1	Bit 0
Control_2	-	-	0	-	1	0	-	-

Clearing the alarm flag (bit AF) operates in the same way; see [Section 8.4.5](#).

## 8.7 Interrupt output

An active LOW interrupt signal is available at pin  $\overline{\text{INT}}$ . Operation is controlled via the bits of register Control\_2. Interrupts can be sourced from three places: second/minute timer, countdown timer, and alarm function.

Bit TI\_TP configures the timer generated interrupts to be either a pulse or to follow the status of the interrupt flags (bits TF and MSF).



When bits SI, MI, TIE and AIE are all disabled, pin  $\overline{\text{INT}}$  remains high-impedance.


**Fig 9.** Interrupt scheme

**Remark:** Note that the interrupts from the three groups are wired-OR, meaning they will mask one another; see [Figure 9](#).

### 8.7.1 Minute and second interrupts

The pulse generator for the minute/second interrupt operates from an internal 64 Hz clock and consequently generates a pulse of  $\frac{1}{64}$  second duration.

If the MSF flag is clear before the end of the  $\overline{\text{INT}}$  pulse, then the  $\overline{\text{INT}}$  pulse is shortened. This allows the source of a system interrupt to be cleared immediately it is serviced, i.e., the system does not have to wait for the completion of the pulse before continuing; see [Figure 10](#). Instructions for clearing MSF are given in [Section 8.6.3](#).



The timing shown for clearing bit MSF in [Figure 10](#) is also valid for the non-pulsed interrupt mode, i.e., when bit  $\text{TI\_TP} = 0$ , where the pulse can be shortened by setting both bits MI and SI logic 0.

### 8.7.2 Countdown timer interrupts

Generation of interrupts from the countdown timer is controlled via bit TIE (register Control\_2, see [Table 7](#)).


The pulse generator for the countdown timer interrupt also uses an internal clock which is dependent on the selected source clock for the countdown timer and on the countdown value T. As a consequence, the width of the interrupt pulse varies; see [Table 36](#).

**Table 36.  $\overline{\text{INT}}$  operation (bit  $\text{TI\_TP} = 1$ )**

Source clock (Hz)	$\overline{\text{INT}}$ period (s)	
	$T = 1$ [1]	$T > 1$
4096	$1/8192$	$1/4096$
64	$1/128$	$1/64$
1	$1/64$	$1/64$
$1/60$	$1/64$	$1/64$

[1] T = loaded countdown value. Timer stopped when  $T = 0$ .


If the TF flag is cleared before the end of the  $\overline{\text{INT}}$  pulse, then the  $\overline{\text{INT}}$  pulse is shortened. This allows the source of a system interrupt to be cleared immediately it is serviced, i.e., the system does not have to wait for the completion of the pulse before continuing; see [Figure 11](#). Instructions for clearing TF are given in [Section 8.6.3](#).



The timing shown for clearing bit TF in [Figure 11](#) is also valid for the non-pulsed interrupt mode, i.e., when bit  $\text{TI\_TP} = 0$ , where the pulse can be shortened by setting bit  $\text{TIE} = 0$ .

### 8.7.3 Alarm interrupts

Generation of interrupts from the alarm function is controlled via bit AIE (register Control\_2, see [Table 7](#)). If bit AIE is enabled, the  $\overline{\text{INT}}$  pin follows the status of bit AF. Clearing bit AF immediately clears  $\overline{\text{INT}}$ . No pulse generation is possible for alarm interrupts; see [Figure 12](#).



## 8.8 External clock test mode

A test mode is available which allows for on-board testing. In this mode, it is possible to set up test conditions and control the operation of the RTC.

The test mode is entered by setting the  $\text{EXT\_TEST}$  bit in register Control\_1 (see [Table 6](#)). The CLKOUT pin then becomes an input. The test mode replaces the internal signal with the signal applied to pin CLKOUT.

The signal applied to pin CLKOUT should have a minimum pulse width of 300 ns and a maximum period of 1000 ns. The internal clock, now sourced from pin CLKOUT, is divided down to 1 Hz by a  $2^6$  divide chain called a prescaler; see [Section 8.9](#). The prescaler can be set into a known state by using the STOP bit. When the STOP bit is set, the prescaler is reset to 0. (STOP must be cleared before the prescaler can operate again.)

From a stop condition, the first 1 second increment will take place after 32 positive edges on pin CLKOUT. Thereafter, every 64 positive edges cause a 1 second increment.

**Remark:** Entry into test mode is not synchronized to the internal 64 Hz clock. When entering the test mode, no assumption as to the state of the prescaler can be made.

Operation example:

1. Set EXT\_TEST test mode (register Control\_1, bit EXT\_TEST = 1).
2. Set STOP (register Control\_1, bit STOP = 1).
3. Clear STOP (register Control\_1, bit STOP = 0).
4. Set time registers to desired value.
5. Apply 32 clock pulses to pin CLKOUT.
6. Read time registers to see the first change.
7. Apply 64 clock pulses to pin CLKOUT.
8. Read time registers to see the second change.

Repeat steps 7 and 8 for additional increments.

## 8.9 STOP bit function

The STOP bit function (register Control\_1, see [Table 6](#)) allows the accurate starting of the time circuits. The STOP bit function causes the upper part of the prescaler ( $F_2$  to  $F_{14}$ ) to be held at reset, thus no 1 Hz ticks are generated. The time circuits can then be set and do not increment until STOP is released; see [Figure 13](#). STOP does not affect the output of 32.768 kHz, 16.384 kHz, or 8.192 kHz; see [Section 8.5](#).




Fig 13. STOP bit functional diagram

The lower two stages of the prescaler ( $F_0$  and  $F_1$ ) are not reset and because the SPI-bus is asynchronous to the crystal oscillator, the accuracy of restarting the time circuits is between 0 and one 8.192 kHz cycle; see [Figure 14](#). The first increment of the time circuits is between 0.499878 s and 0.500000 s after STOP is released. The uncertainty is caused by prescaler bits  $F_0$  and  $F_1$  not being reset; see [Table 37](#).




Fig 14. STOP bit release timing

Table 37. Example: first increment of time circuits after STOP release


Bit STOP	Prescaler bits $F_0F_1F_2$ to $F_{14}$ <sup>[1]</sup>	1 Hz tick	Time hh:mm:ss	Comment
Clock is running normally				
0	01-0 0001 1101 0100		12:45:12	prescaler counting normally
STOP is activated by user. $F_0F_1$ are not reset and values cannot be predicted externally				
1	XX-0 0000 0000 0000		12:45:12	prescaler is reset; time circuits are frozen
New time is set by user				
1	XX-0 0000 0000 0000		08:00:00	prescaler is reset; time circuits are frozen
STOP is released by user				
0	XX-0 0000 0000 0000	<p>0.499878 - 0.500000 s</p> <p>1 s</p> <p>001aaf913</p>	08:00:00	prescaler is now running
	XX-1 0000 0000 0000		08:00:00	-
	XX-0 1000 0000 0000		08:00:00	-
	XX-1 1000 0000 0000		08:00:00	-
	:		:	:
	11-1 1111 1111 1110		08:00:00	-
	00-0 0000 0000 0001		08:00:01	0 to 1 transition of $F_{14}$ increments the time circuits
	10-0 0000 0000 0001		08:00:01	-
	:		:	:
	11-1 1111 1111 1111		08:00:01	-
	00-0 0000 0000 0000		08:00:01	-
	10-0 0000 0000 0000		08:00:01	-
	:		:	:
	11-1 1111 1111 1110		08:00:01	-
	00-0 0000 0000 0001		08:00:02	0 to 1 transition of $F_{14}$ increments the time circuits

[1]  $F_0$  is clocked at 32.768 kHz.




8.10 Reset

The PCA21125 includes an internal reset circuit which is active whenever the oscillator is stopped; see [Figure 15](#). The oscillator can be stopped, for example, by connecting one of the oscillator pins OSCI or OSCO to ground.



The oscillator is considered to be stopped during the time between power-on and stable crystal resonance; see [Figure 16](#). This time can be in the range of 200 ms to 2 s depending on crystal type, temperature and supply voltage. Whenever an internal reset occurs, the reset flag RF (register Seconds, see [Table 8](#)) is set.



**Table 38. Register reset values**

Bits labeled - are not implemented and return logic 0 when read. Bits labeled X are undefined at power-on and unchanged by subsequent resets.

Address	Register name	Bit							
		7	6	5	4	3	2	1	0
00h	Control_1	0	0	0	-	1	0	-	-
01h	Control_2	0	0	0	0	0	0	0	0
02h	Seconds	1	X	X	X	X	X	X	X
03h	Minutes	-	X	X	X	X	X	X	X
04h	Hours	-	-	X	X	X	X	X	X
05h	Days	-	-	X	X	X	X	X	X
06h	Weekdays	-	-	-	-	-	X	X	X
07h	Months	-	-	-	X	X	X	X	X
08h	Years	X	X	X	X	X	X	X	X
09h	Minute_alarm	1	X	X	X	X	X	X	X
0Ah	Hour_alarm	1	-	X	X	X	X	X	X
0Bh	Day_alarm	1	-	X	X	X	X	X	X
0Ch	Weekday_alarm	1	-	-	-	-	X	X	X
0Dh	CLKOUT_control	-	-	-	-	-	0	0	0
0Eh	Timer_control	0	-	-	-	-	-	1	1
0Fh	Countdown_timer	X	X	X	X	X	X	X	X


After reset, the following mode is entered:

- 32.768 kHz on pin CLKOUT active
- POR override available to be set
- 24-hour mode is selected

The SPI-bus is initialized whenever the chip enable pin CE is inactive (LOW).

### 8.10.1 POR override

The Power-On Reset (POR) duration is directly related to the crystal oscillator start-up time. Due to the long start-up times experienced by these types of circuits, a mechanism has been built in to disable the POR and hence speed up the on-board test of the device.

**Fig 17. POR override sequence**

The setting of this mode requires that bit POR\_OVRD (register Control\_1, see [Table 6](#)) be set logic 1 and that the signals at the SPI-bus pins SDI and CE are toggled as illustrated in [Figure 17](#). All timings are required minimums.

Once the override mode has been entered, the device immediately stops being reset and set-up operation can commence, i.e., entry into the external clock test mode via the SPI-bus access. The override mode can be cleared by writing logic 0 to bit POR\_OVRD. Bit POR\_OVRD must be set logic 1 before a re-entry into the override mode is possible. Setting bit POR\_OVRD logic 0 during normal operation has no effect except to prevent accidental entry into the POR override mode. This is the recommended setting.


### 8.11 4-line SPI-bus

Data transfer to and from the device is made via a 4-line SPI-bus; see [Table 39](#).


Table 39. Serial interface

Pin	Function	Description
CE	chip enable input	when HIGH, data transfer is active when LOW, data transfer is inactive; the interface is reset; pull-down resistor included; active input can be higher than V <sub>DD</sub> , but must not be wired HIGH permanently
SCL	serial clock input	when pin CE = LOW, this input might float; input can be higher than V <sub>DD</sub>
SDI	serial data input	when pin CE = LOW, this input might float; input can be higher than V <sub>DD</sub> ; input data is sampled on the rising edge of SCL
SDO	serial data output	push-pull output; drives from V <sub>SS</sub> to V <sub>DD</sub> ; output data is changed on the falling edge of SCL

The data lines for input and output are split. The data input and output lines can be connected together to facilitate a bidirectional data bus (see [Figure 18](#)).



The chip enable signal is used to identify the transmitted data. Each data transfer is a byte, with the Most Significant Bit (MSB) sent first; see [Figure 19](#).




The transmission is initiated by an active HIGH chip enable signal CE and terminated by an inactive LOW signal. The first byte transmitted is the command byte (see [Table 40](#) and [Figure 20](#)). Subsequent bytes are either data to be written or data to be read. Data is captured on the rising edge of the clock and transferred internally on the falling edge.

The command byte defines the address of the first register to be accessed and the read/write mode. The address counter will auto increment after every access and will reset to zero after the last valid register is accessed. The read/write bit ( $R/\overline{W}$ ) defines if the following bytes are read or write information.


**Table 40. Command byte definition**

Bit	Symbol	Value	Description
7	$R/\overline{W}$		data read or data write selection
		0	write data
		1	read data
6 to 4	SA	001	subaddress; other codes cause the device to ignore data transfer
3 to 0	RA	00h to 0Fh	register address




**Fig 20. Command byte**

In [Figure 21](#), the register Seconds is set to 45 seconds and the register Minutes to 10 minutes.



**Fig 21. Serial bus write example**


In [Figure 22](#), the Months and Years registers are read. In this example, pins SDI and SDO are not connected together.




### Fig 22. Serial bus read example

### 8.11.1 Interface watchdog timer

During read/write operations, the time counting circuits are frozen. To prevent a situation where the accessing device becomes locked and does not clear the interface by setting pin CE LOW, the PCA21125 has a built-in watchdog timer. Should the interface be active for more than 1 s from the time a valid subaddress is transmitted, then the PCA21125 will automatically clear the interface and allow the time counting circuits to continue counting. CE must return LOW once more before a new data transfer can be executed.



a. Correct data transfer: read or write



b. Incorrect data transfer; read or write

**Fig 23. Interface watchdog timer**

The watchdog is implemented to prevent the excessive loss of time due to interface access failure, e.g., if main power is removed from a battery backed-up system during an interface access.

Each time the watchdog period is exceeded, 1 s is lost from the time counters. The watchdog will trigger between 1 s and 2 s after receiving a valid subaddress.

## 9. Internal circuitry




Fig 24. Device diode protection diagram

## 10. Safety notes

### CAUTION



This device is sensitive to ElectroStatic Discharge (ESD). Observe precautions for handling electrostatic sensitive devices.

Such precautions are described in the *ANSI/ESD S20.20*, *IEC/ST 61340-5*, *JESD625-A* or equivalent standards.

## 11. Limiting values

**Table 41. Limiting values**

*In accordance with the Absolute Maximum Rating System (IEC 60134).*

Symbol	Parameter	Conditions	Min	Max	Unit
V <sub>DD</sub>	supply voltage		−0.5	+6.5	V
I <sub>DD</sub>	supply current		−50	+50	mA
V <sub>I</sub>	input voltage		−0.5	+6.5	V
V <sub>O</sub>	output voltage		−0.5	+6.5	V
I <sub>I</sub>	input current		−10	+10	mA
I <sub>O</sub>	output current		−10	+10	mA
P <sub>tot</sub>	total power dissipation		-	300	mW
T <sub>amb</sub>	ambient temperature	operating device	−40	+125	°C
V <sub>ESD</sub>	electrostatic discharge voltage	HBM [1]	-	±3500	V
		MM [2]	-	±200	V
		CDM [3]	-	±1500	V
I <sub>Iu</sub>	latch-up current	[4]	-	100	mA
T <sub>stg</sub>	storage temperature	[5]	−65	+150	°C

[1] Pass level; Human Body Model (HBM) according to [Ref. 5 “JESD22-A114”](#).

[2] Pass level; Machine Model (MM), according to [Ref. 6 “JESD22-A115”](#).

[3] Pass level; Charged-Device Model (CDM), according to [Ref. 7 “JESD22-C101”](#).

[4] Pass level; latch-up testing, according to [Ref. 8 “JESD78”](#) at maximum ambient temperature (T<sub>amb(max)</sub> = +125 °C).

[5] According to the store and transport requirements (see [Ref. 11 “UM10569”](#)) the devices have to be stored at a temperature of +8 °C to +45 °C and a humidity of 25 % to 75 %.

## 12. Static characteristics

**Table 42. Static characteristics**

$V_{DD} = 1.3\text{ V to }5.5\text{ V}$ ;  $V_{SS} = 0\text{ V}$ ;  $T_{amb} = -40\text{ °C to }+125\text{ °C}$ ;  $f_{osc} = 32.768\text{ kHz}$ ; quartz  $R_s = 60\text{ k}\Omega$ ;  $C_L = 12.5\text{ pF}$ ; unless otherwise specified.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
Supply: pin V <sub>DD</sub>						
V <sub>DD</sub>	supply voltage	SPI-bus inactive; for clock data integrity <a href="#">[1]</a>	1.3	-	5.5	V
		SPI-bus active	1.6	-	5.5	V
I <sub>DD</sub>	supply current	SPI-bus active				
		f <sub>SCL</sub> = 6.0 MHz	-	-	500	μA
		f <sub>SCL</sub> = 1.0 MHz	-	-	100	μA
		SPI-bus inactive; CLKOUT disabled; V <sub>DD</sub> = 2.0 V to 5.0 V <a href="#">[2]</a>				
		T <sub>amb</sub> = 25 °C	-	820	-	nA
		T <sub>amb</sub> = −40 °C to +125 °C	-	1140	3300	nA
		SPI-bus inactive (f <sub>SCL</sub> = 0 Hz); CLKOUT enabled at 32 kHz				
		T <sub>amb</sub> = 25 °C				
		V <sub>DD</sub> = 5.0 V	-	1220	-	nA
		V <sub>DD</sub> = 3.0 V	-	940	-	nA
		V <sub>DD</sub> = 2.0 V	-	810	-	nA
		T <sub>amb</sub> = −40 °C to +125 °C				
		V <sub>DD</sub> = 5.0 V	-	-	4000	nA
		V <sub>DD</sub> = 3.0 V	-	-	2400	nA
		V <sub>DD</sub> = 2.0 V	-	-	1900	nA
Inputs						
V <sub>I</sub>	input voltage	pin OSCI	−0.5	-	V <sub>DD</sub> + 0.5	V
		pins CE, SDI, SCL	−0.5	-	+5.5	V
V <sub>IL</sub>	LOW-level input voltage		V <sub>SS</sub>	-	0.3V <sub>DD</sub>	V
V <sub>IH</sub>	HIGH-level input voltage		0.7V <sub>DD</sub>	-	V <sub>DD</sub>	V
I <sub>L</sub>	leakage current	V <sub>I</sub> = V <sub>DD</sub> or V <sub>SS</sub> ; on pins SDI, SCL and CLKOUT	−1	0	+1	μA
C <sub>I</sub>	input capacitance	<a href="#">[3]</a>	-	-	7	pF
R <sub>pd</sub>	pull-down resistance	pin CE	-	240	550	kΩ
Outputs						
V <sub>O</sub>	output voltage	pins OSCO and SDO	-	-	V <sub>DD</sub> + 0.5	V
		pins CLKOUT and $\overline{\text{INT}}$ ; refers to external pull-up voltage	-	-	5.5	V
V <sub>OH</sub>	HIGH-level output voltage	pin SDO	0.8V <sub>DD</sub>	-	V <sub>DD</sub>	V



**Table 42. Static characteristics ...continued**

$V_{DD} = 1.3 \text{ V to } 5.5 \text{ V}$ ;  $V_{SS} = 0 \text{ V}$ ;  $T_{amb} = -40 \text{ }^{\circ}\text{C to } +125 \text{ }^{\circ}\text{C}$ ;  $f_{osc} = 32.768 \text{ kHz}$ ; quartz  $R_s = 60 \text{ k}\Omega$ ;  $C_L = 12.5 \text{ pF}$ ; unless otherwise specified.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
$V_{OL}$	LOW-level output voltage	pin SDO	$V_{SS}$	-	$0.2V_{DD}$	V
		pins CLKOUT and $\overline{\text{INT}}$ ; $V_{DD} = 5 \text{ V}$ ; $I_{OL} = -1.5 \text{ mA}$	$V_{SS}$	-	0.4	V
$I_{OH}$	HIGH-level output current	output source current; pin SDO; $V_{OH} = 4.6 \text{ V}$ ; $V_{DD} = 5 \text{ V}$	1.5	-	-	mA
$I_{OL}$	LOW-level output current	output sink current; pins $\overline{\text{INT}}$ , SDO and CLKOUT; $V_{OL} = 0.4 \text{ V}$ ; $V_{DD} = 5 \text{ V}$	1.5	-	-	mA
$I_{LO}$	output leakage current	$V_O = V_{DD} \text{ or } V_{SS}$	-1	0	+1	$\mu\text{A}$
$C_{ext}$	external capacitance	[4]	-	25	-	pF
$C_{OSCO}$	capacitance on pin OSCO	[4]	-	25	-	pF

[1] For reliable oscillator start at power-up:  $V_{DD} = V_{DD(min)} + 0.3 \text{ V}$ .

[2] Timer source clock =  $\frac{1}{60} \text{ Hz}$ ; voltage on pins CE, SDI and SCL at  $V_{DD}$  or  $V_{SS}$ .

[3] Implicit by design.

[4]  $C_L$  is a calculation of  $C_{ext}$  and  $C_{OSCO}$  in series:  $C_L = \frac{(C_{ext} \cdot C_{OSCO})}{(C_{ext} + C_{OSCO})}$ .

## 13. Dynamic characteristics

**Table 43. Dynamic characteristics**

$V_{DD} = 1.6\text{ V to }5.5\text{ V}$ ;  $V_{SS} = 0\text{ V}$ ;  $T_{amb} = -40\text{ °C to }+125\text{ °C}$ ; all timing values are valid within the operating supply voltage at ambient temperature and referenced to  $V_{IL}$  and  $V_{IH}$  with an input voltage swing of  $V_{SS}$  to  $V_{DD}$ .

Symbol	Parameter	Conditions	V <sub>DD</sub> = 1.6 V		V <sub>DD</sub> = 2.7 V		V <sub>DD</sub> = 4.5 V		V <sub>DD</sub> = 5.5 V		Unit
			Min	Max	Min	Max	Min	Max	Min	Max	
Pin SCL											
f <sub>clk(SCL)</sub>	SCL clock frequency		-	1.5	-	4.0	-	5.00	-	6.25	MHz
t <sub>SCL</sub>	SCL time		660	-	250	-	200	-	160	-	ns
t <sub>clk(H)</sub>	clock HIGH time		320	-	120	-	100	-	70	-	ns
t <sub>clk(L)</sub>	clock LOW time		320	-	130	-	100	-	90	-	ns
t <sub>r</sub>	rise time	for SCL signal	-	100	-	100	-	100	-	100	ns
t <sub>f</sub>	fall time	for SCL signal	-	100	-	100	-	100	-	100	ns
Pin CE											
t <sub>su(CE)</sub>	CE set-up time		30	-	30	-	30	-	30	-	ns
t <sub>h(CE)</sub>	CE hold time		100	-	60	-	40	-	30	-	ns
t <sub>rec(CE)</sub>	CE recovery time		100	-	100	-	100	-	100	-	ns
t <sub>w(CE)</sub>	CE pulse width		-	0.99	-	0.99	-	0.99	-	0.99	s
Pin SDI											
t <sub>su</sub>	set-up time		25	-	15	-	15	-	10	-	ns
t <sub>h</sub>	hold time		100	-	60	-	40	-	30	-	ns
Pin SDO											
t <sub>d(R)SDO</sub>	SDO read delay time	bus load = 85 pF	-	320	-	130	-	100	-	90	ns
t <sub>dis(SDO)</sub>	SDO disable time	no load value <a href="#">[1]</a>	-	50	-	30	-	30	-	25	ns
t <sub>t(SDI-SDO)</sub>	transition time from SDI to SDO	to avoid bus conflict	0	-	0	-	0	-	0	-	ns

[1] Bus is held up by bus capacitance; use RC time constant with application values.





Fig 25. SPI interface timing

## 14. Application information

### 14.1 Application diagram



### 14.2 Quartz frequency adjustment

#### 1. Method 1: fixed OSCI capacitor

A fixed capacitor can be used whose value can be determined by evaluating the average capacitance necessary for the application layout; see [Figure 26](#). The frequency is best measured via the 32.768 kHz signal at pin CLKOUT available after power-on. The frequency tolerance depends on the quartz crystal tolerance, the capacitor tolerance and the device-to-device tolerance (on average  $\pm 5 \times 10^{-6}$ ). An average deviation of  $\pm 5$  minutes per year can easily be achieved.

#### 2. Method 2: OSCI trimmer

Fast setting of a trimmer is possible using the 32.768 kHz signal at pin CLKOUT available after power-on.

#### 3. Method 3: OSCO output

Direct measurement of OSCO output (accounting for test probe capacitance).

## 15. Test information

### 15.1 Quality information

This product has been qualified in accordance with the Automotive Electronics Council (AEC) standard Q100 - *Failure mechanism based stress test qualification for integrated circuits*, and is suitable for use in automotive applications.

16. Package outline

TSSOP14: plastic thin shrink small outline package; 14 leads; body width 4.4 mm SOT402-1




Fig 27. Package outline SOT402-1 (TSSOP14)

## 17. Handling information

All input and output pins are protected against ElectroStatic Discharge (ESD) under normal handling. When handling Metal-Oxide Semiconductor (MOS) devices ensure that all normal precautions are taken as described in *JESD625-A*, *IEC 61340-5* or equivalent standards.

## 18. Packing information

### 18.1 Tape and reel information

For tape and reel packing information, see [Ref. 10 "SOT402-1\\_118" on page 43](#).

## 19. Soldering of SMD packages

This text provides a very brief insight into a complex technology. A more in-depth account of soldering ICs can be found in Application Note *AN10365 "Surface mount reflow soldering description"*.

### 19.1 Introduction to soldering

Soldering is one of the most common methods through which packages are attached to Printed Circuit Boards (PCBs), to form electrical circuits. The soldered joint provides both the mechanical and the electrical connection. There is no single soldering method that is ideal for all IC packages. Wave soldering is often preferred when through-hole and Surface Mount Devices (SMDs) are mixed on one printed wiring board; however, it is not suitable for fine pitch SMDs. Reflow soldering is ideal for the small pitches and high densities that come with increased miniaturization.

### 19.2 Wave and reflow soldering

Wave soldering is a joining technology in which the joints are made by solder coming from a standing wave of liquid solder. The wave soldering process is suitable for the following:

- Through-hole components
- Leaded or leadless SMDs, which are glued to the surface of the printed circuit board

Not all SMDs can be wave soldered. Packages with solder balls, and some leadless packages which have solder lands underneath the body, cannot be wave soldered. Also, leaded SMDs with leads having a pitch smaller than ~0.6 mm cannot be wave soldered, due to an increased probability of bridging.

The reflow soldering process involves applying solder paste to a board, followed by component placement and exposure to a temperature profile. Leaded packages, packages with solder balls, and leadless packages are all reflow solderable.

Key characteristics in both wave and reflow soldering are:

- Board specifications, including the board finish, solder masks and vias
- Package footprints, including solder thieves and orientation
- The moisture sensitivity level of the packages

- Package placement
- Inspection and repair
- Lead-free soldering versus SnPb soldering

### 19.3 Wave soldering

Key characteristics in wave soldering are:

- Process issues, such as application of adhesive and flux, clinching of leads, board transport, the solder wave parameters, and the time during which components are exposed to the wave
- Solder bath specifications, including temperature and impurities

### 19.4 Reflow soldering

Key characteristics in reflow soldering are:

- Lead-free versus SnPb soldering; note that a lead-free reflow process usually leads to higher minimum peak temperatures (see [Figure 28](#)) than a SnPb process, thus reducing the process window
- Solder paste printing issues including smearing, release, and adjusting the process window for a mix of large and small components on one board
- Reflow temperature profile; this profile includes preheat, reflow (in which the board is heated to the peak temperature) and cooling down. It is imperative that the peak temperature is high enough for the solder to make reliable solder joints (a solder paste characteristic). In addition, the peak temperature must be low enough that the packages and/or boards are not damaged. The peak temperature of the package depends on package thickness and volume and is classified in accordance with [Table 44](#) and [45](#)

**Table 44. SnPb eutectic process (from J-STD-020D)**


Package thickness (mm)	Package reflow temperature (°C)	
	Volume (mm <sup>3</sup> )	
	< 350	≥ 350
< 2.5	235	220
≥ 2.5	220	220

**Table 45. Lead-free process (from J-STD-020D)**

Package thickness (mm)	Package reflow temperature (°C)		
	Volume (mm <sup>3</sup> )		
	< 350	350 to 2000	> 2000
< 1.6	260	260	260
1.6 to 2.5	260	250	245
> 2.5	250	245	245

Moisture sensitivity precautions, as indicated on the packing, must be respected at all times.

Studies have shown that small packages reach higher temperatures during reflow soldering, see [Figure 28](#).



For further information on temperature profiles, refer to Application Note *AN10365* “Surface mount reflow soldering description”.



## 20. Appendix

### 20.1 Real-Time Clock selection

Table 46. Selection of Real-Time Clocks

Type name	Alarm, Timer, Watchdog	Interrupt output	Interface	I <sub>DD</sub> , typical (nA)	Battery backup	Timestamp, tamper input	AEC-Q100 compliant	Special features	Packages
PCF8563	X	1	I <sup>2</sup> C	250	-	-	-	-	SO8, TSSOP8, HVSON10
PCF8564A	X	1	I <sup>2</sup> C	250	-	-	-	integrated oscillator caps	WLCSP
PCA8565	X	1	I <sup>2</sup> C	600	-	-	grade 1	high robustness, T <sub>amb</sub> = -40 °C to 125 °C	TSSOP8, HVSON10
PCA8565A	X	1	I <sup>2</sup> C	600	-	-	-	integrated oscillator caps, T <sub>amb</sub> = -40 °C to 125 °C	WLCSP
PCF85063	-	1	I <sup>2</sup> C	220	-	-	-	basic functions only, no alarm	HXSON8
PCF85063A	X	1	I <sup>2</sup> C	220	-	-	-	tiny package	SO8, DFN2626-10
PCF85063B	X	1	SPI	220	-	-	-	tiny package	DFN2626-10
PCF85263A	X	2	I <sup>2</sup> C	230	X	X	-	time stamp, battery backup, stopwatch 1/100 s	SO8, TSSOP10, TSSOP8, DFN2626-10
PCF85263B	X	2	SPI	230	X	X	-	time stamp, battery backup, stopwatch 1/100s	TSSOP10, DFN2626-10
PCF85363A	X	2	I <sup>2</sup> C	230	X	X	-	time stamp, battery backup, stopwatch 1/100s, 64 Byte RAM	TSSOP10, DFN2626-10
PCF85363B	X	2	SPI	230	X	X	-	time stamp, battery backup, stopwatch 1/100s, 64 Byte RAM	TSSOP10, DFN2626-10
PCF8523	X	2	I <sup>2</sup> C	150	X	-	-	lowest power 150 nA in operation, FM+ 1 MHz	SO8, HVSON8, TSSOP14, WLCSP
PCF2123	X	1	SPI	100	-	-	-	lowest power 100 nA in operation	TSSOP14, HVQFN16
PCF2127	X	1	I <sup>2</sup> C and SPI	500	X	X	-	temperature compensated, quartz built in, calibrated, 512 Byte RAM	SO16

Table 46. Selection of Real-Time Clocks ...continued

Type name	Alarm, Timer, Watchdog	Interrupt output	Interface	I <sub>DD</sub> , typical (nA)	Battery backup	Timestamp, tamper input	AEC-Q100 compliant	Special features	Packages
PCF2127A	X	1	I <sup>2</sup> C and SPI	500	X	X	-	temperature compensated, quartz built in, calibrated, 512 Byte RAM	SO20
PCF2129	X	1	I <sup>2</sup> C and SPI	500	X	X	-	temperature compensated, quartz built in, calibrated	SO16
PCF2129A	X	1	I <sup>2</sup> C and SPI	500	X	X	-	temperature compensated, quartz built in, calibrated	SO20
PCA2129	X	1	I <sup>2</sup> C and SPI	500	X	X	grade 3	temperature compensated, quartz built in, calibrated	SO16
PCA21125	X	1	SPI	820	-	-	grade 1	high robustness, T <sub>amb</sub> = -40 °C to 125 °C	TSSOP14

## 21. Abbreviations

Table 47. Abbreviations

Acronym	Description
AEC	Automotive Electronics Council
AM	Ante Meridiem
BCD	Binary Coded Decimal
CDM	Charged-Device Model
CMOS	Complementary Metal Oxide Semiconductor
HBM	Human Body Model
IC	Integrated Circuit
MM	Machine Model
MOS	Metal Oxide Semiconductor
MSB	Most Significant Bit
MSL	Moisture Sensitivity Level
PCB	Printed-Circuit Board
PM	Post Meridiem
POR	Power-On Reset
RC	Resistance-Capacitance
RTC	Real-Time Clock
SMD	Surface Mount Device
SPI	Serial Peripheral Interface

## 22. References

- [1] **AN10365** — Surface mount reflow soldering description
- [2] **IEC 60134** — Rating systems for electronic tubes and valves and analogous semiconductor devices
- [3] **IEC 61340-5** — Protection of electronic devices from electrostatic phenomena
- [4] **IPC/JEDEC J-STD-020D** — Moisture/Reflow Sensitivity Classification for Nonhermetic Solid State Surface Mount Devices
- [5] **JESD22-A114** — Electrostatic Discharge (ESD) Sensitivity Testing Human Body Model (HBM)
- [6] **JESD22-A115** — Electrostatic Discharge (ESD) Sensitivity Testing Machine Model (MM)
- [7] **JESD22-C101** — Field-Induced Charged-Device Model Test Method for Electrostatic-Discharge-Withstand Thresholds of Microelectronic Components
- [8] **JESD78** — IC Latch-Up Test
- [9] **JESD625-A** — Requirements for Handling Electrostatic-Discharge-Sensitive (ESDS) Devices
- [10] **SOT402-1\_118** — TSSOP14; Reel pack; SMD, 13", packing information
- [11] **UM10569** — Store and transport requirements

## 23. Revision history

Table 48. Revision history

Document ID	Release date	Data sheet status	Change notice	Supersedes
PCA21125 v.2	20141125	Product data sheet	-	PCA21125 v.1
Modifications:	<ul style="list-style-type: none"><li>• The format of this data sheet has been redesigned to comply with the new identity guidelines of NXP Semiconductors.</li><li>• Legal texts have been adapted to the new company name where appropriate.</li><li>• Corrected delay time of first increment of the time circuits</li><li>• Added C<sub>OSCO</sub> value in <a href="#">Table 42</a></li><li>• Added <a href="#">Section 18.1</a> and <a href="#">Section 20.1</a></li><li>• Fixed typos</li></ul>			
PCA21125 v.1	20091116	Product data sheet	-	-

## 24. Legal information

### 24.1 Data sheet status

Document status <sup>[1][2]</sup>	Product status <sup>[3]</sup>	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

[1] Please consult the most recently issued document before initiating or completing a design.

[2] The term 'short data sheet' is explained in section "Definitions".

[3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL <http://www.nxp.com>.

### 24.2 Definitions

**Draft** — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

**Short data sheet** — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

**Product specification** — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

### 24.3 Disclaimers

**Limited warranty and liability** — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. NXP Semiconductors takes no responsibility for the content in this document if provided by an information source outside of NXP Semiconductors.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

**Right to make changes** — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

**Suitability for use in automotive applications** — This NXP Semiconductors product has been qualified for use in automotive applications. Unless otherwise agreed in writing, the product is not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors and its suppliers accept no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

**Applications** — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

**Limiting values** — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

**Terms and conditions of commercial sale** — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at <http://www.nxp.com/profile/terms>, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

**No offer to sell or license** — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

**Export control** — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

**Translations** — A non-English (translated) version of a document is for reference only. The English version shall prevail in case of any discrepancy between the translated and English versions.

## 24.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

## 25. Contact information

---

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: [salesaddresses@nxp.com](mailto:salesaddresses@nxp.com)

## 26. Tables

Table 1.	Ordering information	2	Table 37.	Example: first increment of time circuits after STOP release	24
Table 2.	Ordering options	2	Table 38.	Register reset values	26
Table 3.	Marking codes	2	Table 39.	Serial interface	27
Table 4.	Pin description	4	Table 40.	Command byte definition	28
Table 5.	Register overview	6	Table 41.	Limiting values	31
Table 6.	Control_1 - control and status register 1 (address 00h) bit description	7	Table 42.	Static characteristics	32
Table 7.	Control_2 - control and status register 2 (address 01h) bit description	7	Table 43.	Dynamic characteristics	34
Table 8.	Seconds - seconds and clock integrity status register (address 02h) bit description	8	Table 44.	SnPb eutectic process (from J-STD-020D)	39
Table 9.	Seconds coded in BCD format	8	Table 45.	Lead-free process (from J-STD-020D)	39
Table 10.	Minutes - minutes register (address 03h) bit description	8	Table 46.	Selection of Real-Time Clocks	41
Table 11.	Hours - hours register (address 04h) bit description	9	Table 47.	Abbreviations	43
Table 12.	Days - days register (address 05h) bit description	9	Table 48.	Revision history	44
Table 13.	Weekdays - weekdays register (address 06h) bit description	9			
Table 14.	Weekday assignments	9			
Table 15.	Months - months register (address 07h) bit description	10			
Table 16.	Month assignments in BCD format	10			
Table 17.	Years - years register (08h) bit description	10			
Table 18.	Minute_alarm - minute alarm register (address 09h) bit description	12			
Table 19.	Hour_alarm - hour alarm register (address 0Ah) bit description	12			
Table 20.	Day_alarm - day alarm register (address 0Bh) bit description	13			
Table 21.	Weekday_alarm - weekday alarm register (address 0Ch) bit description	13			
Table 22.	Flag location in register Control_2	14			
Table 23.	Example to clear only AF (bit 3) in register Control_2	14			
Table 24.	CLKOUT_control - CLKOUT control register (address 0Dh) bit description	15			
Table 25.	CLKOUT frequency selection	15			
Table 26.	Timer_control - timer control register (address 0Eh) bit description	16			
Table 27.	Countdown_timer - countdown timer register (address 0Fh) bit description	16			
Table 28.	Effect of bits MI and SI on INT generation	16			
Table 29.	Effect of bits MI and SI on bit MSF	16			
Table 30.	CTD[1:0] for timer frequency selection and countdown timer durations	17			
Table 31.	First period delay for timer counter value T	18			
Table 32.	Flag location in register Control_2	19			
Table 33.	Example to clear only TF (bit 2) in register Control_2	19			
Table 34.	Example to clear only MSF (bit 5) in register Control_2	19			
Table 35.	Example to clear both TF and MSF (bits 2 and 5) in register Control_2	19			
Table 36.	INT operation (bit TI_TP = 1)	21			

## 27. Figures

Fig 1.	Block diagram of PCA21125	3
Fig 2.	Pin configuration for TSSOP14	4
Fig 3.	Data flow of the time function.	11
Fig 4.	Access time for read/write operations	11
Fig 5.	Alarm function block diagram.	13
Fig 6.	Alarm flag timing	14
Fig 7.	$\overline{\text{INT}}$ example for bits SI and MI	17
Fig 8.	General countdown timer behavior	18
Fig 9.	Interrupt scheme	20
Fig 10.	Example of shortening the $\overline{\text{INT}}$ pulse by clearing the MSF flag	21
Fig 11.	Example of shortening the $\overline{\text{INT}}$ pulse by clearing the TF flag	22
Fig 12.	AF timing	22
Fig 13.	STOP bit functional diagram	23
Fig 14.	STOP bit release timing	24
Fig 15.	Reset system	25
Fig 16.	Power-On Reset (POR)	25
Fig 17.	POR override sequence	26
Fig 18.	SDI, SDO configurations	27
Fig 19.	Data transfer overview	27
Fig 20.	Command byte	28
Fig 21.	Serial bus write example	28
Fig 22.	Serial bus read example	29
Fig 23.	Interface watchdog timer	29
Fig 24.	Device diode protection diagram	30
Fig 25.	SPI interface timing	35
Fig 26.	Application diagram	36
Fig 27.	Package outline SOT402-1 (TSSOP14)	37
Fig 28.	Temperature profiles for large and small components	40



## 28. Contents

<b>1</b>	<b>General description</b> . . . . .	<b>1</b>	<b>10</b>	<b>Safety notes</b> . . . . .	<b>30</b>
<b>2</b>	<b>Features and benefits</b> . . . . .	<b>1</b>	<b>11</b>	<b>Limiting values</b> . . . . .	<b>31</b>
<b>3</b>	<b>Applications</b> . . . . .	<b>1</b>	<b>12</b>	<b>Static characteristics</b> . . . . .	<b>32</b>
<b>4</b>	<b>Ordering information</b> . . . . .	<b>2</b>	<b>13</b>	<b>Dynamic characteristics</b> . . . . .	<b>34</b>
4.1	Ordering options . . . . .	2	<b>14</b>	<b>Application information</b> . . . . .	<b>36</b>
<b>5</b>	<b>Marking</b> . . . . .	<b>2</b>	14.1	Application diagram . . . . .	36
<b>6</b>	<b>Block diagram</b> . . . . .	<b>3</b>	14.2	Quartz frequency adjustment . . . . .	36
<b>7</b>	<b>Pinning information</b> . . . . .	<b>4</b>	<b>15</b>	<b>Test information</b> . . . . .	<b>36</b>
7.1	Pinning . . . . .	4	15.1	Quality information . . . . .	36
7.2	Pin description . . . . .	4	<b>16</b>	<b>Package outline</b> . . . . .	<b>37</b>
<b>8</b>	<b>Functional description</b> . . . . .	<b>5</b>	<b>17</b>	<b>Handling information</b> . . . . .	<b>38</b>
8.1	Register overview . . . . .	6	<b>18</b>	<b>Packing information</b> . . . . .	<b>38</b>
8.2	Control and status registers . . . . .	7	18.1	Tape and reel information . . . . .	38
8.2.1	Register Control_1 . . . . .	7	<b>19</b>	<b>Soldering of SMD packages</b> . . . . .	<b>38</b>
8.2.2	Register Control_2 . . . . .	7	19.1	Introduction to soldering . . . . .	38
8.3	Time and date registers . . . . .	8	19.2	Wave and reflow soldering . . . . .	38
8.3.1	Register Seconds . . . . .	8	19.3	Wave soldering . . . . .	39
8.3.2	Register Minutes . . . . .	8	19.4	Reflow soldering . . . . .	39
8.3.3	Register Hours . . . . .	9	<b>20</b>	<b>Appendix</b> . . . . .	<b>41</b>
8.3.4	Register Days . . . . .	9	20.1	Real-Time Clock selection . . . . .	41
8.3.5	Register Weekdays . . . . .	9	<b>21</b>	<b>Abbreviations</b> . . . . .	<b>43</b>
8.3.6	Register Months . . . . .	10	<b>22</b>	<b>References</b> . . . . .	<b>43</b>
8.3.7	Register Years . . . . .	10	<b>23</b>	<b>Revision history</b> . . . . .	<b>44</b>
8.3.8	Setting and reading the time . . . . .	11	<b>24</b>	<b>Legal information</b> . . . . .	<b>45</b>
8.4	Alarm registers . . . . .	12	24.1	Data sheet status . . . . .	45
8.4.1	Register Minute_alarm . . . . .	12	24.2	Definitions . . . . .	45
8.4.2	Register Hour_alarm . . . . .	12	24.3	Disclaimers . . . . .	45
8.4.3	Register Day_alarm . . . . .	13	24.4	Trademarks . . . . .	46
8.4.4	Register Weekday_alarm . . . . .	13	<b>25</b>	<b>Contact information</b> . . . . .	<b>46</b>
8.4.5	Alarm flag . . . . .	13	<b>26</b>	<b>Tables</b> . . . . .	<b>47</b>
8.5	Register CLKOUT_control and clock output . . . . .	15	<b>27</b>	<b>Figures</b> . . . . .	<b>48</b>
8.6	Timer registers . . . . .	15	<b>28</b>	<b>Contents</b> . . . . .	<b>49</b>
8.6.1	Second and minute interrupt . . . . .	16			
8.6.2	Countdown timer function . . . . .	17			
8.6.3	Timer flags . . . . .	19			
8.7	Interrupt output . . . . .	20			
8.7.1	Minute and second interrupts . . . . .	20			
8.7.2	Countdown timer interrupts . . . . .	21			
8.7.3	Alarm interrupts . . . . .	22			
8.8	External clock test mode . . . . .	22			
8.9	STOP bit function . . . . .	23			
8.10	Reset . . . . .	25			
8.10.1	POR override . . . . .	26			
8.11	4-line SPI-bus . . . . .	27			
8.11.1	Interface watchdog timer . . . . .	29			
<b>9</b>	<b>Internal circuitry</b> . . . . .	<b>30</b>			

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP Semiconductors N.V. 2014.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: [salesaddresses@nxp.com](mailto:salesaddresses@nxp.com)

Date of release: 25 November 2014

Document identifier: PCA21125



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.