

RELIABILITY REPORT  
FOR

**DS1961S**

**Dallas Semiconductor**

4401 South Beltwood Parkway  
Dallas, TX 75244-3292

Prepared by:



Ken Wendel  
Reliability Engineering Manager  
Dallas Semiconductor  
4401 South Beltwood Pkwy.  
Dallas, TX 75244-3292  
Email : ken.wendel@dalsemi.com  
ph: 972-371-3726  
fax: 972-371-6016  
mbl: 214-435-6610

**Conclusion:**

The following qualification successfully meets the quality and reliability standards required of all Dallas Semiconductor products and processes:

DS1961S

In addition, Dallas Semiconductor's continuous reliability monitor program ensures that all outgoing product will continue to meet Maxim's quality and reliability standards. The current status of the reliability monitor program can be viewed at <http://www.maxim-ic.com/TechSupport/dsreliability.html>.\*

**Module Description:**

A description of this Module can be found in the product data sheet. You can find the product data sheet at [http://dbserv.maxim-ic.com/l\\_datasheet3.cfm](http://dbserv.maxim-ic.com/l_datasheet3.cfm).\*

**Reliability Derating:**

A module device consists of one or more IC's in a single, upward integrated, package. This package is assembled to include batteries, crystals, and other piece parts that make up the configuration of the Module. Because of either the complexity of the package or the included piece parts, standard high temperature reliability testing is not possible. Therefore, in order to determine the reliability of module products, the reliability of each of the piece parts is individually determined, then summed to determine the reliability of the integrated module product. If there are "n" significant components in the module then:

$$Fr(\text{module}) = Fr(1) + Fr(2) + Fr(3) + \dots + Fr(n)$$

Fr (module) = Failure rate of module

Fr(n) = Failure rate of the nth component

Failure Rates are reported in FITs (Failures in Time) or MTTF (Mean Time To Failure). The FIT rate is related to MTTF by:

$$MTTF = 1/Fr$$

NOTE: MTTF is frequently used interchangeably with MTBF.

The calculated failure rate for this module/assembly is:

| <u>Module Device:</u> | <u>Quantity:</u> | <u>MTTF (Yrs):</u> | <u>FITs:</u> |
|-----------------------|------------------|--------------------|--------------|
| DS1961                | 1                | <u>18096</u>       | <u>6.3</u>   |
| <b>Totals:</b>        |                  | <b>18096</b>       | <b>6.3</b>   |

The parameters used to calculate the module failure rate are as follows:

Cf: 60%      Ea: 0.7      B: 0      Tu: 25 °C      Vu: 5.5 Volts

The reliability data follows. At the start of this data is the module assembly information. This is a description of the module. The next section is the detailed reliability data for each stress found in the qualification / monitor. If there are additional processes or assemblies used as part of this report, a description of each will follow which includes the respective reliability data for that process/ assembly. The reliability data section includes the latest data available. Some of this data may be generic with other packages or products.

\* Some proprietary products may be excepted from this requirement.

---

#### Assembly Information:

|                  |                                |
|------------------|--------------------------------|
| Assembly Site:   | Fastech                        |
| Pin Count:       | 2                              |
| Package Type:    | iButton F50                    |
| Body Size:       | 16.25mm                        |
| Glob Top:        | FP4323, Dexter Hysol           |
| Lead Frame:      | PCB; FR4                       |
| Lead Finsh:      | Stainless Steel                |
| Die Attach:      | Underfill FP4527, Dexter Hysol |
| Flammability:    | UL 94-V0                       |
| Date Code Range: | 0230 to 0303                   |

---

#### ELECTRICAL CHARACTERIZATION

| DESCRIPTION     | DATE CODE | CONDITION                       | READPOINT | QUANTITY | FAILS |
|-----------------|-----------|---------------------------------|-----------|----------|-------|
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 CONTACT 2000 VOLTS | 10 PUL'S  | 3        | 0     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 CONTACT 4000 VOLTS | 10 PUL'S  | 3        | 0     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 CONTACT 8000 VOLTS | 10 PUL'S  | 3        | 0     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 AIR 8000 VOLTS     | 10 PUL'S  | 3        | 0     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 AIR 10000 VOLTS    | 10 PUL'S  | 3        | 0     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 AIR 15000 VOLTS    | 10 PUL'S  | 3        | 3     |
| ESD SENSITIVITY | 0230      | IEC 1000-4-2 AIR 20000 VOLTS    | 10 PUL'S  | 3        | 3     |
| Total:          |           |                                 |           |          | 6     |

---

#### OPERATING LIFE

| DESCRIPTION       | DATE CODE | CONDITION       | READPOINT | QUANTITY | FAILS |
|-------------------|-----------|-----------------|-----------|----------|-------|
| HIGH VOLTAGE LIFE | 0230      | 125C, 6.0 VOLTS | 1000 HRS  | 77       | 0     |
| HIGH VOLTAGE LIFE | 0303      | 125C, 6.0 VOLTS | 1000 HRS  | 77       | 0     |
| Total:            |           |                 |           |          | 0     |

---

#### TEMPERATURE CYCLE

| DESCRIPTION | DATE CODE | CONDITION    | READPOINT | QUANTITY | FAILS |
|-------------|-----------|--------------|-----------|----------|-------|
| TEMP CYCLE  | 0240      | -55C TO 125C | 1000 CYS  | 77       | 0     |
| TEMP CYCLE  | 0240      | -55C TO 125C | 1000 CYS  | 77       | 0     |
| Total:      |           |              |           |          | 0     |

---

#### W/E ENDURANCE AND DATA RET'N

| DESCRIPTION | DATE CODE | CONDITION | READPOINT | QUANTITY | FAILS |
|-------------|-----------|-----------|-----------|----------|-------|
|-------------|-----------|-----------|-----------|----------|-------|

|                    |      |                   |      |      |    |          |
|--------------------|------|-------------------|------|------|----|----------|
| WRITE CYCLE STRESS | 0230 | 85 C , 5.25 VOLTS | 50   | KCYS | 77 | 1        |
| STORAGE LIFE       |      | 150C              | 1000 | HRS  | 66 | 0        |
| WRITE CYCLE STRESS | 0303 | 85 C , 5.25 VOLTS | 20   | KCYS | 77 | 0        |
| STORAGE LIFE       |      | 150C              | 1000 | HRS  | 77 | 0        |
| WRITE CYCLE STRESS | 0303 | 85 C , 5.25 VOLTS | 50   | KCYS | 77 | 0        |
| STORAGE LIFE       |      | 150C              | 1000 | HRS  | 77 | 2        |
| WRITE CYCLE STRESS | 0303 | 25 C, 5.25 VOLTS  | 50   | KCYS | 77 | 0        |
| STORAGE LIFE       |      | 150C              | 1000 | HRS  | 77 | 0        |
| WRITE CYCLE STRESS | 0303 | 25 C, 5.25 VOLTS  | 40   | KCYS | 77 | 0        |
| STORAGE LIFE       |      | 150C              | 1000 | HRS  | 77 | 1        |
| <b>Total:</b>      |      |                   |      |      |    | <b>4</b> |



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.