



Low Noise, Precision, 16 V, CMOS, Rail-to-Rail Operational Amplifiers

AD8663/AD8667/AD8669

FEATURES

Low offset voltage: 175 μ V maximum @ $V_{SY} = 5$ V
Low supply current: 275 μ A maximum per amplifier
Single-supply operation: 5 V to 16 V
Low noise: 23 nV/ $\sqrt{\text{Hz}}$
Low input bias current: 300 fA
Unity-gain stable
Small packages available
 3 mm $\times$ 3 mm, 8-lead LFCSP
 8-lead MSOP

APPLICATIONS

Sensor front ends
Transimpedance amps
Electrometer applications
Photodiode amplification
Low power ADC drivers
Medical diagnostic instruments
pH and ORP meters and probes
DAC or REF buffers

GENERAL DESCRIPTION

The AD866x are rail-to-rail output amplifiers that use the Analog Devices, Inc., patented DigiTrim[®] trimming technique to achieve low offset voltage. The AD866x feature an extended operating range with supply voltages up to 16 V. They also feature low input bias current, low input offset voltage, and low current noise.

The combination of low offset, very low input bias current, and a wide supply range makes these amplifiers useful in a wide variety of applications usually associated with higher priced JFET amplifiers. Systems using high impedance sensors, such as photodiodes, benefit from the combination of low input bias current, low noise, low offset, and wide bandwidth.

The ability to operate the device for single (5 V to 16 V) or dual supplies (± 2.5 V to ± 8 V) supports many applications. The rail-to-rail outputs provide increased dynamic range to drive low frequency data converters. The low bias current drift is well

PIN CONFIGURATIONS




Figure 1. 8-Lead SOIC (R-8)




Figure 2. 8-Lead LFCSP (CP-8-2)




Figure 3. 8-Lead MSOP (RM-8),
8-Lead SOIC (R-8)




Figure 4. 14-Lead SOIC (R-14)

suited for precision I-to-V converters. The combination of precision offset, offset drift, and low noise also make the op amps ideal for gain, dc offset adjust, and active filter in both instrumentation and medical applications. These low power op amps can be used in IR thermometers, pH and ORP instruments, pressure transducer front ends, and other sensor signal conditioning circuits that are used in remote or wireless applications.

The AD8663/AD8667/AD8669 are specified over the extended industrial temperature range of -40°C to $+125^{\circ}\text{C}$. The single AD8663 is available in a narrow 8-lead SOIC package and a very thin, 8-lead LFCSP. The dual AD8667 is available in a narrow 8-lead SOIC package and an 8-lead MSOP. The quad AD8669 is available in a 14-lead SOIC package.

Rev. A

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781.329.4700
Fax: 781.461.3113
www.analog.com
©2007 Analog Devices, Inc. All rights reserved.

TABLE OF CONTENTS

Features	1	Absolute Maximum Ratings	5
Applications	1	Thermal Resistance	5
Pin Configurations	1	ESD Caution.....	5
General Description	1	Typical Performance Characteristics	6
Revision History	2	Outline Dimensions	13
Specifications.....	3	Ordering Guide	15
AD8663/AD8667/AD8669 Electrical Characteristics.....	3		

REVISION HISTORY

10/07—Rev. 0 to Rev. A

Added AD8667 and AD8669	Universal
Changes to Features.....	1
Changes to General Description	1
Inserted Figure 3 and Figure 4	1
Changes to Table 1, Power Supply Section.....	3
Changes to Table 2.....	4
Reformatted Typical Performance Characteristics Section	6
Changes to Figure 5.....	6
Changes to Figure 13.....	7
Changes to Figure 17 and Figure 20.....	8
Inserted Figure 35 Through Figure 39.....	11
Inserted Figure 40 and Figure 41.....	12
Updated Outline Dimensions	13
Changes to Ordering Guide	15

7/07—Revision 0: Initial Version

SPECIFICATIONS

AD8663/AD8667/AD8669 ELECTRICAL CHARACTERISTICS

$V_{SY} = 5.0\text{ V}$, $V_{CM} = V_{SY}/2$, $T_A = 25^\circ\text{C}$, unless otherwise noted.

Table 1.

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
INPUT CHARACTERISTICS						
Offset Voltage	V _{OS}	V _{CM} = V _{SY} /2 −40°C < T _A < +125°C		30	175 450	μV μV
Input Bias Current	I _B	−40°C < T _A < +85°C −40°C < T _A < +125°C		0.3	45 105	pA pA
Input Offset Current	I _{OS}	−40°C < T _A < +85°C −40°C < T _A < +125°C		0.2	35 65	pA pA
Input Voltage Range			0.2		3.0	V
Common-Mode Rejection Ratio	CMRR	V _{CM} = 0.2 V to 3.0 V −40°C < T _A < +125°C	76 76	100 100		dB dB
Large Signal Voltage Gain	A _{VO}	R _L = 100 kΩ, V _{OUT} = 0.5 V to 4.5 V R _L = 2 kΩ, V _{OUT} = 0.5 V to 4.5 V	115 106	140 114		dB dB
Offset Voltage Drift	TCV _{OS}	−40°C < T _A < +125°C		1.5	5	μV/°C
OUTPUT CHARACTERISTICS						
Output Voltage High	V _{OH}	I _L = 100 μA −40°C < T _A < +125°C	4.95 4.90	4.97		V V
Output Voltage High	V _{OH}	I _L = 1 mA −40°C < T _A < +125°C	4.65 4.60	4.80		V V
Output Voltage Low	V _{OL}	I _L = 100 μA −40°C < T _A < +125°C		17	25 35	mV mV
Output Voltage Low	V _{OL}	I _L = 1 mA −40°C < T _A < +125°C		150	200 250	mV mV
Short-Circuit Current	I _{SC}			±7		mA
Closed-Loop Output Impedance	Z _{OUT}	f = 100 kHz, A _V = 1		120		Ω
POWER SUPPLY						
Power Supply Rejection Ratio	PSRR	V _{SY} = 5 V to 16 V −40°C < T _A < +125°C	95 95	105		dB dB
Supply Current per Amplifier	I _{SY}	V _{OUT} = V _{SY} /2 −40°C < T _A < +125°C		210	275 325	μA μA
DYNAMIC PERFORMANCE						
Slew Rate	SR	R _L = 2 kΩ		0.26		V/μs
Gain Bandwidth Product	GBP	C _L = 20 pF		520		kHz
Phase Margin	Φ _M	C _L = 20 pF		60		Degrees
NOISE PERFORMANCE						
Peak-to-Peak Noise	e _n p-p	f = 0.1 Hz to 10 Hz		2.5		μV p-p
Voltage Noise Density	e _n	f = 1 kHz f = 10 kHz		23 21		nV/√Hz nV/√Hz
Current Noise Density	i _n	f = 1 kHz		0.05		pA/√Hz

AD8663/AD8667/AD8669

$V_{SY} = 16.0 \text{ V}$, $V_{CM} = V_{SY}/2$, $T_A = 25^\circ\text{C}$, unless otherwise noted.

Table 2.

Parameter	Symbol	Conditions	Min	Typ	Max	Unit
INPUT CHARACTERISTICS						
Offset Voltage	V_{OS}	$V_{CM} = V_{SY}/2$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$		40	300	μV
Input Bias Current	I_B			0.3	500	μV pA
		$-40^\circ\text{C} < T_A < +85^\circ\text{C}$			45	pA
Input Offset Current	I_{OS}	$-40^\circ\text{C} < T_A < +125^\circ\text{C}$			120	pA
		$-40^\circ\text{C} < T_A < +85^\circ\text{C}$		0.2		pA
		$-40^\circ\text{C} < T_A < +125^\circ\text{C}$			35	pA
Input Voltage Range			0.2		65	pA
Common-Mode Rejection Ratio	CMRR	$V_{CM} = 0.2 \text{ V to } 14.5 \text{ V}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$	87	109	14.5	V dB
Large Signal Voltage Gain	A_{VO}	$R_L = 100 \text{ k}\Omega$, $V_{OUT} = 0.5 \text{ V to } 15.5 \text{ V}$	87	109		dB
		$R_L = 2 \text{ k}\Omega$, $V_{OUT} = 0.5 \text{ V to } 15.5 \text{ V}$	115	140		dB
Offset Voltage Drift	TCV_{OS}	$-40^\circ\text{C} < T_A < +125^\circ\text{C}$	106	111		dB $\mu\text{V}/^\circ\text{C}$
OUTPUT CHARACTERISTICS						
Output Voltage High	V_{OH}	$I_L = 100 \mu\text{A}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$	15.95	15.98		V
			15.90			V
Output Voltage High	V_{OH}	$I_L = 1 \text{ mA}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$	15.85	15.92		V
			15.80			V
Output Voltage Low	V_{OL}	$I_L = 100 \mu\text{A}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$		17	25	mV
					35	mV
Output Voltage Low	V_{OL}	$I_L = 1 \text{ mA}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$		70	100	mV
					125	mV
Short-Circuit Current	I_{SC}			± 50		mA
Closed-Loop Output Impedance	Z_{OUT}	$f = 100 \text{ kHz}$, $A_v = 1$		100		Ω
POWER SUPPLY						
Power Supply Rejection Ratio	PSRR	$V_{SY} = 5 \text{ V to } 16 \text{ V}$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$	95	105		dB
			95			dB
Supply Current per Amplifier	I_{SY}	$V_{OUT} = V_{SY}/2$ $-40^\circ\text{C} < T_A < +125^\circ\text{C}$		230	285	μA
					355	μA
DYNAMIC PERFORMANCE						
Slew Rate	SR	$R_L = 2 \text{ k}\Omega$		0.3		$\text{V}/\mu\text{s}$
Gain Bandwidth Product	GBP	$C_L = 20 \text{ pF}$		540		kHz
Phase Margin	Φ_M	$C_L = 20 \text{ pF}$		64		Degrees
NOISE PERFORMANCE						
Peak-to-Peak Noise	$e_n \text{ p-p}$	$f = 0.1 \text{ Hz to } 10 \text{ Hz}$		2.5		$\mu\text{V p-p}$
Voltage Noise Density	e_n	$f = 1 \text{ kHz}$		23		$\text{nV}/\sqrt{\text{Hz}}$
		$f = 10 \text{ kHz}$		21		$\text{nV}/\sqrt{\text{Hz}}$
Current Noise Density	i_n	$f = 1 \text{ kHz}$		0.05		$\text{pA}/\sqrt{\text{Hz}}$

ABSOLUTE MAXIMUM RATINGS

Table 3.

Parameter	Rating
Supply Voltage	18 V
Input Voltage	−0.1 V to V_{SY}
Differential Input Voltage	18 V
Output Short-Circuit Duration to GND	Indefinite
Storage Temperature Range	−60°C to +150°C
Operating Temperature Range	−40°C to +125°C
Junction Temperature Range	−65°C to +150°C
Lead Temperature, Soldering (60 sec)	300°C

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the operational section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

THERMAL RESISTANCE

θ_{JA} is specified for the worst-case conditions, that is, a device soldered in a circuit board for surface-mount packages.

Table 4. Thermal Resistance

Package Type	θ_{JA}	θ_{JC}	Unit
8-Lead SOIC (R-8)	121	43	°C/W
8-Lead LFCSP (CP-8-2)	75 ¹	18 ¹	°C/W
8-Lead MSOP (RM-8)	145	45	°C/W
14-Lead SOIC (R-14)	90	45	°C/W

¹ Exposed pad soldered to application board.

ESD CAUTION



ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore, proper ESD precautions should be taken to avoid performance degradation or loss of functionality.

TYPICAL PERFORMANCE CHARACTERISTICS




Figure 5. Input Offset Voltage Distribution




Figure 8. Input Offset Voltage Distribution




Figure 6. Offset Voltage Drift Distribution




Figure 9. Offset Voltage Drift Distribution




Figure 7. Input Offset Voltage vs. Common-Mode Voltage




Figure 10. Input Offset Voltage vs. Common-Mode Voltage




Figure 11. Input Bias Current vs. Common-Mode Voltage at 125°C




Figure 14. Input Bias Current vs. Common-Mode Voltage at 125°C




Figure 12. CMRR vs. Frequency, $V_{SY} = 5\text{ V}$




Figure 15. CMRR vs. Frequency, $V_{SY} = 16\text{ V}$




Figure 13. Output Swing Saturation Voltage vs. Load Current




Figure 16. Output Swing Saturation Voltage vs. Load Current




Figure 17. Output Voltage Saturation vs. Temperature




Figure 20. Output Voltage Saturation vs. Temperature




Figure 18. Open-Loop Gain and Phase Shift vs. Frequency




Figure 21. Open-Loop Gain and Phase Shift vs. Frequency




Figure 19. Closed-Loop Gain vs. Frequency




Figure 22. Closed-Loop Gain vs. Frequency, $V_{SY} = 16V$




Figure 23. Closed-Loop Output Impedance vs. Frequency, $V_{SY} = 5 V$




Figure 26. Closed-Loop Output Impedance vs. Frequency, $V_{SY} = 16 V$




Figure 24. PSRR vs. Frequency, $V_{SY} = 5 V$




Figure 27. PSRR vs. Frequency, $V_{SY} = 16 V$




Figure 25. Small-Signal Overshoot vs. Load Capacitance, $V_{SY} = 5 V$




Figure 28. Small-Signal Overshoot vs. Load Capacitance, $V_{SY} = 16 V$

AD8663/AD8667/AD8669




Figure 29. Large Signal Transient Response, $V_{SV} = \pm 2.5\text{ V}$




Figure 32. Large Signal Transient Response, $V_{SV} = \pm 8\text{ V}$




Figure 30. Small Signal Transient Response, $V_{SV} = \pm 2.5\text{ V}$




Figure 33. Small Signal Transient Response, $V_{SV} = \pm 8\text{ V}$




Figure 31. Supply Current vs. Supply Voltage AD8663




Figure 34. Supply Current vs. Supply Voltage AD8669




Figure 35. Supply Current vs. Supply Voltage AD8667




Figure 38. Voltage Noise Density




Figure 36. Positive Overload Recovery




Figure 39. Positive Overload Recovery




Figure 37. Negative Overload Recovery




Figure 40. Negative Overload Recovery




Figure 41. Channel Separation vs. Frequency





Figure 42. Channel Separation vs. Frequency


OUTLINE DIMENSIONS



COMPLIANT TO JEDEC STANDARDS MS-012-AA
CONTROLLING DIMENSIONS ARE IN MILLIMETERS; INCH DIMENSIONS
(IN PARENTHESES) ARE ROUNDED-OFF MILLIMETER EQUIVALENTS FOR
REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN.


012407-A

Figure 43. 8-Lead Small Outline Package [SOIC_N]
Narrow Body
(R-8)
Dimensions shown in millimeters and (inches)



061507-B


Figure 44. 8-Lead Lead Frame Chip Scale Package [LFCSP_VD]
3 mm x 3 mm Body, Very Thin, Dual Lead
(CP-8-2)
Dimensions shown in millimeters



COMPLIANT TO JEDEC STANDARDS MO-187-AA

Figure 45. 8-Lead Mini Small Outline Package [MSOP]
(RM-8)

Dimensions shown in millimeters



COMPLIANT TO JEDEC STANDARDS MS-012-AB

CONTROLLING DIMENSIONS ARE IN MILLIMETERS; INCH DIMENSIONS
(IN PARENTHESES) ARE ROUNDED-OFF MILLIMETER EQUIVALENTS FOR
REFERENCE ONLY AND ARE NOT APPROPRIATE FOR USE IN DESIGN.

Figure 46. 14-Lead Small Outline Package [SOIC_N]
Narrow Body
(R-14)

Dimensions shown in millimeters

060606-A

ORDERING GUIDE

Model	Temperature Range	Package Description	Package Option	Branding
AD8663ARZ ¹	–40°C to +125°C	8-Lead SOIC_N	R-8	A1U
AD8663ARZ-REEL ¹	–40°C to +125°C	8-Lead SOIC_N	R-8	
AD8663ARZ-REEL7 ¹	–40°C to +125°C	8-Lead SOIC_N	R-8	
AD8663ACPZ-R2 ¹	–40°C to +125°C	8-Lead LFCSP_VD	CP-8-2	
AD8663ACPZ-REEL ¹	–40°C to +125°C	8-Lead LFCSP_VD	CP-8-2	
AD8663ACPZ-REEL7 ¹	–40°C to +125°C	8-Lead LFCSP_VD	CP-8-2	
AD8667ARZ ¹	–40°C to +125°C	8-Lead MSOP	R-8	A1E
AD8667ARZ-REEL ¹	–40°C to +125°C	8-Lead MSOP	R-8	
AD8667ARZ-REEL7 ¹	–40°C to +125°C	8-Lead MSOP	R-8	
AD8667ARMZ-R2 ¹	–40°C to +125°C	8-Lead MSOP	RM-8	
AD8667ARMZ-REEL ¹	–40°C to +125°C	8-Lead MSOP	RM-8	
AD8669ARZ ¹	–40°C to +125°C	14-Lead SOIC_N	R-14	
AD8669ARZ-REEL ¹	–40°C to +125°C	14-Lead SOIC_N	R-14	
AD8669ARZ-REEL7 ¹	–40°C to +125°C	14-Lead SOIC_N	R-14	

¹ Z = RoHS Compliant Part.

NOTES



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.