TOSHIBA CMOS Linear Integrated Circuit Silicon Monolithic

TCR3UG series

Ultra low quiescent current, Fast Load Transient 300 mA CMOS Low Drop-Out Regulator in ultra small package

The TCR3UG series are CMOS general-purpose single-output voltage regulators with an on/off control input, featuring ultra low quiescent bias current and low dropout voltage.

These voltage regulators are available in fixed output voltages between 0.8 V and 5.0 V and capable of driving up to 300 mA. They feature Over-current protection, Thermal Shutdown function and Auto-discharge option.

The TCR3UG series is offered in the ultra small plastic mold package WCSP4F (0.645 mm x 0.645 mm; t 0.33 mm (max)) and has a low dropout voltage of 155 mV (3.3 V output, I_{OUT} = 300 mA). As small ceramic input and output capacitors 1 µF can be used with the TCR3UG series, these devices are ideal for portable applications that require high-density board assembly such as cellular phones, IoT equipment and wearable devices.



Weight: 0.26 mg (typ.)

Applications

Power IC developed for portable applications, IoT equipment and wearable devices

Features

- Ultra small package WCSP4F (0.645 mm x 0.645 mm; t 0.33 mm (max)).
- Low quiescent bias current (I_B = 0.34 µA (typ.) at I_{OUT} = 0 mA, output voltage up to 1.5 V)
- High ripple rejection ratio 70 dB at 0.8 V-output
- Fast load transient response ± 60 mV at 0.8 V-output, I_{OUT} = 1 mA ⇔ 50 mA
- Low dropout voltage
  V_{DO} =V_{IN}-V_{OUT} = 155 mV (typ.) at 3.3 V-output, I_{OUT} = 300 mA
- Wide range output voltage line up (V_{OUT} = 0.8 to 5.0 V)
- High V_{OUT} accuracy ± 1.0 % (1.8 V ≤ V_{OUT})
- Auto-discharge (TCR3UGxxA series)/ Non-discharge (TCR3UGxxB series) line up
- Overcurrent protection
- Thermal shutdown function
- Inrush current protection circuit
- Pull down connection between CONTROL and GND
- Ceramic capacitors can be used (C_{IN} = 1 µF, C_{OUT} = 1 µF)

Start of commercial production
2017-10

© 2018
Toshiba Electronic Devices & Storage Corporation

Absolute Maximum Ratings (Ta = 25°C)

Characteristics	Symbol	Rating	Unit
Input voltage	V_{IN}	-0.3 to 6.0	V
Control voltage	V_{CT}	-0.3 to V_{IN} + 0.3 ≤ 6.0	V
Output voltage	V_{OUT}	-0.3 to V_{IN} + 0.3 ≤ 6.0	V
Power dissipation	P_D	800 (Note1)	mW
Junction temperature	T_j	150	°C
Storage temperature range	T_{stg}	−55 to 150	°C

Note: Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings and the operating ranges.
Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook (“Handling Precautions”/“Derating Concept and Methods”) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

Note1: Rating at mounting on a board
Glass epoxy (FR4) board dimension: 40 mm x 40 mm (both sides of board), t = 1.6 mm
Metal pattern ratio: a surface approximately 50 %, the reverse side approximately 50 %
Through hole : diameter 0.5 mm x 24

Operating Ranges

Characteristics	Symbol	Rating			Unit
Input voltage	V_{IN}	1.5 to 5.5		(Note 2)	V
Control voltage	V_{CT}	0 to V_{IN}			V
Output voltage	V_{OUT}	0.8 to 5.0			V
Output current	I_{OUT}	DC	300	(Note 3)	mA
Operation Temperature	T_{opr}	-40 to 85			°C
Output Capacitance	C_{OUT}	≥ 1.0 μF			—
Input Capacitance	C_{IN}	≥ 1.0 μF			—

Note 2: I_{OUT} = 1 mA.
Please refer to Dropout Voltage (Page 10) and use it within Absolute Maximum Ratings Junction temperature and Operation Temperature Ranges.

Note 3: Do not operate at or near the maximum ratings of operating ranges for extended periods of time. Exposure to such conditions may adversely impact product reliability and results in failures not covered by warranty.

© 2018
Toshiba Electronic Devices & Storage Corporation

Pin Assignment (top view)



	1	2
A	VIN	VOUT
B	CONTROL	GND

© 2018
Toshiba Electronic Devices & Storage Corporation

List of Products Number, Output voltage and Marking

Product No.	Output voltage(V)	Auto dis-charge	Marking	Product No.	Output voltage(V)	Auto dis-charge	Marking**
TCR3UG08A	0.8	Yes	A	TCR3UG08B	0.8	No	A
TCR3UG085A	0.85		B	TCR3UG085B	0.85		B
TCR3UG09A	0.9		C	TCR3UG09B	0.9		C
TCR3UG095A	0.95		D	TCR3UG095B	0.95		D
TCR3UG10A	1.0		E	TCR3UG10B	1.0		E
TCR3UG105A	1.05		F	TCR3UG105B	1.05		F
TCR3UG11A	1.1		H	TCR3UG11B	1.1		H
TCR3UG115A	1.15		J	TCR3UG115B	1.15		J
TCR3UG12A	1.2		K	TCR3UG12B	1.2		K
TCR3UG13A	1.3		L	TCR3UG13B	1.3		L
TCR3UG135A	1.35		M	TCR3UG135B	1.35		M
TCR3UG15A	1.5		N	TCR3UG15B	1.5		N
TCR3UG175A	1.75		P	TCR3UG175B	1.75		P
TCR3UG18A	1.8		R	TCR3UG18B	1.8		R
TCR3UG185A	1.85		S	TCR3UG185B	1.85		S
TCR3UG19A	1.9		T	TCR3UG19B	1.9		T
TCR3UG25A	2.5		U	TCR3UG25B	2.5		U
TCR3UG26A	2.6		V	TCR3UG26B	2.6		V
TCR3UG27A	2.7		W	TCR3UG27B	2.7		W
TCR3UG28A	2.8		X	TCR3UG28B	2.8		X
TCR3UG285A	2.85		Y	TCR3UG285B	2.85		Y
TCR3UG30A	3.0		0	TCR3UG30B	3.0		0
TCR3UG31A	3.1		1	TCR3UG31B	3.1		1
TCR3UG32A	3.2		2	TCR3UG32B	3.2		2
TCR3UG33A	3.3		3	TCR3UG33B	3.3		3
TCR3UG35A	3.5		4	TCR3UG35B	3.5		4
TCR3UG36A	3.6		5	TCR3UG36B	3.6		5
TCR3UG41A	4.1		9	TCR3UG41B	4.1		9
TCR3UG42A	4.2		6	TCR3UG42B	4.2		6
TCR3UG45A	4.5		7	TCR3UG45B	4.5		7
TCR3UG50A	5.0		8	TCR3UG50B	5.0		8

**Marking is rotated 90 degrees to the left.

Top Marking (top view)

Example: TCR3UG08A (0.8 V output)



Example: TCR3UG08B (0.8 V output)



© 2018
Toshiba Electronic Devices & Storage Corporation

Block Diagram



Electrical Characteristics

(Unless otherwise specified,

V_{IN} = V_{OUT}+1 V (V_{OUT}>1.5V), V_{IN}=2.5V (V_{OUT}≤1.5V), I_{OUT} = 50 mA, C_{IN} = C_{OUT} = 1 μF)

Characteristics	Symbol	Test Condition		T_j = 25°C			T_j = -40 to 85°C (Note 9)		Unit
				Min	Typ.	Max	Min	Max	
Output voltage accuracy	V_{OUT}	I_{OUT} = 50 mA (Note 4)	V_{OUT} < 1.8 V	-18	—	+18	—	—	mV
			1.8V ≤ V_{OUT}	-1.0	—	+1.0	—	—	%
Input voltage	V_{IN}	I_{OUT} = 1 mA		1.5	—	5.5	1.5	5.5	V
Line regulation	Reg·line	I_{OUT} = 1 mA (Note 5)		—	1	15	—	—	mV
Load regulation	Reg·load	1 mA ≤ I_{OUT} ≤ 300 mA (Note 6)		—	10	30	—	—	mV
Quiescent current	$I_{B(ON1)}$	I_{OUT} = 0 mA, V_{OUT} ≤ 1.5V (Note 7)		—	0.34	—	—	0.58	μA
	$I_{B(ON2)}$	I_{OUT} = 0 mA, 1.75 V ≤ V_{OUT} ≤ 5 V (Note 7)		—	0.38	—	—	0.68	μA
Stand-by current	$I_{B\ (OFF1)}$	V_{CT} = 0 V, V_{IN} = 2.5 V		—	0.03	—	—	0.16	μA
	$I_{B\ (OFF2)}$	V_{CT} = 0 V, V_{IN} = 5.5 V		—	0.03	—	—	0.20	μA
Control pull down current	I_{CT}	—		—	0.1	—	—	—	μA
Drop-out voltage	V_{DO}	I_{OUT} = 300 mA	V_{OUT} = 1.8 V	—	335	—	—	457	mV
			V_{OUT} = 3.3 V	—	140	—	—	273	mV
Output noise voltage	V_{NO}	I_{OUT} = 10 mA, 10 Hz ≤ f ≤ 100 kHz, Ta = 25°C (Note 6)		—	50	—	—	—	μV_{rms}
Ripple rejection ratio	R.R.	I_{OUT} = 10 mA, f = 1 kHz, V_{Ripple} = 200 mV_{p-p}, Ta = 25°C (Note 6)		—	70	—	—	—	dB
Load transient response	⊿V_{OUT}	I_{OUT}=1mA → 50mA (Note 8)		—	-60	—	—	—	mV
		I_{OUT}=50mA → 1mA (Note 8)		—	+60	—	—	—	mV
Temperature coefficient	T_{CVO}	−40°C ≤ T_{opr} ≤ 85°C		—	75	—	—	—	ppm/°C
Control voltage (ON)	$V_{CT\ (ON)}$	—		1.0	—	5.5	1.0	5.5	V
Control voltage (OFF)	$V_{CT\ (OFF)}$	—		0	—	0.4	0	0.4	V
Discharge on resistance	R_{SD}	—		—	10	—	—	—	Ω

Note 4: stable state with fixed I_{OUT} condition

Note 5: V_{OUT} ≤ 1.5 V, 2.5 V ≤ V_{IN} ≤ 5.5 V
1.75 V ≤ V_{OUT} ≤ 4.2 V, V_{OUT} + 1 V ≤ V_{IN} ≤ 5.5 V
V_{OUT} = 4.5 V, V_{OUT} = 5.0 V, not applicable

Note 6: V_{OUT} = 0.8V

Note 7: except Control pull down current (I_{CT})

Note 8: V_{OUT} = 0.8 V, V_{IN} = 3.3 V

Note 9: This parameter is warranted by design

© 2018
Toshiba Electronic Devices & Storage Corporation

Dropout voltage

(I_{OUT} = 300 mA, C_{IN} = C_{OUT} = 1 μF)

Output voltages	Symbol	Min	Typ. T_j = 25°C	Max (Note 10)	Unit
0.8 V ≤ V_{OUT} < 0.9 V	V_{DO}	—	1025	1257	mV
0.9 V ≤ V_{OUT} < 1.0 V		—	930	1157	
1.0 V ≤ V_{OUT} < 1.1 V		—	835	1057	
1.1 V ≤ V_{OUT} < 1.2 V		—	740	957	
1.2 V ≤ V_{OUT} < 1.3 V		—	660	857	
1.3 V ≤ V_{OUT} < 1.5 V		—	580	757	
1.5 V ≤ V_{OUT} < 1.6 V		—	450	617	
1.6 V ≤ V_{OUT} < 1.8 V		—	400	537	
1.8 V ≤ V_{OUT} < 2.0 V		—	335	457	
2.0 V ≤ V_{OUT} < 2.5 V		—	260	405	
2.5 V ≤ V_{OUT} < 3.0 V		—	185	327	
3.0 V ≤ V_{OUT} < 3.6 V		—	140	273	
3.6 V ≤ V_{OUT} < 4.5 V		—	130	228	
4.5 V ≤ V_{OUT} ≤ 5.0 V		—	120	195	

Note 10: T_j = -40 to 85 °C. This parameter is warranted by design

© 2018
Toshiba Electronic Devices & Storage Corporation

Application Note

1. Example of Application Circuit



CONTROL voltage	VOUT voltage
HIGH	ON
LOW	OFF
OPEN	OFF

The figure above shows the Example of configuration for using a Low-Dropout regulator. Insert a capacitor at V_{OUT} and V_{IN} pins for stable input/output operation. (Ceramic capacitors can be used).

2. Power Dissipation

Board-mounted power dissipation ratings are available in the Absolute Maximum Ratings table.
Power dissipation is measured on the board condition shown below.

[The Board Condition]
Board material: Glass epoxy (FR4)
Board dimension: 40 mm x 40 mm (both sides of board), t = 1.6 mm
Metal pattern ratio: a surface approximately 50 %, the reverse side approximately 50 %
Through hole: diameter 0.5 mm x 24



© 2018
Toshiba Electronic Devices & Storage Corporation

Attention in Use

- Output Capacitors
  Ceramic capacitors can be used for these devices. However, because of the type of the capacitors, there might be unexpected thermal features. Please consider application condition for selecting capacitors. And Toshiba recommend the ESR of ceramic capacitor is under 10 Ω. For stable operation, we recommend over 1 μF.

- Mounting
  The long distance between IC and input output capacitor might affect phase compensation by impedance in wire and inductor. For stable power supply, input output capacitor need to mount near IC as much as possible. Also VIN and GND pattern need to be large and make the wire impedance small as possible.

- Permissible Loss
  Please have enough design patterns for expected maximum permissible loss. And under consideration of ambient temperature, input voltage, and output current etc., we recommend proper dissipation ratings for maximum permissible loss; in general maximum dissipation rating is 70 to 80 %.

- Over current Protection and Thermal shut down function
  Over current protection and Thermal shut down function are designed in these products, but these are not designed to constantly ensure the suppression of the device within operation limits. Depending on the condition during actual usage, it could affect the electrical characteristic specification and reliability. Also note that if output pins and GND pins are not completely shorted out, these products might break down.
  When using these products, please read through and understand the concept of dissipation for absolute maximum ratings from the above mention or our ‘Semiconductor Reliability Handbook’. Then use these products under absolute maximum ratings in any condition. Furthermore, Toshiba recommends inserting failsafe system into the design.

© 2018
Toshiba Electronic Devices & Storage Corporation

Representative Typical Characteristics

Output Voltage vs. Input Voltage



Output Voltage vs. Output Current



Dropout Voltage vs. Output Current







© 2018
Toshiba Electronic Devices & Storage Corporation

Dropout Voltage vs. Temprature







Quiescent Current vs. Input Voltage



© 2018
Toshiba Electronic Devices & Storage Corporation

Ripple Rejection Ratio vs. Frequency







t_{ON} / t_{OFF} Response





© 2018
Toshiba Electronic Devices & Storage Corporation

Load Transient Response

V_{OUT} = 1.8 V
(I_{OUT} = 1 mA ⇒ 50 mA)



V_{OUT} = 1.8 V
(I_{OUT} = 50 mA ⇒ 1 mA)



Note: The above characteristics curves are presented for reference only and not guaranteed by production test, unless otherwise noted.

© 2018
Toshiba Electronic Devices & Storage Corporation

Package Information

WCSP4F

Unit: mm



Weight: 0.26 mg (typ.)

Land pattern dimensions for reference only

Unit: mm



© 2018
Toshiba Electronic Devices & Storage Corporation

RESTRICTIONS ON PRODUCT USE

Toshiba Corporation and its subsidiaries and affiliates are collectively referred to as “TOSHIBA”.
Hardware, software and systems described in this document are collectively referred to as “Product”.

- TOSHIBA reserves the right to make changes to the information in this document and related Product without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA's written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product's quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before customers use the Product, create designs including the Product, or incorporate the Product into their own applications, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the "TOSHIBA Semiconductor Reliability Handbook" and (b) the instructions for the application with which the Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications, including but not limited to (a) determining the appropriateness of the use of this Product in such design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. **TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGN OR APPLICATIONS.**
- **PRODUCT IS NEITHER INTENDED NOR WARRANTED FOR USE IN EQUIPMENTS OR SYSTEMS THAT REQUIRE EXTRAORDINARILY HIGH LEVELS OF QUALITY AND/OR RELIABILITY, AND/OR A MALFUNCTION OR FAILURE OF WHICH MAY CAUSE LOSS OF HUMAN LIFE, BODILY INJURY, SERIOUS PROPERTY DAMAGE AND/OR SERIOUS PUBLIC IMPACT ("UNINTENDED USE").** Except for specific applications as expressly stated in this document, Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, lifesaving and/or life supporting medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, and devices related to power plant. **IF YOU USE PRODUCT FOR UNINTENDED USE, TOSHIBA ASSUMES NO LIABILITY FOR PRODUCT.** For details, please contact your TOSHIBA sales representative or contact us via our website.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- **ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.**
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). Product and related software and technology may be controlled under the applicable export laws and regulations including, without limitation, the Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. **TOSHIBA ASSUMES NO LIABILITY FOR DAMAGES OR LOSSES OCCURRING AS A RESULT OF NONCOMPLIANCE WITH APPLICABLE LAWS AND REGULATIONS.**

© 2018
Toshiba Electronic Devices & Storage Corporation

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Toshiba:

TCR3UG41A,LF TCR3UG33A,LF TCR3UG12A,LF TCR3UG18A,LF TCR3UG28A,LF TCR3UG31A,LF TCR3UG27A,LF TCR3UG30A,LF TCR3UG50A,LF TCR3UG25A,LF TCR3UG08A,LF TCR3UG25B,LF TCR3UG50B,LF TCR3UG33B,LF TCR3UG32A,LF TCR3UG285A,LF TCR3UG19A,LF

Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.