

DESCRIPTION

The MP62040-1/MP62041-1 Power Distribution Switch is designed for high-side load switch applications. The switch operates from 1.7V to 5.5V nominal input voltage and includes an 85mΩ Power MOSFET to handle up to 2A continuous load.

The MP62040-1/MP62041-1 has slew rate control with 115μs rise time to limit inrush current when enabling the switch. In addition, the part features a discharge function that provides a resistive discharge path for the external output capacitor when the part is disabled.

The built-in level shift function allows a logic signal on enable input that may be different from the supply voltage to switch the high side P-channel MOSFET ON or OFF.

The MP62040-1/MP62041-1 is available in an ultra-small UTQFN4 package, with ultra-low height (0.55mm typ.).

FEATURES


- 2A Continuous Current
- 1.7V to 5.5V Supply Range
- Output Discharge Function
- Soft Start: 115μs
- 1μA Shutdown Current
- 85mΩ MOSFET
- Active High & Active Low Options
- Space Saving 1.6x1.2mm UTQFN4 Package (0.55mm Height)

APPLICATIONS

- Load Switch in Portable Applications
- Battery Switch-over Circuits

For MPS green status, please visit MPS website under Quality Assurance. "MPS" and "The Future of Analog IC Technology" are Registered Trademarks of Monolithic Power Systems, Inc.

TYPICAL APPLICATION



MP62040-1/MP62041-1

(*: EN is active high for MP62041-1)
Single Channel


ORDERING INFORMATION

Part Number	Enable	Switch	Maximum Continuous Load Current	Package	Top Marking	Free Air Temperature (T _A)
MP62040DQFU-1*	Active Low	Single	2A	UTQFN4	AFY	-40°C to +85°C
MP62041DQFU-1	Active High			UTQFN4	5UY	

* For Tape & Reel, add suffix -Z (e.g. MP62040DQFU-1-Z).

For RoHS compliant packaging, add suffix -LF (e.g. MP62040DQFU-1-LF-Z)

PACKAGE REFERENCE

ABSOLUTE MAXIMUM RATINGS ⁽¹⁾

IN	-0.3V to +6.0V
EN, OUT to GND	-0.3V to +6.0V
Continuous Power Dissipation (T _A = +25°C) ⁽²⁾	
UTQFN4.....	0.7W
Junction Temperature	150°C
Lead Temperature	260°C
Storage Temperature.....	-65°C to +150°C
Maximum Junction Temp. (T _J).....	+125°C

Thermal Resistance ⁽³⁾

	θ_{JA}	θ_{JC}
UTQFN4	173	127.. °C/W

Notes:

- Exceeding these ratings may damage the device.
- The maximum allowable power dissipation is a function of the maximum junction temperature T_J(MAX), the junction-to-ambient thermal resistance θ_{JA} , and the ambient temperature T_A. The maximum allowable continuous power dissipation at any ambient temperature is calculated by P_D(MAX)=(T_J(MAX)-T_A)/ θ_{JA} . Exceeding the maximum allowable power dissipation will cause excessive die temperature, and the regulator will go into thermal shutdown. Internal thermal shutdown circuitry protects the device from permanent damage.
- Measured on JESD51-7, 4-layer PCB.

ELECTRICAL CHARACTERISTICS**V_{IN}=3.6V, T_A=+25°C, unless otherwise noted.**

Parameter	Symbol	Condition	Min	Typ	Max	Units
IN Voltage Range	V _{IN}		1.7		5.5	V
Supply Current		Device active, V _{IN} =3.6V, I _{OUT} =0		2		μA
Shutdown Current		Device disable, V _{IN} =5.5V, V _{OUT} =float			1	μA
FET On_Resistance		V _{IN} =1.7V, I _{OUT} =100mA		165	225	mΩ
		V _{IN} =1.8V, I _{OUT} =100mA		155	215	mΩ
		V _{IN} =2.5V, I _{OUT} =100mA		130	200	mΩ
		V _{IN} =3.6V, I _{OUT} =100mA		100	140	mΩ
		V _{IN} =4.5V, I _{OUT} =100mA		85	115	mΩ
EN Input Logic High Voltage		V _{IN} = 1.7V to 4.5V, I _D = -250μA	1.2			V
EN Input Logic Low Voltage		V _{IN} = 1.7V to 4.5V, I _D = -250μA			0.4	V
EN Input Current		Device active, V _{IN} = 5.5V		2	4	μA
Discharge Resistance		Device disable, V _{IN} =3.6V, I _{TEST} = 1mA		200	300	Ω
V _{OUT} Rising Time ⁽⁴⁾	Tr	V _{IN} =3.6V, I _{OUT} =100mA, C _L =1μF	75	115	200	μs
V _{OUT} Falling Time ⁽⁵⁾	Tf	V _{IN} =3.6V, I _{OUT} =100mA, C _L =1μF	65	75	100	μs
Turn On_Time ⁽⁶⁾	Ton	V _{IN} =3.6V, I _{OUT} =100mA, C _L =1μF		235	350	μs
Turn Off_Time ⁽⁷⁾	Toff	V _{IN} =3.6V, I _{OUT} =100mA, C _L =1μF		100	200	μs

Notes:

4) Measured from 10% to 90%.

5) Measured from 90% to 10%.

6) Measured from (50%) EN signal to (90%) output signal.

7) Measured from (50%) EN signal to (10%) output signal.

PIN FUNCTIONS

UTQFN	Name	Description
1	OUT	IN-to-OUT Power-Distribution Output
2	GND	Ground and the thermal pad should both be connected to electrical ground.
3	IN	Input Voltage. Accepts 1.7V to 5.5V input.
4	$\overline{\text{EN}}$	Active Low: (MP62040-1), Active High: (MP62041-1)

PARAMETER MEASUREMENT INFORMATION





Figure 1 — Definition of Tr, Tf, Ton and Toff

TYPICAL PERFORMANCE CHARACTERISTICS

$V_{IN} = V_{EN} = 3.6V$, $C_L = 1\mu F$, $T_A = +25^\circ C$, unless otherwise noted.


Turn_on Time vs.
Input Voltage

$C_L = 10\mu F$, $R_L = 2.75\Omega$




Turn_off Time vs.
Input Voltage

$C_L = 10\mu F$, $R_L = 2.75\Omega$




Rise Time vs. Input Voltage

$R_L = 2.75\Omega$




Fall Time vs.
Input Voltage

$R_L = 2.75\Omega$




Supply Current,
Output Enabled vs.
Input Voltage




On- Resistance vs. Ambient
Temperature


$I_{OUT} = 0.1A$



On- Resistance vs Input
Voltage



Input to Output Voltage vs.
Load Current




TYPICAL PERFORMANCE CHARACTERISTICS *(continued)*

$V_{IN} = V_{EN} = 3.6V$, $C_L = 1\mu F$, $T_A = +25^\circ C$, unless otherwise noted.


**Turn_on Delay and Rise Time
with 1 μF Load**

$R_L = 3.6\Omega$




**Turn_off Delay and Fall Time
with 1 μF Load**

$R_L = 3.6\Omega$




**Turn_on Delay and Rise Time
with 10 μF Load**

$C_{OUT} = 10\mu F$, $R_L = 3.6\Omega$



**Turn_off Delay and Fall Time
with 10 μF Load**

$C_{OUT} = 10\mu F$, $R_L = 3.6\Omega$



FUNCTION BLOCK DIAGRAM




Figure 2—Function Block Diagram

DETAILED DESCRIPTION

The MP62040-1/MP62041-1 Power Distribution Switch is designed for high-side load switch. The switch operates from 1.7V to 5.5V nominal input voltage and can handle up to 2A continuous load.

Enable

The logic pin disables the switch to reduce overall supply current. Once the EN pin reaches logic enable threshold, the MP62040-1/MP62041-1 is enabled and the supply current is very small, only 2μA.

Output Discharge

The part includes a discharge function that provides a resistive discharge path for the external output capacitor. This function allows the device to quickly discharge the output voltage when it's disabled.

APPLICATION INFORMATION


Power-Supply Considerations

Over 10μF capacitor between IN and GND is recommended. This precaution reduces power-supply transients that may cause ringing on the input.


In order to achieve smaller output load transient ripple, placing a high-value electrolytic capacitor on the output pin(s) is recommended when the load is heavy.

PACKAGE INFORMATION


UTQFN (1.6x1.2mm)



TOP VIEW




BOTTOM VIEW




SIDE VIEW


PIN 1 ID OPTION A
R 0.10 TYP.



PIN 1 ID OPTION B
0.20x45° TYP.



DETAIL A



RECOMMENDED LAND PATTERN

NOTE:

- 1) ALL DIMENSIONS ARE IN MILLIMETERS
- 2) EXPOSED PADDLE SIZE DOES NOT INCLUDE MOLD FLASH
- 3) LEAD COPLANARITY SHALL BE 0.10 MILLIMETER MAX
- 4) JEDEC REFERENCE IS MO-229.
- 5) DRAWING IS NOT TO SCALE

NOTICE: The information in this document is subject to change without notice. Users should warrant and guarantee that third party Intellectual Property rights are not infringed upon when integrating MPS products into any application. MPS will not assume any legal responsibility for any said applications.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.