# **Surface Mount Optically Coupled** Isolator



**OPI210, OPI211** 

# Features:

- 1kV electrical isolation
- Miniature package ideal for surface mount applications
- TTL, DTL compatible •
- High DC Current Transfer ratio



# **Description:**

Each Optically coupled isolator in this data sheet contains an infrared Light Emitting Diode (LED) and a NPN silicon Photosensor. The OPI210 and OPI211 devices have 890 nm Light Emitting Diode (LED) and NPN phototransistor and coupled on an FR-4 substrate. The devices are made with a sealed internal optically transmissive path between the LED and the photosensor.

The OPI210 and OPI211 are identical except for the DC current transfer ratio. Both were designed with high reliability in mind and are ideally suited for use in MIL-STD-883 applications. The devices may be mounted using either silver or gold filled epoxies. The top of the device is covered with a silicone material and is very sensitive to acetone type cleaning material.

This series is designed for transmission of information between one power supply voltage to another where the potentials during surge conditions are not greater than the guaranteed isolation voltage.

LED

Contact your local representative or OPTEK for more information.

## **Applications:**

- Military equipment
- **High-Reliability environments**
- High voltage isolation between input and output
- Electrical isolation in dirty environments
- Medical equipment
- Office equipment



**Ordering Information** 

Isolation

#### General Note

RoHS

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc. 1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 |Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com

VCE



# OPI210, OPI211

# Absolute Maximum Ratings (T<sub>A</sub> = 25° C unless otherwise noted)

Storage	Temperature					-65° C to +150° C
Operating Temperature						-55° C to +125° C
Input-to-Output Isolation Voltage <sup>(1)(2)</sup>						± 1 kVDC
Lead Soldering Temperature (1/16" (1.6 mm) from case for 5 seconds with soldering iron) <sup>(3)</sup>						ing iron) <sup>(3)</sup> 260° C
nput Diod	e					
Forward DC Current <sup>(4)</sup>						50 mA
Reverse DC Voltage						3 \
Power Dissipation <sup>(5)</sup>						60 mV
Output Ph	otosensor					
Collector-Emitter Voltage						35 \
Emitter-Collector Voltage						7.0 V
Power Dissipation <sup>(6)</sup>						100 mV
Electrica	al Characteristics (T <sub>A</sub> = 25° C unles	ss othei	wise n	oted)		
SYMBOL	PARAMETER	MIN	TYP	MAX	UNITS	TEST CONDITIONS
	I See OP265 for additional information -				onno	
					V	I <sub>F</sub> = 10 mA
Input Dioc	le (See OP265 for additional information -			nly)		
Input Dioc V <sub>F</sub> I <sub>R</sub>	e (See OP265 for additional information - Forward Voltage	for refe	rence o - -	nly) 1.6 100	V µA	I <sub>F</sub> = 10 mA
Input Dioc V <sub>F</sub> I <sub>R</sub>	e (See OP265 for additional information - Forward Voltage Reverse Current	for refe	rence o - -	nly) 1.6 100	V µA	I <sub>F</sub> = 10 mA
Input Dioc V <sub>F</sub> I <sub>R</sub> Output Ph	e (See OP265 for additional information - Forward Voltage Reverse Current otosensor (See OP505 for additional info	for refe - - prmation	rence o - - - for re	nly) 1.6 100	V μA only)	I <sub>F</sub> = 10 mA V <sub>R</sub> = 2 V
Input Dioc V <sub>F</sub> I <sub>R</sub> Output Ph V <sub>(BR)CEO</sub>	e (See OP265 for additional information - Forward Voltage Reverse Current otosensor (See OP505 for additional info Collector-Emitter Breakdown Voltage	for refe - - ormation 35	rence o - - - for re 80	nly) 1.6 100 ference	V µA only) V	$I_{F} = 10 \text{ mA}$ $V_{R} = 2 \text{ V}$ $I_{C} = 100 \mu\text{A}, I_{F} = 0$
Input Dioc V <sub>F</sub> I <sub>R</sub> Output Ph V <sub>(BR)CEO</sub> V <sub>(BR)ECO</sub>	e (See OP265 for additional information - Forward Voltage Reverse Current otosensor (See OP505 for additional info Collector-Emitter Breakdown Voltage Emitter-Collector Breakdown Voltage	for refe - - ormation 35	rence o - - - for re 80 10	nly) 1.6 100 ference - -	V μA only) V V	$I_F = 10 \text{ mA}$ $V_R = 2 \text{ V}$ $I_C = 100 \ \mu\text{A}, I_F = 0$ $I_E = 100 \ \mu\text{A}, I_F = 0$
Input Dioc V <sub>F</sub> I <sub>R</sub> Output Ph V <sub>(BR)CEO</sub> V <sub>(BR)ECO</sub> I <sub>CEO</sub>	e (See OP265 for additional information - Forward Voltage Reverse Current otosensor (See OP505 for additional info Collector-Emitter Breakdown Voltage Emitter-Collector Breakdown Voltage	for refe - - ormation 35	rence o - - - for re 80 10	nly) 1.6 100 ference - -	V μA only) V V	$I_F = 10 \text{ mA}$ $V_R = 2 \text{ V}$ $I_C = 100 \ \mu\text{A}, I_F = 0$ $I_E = 100 \ \mu\text{A}, I_F = 0$
Input Dioc V <sub>F</sub> I <sub>R</sub> Output Ph V <sub>(BR)CEO</sub> V <sub>(BR)ECO</sub> I <sub>CEO</sub> Coupled	e (See OP265 for additional information - Forward Voltage Reverse Current otosensor (See OP505 for additional info Collector-Emitter Breakdown Voltage Emitter-Collector Breakdown Voltage Collector-Emitter Dark Current DC Current Transfer Ratio OPI210	for refe           -           -           ormation           35           7           -           50	rence o - - for re 80 10 20	nly) 1.6 100 ference - -	V µA only) V V nA	$I_{F} = 10 \text{ mA}$ $V_{R} = 2 \text{ V}$ $I_{C} = 100 \mu\text{A}, I_{F} = 0$ $I_{E} = 100 \mu\text{A}, I_{F} = 0$ $V_{CE} = 20 \text{ V}, I_{F} = 0$

Notes:

(1) Measured with input and output leads shorted. Typical input/output capacitance is 0.06 pF.

(2) UL recognition is for 3500 VAC for one minute.

(3) RMA flux is recommended. The duration can be extended to 10 seconds maximum when flow soldering.

(4) Derate linearly 0.67 mA/°C above 25°C.

(5) Derate linearly 0.83 mA/°C above 25°C.

(6) Derate linearly 1.67 mA/°C above 25°C.

General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc. 1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 |Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com

# Surface Mount Optically Coupled Isolator



OPI210, OPI211



Forward Voltage Vs Forward Current Vs Ambient Temperature



OPTEK reserves the right to make changes at any time in order to improve design and to supply the best product possible.

General Note

TT Electronics reserves the right to make changes in product specification without notice or liability. All information is subject to TT Electronics' own data and is considered accurate at time of going to print.

TT Electronics | Optek Technology, Inc. 1645 Wallace Drive, Ste. 130, Carrollton, TX USA 75006 |Ph: +1 972 323 2200 www.ttelectronics.com | sensors@ttelectronics.com



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный) **Факс:** 8 (812) 320-02-42 **Электронная почта:** <u>org@eplast1.ru</u> **Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.