
ANALOG DEVICES

Hittite MICROWAVE PRODUCTS FROM ANALOG DEVICES

Analog Devices Welcomes Hittite Microwave Corporation

NO CONTENT ON THE ATTACHED DOCUMENT HAS CHANGED



www.analog.com

www.hittite.com

THIS PAGE INTENTIONALLY LEFT BLANK

v00.1010

HMC894LP5E

FILTER - TUNABLE, BAND PASS SMT 5.9 - 11.2 GHz

Typical Applications

The HMC894LP5E is ideal for:

- Test & Measurement Equipment
- Military RADAR & EW/ECM
- SATCOM & Space
- Industrial & Medical Equipment

Features


Fast Tuning Response; 200 ns

Excellent Wideband Rejection; >30 dB

Single Chip Replacement
for Mechanically Tuned Designs

32 Lead 5x5 mm SMT Package

Functional Diagram



General Description

The HMC894LP5E is a MMIC band pass filter which features a user selectable passband frequency. The 3 dB filter bandwidth is approximately 6%. The 20 dB filter bandwidth is approximately 16.5%. The center frequency can be varied between 5.9 and 11.2 GHz by applying an analog tune voltage between 0 and 14V. This tunable filter can be used as a much smaller alternative to physically large switched filter banks and cavity tuned filters. The HMC894LP5E has excellent microphonics due to the monolithic design, and provides a dynamically adjustable solution in advanced communications applications.


Electrical Specifications, T_A = +25°C, V_{fctl} = V_{bwctl} Unless Otherwise Stated

Parameter	Min.	Typ.	Max.	Units
F_{center} Tuning Range	5.9		11.2	GHz
3 dB Bandwidth		6		%
Low Side Rejection Frequency (Rejection >20 dB)		0.92*F_{center}		GHz
High Side Rejection Frequency (Rejection >20 dB)		1.08*F_{center}		GHz
Re-entry Frequency (Rejection <30 dB)		25		GHz
3 dB Bandwidth Control (V_{bwctl})		±3		%
Insertion Loss		9		dB
Return Loss (2 dB Bandwidth)		7.5		dB
Maximum Input Power for Linear Operation			10	dBm
Frequency Control Voltage (V_{fctl})	0		14	V
Source/Sink Current (I_{fctl})			±1	mA
Bandwidth Control Voltage (V_{bwctl})	0		14	V
Source/Sink Current (I_{bwctl})			±1	mA
Residual Phase Noise [1] (1 MHz Offset)		-165		dBc/Hz
F_{center} Drift Rate		-0.86		MHz/°C
Tuning Characteristics [2] tFULLBAND (0% Vfctl to 90% RF)		200		ns


[1] Optimum residual phase noise performance requires the use of a low noise driver circuit.
[2] Tuning speed is dependent on driver circuit. Data measured with a high speed op-amp driver and includes driver slew rate delay.

FILTER - TUNABLE, BAND PASS SMT
5.9 - 11.2 GHz


Broadband Insertion Loss vs. Control Voltages, Vfctl = Vbwctl




Broadband Return Loss vs. Control Voltages, Vfctl = Vbwctl




Insertion Loss vs. Control Voltages, Vfctl = Vbwctl




Return Loss vs. Control Voltages, Vfctl = Vbwctl



Insertion Loss vs. Temperature, Vfctl = Vbwctl = 7V




Return Loss vs. Temperature, Vfctl = Vbwctl = 7V




FILTER - TUNABLE, BAND PASS SMT 5.9 - 11.2 GHz


Broadband Insertion Loss vs. Vbwctl, Vfctl = 7V




Broadband Return Loss vs. Vbwctl, Vfctl = 7V




Insertion Loss vs. Vbwctl, Vfctl = 7V




Return Loss vs. Vbwctl, Vfctl = 7V




Center Frequency vs. Temperature, Vfctl = Vbwctl




Insertion Loss vs. Temperature, Vfctl = Vbwctl




3 dB Bandwidth vs. Temperature, Vfctl = Vbwctl




Maximum Return Loss in a 2 dB Bandwidth vs. Temperature, Vfctl = Vbwctl




Low Side Rejection Ratio vs. Temperature, Vfctl = Vbwctl [1]




High Side Rejection Ratio vs. Temperature, Vfctl = Vbwctl [1]



Tuning Sensitivity vs. Temperature, Vfctl = Vbwctl




Group Delay, Vctl = Vbwctl




[1] Rejection ratio is defined as the ratio of the frequency at which the relative insertion loss is 20 dB to *f*center


Group Delay vs. Fcenter vs. Temperature




3 dB Bandwidth vs. Bandwidth Control




Insertion Loss vs. Bandwidth Control




Low Side Rejection Ratio vs. Bandwidth Control [1]



High Side Rejection Ratio vs. Bandwidth Control [1]




Maximum Return Loss in a 2 dB Bandwidth vs. Bandwidth Control




[1] Rejection ratio is defined as the ratio of the frequency at which the relative insertion loss is 20 dB to *f*center

FILTER - TUNABLE, BAND PASS SMT 5.9 - 11.2 GHz

Input IP3 vs. Power Input Vfctl = Vbwctl



Residual Phase Noise Vfctl = Vbwctl



Absolute Maximum Ratings


Frequency Control Voltage (Vfctl)	-0.5 to +15V
Bandwidth Control Voltage (Vbwctl)	-0.5 to +15V
RF Power Input	26 dBm
Storage Temperature	-65 to +150 °C
ESD Rating (HBM)	Class 1B

ELECTROSTATIC SENSITIVE DEVICE
OBSERVE HANDLING PRECAUTIONS

Reliability Information

Junction Temperature to Maintain 1 Million Hour MTTF	150 °C
Nominal Junction Temperature (T= 85 °C and Pin = 10 dBm)	90 °C
Operating Temperature	-40 to +85 °C

Outline Drawing



NOTES:





1. LEADFRAME MATERIAL: COPPER ALLOY
2. DIMENSIONS ARE IN INCHES [MILLIMETERS]
3. LEAD SPACING TOLERANCE IS NON-CUMULATIVE.
4. Pin BURR LENGTH SHALL BE 0.15mm MAXIMUM. Pin BURR HEIGHT SHALL BE 0.05mm MAXIMUM.
5. PACKAGE WARP SHALL NOT EXCEED 0.05mm.
6. ALL GROUND LEADS AND GROUND PADDLE MUST BE SOLDERED TO PCB RF GROUND.
7. REFER TO HITTITE APPLICATION NOTE FOR SUGGESTED LAND PATTERN.

Package Information


Part Number	Package Body Material	Lead Finish	MSL Rating	Package Marking [1]
HMC894LP5E	RoHS-compliant Low Stress Injection Molded Plastic	100% matte Sn	MSL1 [2]	H894 XXXX

[1] 4-Digit lot number XXXX
[2] Max peak reflow temperature of 260 °C


Pin Descriptions

Pin Number	Function	Description	Interface Schematic
1 - 4, 7 - 11, 13 15 - 18, 21 - 32	N/C	The pins are not connected internally; however, all data shown herein was measured with these pins connected to RF/DC ground externally.	
5, 20	GND	These pins and exposed paddle must be connected to RF/DC ground.	
6	RFIN	This pin is DC coupled and matched to 50 Ohms. External voltage must not be applied to this pin.	
12	Vfctl	Center frequency control voltage.	
14	Vbwctl	Bandwidth control voltage.	
19	RFOUT	This pin is DC coupled and matched to 50 Ohms. External voltage must not be applied to this pin.	

Application Circuit



Evaluation PCB



List of Materials for Evaluation PCB 128531 [1]

Item	Description
J1, J2	SMA - SRI
J3, J4	SMA - Johnson
C1, C2	100 pF Capacitor, 0402 Pkg.
U1	HMC894LP5E Filter - Tunable
PCB [2]	127338 Evaluation PCB

[1] Reference this number when ordering complete evaluation PCB

[2] Circuit Board Material: Arlon 25FR or Rogers 25FR

The circuit board used in the application should use RF circuit design techniques. Signal lines should have 50 Ohms impedance while the package ground leads and exposed paddle should be connected directly to the ground plane similar to that shown. A sufficient number of via holes should be used to connect the top and bottom ground planes. The evaluation circuit board shown is available from Hittite upon request.

Notes:


Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.