Power Supplies

CXA Series CXA-L10A/-L10L

DC to AC Inverters
On-board type, Non-dimming, 4.5W, For 1 and 2 Bulbs

FEATURES

- The CXA-L10 series inverters for 2-cold cathode fluorescent lamps support a wide range of CCFL devices and are characterized by highly stable output current.
- Employing a resonance-type push-pull circuit, these inverters deliver sine wave output with very low noise levels.
- Through the use of four different connection methods and combinations of 1 and 2 lamps, different output currents can be selected.
- Compact, lightweight printed circuit board design.
- High efficiency (typically 80%).

APPLICATIONS

Industrial and other equipment employing LCD panels, products employing small lamps, information terminal devices.

TEMPERATURE AND HUMIDITY RANGES

Temperature range (°C)	Operating	–10 to +60
	Storage	–20 to +85
Humidity range(%)RH		95max. [Maximum wet-bulb temperature 38°C]

SHAPES AND DIMENSIONS



Bottom View

*1 Terminal numbers 2 and 5 are connected by the jumper. Cut this jumper to let the secondary side float with respect to the primary side.
*2 ▭: High-voltage generator (The entire surface within a range of 25mm away from the end of the base in the output)

Weight: 11g typ.

Dimensions in mm

CIRCUIT DIAGRAMS

CONNECTION A



CONNECTION B



CONNECTION C



CONNECTION D



TERMINAL NUMBERS AND FUNCTIONS

Terminal No.	Functions	CXA-L10A	CXA-L10L	Symbol
1	Input voltage Edc	0 to 6V 5V[nom.]	0 to 14.4V 12V[nom.]	Vin
2		0V	0V	GND
3	Output 1 [High voltage] Irms	5mA	5mA	V_{HIGH1}
4	Output 2 [High voltage] Irms	5mA	5mA	V_{HIGH2}
5	Output[Low voltage]	0V	0V	V_{LOW}

Power Supplies

CXA Series CXA-L10A/-L10L

DC to AC Inverters
On-board type, Non-dimming, 4.5W, For 1 and 2 Bulbs

ELECTRICAL CHARACTERISTICS
5V INPUT TYPE/CXA-L10A

Connections	Items	Unit	Symbol	Specifications			Conditions		
				min.	typ.	max.	Vin(V)	Ta(°C)	R_L(kΩ)
A	Output current Irms	mA	Iout	9	10	11	5±1%	23±5	30
				8	10	12	5±5%	–10 to +60	23 to 37
	Input current Idc	A	Iin	—	0.8	1.2	5±5%	–10 to +60	23 to 37
	Oscillation frequency	kHz	F_L	25	30	35	5±5%	–10 to +60	23 to 37
	Open circuit output voltage Erms	V	Vopen	800	900	—	5±5%	–10 to +60	∞
	Output power	W	Pout	—	—	4.5	5±5%	–10 to +60	—
B	Output current Irms	mA	Iout	5.2	6	6.6	5±1%	23±5	50
				4.6	6	7.2	5±5%	–10 to +60	38 to 62
	Input current Idc	A	Iin	—	0.51	0.77	5±5%	–10 to +60	38 to 62
	Oscillation frequency	kHz	F_L	30	35	40	5±5%	–10 to +60	38 to 62
	Open circuit output voltage Erms	V	Vopen	800	900	—	5±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.7	5±5%	–10 to +60	—
C	Output current Irms	mA	Iout	4.5	5	5.6	5±1%	23±5	60
				4	5	6.1	5±5%	–10 to +60	45 to 75
	Input current Idc	A	Iin	—	0.45	0.68	5±5%	–10 to +60	45 to 75
	Oscillation frequency	kHz	F_L	25	30	35	5±5%	–10 to +60	45 to 75
	Open circuit output voltage Erms	V	Vopen	800	900	—	5±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.25	5±5%	–10 to +60	—
D	Output current Irms	mA	Iout1	4.5	5	5.5	5±1%	23±5	60
			Iout2	4.5	5	5.5	5±1%	23±5	60
			Iout1	4	5	6	5±5%	–10 to +60	45 to 75
			Iout2	4	5	6	5±5%	–10 to +60	45 to 75
	Input current Idc	A	Iin	—	0.8	1.2	5±5%	–10 to +60	45 to 75
	Oscillation frequency	kHz	F_L	25	30	35	5±5%	–10 to +60	45 to 75
	Open circuit output voltage Erms	V	Vopen	800	900	—	5±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.25×2	5±5%	–10 to +60	—

Power Supplies

CXA Series CXA-L10A/-L10L

DC to AC Inverters

On-board type, Non-dimming, 4.5W, For 1 and 2 Bulbs

ELECTRICAL CHARACTERISTICS
12V INPUT TYPE/CXA-L10L

Connections	Items	Unit	Symbol	Specifications			Conditions		
				min.	typ.	max.	Vin(V)	Ta(°C)	R_L(kΩ)
A	Output current Irms	mA	Iout	9	10	11	12±1%	23±5	30
				8	10	12	12±5%	–10 to +60	23 to 37
	Input current Idc	A	Iin	—	0.32	0.48	12±5%	–10 to +60	23 to 37
	Oscillation frequency	kHz	F_L	25	30	35	12±5%	–10 to +60	23 to 37
	Open circuit output voltage Erms	V	Vopen	800	900	—	12±5%	–10 to +60	∞
	Output power	W	Pout	—	—	4.5	12±5%	–10 to +60	—
B	Output current Irms	mA	Iout	5.3	6	6.7	12±1%	23±5	50
				4.7	6	7.3	12±5%	–10 to +60	38 to 62
	Input current Idc	A	Iin	—	0.2	0.3	12±5%	–10 to +60	38 to 62
	Oscillation frequency	kHz	F_L	30	35	40	12±5%	–10 to +60	38 to 62
	Open circuit output voltage Erms	V	Vopen	800	900	—	12±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.7	12±5%	–10 to +60	—
C	Output current Irms	mA	Iout	4.5	5	5.6	12±1%	23±5	60
				4	5	6.1	12±5%	–10 to +60	45 to 75
	Input current Idc	A	Iin	—	0.18	0.27	12±5%	–10 to +60	45 to 75
	Oscillation frequency	kHz	F_L	25	30	35	12±5%	–10 to +60	45 to 75
	Open circuit output voltage Erms	V	Vopen	800	900	—	12±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.25	12±5%	–10 to +60	—
D	Output current Irms	mA	Iout1	4.5	5	5.5	12±1%	23±5	60
			Iout2	4.5	5	5.5	12±1%	23±5	60
			Iout1	4	5	6	12±5%	–10 to +60	45 to 75
			Iout2	4	5	6	12±5%	–10 to +60	45 to 75
	Input current Idc	A	Iin	—	0.32	0.48	12±5%	–10 to +60	45 to 75
	Oscillation frequency	kHz	F_L	25	30	35	12±5%	–10 to +60	45 to 75
	Open circuit output voltage Erms	V	Vopen	800	900	—	12±5%	–10 to +60	∞
	Output power	W	Pout	—	—	2.25×2	12±5%	–10 to +60	—



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits,General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.

Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)
Факс: 8 (812) 320-02-42
Электронная почта: org@eplast1.ru
Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.