

Medium power transistor (60V, 0.5A)

2SC5868

●Features

- 1) High speed switching.
(T_f : Typ. : 80ns at $I_c = 500\text{mA}$)
- 2) Low saturation voltage, typically
(Typ. : 75mV at $I_c = 100\text{mA}$, $I_B = 10\text{mA}$)
- 3) Strong discharge power for inductive load and capacitance load.
- 4) Complements the 2SA2090

●Applications

Small signal low frequency amplifier
High speed switching


●Structure

NPN Silicon epitaxial planar transistor

●Packaging specifications

Type	Package	Taping
	Code	TL
	Basic ordering unit (pieces)	3000
2SC5868		○

●Dimensions (Unit : mm)



●Absolute maximum ratings ($T_a=25^\circ\text{C}$)

Parameter		Symbol	Limits	Unit
Collector-base voltage		V_{CBO}	60	V
Collector-emitter voltage		V_{CEO}	60	V
Emitter-base voltage		V_{EBO}	6	V
Collector current	DC	I_c	0.5	A
	Pulsed	I_{CP}	1.0	A ^{*1}
Power dissipation		P_C	500	mW ^{*2}
Junction temperature		T_j	150	$^\circ\text{C}$
Range of storage temperature		T_{stg}	-55 to 150	$^\circ\text{C}$

^{*1} $P_w=10\text{ms}$

^{*2} Each terminal mounted on a recommended land

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Condition
Collector-emitter breakdown voltage	BV_{CEO}	60	—	—	V	$I_C=1\text{mA}$
Collector-base breakdown voltage	BV_{CBO}	60	—	—	V	$I_C=100\mu\text{A}$
Emitter-base breakdown voltage	BV_{EBO}	6	—	—	V	$I_E=100\mu\text{A}$
Collector cut-off current	I_{CBO}	—	—	1.0	μA	$V_{CB}=40\text{V}$
Emitter cut-off current	I_{EBO}	—	—	1.0	μA	$V_{EB}=4\text{V}$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	75	300	mV	$I_C=100\text{mA}$ $I_B=10\text{mA}$ *1
DC current gain	h_{FE}	120	—	390	—	$V_{CE}=2\text{V}$ $I_C=50\text{mA}$
Transition frequency	f_T	—	300	—	MHz	$V_{CE}=10\text{V}$ $I_E=-100\text{mA}$ $f=10\text{MHz}$ *1
Collector output capacitance	C_{ob}	—	5	—	pF	$V_{CB}=10\text{V}$ $I_E=0\text{mA}$ $f=1\text{MHz}$
Turn-on time	T_{on}	—	70	—	ns	$I_C=500\text{mA}$ $I_{B1}=50\text{mA}$ $I_{B2}=-50\text{mA}$ $V_{CC}\approx 25\text{V}$ *2
Storage time	T_{stg}	—	130	—	ns	
Fall time	T_f	—	80	—	ns	

*1 Non repetitive pulse

*2 See Switching characteristics measurement circuits

● h_{FE} RANK

Q	R
120~270	180~390

●Electrical characteristic curves




Fig.1 Switching Time




Fig.2 DC Current Gain vs. Collector Current (I)




Fig.3 DC Current Gain vs. Collector Current (II)




Fig.4 Collector-Emitter Saturation Voltage vs. Collector Current (I)




Fig.5 Collector-Emitter Saturation Voltage vs. Collector Current (II)




Fig.6 Base-Emitter Saturation Voltage vs. Collector Current




Fig.7 Grounded Emitter Propagation Characteristics




Fig.8 Transition Frequency





Fig.9 Collector Output Capacitance

●Switching characteristics measurement circuits



Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.