

CS424XX

MULTICHANNEL SURROUND-SOUND CODECS IDEAL FOR HOME THEATER AND AUTOMOTIVE AUDIO SYSTEMS



52-PIN MQFP

(actual size: 13.2 mm x 13.2 mm)



64-PIN LQFP

(actual size: 12 mm x 12 mm)



CIRRUS LOGIC, INC.

2901 Via Fortuna
Austin, Texas 78746

United States

T +1-512-851-4000

F +1-512-851-4977

Toll-Free +1-800-888-5016

SALES SUPPORT

North America +1 800-625-4084

Asia Pacific +852 2376-0801

Japan +81 (3) 5226-7757

Europe/UK +44 (90) 1628-891-300

LEARN MORE AT

www.cirrus.com

Part	Resolution (bits)	Dynamic Range (dB)	THD+N (dB)	Sample Rate (kHz)	Analog Outputs	Power Supply (V)	Type	Comments	Package
CS42432/35/36/38	24	105/108 DACs; 102/105 ADCs	-95/-98 DACs; -95/-98 ADCs	192	Single-Ended or Differential DACs and ADCs	VA=3.3 or 5; VD=3.3; VL=1.8 to 5	Multi-channel	Multichannel CODEC, 6/8 DACs, 4/6 ADCs, TDM I/F	52 MQFP
CS42448/888	24	105/108 DACs; 102/105 ADCs	-95/-98 DACs; -95/-98 ADCs	192	Single-Ended or Differential DACs and ADCs	VA=3.3 or 5; VD=3.3 or 5; VL=1.8 to 5	Multi-channel	Multichannel CODEC, 8 DACs, 4/6 ADCs, TDM and PCM I/F	64 LQFP

CS42432/35/36/38 AND CS42448/888

The CS424XX from Cirrus Logic are highly integrated CODECs that are engineered to simplify the design process and enhance listening enjoyment in today's home theater and automotive audio systems.

With a wide dynamic range, negligible distortion and low-noise operation, this family is loaded with high-demand features that designers will appreciate.

The CS424XX are the most highly integrated surround-sound CODECs on the market today, allowing system designers to incorporate up to eight single-ended or six differential audio input sources and up to eight single-ended or differential output sources. This high level of integration is a boost to designers of audio systems, as it eliminates the need for external analog-to-digital (A/D) converters in order to pass multiple audio channels to a DSP chip for audio processing.


The increased input capability allows design of A/V receivers that can receive audio from multiple sources such as set-top boxes, home theater systems, or automotive entertainment systems. The audio input sources could include in-car navigation systems, mobile phones, CD/DVD players, and the radio tuner. Each of these CODECs features multibit Delta-Sigma modulators, resulting in low out-of-band noise, as well as separate control port and serial port supplies for a glueless interface to DSPs.


The CS42432/35/36/38 includes a Time Division Multiplexing only serial port. The CS42448 and CS42888 feature a complete serial port that supports all standard audio data formats, as well as TDM mode.

All D/A converters are 24 bit, with support for sample rates up to 192 kHz, and provide impressive dynamic range of up to 108 dB. In addition, all devices feature 24-bit A/D converters and provide dynamic range up to 105 dB.

The CS424XX outputs feature Cirrus Logic's Popguard® technology to eliminate powercycling clicks and pops. By eliminating external components, Popguard® technology enhances the listening experience for the consumer while simplifying system design and reducing BOM costs.

The CS424XX family delivers advanced performance, design flexibility, reduction in BOM costs, and a competitive price-point, providing exactly what designers need to get their next product to market fast!





FEATURES

- Four to six 24-bit A/D converters & six to eight 24-bit D/A converters
 - Multibit Delta-Sigma architecture
 - Input mux allows up to 8 inputs
- System sampling rates up to 192 kHz
- A/D dynamic range
 - 105 dB differential
 - 102 dB single-ended
- D/A dynamic range
 - 108 dB differential
 - 105 dB single-ended
- THD+N (A/D & D/A)
 - -98 dB differential
 - -95 dB single-ended
- Programmable A/D high pass filter for DC offset calibration
- Auxiliary input source for additional external A/D or S/PDIF receiver
- Logarithmic digital-volume control
- I²C®/SPI™ host-control port
- Cirrus Logic Popguard® technology minimizes clicks and pops
- Support logic levels between 5V and 1.8 V
- Available in automotive (-40°C to +105°C) and commercial (-40°C to 85°C) grades
- CS42432/35/36/38 available in a 52-pin MQFP
- CS42448 and CS42888 available in a 64-pin LQFP

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Cirrus Logic:](#)

[CS42438-CMZ](#) [CS42438-DMZ](#) [CS42438-DMZR](#) [CS42438-CMZR](#)



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



Как с нами связаться

Телефон: 8 (812) 309 58 32 (многоканальный)

Факс: 8 (812) 320-02-42

Электронная почта: org@eplast1.ru

Адрес: 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.