

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter

### General Description

The MAX17595 evaluation kit (EV kit) is a fully assembled and tested circuit board that contains MAX17595 peak-current-mode controller for a flyback regulator. The EV kit is configured for an isolated 15V DC output voltage that can supply up to 1.5A current. The line input voltage range is from 85V AC to 265V AC or 120V DC to 375V DC.

The EV kit demonstrates low quiescent current and efficiency up to 86%. This high efficiency is achieved by using a single-transistor (MOSFET) flyback converter topology that operates at 120kHz switching frequency. The surface-mount transformer has a tertiary winding to power the IC after startup. An optocoupler, along with the transformer, provides galvanic isolation up to 3500VRMS.

**Warning:** The EV kit is designed to operate with high voltages. Dangerous voltages are present on this EV kit and on equipment connected to it. Users who power up this EV kit or the power sources connected to it must be careful to follow safety procedures appropriately to work with high-voltage electrical equipment.

Under severe fault or failure conditions, this EV kit may dissipate large amounts of power, which could result in the mechanical ejection of a component or of component debris at high velocity. Operate this EV kit with care to avoid possible personal injury.

### Features

- ◆ 85V AC to 265V AC or 120V DC to 375V DC Input Range
- ◆ 15V DC at 1.5A Isolated Output Voltage
- ◆ Galvanic Isolation Up to 3500VRMS
- ◆ 120kHz Switching Frequency
- ◆ Efficiency Up to 86%
- ◆ Low-Cost Flyback Design
- ◆ Proven PCB Layout
- ◆ Fully Assembled and Tested

[Ordering Information](#) appears at end of data sheet.

### Component List

DESIGNATION	QTY	DESCRIPTION
C1	1	0.1μF ±20%, 275V AC X2 plastic film capacitor (17mm x 5mm) Panasonic ECQ-U2A104ML
C2	1	0Ω ±5% resistor (0603)
C3, C12, C18	0	Not installed, ceramic capacitors (0603) C3 is short (PC trace); C12, C18 are open
C4	1	56pF ±5%, 50V C0G ceramic capacitor (0603) Murata GRM1885C1H560J
C5	1	100μF ±20%, 450V aluminum electrolytic capacitor (25mm diameter) Panasonic ECO-S2GP101CA

DESIGNATION	QTY	DESCRIPTION
C6, C21	2	0.47μF ±10%, 25V X7R ceramic capacitors (0603) Murata GRM188R71E474K
C7	1	0.1μF ±10%, 16V X7R ceramic capacitor (0603) Murata GRM188R71C104K
C8	1	1μF ±10%, 25V X7R ceramic capacitor (0603) Murata GRM188R71E105K
C9	1	4.7μF ±10%, 50V X7R ceramic capacitor (1206) Murata GRM31CR71H475K
C10	1	3300pF ±10%, 250V X7R ceramic capacitor (0805) Murata GRM21AR72E332K

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter

### Component List (continued)

DESIGNATION	QTY	DESCRIPTION
C11	1	1000pF $\pm 10\%$ , 50V X7R ceramic capacitor (0603) Murata GRM188R71H102K
C13–C16	4	22 $\mu$ F $\pm 10\%$ , 25V X7R ceramic capacitors (1210) Murata GRM32ER71E226K
C17	1	68nF $\pm 10\%$ , 50V X7R ceramic capacitor (0603) TDK C1608X7R1H683K
C19	0	Not installed, capacitor (0805)
C20	1	2200pF $\pm 20\%$ , 250V X7R ceramic capacitor (11mm diameter) TDK CD12-E2GA222MYNS
D1	1	600V, 1.5A bridge rectifier (DF-S) Diodes Inc. DF1506S
D2	1	100V, 300mA fast-switching diode (SOD123) Diodes Inc. 1N4148W-7-F
D3	1	800V, 1A ultra-fast rectifier (SMA) Diodes Inc. US1K-TP
D4	1	200V, 6A ultra-fast recovery rectifier (5 PowerDI) Diodes Inc. PDU620-13
D5	1	0 $\Omega$ $\pm 5\%$ resistor (1206)
L1	1	6.8mH, 0.8A line filter (13mm x 10mm) Würth Elektronik 7448640401
N1	1	800V, 11A n-channel MOSFET (D2PAK) ST Micro STB11NM80T4
R1	1	10 $\Omega$ , 2A NTC thermistor (5mm) EPCOS B57153S0100M000
R2–R4	3	549k $\Omega$ $\pm 1\%$ resistors (1206)
R5	1	19.8k $\Omega$ $\pm 1\%$ resistor (0603)

DESIGNATION	QTY	DESCRIPTION
R6	1	4.99k $\Omega$ $\pm 1\%$ resistor (0603)
R7, R8, R17	0	Not installed, resistors (1206)
R9	1	82.5k $\Omega$ $\pm 1\%$ resistor (0603)
R10, R11, R23–R25, R27	0	Not installed, resistors (0603)
R12	1	49.9k $\Omega$ $\pm 1\%$ resistor (0603)
R13	1	22k $\Omega$ $\pm 1\%$ resistor (0603)
R14–R16	3	402k $\Omega$ $\pm 1\%$ resistors (1206)
R18	1	100k $\Omega$ $\pm 5\%$ resistor (1206) Panasonic ERJ-P08J104V
R19	1	10 $\Omega$ $\pm 1\%$ resistor (0603)
R20	1	100 $\Omega$ $\pm 1\%$ resistor (0603)
R21	1	0.2 $\Omega$ $\pm 1\%$ resistor (1206) Panasonic ERJ-8BSFR20V
R22	1	470 $\Omega$ $\pm 1\%$ resistor (0603)
R26	1	4.99k $\Omega$ $\pm 1\%$ resistor (0603)
R28	1	2.49k $\Omega$ $\pm 1\%$ resistor (0603)
R29	1	221 $\Omega$ $\pm 1\%$ resistor (0603)
R30	0	Not installed, resistor (0805)
T1	1	180 $\mu$ H, 0.8A, 1:0.24:0.2 transformer (EFD25) Coilcraft MA5475-AL
U1	1	Peak-current-mode controller for flyback regulator (16 TQFN-EP*) Maxim MAX17595ATE+
U2	1	Phototransistor (6 DIP) Avago 4N35-300E
U3	1	1.24V, 0.5% shunt regulator (3 SOT23) Diodes Inc. TLV431BFTA
—	1	PCB: MAX17595 EVALUATION KIT

\*EP = Exposed pad.

### Component Suppliers

SUPPLIER	PHONE	WEBSITE
Coilcraft, Inc.	847-639-6400	www.coilcraft.com
Diodes Incorporated	805-446-4800	www.diodes.com
EPCOS AG	732-906-4300	www.epcos.com
Murata Electronics North America, Inc.	770-436-1300	www.murata-northamerica.com
Panasonic Corp.	800-344-2112	www.panasonic.com
STMicroelectronics	408-452-8585	www.us.st.com
TDK Corp.	847-803-6100	www.component.tdk.com

**Note:** Indicate that you are using the MAX17595ATE+ when contacting these component suppliers.

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter

### Quick Start

#### Required Equipment

- Isolation transformer
- Variac
- Two voltmeters

#### Warnings:

- Exercise **Caution** when connecting and measuring off-line voltages.
- Voltage at the primary side can be as high as 700V DC.
- Wear eye protective gear at all times.
- Do not touch any part of the circuit with bare hands or conductive materials when powering up.
- Make sure that all high-voltage capacitors are fully discharged before handling.

#### VOUT Setup Procedure

The MAX17595 EV kit is fully assembled and tested. Follow these steps to verify board operation. **Caution: Do not turn on the power supply until all connections are completed.**

- 1) Connect the positive lead of a DC voltmeter to the VOUT PCB pad.
- 2) Connect the negative lead of a DC voltmeter to the GNDO PCB pad.
- 3) Make sure that the isolation transformer is not powered up. Connect the variac to the output of the isolation transformer.
- 4) Connect one lead of an AC voltmeter to the wiper terminal of the variac.
- 5) Connect the other lead of the AC voltmeter to one of the fixed terminals of the variac.
- 6) Set the output voltage of the variac to 0V AC.
- 7) Connect the wiper terminal of the isolated variac to the AC1 PCB pad on the EV kit.
- 8) Connect the fixed tap of the isolated variac to the AC2 PCB pad on the EV kit.
- 9) Power up the isolation transformer and gradually increase the voltage of the variac to 85V AC and up to 265V AC.
- 10) Verify that VOUT is 15V throughout the 85V AC to 265V AC input voltage range.

### Detailed Description of Hardware

The MAX17595 EV kit evaluates MAX17595 off-line flyback converter operating in discontinuous-conduction mode (DCM), configured for a 15V DC, 1.5A output.

This EV kit uses the peak current mode, pulse-width modulating (PWM) controller IC in a 16-pin TQFN package with an exposed pad. A simple RC charging circuit is used to start up the device. Bias winding feedback is used to supply power during normal operation. Input DC bus capacitor (C5) is designed based on 100Hz ripple content. The 100Hz ripple is chosen to be 25% at 85V AC and 1.5A load current. This PWM controller varies the duty cycle to compensate for the variation in VIN and the output load to maintain a constant output voltage. The duty cycle determines the on/off duration of the MOSFET (N1). The n-channel MOSFET is used as a switch to control the current through the primary winding of transformer T1.

The duty cycle is controlled by the feedback loop consisting of voltage-divider resistors (R28, R29), a shunt regulator (U3), an optocoupler (U2), and the PWM comparator inside the IC. This network provides isolated-voltage-mode feedback, regulating the output voltage to 15V ±2% with up to 3500VRMS galvanic isolation. A thermistor (R1) prevents high inrush currents present due to charging the input capacitor at startup. A snubber circuit (D3, C10, and R18) is used to prevent excessive drain voltages due to leakage inductance of the transformer.

#### Current Limit

The IC features current limiting for the transformer's primary side by monitoring the peak current through the sense resistor (R21). Resistor R21 sets the EV kit circuit peak current (IPEAK) to 1.52A. The IC turns off the N1 MOSFET when the peak current reaches the current limit. To reconfigure the peak current limit to a different value, use the following equation to choose a new R21 resistor:

$$R21 = \frac{305}{I_{PEAK}} \text{ m}\Omega$$

where IPEAK is in amps and R21 is in mΩ.

#### Undervoltage Lockout and Overvoltage Protection

The EV kit features a UVLO and OVI circuit that prevents operation below the programmed input supply startup voltage and above the overvoltage threshold. Resistors R2–R6 set the undervoltage and overvoltage thresholds. The circuit undervoltage and overvoltage thresholds are set at 60V AC (85V DC) and 274V AC (387V DC), respectively. To reconfigure the UVLO and OVI voltages, refer to the *Startup Voltage and Input Overvoltage Protection Setting (EN/UVLO, OVI)* section in the MAX17595/MAX17596/MAX17597 IC data sheet.

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter

EN/UVLO and OVI PCB pads are available for monitoring the voltages present at the respective inputs.

### Soft-Start

The EV kit provides an option to configure the circuit soft-start. Capacitor C7 configures the soft-start time ( $t_{SS}$ ) to 12ms. To reconfigure the soft-start time to a different value, use the following equation to choose a new C7 capacitor:

$$C7 = 8.2645 \times t_{SS} \text{ nF}$$

where  $t_{SS}$  is in ms and C7 is in nF.

### Switching Frequency

The EV kit switching frequency is set to 120kHz by resistor R9. To configure the IC's switching frequency to a different value, between 100kHz and 1MHz, use the following equation to choose a new R9 resistor:

$$R9 = \frac{10^{10}}{f_{SW}} \Omega$$

where  $f_{SW}$  is in Hz and R9 is in  $\Omega$ .

### Frequency Dithering

The EV kit switching frequency can be dithered in a range of  $\pm 10\%$  to reduce EMI. There are two specifications for the frequency dithering: the frequency (how often) of dithering and the amount (how much) of dithering.

Capacitor C2 configures the dither frequency using the following equation:

$$C2 = \frac{50\mu\text{A}}{3.2\text{V} \times f_{\text{DITHER}}} \text{F}$$

where  $f_{\text{DITHER}}$  is in Hz and C2 is in farads, and the dither frequency ( $f_{\text{DITHER}}$ ) is recommended to be set close to 1kHz.

Resistors R9 and R10 configure the amount of dithering in percentage (%) of the switching frequency using the following equation:

$$\% \text{DITHER} = \frac{R9}{R11}$$

The EV kit is shipped with the frequency dithering disabled and the DITHER/SYNC pin shorted to SGND by a  $0\Omega$  resistor installed on the C2 footprint. To set the desired frequency dither, replace capacitor C2 and install resistor R11 with the appropriate values. The DITHER/SYNC PCB pad is available for monitoring the signal at the DITHER/SYNC pin.

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter




Figure 1. MAX17595 EV Kit Schematic

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter




Figure 2. MAX17595 EV Kit Component Placement Guide—Component Side




Figure 3. MAX17595 EV Kit PCB Layout—Component Side

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter




Figure 4. MAX17595 EV Kit PCB Layout—Solder Side

# **MAX17595 Evaluation Kit**

## **Evaluates: MAX17595 as Flyback Converter**

### ***Ordering Information***

<b>PART</b>	<b>TYPE</b>
MAX17595EVKIT#	EV Kit

*#Denotes RoHS compliant.*

# MAX17595 Evaluation Kit

## Evaluates: MAX17595 as Flyback Converter

### Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
0	5/12	Initial release	—
1	4/13	Updated <i>Component List</i> , EV kit specifications, and Figure 1	1–5
2	11/14	Updated L1 supplier in <i>Component List</i>	2



Maxim Integrated cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim Integrated product. No circuit patent licenses are implied. Maxim Integrated reserves the right to change the circuitry and specifications without notice at any time. The parametric values (min and max limits) shown in the Electrical Characteristics table are guaranteed. Other parametric values quoted in this data sheet are provided for guidance.

**Maxim Integrated 160 Rio Robles, San Jose, CA 95134 USA 1-408-601-1000**

© 2014 Maxim Integrated Products, Inc.

Maxim Integrated and the Maxim Integrated logo are trademarks of Maxim Integrated Products, Inc.



Компания «ЭлектроПласт» предлагает заключение долгосрочных отношений при поставках импортных электронных компонентов на взаимовыгодных условиях!

Наши преимущества:

- Оперативные поставки широкого спектра электронных компонентов отечественного и импортного производства напрямую от производителей и с крупнейших мировых складов;
- Поставка более 17-ти миллионов наименований электронных компонентов;
- Поставка сложных, дефицитных, либо снятых с производства позиций;
- Оперативные сроки поставки под заказ (от 5 рабочих дней);
- Экспресс доставка в любую точку России;
- Техническая поддержка проекта, помощь в подборе аналогов, поставка прототипов;
- Система менеджмента качества сертифицирована по Международному стандарту ISO 9001;
- Лицензия ФСБ на осуществление работ с использованием сведений, составляющих государственную тайну;
- Поставка специализированных компонентов (Xilinx, Altera, Analog Devices, Intersil, Interpoint, Microsemi, Aeroflex, Peregrine, Syfer, Eurofarad, Texas Instrument, Miteq, Cobham, E2V, MA-COM, Hittite, Mini-Circuits, General Dynamics и др.);

Помимо этого, одним из направлений компании «ЭлектроПласт» является направление «Источники питания». Мы предлагаем Вам помощь Конструкторского отдела:

- Подбор оптимального решения, техническое обоснование при выборе компонента;
- Подбор аналогов;
- Консультации по применению компонента;
- Поставка образцов и прототипов;
- Техническая поддержка проекта;
- Защита от снятия компонента с производства.



#### Как с нами связаться

**Телефон:** 8 (812) 309 58 32 (многоканальный)

**Факс:** 8 (812) 320-02-42

**Электронная почта:** [org@eplast1.ru](mailto:org@eplast1.ru)

**Адрес:** 198099, г. Санкт-Петербург, ул. Калинина, дом 2, корпус 4, литера А.